

BC-002 CONTROL MANUAL



Charging :Charger Port

When the LED-1 turns Red, the battery of the kit is low. Charge the unit.
1. Connect the charger's plug into Charger Port.

Charge Indicator Statue:

Steady Red LED-1	: Low Battery
Steady Orange of LED-2	: Charging
Steady Red of LED-2	: Full Charge

Power On/Off :

Switch the Power Button Left/Right to turn on the power of unit.

Pairing :

1. Turn the power switch on top, Blue LED-1 will blink.
2. Press and Hold the Reject button for 4 seconds, LED-1 turns blinking Red/Blue.
3. Then, user can search for the car-kit (BC-002) under mobilephone Bluetooth setup.
The mobilephone will ask for password after detecting the BC-002. Enter :
Password: 0000
4. After paired successfully, Blue LED-1 resumes blinking. The kit is ready to use.
5. To cancel pairing by pressing Reject button when the pairing is going on.
Make a Call: Dial the number on your phone. Audio will automatically be on the kit.

P1

Answer a Call :

During the ring tone, press Accept Button for 1 second to answer the call.

End a Call :

Press Reject Button for 1 second to end the call.

Answer A Waiting Call :

During an active call, press Accept Button for 2 seconds to pickup the 2nd incoming call. And press Accept Button for 2 seconds again to switch back the 1st incoming call.

Redial :

Press Accept Button for 3 seconds. The last dialed number will be redial.

Reject a call :

During the ring tone, press Reject Button to reject the incoming call.

Volume Setting :

Increase or decrease the volume by pressing the Volume Up and Volume Down button.

Audio Transfer: (For Handfree Profile Phone only)

During an ongoing call, you can transfer the audio. Kit to Phone: Press "Volume Up" button for 3 seconds, the audio will be transferred to the phone. Phone to Kit: Please follow the operation manual of your phone (select the audio output to the carkit).

Mute of Kit :

Press "Volume Down" for 3 seconds, the Microphone will be muted. And user of far-side cannot listen your voice. (reminding audio signal will be on in this statue) Press "Volume Down" for 3 seconds, the mute will be cancelled. (Reminding audio signal will be off).

Reconnection :

The kit will reconnect to the last paired phone after its power is restarted. Press the Reject button for 3 seconds to reconnect if the kit is disconnected from the phone. Or reconnect the phone to Kit through Bluetooth Setup on The Phone.

BC-002: can maintains 8 phones in its memory. An additional pairing will automatically delete the phone that has not been used for the longest time.

P2

Specification :

Bluetooth Version: 1.2

Supported Bluetooth Profiles: Supports headset and handfree profile with automatic detection

Operating Range: Up to 10 meters

Frequency: 2.4GHz

Talk Time: 7 Hrs

Stand-by Time: 200 Hrs

Charging Time: 2.5 Hrs

Battery Type: Rechargeable Lithium Ion

Special Feature: Full Duplex

CSR Noise Cancellation/Echo Cancellation

Digital Volume Control

Last Call Redial

Reject Incoming Call

Can be charged directly from PC via USB cable
(not included)

Compact Size

Quick fixation on sun visor magnetic clip

Changes or modification not expressly approved by the party responsible for compliance could not viol the user's authority to operate the equitment.

FCC ID: VMNBC002

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) this device may not cause harmful interference, and
(2) this device must accept any interference received, including interference that may cause undesired operations.

FCC RF Exposure requirements:

"This device and its antenna(s) must not be co-located or operating in conjunction with any other antenna or transmitter."

Disclaimer:

Talk time and stand-by time of the Kit will vary depending on mobile phone model being used.

This Kit is compatible to most Bluetooth mobilephones in the market.

P3

P4