



RN2903

Low-Power Long Range LoRa™ Technology Transceiver Module

General Features

- On-board LoRaWAN™ Class A protocol stack
- ASCII command interface over UART
- Compact form factor: 17.8 x 26.7 x 3 mm
- Castellated SMT pads for easy and reliable PCB mounting
- Environmentally friendly, RoHS compliant
- Compliance:
 - Modular Certified for the United States (FCC) and Canada (IC)
 - Australia and New Zealand
- Device Firmware Upgrade (DFU) over UART (see “RN2903 LoRa™ Technology Module Command Reference User’s Guide” DS40000000A)

Operational

- Single operating voltage: 2.1V to 3.6V (3.3V typical)
- Temperature range: -40°C to +85°C
- Low-power consumption
- Programmable RF Communication Bit Rate up to 300 kbps with FSK modulation, 12500 bps with LoRa™ Technology modulation
- Integrated MCU, Crystal, EUI-64 Node Identity Serial EEPROM, Radio Transceiver with Analog Front End, Matching Circuitry
- 14 GPIOs for control and status

RF/Analog Features

- Low-Power Long Range Transceiver operating in the 915 MHz frequency band
- High Receiver Sensitivity: down to -148 dBm
- TX Power: adjustable up to +20 dBm high efficiency PA
- FSK, GFSK, and LoRa Technology modulation
- IIP3 = -11 dBm
- >15 km coverage at suburban and >5 km coverage at urban area



LoRa™ Long-Range Sub-GHz Module
(Part # RN2903)

Description

Microchip’s RN2903 Low-Power Long Range LoRa Technology Transceiver module provides an easy to use, low-power solution for long range wireless data transmission. The advanced command interface offers rapid time to market.

The RN2903 module complies with the LoRaWAN Class A protocol specifications. It integrates RF, a baseband controller, command Application Programming Interface (API) processor, making it a complete long range solution.

The RN2903 module is suitable for simple long range sensor applications with external host MCU.

Applications

- Automated Meter Reading
- Home and Building Automation
- Wireless Alarm and Security Systems
- Industrial Monitoring and Control
- Machine to Machine
- Internet of Things (IoT)

Table of Contents

1.0	Device Overview	3
2.0	General Specifications.....	6
3.0	Typical Hardware Connections.....	8
4.0	Physical Dimensions	9
5.0	Application Information	10
6.0	Regulatory Approval.....	12
	Appendix A: Revision History.....	17
	The Microchip Web Site	19
	Customer Change Notification Service	19
	Customer Support.....	19
	Product Identification System.....	21

TO OUR VALUED CUSTOMERS

It is our intention to provide our valued customers with the best documentation possible to ensure successful use of your Microchip products. To this end, we will continue to improve our publications to better suit your needs. Our publications will be refined and enhanced as new volumes and updates are introduced.

If you have any questions or comments regarding this publication, please contact the Marketing Communications Department via E-mail at docerrors@microchip.com. We welcome your feedback.

Most Current Data Sheet

To obtain the most up-to-date version of this data sheet, please register at our Worldwide Web site at:

<http://www.microchip.com>

You can determine the version of a data sheet by examining its literature number found on the bottom outside corner of any page. The last character of the literature number is the version number, (e.g., DS30000000A is version A of document DS30000000).

Errata

An errata sheet, describing minor operational differences from the data sheet and recommended workarounds, may exist for current devices. As device/documentation issues become known to us, we will publish an errata sheet. The errata will specify the revision of silicon and revision of document to which it applies.

To determine if an errata sheet exists for a particular device, please check with one of the following:

- Microchip's Worldwide Web site; <http://www.microchip.com>
- Your local Microchip sales office (see last page)

When contacting a sales office, please specify which device, revision of silicon and data sheet (include literature number) you are using.

Customer Notification System


Register on our web site at www.microchip.com to receive the most current information on all of our products.

1.0 DEVICE OVERVIEW

The RN2903 transceiver module features LoRa Technology RF modulation, which provides long range spread spectrum communication with high interference immunity.

Using LoRa Technology modulation technique, RN2903 can achieve a receiver sensitivity of -148 dBm. The high sensitivity combined with the integrated +20 dBm power amplifier yields industry leading link budget, which makes it optimal for applications requiring extended range and robustness.

FIGURE 1-1: RN2903 TOP VIEW



LoRa Technology modulation also provides significant advantages in both blocking and selectivity compared to the conventional modulation techniques, solving the traditional design compromise between extended range, interference immunity, and low-power consumption.

The RN2903 module delivers exceptional phase noise, selectivity, receiver linearity, and IIP3 for significantly lower power consumption. [Figure 1-1](#), [Figure 1-2](#), and [Figure 1-3](#) show the module's top view, the pinout, and the block diagram.

FIGURE 1-2: RN2903 PIN DIAGRAM

27	GND	26	GND	25	NC	24	GND	23	RF	22	GND	21	GND
28	GND	29	NC	30	TEST0	31	TEST1	32	RESET	33	GND	34	VDD
35	GPIO0	36	GPIO1	37	GPIO2	38	GPIO3	39	GPIO4	40	GPIO5	41	GND
42	NC	43	GPIO6	44	GPIO7	45	GPIO8	46	GPIO9	47	GND	48	UART_RX
49	UART_TX	50	RESERVED	51	RESERVED	52	UART_CTS	53	UART_RTS	54	GND	55	GND
56	RESERVED	57	RESERVED	58	RESERVED	59	RESERVED	60	RESERVED	61	RESERVED	62	RESERVED
63	RESERVED	64	RESERVED	65	RESERVED	66	RESERVED	67	RESERVED	68	RESERVED	69	RESERVED
70	RESERVED	71	RESERVED	72	RESERVED	73	RESERVED	74	RESERVED	75	RESERVED	76	RESERVED
77	RESERVED	78	RESERVED	79	RESERVED	80	RESERVED	81	RESERVED	82	RESERVED	83	RESERVED
84	RESERVED	85	RESERVED	86	RESERVED	87	RESERVED	88	RESERVED	89	RESERVED	90	RESERVED
91	RESERVED	92	RESERVED	93	RESERVED	94	RESERVED	95	RESERVED	96	RESERVED	97	RESERVED
98	RESERVED	99	RESERVED	100	RESERVED	101	RESERVED	102	RESERVED	103	RESERVED	104	RESERVED
105	RESERVED	106	RESERVED	107	RESERVED	108	RESERVED	109	RESERVED	110	RESERVED	111	RESERVED
112	RESERVED	113	RESERVED	114	RESERVED	115	RESERVED	116	RESERVED	117	RESERVED	118	RESERVED
119	RESERVED	120	RESERVED	121	RESERVED	122	RESERVED	123	RESERVED	124	RESERVED	125	RESERVED
126	RESERVED	127	RESERVED	128	RESERVED	129	RESERVED	130	RESERVED	131	RESERVED	132	RESERVED
133	RESERVED	134	RESERVED	135	RESERVED	136	RESERVED	137	RESERVED	138	RESERVED	139	RESERVED
140	RESERVED	141	RESERVED	142	RESERVED	143	RESERVED	144	RESERVED	145	RESERVED	146	RESERVED
147	RESERVED	148	RESERVED	149	RESERVED	150	RESERVED	151	RESERVED	152	RESERVED	153	RESERVED
154	RESERVED	155	RESERVED	156	RESERVED	157	RESERVED	158	RESERVED	159	RESERVED	160	RESERVED
161	RESERVED	162	RESERVED	163	RESERVED	164	RESERVED	165	RESERVED	166	RESERVED	167	RESERVED
168	RESERVED	169	RESERVED	170	RESERVED	171	RESERVED	172	RESERVED	173	RESERVED	174	RESERVED
175	RESERVED	176	RESERVED	177	RESERVED	178	RESERVED	179	RESERVED	180	RESERVED	181	RESERVED
182	RESERVED	183	RESERVED	184	RESERVED	185	RESERVED	186	RESERVED	187	RESERVED	188	RESERVED
189	RESERVED	190	RESERVED	191	RESERVED	192	RESERVED	193	RESERVED	194	RESERVED	195	RESERVED
196	RESERVED	197	RESERVED	198	RESERVED	199	RESERVED	200	RESERVED	201	RESERVED	202	RESERVED
203	RESERVED	204	RESERVED	205	RESERVED	206	RESERVED	207	RESERVED	208	RESERVED	209	RESERVED
210	RESERVED	211	RESERVED	212	RESERVED	213	RESERVED	214	RESERVED	215	RESERVED	216	RESERVED
217	RESERVED	218	RESERVED	219	RESERVED	220	RESERVED	221	RESERVED	222	RESERVED	223	RESERVED
224	RESERVED	225	RESERVED	226	RESERVED	227	RESERVED	228	RESERVED	229	RESERVED	230	RESERVED
231	RESERVED	232	RESERVED	233	RESERVED	234	RESERVED	235	RESERVED	236	RESERVED	237	RESERVED
238	RESERVED	239	RESERVED	240	RESERVED	241	RESERVED	242	RESERVED	243	RESERVED	244	RESERVED
245	RESERVED	246	RESERVED	247	RESERVED	248	RESERVED	249	RESERVED	250	RESERVED	251	RESERVED
252	RESERVED	253	RESERVED	254	RESERVED	255	RESERVED	256	RESERVED	257	RESERVED	258	RESERVED
259	RESERVED	260	RESERVED	261	RESERVED	262	RESERVED	263	RESERVED	264	RESERVED	265	RESERVED
266	RESERVED	267	RESERVED	268	RESERVED	269	RESERVED	270	RESERVED	271	RESERVED	272	RESERVED
273	RESERVED	274	RESERVED	275	RESERVED	276	RESERVED	277	RESERVED	278	RESERVED	279	RESERVED
280	RESERVED	281	RESERVED	282	RESERVED	283	RESERVED	284	RESERVED	285	RESERVED	286	RESERVED
287	RESERVED	288	RESERVED	289	RESERVED	290	RESERVED	291	RESERVED	292	RESERVED	293	RESERVED
294	RESERVED	295	RESERVED	296	RESERVED	297	RESERVED	298	RESERVED	299	RESERVED	300	RESERVED
301	RESERVED	302	RESERVED	303	RESERVED	304	RESERVED	305	RESERVED	306	RESERVED	307	RESERVED
308	RESERVED	309	RESERVED	310	RESERVED	311	RESERVED	312	RESERVED	313	RESERVED	314	RESERVED
315	RESERVED	316	RESERVED	317	RESERVED	318	RESERVED	319	RESERVED	320	RESERVED	321	RESERVED
322	RESERVED	323	RESERVED	324	RESERVED	325	RESERVED	326	RESERVED	327	RESERVED	328	RESERVED
329	RESERVED	330	RESERVED	331	RESERVED	332	RESERVED	333	RESERVED	334	RESERVED	335	RESERVED
336	RESERVED	337	RESERVED	338	RESERVED	339	RESERVED	340	RESERVED	341	RESERVED	342	RESERVED
343	RESERVED	344	RESERVED	345	RESERVED	346	RESERVED	347	RESERVED	348	RESERVED	349	RESERVED
350	RESERVED	351	RESERVED	352	RESERVED	353	RESERVED	354	RESERVED	355	RESERVED	356	RESERVED
357	RESERVED	358	RESERVED	359	RESERVED	360	RESERVED	361	RESERVED	362	RESERVED	363	RESERVED
364	RESERVED	365	RESERVED	366	RESERVED	367	RESERVED	368	RESERVED	369	RESERVED	370	RESERVED
371	RESERVED	372	RESERVED	373	RESERVED	374	RESERVED	375	RESERVED	376	RESERVED	377	RESERVED
378	RESERVED	379	RESERVED	380	RESERVED	381	RESERVED	382	RESERVED	383	RESERVED	384	RESERVED
385	RESERVED	386	RESERVED	387	RESERVED	388	RESERVED	389	RESERVED	390	RESERVED	391	RESERVED
392	RESERVED	393	RESERVED	394	RESERVED	395	RESERVED	396	RESERVED	397	RESERVED	398	RESERVED
399	RESERVED	400	RESERVED	401	RESERVED	402	RESERVED	403	RESERVED	404	RESERVED	405	RESERVED
406	RESERVED	407	RESERVED	408	RESERVED	409	RESERVED	410	RESERVED	411	RESERVED	412	RESERVED
413	RESERVED	414	RESERVED	415	RESERVED	416	RESERVED	417	RESERVED	418	RESERVED	419	RESERVED
420	RESERVED	421	RESERVED	422	RESERVED	423	RESERVED	424	RESERVED	425	RESERVED	426	RESERVED
427	RESERVED	428	RESERVED	429	RESERVED	430	RESERVED	431	RESERVED	432	RESERVED	433	RESERVED
434	RESERVED	435	RESERVED	436	RESERVED	437	RESERVED	438	RESERVED	439	RESERVED	440	RESERVED
441	RESERVED	442	RESERVED	443	RESERVED	444	RESERVED	445	RESERVED	446	RESERVED	447	RESERVED
448	RESERVED	449	RESERVED	450	RESERVED	451	RESERVED	452	RESERVED	453	RESERVED	454	RESERVED
455	RESERVED	456	RESERVED	457	RESERVED	458	RESERVED	459	RESERVED	460	RESERVED	461	RESERVED
462	RESERVED	463	RESERVED	464	RESERVED	465	RESERVED	466	RESERVED	467	RESERVED	468	RESERVED
469	RESERVED	470	RESERVED	471	RESERVED	472	RESERVED	473	RESERVED	474	RESERVED	475	RESERVED
476	RESERVED	477	RESERVED	478	RESERVED	479	RESERVED	480	RESERVED	481	RESERVED	482	RESERVED
483	RESERVED	484	RESERVED	485	RESERVED	486	RESERVED	487	RESERVED	488	RESERVED	489	RESERVED
490	RESERVED	491	RESERVED	492	RESERVED	493	RESERVED	494	RESERVED	495	RESERVED	496	RESERVED
497	RESERVED	498	RESERVED	499	RESERVED	500	RESERVED	501	RESERVED	502	RESERVED	503	RESERVED
504	RESERVED	505	RESERVED	506	RESERVED	507	RESERVED	508	RESERVED	509	RESERVED	510	RESERVED
511	RESERVED	512	RESERVED	513	RESERVED	514	RESERVED	515	RESERVED	516	RESERVED	517	RESERVED
518	RESERVED	519	RESERVED	520	RESERVED	521	RESERVED	522	RESERVED	523	RESERVED	524	RESERVED
525	RESERVED	526	RESERVED	527	RESERVED	528	RESERVED	529	RESERVED	530	RESERVED	531	RESERVED
532	RESERVED	533	RESERVED	534	RESERVED	535	RESERVED	536	RESERVED	537	RESERVED	538	RESERVED
539	RESERVED	540	RESERVED	541	RESERVED	542	RESERVED	543	RESERVED	544	RESERVED	545	RESERVED
546	RESERVED	547	RESERVED	548	RESERVED	549	RESERVED	550	RESERVED	551	RESERVED	552	RESERVED
553	RESERVED	554	RESERVED	555	RESERVED	556	RESERVED	557	RESERVED	558	RESERVED	559	RESERVED
560	RESERVED	561	RESERVED	562	RESERVED	563	RESERVED	564	RESERVED	565	RESERVED	566	RESERVED
567	RESERVED	568	RESERVED	569	RESERVED	570	RESERVED	571	RESERVED	572	RESERVED	573	RESERVED
574	RESERVED	575	RESERVED	576	RESERVED	577	RESERVED	578	RESERVED	579	RESERVED	580	RESERVED
581	RESERVED	582	RESERVED	583	RESERVED	584	RESERVED	585	RESERVED	586	RESERVED	587	RESERVED
588	RESERVED	589	RESERVED	590	RESERVED	591	RESERVED	592	RESERVED	593	RESERVED	594	RESERVED
595	RESERVED	596	RESERVED	597	RESERVED	598	RESERVED	599	RESERVED	600	RESERVED	601	RESERVED
602	RESERVED	603	RESERVED	604	RESERVED	605	RESERVED	606	RESERVED	607	RESERVED	608	RESERVED
609	RESERVED	610	RESERVED	611	RESERVED	612	RESERVED	613	RESERVED	614	RESERVED	615	RESERVED
616	RESERVED	617	RESERVED	618	RESERVED	619	RESERVED	620	RESERVED	621	RESERVED	622	RESERVED
623	RESERVED	624	RESERVED	625	RESERVED	626	RESERVED	627	RESERVED	628	RESERVED	629	RESERVED
630	RESERVED	631	RESERVED	632	RESERVED	633	RESERVED	634	RESERVED	635	RESERVED	636	RESERVED
637	RESERVED	638	RESERVED	639	RESERVED	640	RESERVED	641	RESERVED	642	RESERVED	643	RESERVED
644	RESERVED	645	RESERVED	646	RESERVED	647	RESERVED	648	RESERVED	649	RESERVED	650	RESERVED
651	RESERVED	652	RESERVED	653	RESERVED	654	RESERVED	655	RESERVED	656	RESERVED	657	RESERVED
658	RESERVED	659	RESERVED	660	RESERVED	661	RESERVED	662	RESERVED	663	RESERVED	664	RESERVED
665	RESERVED	666	RESERVED	667	RESERVED	668	RESERVED	669	RESERVED	670	RESERVED	671	RESERVED
672	RESERVED	673	RESERVED	674	RESERVED	675	RESERVED	676	RESERVED	677	RESERVED	678	RESERVED
679	RESERVED	680	RESERVED	681	RESERVED	682	RESERVED	683	RESERVED	684	RESERVED	685	RESERVED
686	RESERVED	687	RESERVED	688	RESERVED	689	RESERVED	690	RESERVED	691	RESERVED	692	RESERVED
693	RESERVED	694	RESERVED	695	RESERVED	696	RESERVED	697	RESERVED	698	RESERVED	699	RESERVED

RN2903

Table 1-1 describes the module's pins.

TABLE 1-1: PIN DESCRIPTION

Pin	Name	Type	Description
1	GND	Power	Ground supply terminal
2	UART_RTS	Output	Communication UART RTS signal ⁽¹⁾
3	UART_CTS	Input	Communication UART CTS signal ⁽¹⁾
4	RESERVED	—	Do not connect
5	RESERVED	—	Do not connect
6	UART_TX	Output	Communication UART Transmit (TX)
7	UART_RX	Input	Communication UART Receive (RX)
8	GND	Power	Ground supply terminal
9	GPIO13	Input/Output	General purpose I/O pin
10	GPIO12	Input/Output	General purpose I/O pin
11	GND	Power	Ground supply terminal
12	VDD	Power	Positive supply terminal
13	GPIO11	Input/Output	General purpose I/O pin
14	GPIO10	Input/Output	General purpose I/O pin
15	NC	—	Not connected
16	NC	—	Not connected
17	NC	—	Not connected
18	NC	—	Not connected
19	NC	—	Not connected
20	GND	Power	Ground supply terminal
21	GND	Power	Ground supply terminal
22	GND	Power	Ground supply terminal
23	RF	RF analog	RF signal pin
24	GND	Power	Ground supply terminal
25	NC	—	Not connected
26	GND	Power	Ground supply terminal
27	GND	Power	Ground supply terminal
28	GND	Power	Ground supply terminal
29	NC	—	Not connected
30	TEST0	—	Do not connect
31	TEST1	—	Do not connect
32	RESET	Input	Active-low device Reset input
33	GND	Power	Ground supply terminal
34	VDD	Power	Positive supply terminal
35	GPIO0	Input/Output	General purpose I/O pin
36	GPIO1	Input/Output	General purpose I/O pin
37	GPIO2	Input/Output	General purpose I/O pin
38	GPIO3	Input/Output	General purpose I/O pin
39	GPIO4	Input/Output	General purpose I/O pin
40	GPIO5	Input/Output	General purpose I/O pin
41	GND	Power	Ground supply terminal
42	NC	—	Not connected
43	GPIO6	Input/Output	General purpose I/O pin

TABLE 1-1: PIN DESCRIPTION (CONTINUED)

Pin	Name	Type	Description
44	GPIO7	Input/Output	General purpose I/O pin
45	GPIO8	Input/Output	General purpose I/O pin
46	GPIO9	Input/Output	General purpose I/O pin
47	GND	Power	Ground supply terminal

Note 1: Optional handshake lines are supported in future firmware releases.

2.0 GENERAL SPECIFICATIONS

Table 2-1 provides the general specifications for the module. Table 2-2 and Table 2-3 provide the module's electrical characteristics and current consumption. Table 2-4 and Table 2-5 show the module's dimensions and the RF output power calibration data.

TABLE 2-1: GENERAL SPECIFICATIONS

Specification	Description
Frequency Band	902.000 MHz to 928.000 MHz
Modulation Method	FSK, GFSK and LoRa™ Technology modulation
Maximum Over-the-Air Data Rate	300 kbps with FSK modulation; 12500 bps with LoRa Technology modulation
RF connection	Board edge connection
Interface	UART
Operation Range	>15 km coverage at suburban; >5 km coverage at urban area
Sensitivity at 0.1% BER	-148 dBm ⁽¹⁾
RF TX Power	Adjustable up to max. 20 dBm on 915 MHz band ⁽²⁾
Temperature (operating)	-40°C to +85°C
Temperature (storage)	-40°C to +115°C
Humidity	10% ~ 90% non-condensing

Note 1: Depends on modulation. Expand Spreading Factor (SF).

2: TX power is adjustable. For more information, refer to the "RN2903 LoRa™ Technology Module Command Reference User's Guide" (DS40000000A).

TABLE 2-2: ELECTRICAL CHARACTERISTICS

Parameter	Min.	Typ.	Max.	Units
Supply Voltage	2.1	—	3.6	V
Voltage on any pin with respect to VSS (except VDD)	-0.3	—	VDD + 0.3	V
Voltage on VDD with respect to VSS	-0.3	—	3.9	V
Input Clamp Current (IIK) (VI < 0 or VI > VDD)	—	—	+/-20	mA
Output Clamp Current (IOK) (VO < 0 or VO > VDD)	—	—	+/-20	mA
GPIO sink/source current each	—	—	25/25	mA
Total GPIO sink/source current	—	—	200/185	mA
RAM Data Retention Voltage (in Sleep mode or Reset state)	1.5	—	—	V
VDD Start Voltage to ensure internal Power-on Reset signal	—	—	0.7	V
VDD Rise Rate to ensure internal Power-on Reset signal	0.05	—	—	V/ms
Brown-out Reset Voltage	1.75	1.9	2.05	V
Logic Input Low Voltage	—	—	0.15 x VDD	V
Logic Input High Voltage	0.8 x VDD	—	—	V
Input Leakage at <25°C (VSS<VPIN<VDD, Pin at high-impedance)	—	0.1	50	nA
Input Leakage at +60°C (VSS<VPIN<VDD, Pin at high-impedance)	—	0.7	100	nA
Input Leakage at +85°C (VSS<VPIN<VDD, Pin at high-impedance)	—	4	200	nA
RF Input Level	—	—	+10	dBm

TABLE 2-3: CURRENT CONSUMPTION

Mode	Typical Current at 3V (mA)
Idle	2.7
RX	13.5
Deep Sleep	0.022

TABLE 2-4: MODULE DIMENSIONS

Parameter	Value
Dimensions	17.8 x 26.7 x 3 mm
Weight	2.05g


TABLE 2-5: OUTPUT POWER OF TX POWER SETTING

TX Power Setting	Output Power (dBm)	Typical Supply Current at 3V (mA)
2	3.0	42.6
3	4.0	44.8
4	5.0	47.3
5	6.0	49.6
6	7.0	52.0
7	8.0	55.0
8	9.0	57.7
9	10.0	61.0
10	11.0	64.8
11	12.0	73.1
12	13.0	78.0
14	14.7	83.0
15	15.5	88.0
16	16.3	95.8
17	17.0	103.6
20	18.5	124.4

3.0 TYPICAL HARDWARE CONNECTIONS

Figure 3-1 shows the typical hardware connections.

FIGURE 3-1: HARDWARE CONNECTIONS



3.1 INTERFACE TO HOST MCU

The RN2903 module has a dedicated UART interface to communicate with a host controller. Optional handshake lines are supported in future firmware releases. The “RN2903 LoRa™ Technology Module Command Reference User’s Guide” (DS40000000A) provides a detailed UART command description. Table 3-1 shows the default settings for the UART communication.

TABLE 3-1: DEFAULT UART SETTINGS

Specification	Description
Baud Rate	57600 bps
Packet Length	8 bit
Parity Bit	No
Stop Bits	1 bit
Hardware Flow Control	No

3.2 GPIO PINS (GPIO1–GPIO14)

The module has 14 GPIO pins. These lines can be connected to switches, LEDs, and relay outputs. The pins are either logic inputs or outputs that can be accessed via the module firmware. These pins have limited sink and source capabilities. The current firmware release only supports output function on all GPIOs. Electrical characteristics are described in Table 2-2.

3.3 RF CONNECTION

When routing RF path, use proper strip lines with an impedance of 50 Ohm.

3.4 RESET PIN

The module’s reset pin is an active-low logic input.

3.5 POWER PINS

It is recommended to connect power pins (Pin 12 and 34) to a stable supply voltage with sufficient source current. Table 2-2 shows the current consumption.

Additional filtering capacitors are not required but can be used to ensure stable supply voltage in noisy environment.

4.0 PHYSICAL DIMENSIONS

Figure 4-1 and Figure 4-2 illustrate the physical dimensions and the recommended PCB layout for the RN2903 module.

FIGURE 4-1: RN2903 PHYSICAL DIMENSIONS





FIGURE 4-2: RECOMMENDED PCB FOOTPRINT




5.0 APPLICATION INFORMATION

5.1 RF pins and strip line

The RF signals must be routed with properly terminated 50 Ohm strip lines. Use curves instead of sharp corners. Keep the routing path as short as possible. [Figure 5.3](#) shows a routing example.

FIGURE 5-1: RF ROUTING (EXAMPLE)



5.2 Approved Antennas

Modular certification of the RN2903 module was performed with the external antenna type mentioned in [Table 5-1](#). Refer to [Section 6.0 "Regulatory Approval"](#) for specific regulatory requirements by country.


TABLE 5-1: TESTED EXTERNAL ANTENNA TYPES

Type	Gain (dBi)
Dipole	6
Chip Antenna	-1

5.3 APPLICATION SCHEMATIC

Figure 5-2 shows the schematic for the RN2903 PICTail™/PICTail Plus Daughter Board.

FIGURE 5-2: PICTAIL™/PICTAIL PLUS DAUGHTER BOARD SCHEMATIC



6.0 REGULATORY APPROVAL

This section outlines the regulatory information for the RN2903 module for the following countries:

- United States
- Canada
- Australia
- New Zealand

6.1 United States

The RN2903 module has received Federal Communications Commission (FCC) CFR47 Telecommunications, Part 15 Subpart C "Intentional Radiators" modular approval in accordance with Part 15.212 Modular Transmitter approval. Modular approval allows the end user to integrate the RN2903 module into a finished product without obtaining subsequent and separate FCC approvals for intentional radiation, provided no changes or modifications are made to the module circuitry. Changes or modifications could void the user's authority to operate the equipment. The end user must comply with all of the instructions provided by the Grantee, which indicate installation and/or operating conditions necessary for compliance.

The finished product is required to comply with all applicable FCC equipment authorizations regulations, requirements and equipment functions not associated with the transmitter module portion. For example, compliance must be demonstrated to regulations for other transmitter components within the host product; to requirements for unintentional radiators (Part 15 Subpart B "Unintentional Radiators"), such as digital devices, computer peripherals, radio receivers, etc.; and to additional authorization requirements for the non-transmitter functions on the transmitter module (i.e., Verification, or Declaration of Conformity) (e.g., transmitter modules may also contain digital logic functions) as appropriate.

6.1.1 LABELING AND USER INFORMATION REQUIREMENTS

The RN2903 module has been labeled with its own FCC ID number, and if the FCC ID is not visible when the module is installed inside another device, then the outside of the finished product into which the module is installed must also display a label referring to the enclosed module. This exterior label can use wording as follows: Label for LoRa and BLE Modules

Contains FCC ID: W3I281333888668
Contains FCC ID: WAP4008

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

A user's manual for the finished product should include the following statement:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy, and if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Additional information on labeling and user information requirements for Part 15 devices can be found in KDB Publication 784748 available at the FCC Office of Engineering and Technology (OET) Laboratory Division Knowledge Database (KDB)

6.1.2 RF EXPOSURE

All transmitters regulated by FCC must comply with RF exposure requirements. KDB 447498 General RF Exposure Guidance provides guidance in determining whether proposed or existing transmitting facilities, operations or devices comply with limits for human exposure to Radio Frequency (RF) fields adopted by the Federal Communications Commission (FCC).

From the RN2903 FCC Grant: Output power listed is conducted. This grant is valid only when the module is sold to OEM integrators and must be installed by the OEM or OEM integrators. This transmitter is restricted for use with the specific antenna(s) tested in this application for Certification and must not be co-located or operating in conjunction with any other antenna or transmitters within a host device, except in accordance with FCC multi-transmitter product procedures.

6.1.3 APPROVED EXTERNAL ANTENNA TYPES

To maintain modular approval in the United States, only the antenna types that have been tested shall be used. It is permissible to use different antenna manufacturer provided the same antenna type and antenna gain (equal to or less than) is used.

Testing of the RN2903 module was performed with the antenna types listed in [Table 5-1](#) Tested External Antenna Types.

6.1.4 HELPFUL WEB SITES

Federal Communications Commission (FCC):
<http://www.fcc.gov>

FCC Office of Engineering and Technology (OET) Laboratory Division Knowledge Database (KDB):
<https://apps.fcc.gov/oetcf/kdb/index.cfm>.

6.2 Canada

The RN2903 module has been certified for use in Canada under Industry Canada (IC) Radio Standards Specification (RSS) RSS-210 and RSS-Gen. Modular approval permits the installation of a module in a host device without the need to recertify the device.

6.2.1 LABELING AND USER INFORMATION REQUIREMENTS

Labeling Requirements for the Host Device (from Section 3.2.1, RSS-Gen, Issue 5, March 2019):
 The host device shall be properly labeled to identify the module within the host device.

The Industry Canada certification label of a module shall be clearly visible at all times when installed in the host device, otherwise the host device must be labeled to display the Industry Canada certification number of

the module, preceded by the words "Contains transmitter module", or the word "Contains", or similar wording expressing the same meaning, as follows:

Contains transmitter module IC: 8266A-28133388868.

User Manual Notice for License-Exempt Radio Apparatus (from Section 7.1.3 RSS-Gen, Issue 5, User manuals for license-exempt radio apparatus shall contain the following or equivalent notice in a conspicuous location in the user manual or alternatively on the device or both:

This device complies with Industry Canada license-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes: (1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

Transmitter Antenna (from Section 7.1.2 RSS-Gen, Issue 5 (March 2019) User manuals for transmitters shall display the following notice in a conspicuous location:

Under Industry Canada regulations, this radio transmitter may only operate using an antenna of a type and maximum (or lesser) gain approved for the transmitter by Industry Canada. To reduce potential radio interference to other users, the antenna type and its gain should be so chosen that the equivalent isotropically radiated power (e.i.r.p.) is not more than that necessary for successful communication.

Conformément à la réglementation d'Industrie Canada, le présent émetteur radio peut fonctionner avec une antenne d'un type et d'un gain maximal (ou inférieur) approuvé pour l'émetteur par Industrie Canada. Dans le but de réduire les risques de brouillage radioélectrique à l'intention des autres utilisateurs, il faut choisir le type d'antenne et son gain de sorte que la puissance isotrope rayonnée équivalente (p.i.r.e.) ne dépasse pas l'intensité nécessaire à l'établissement d'une communication satisfaisante.

The above notice may be affixed to the device instead of displayed in the user manual.

User manuals for transmitters equipped with detachable antennas shall also contain the following notice in a conspicuous location:

This radio transmitter (identify the device by certification number, or model number if Category II) has been approved by Industry Canada to operate with the antenna types listed below with the maximum permissible gain and required antenna impedance for each antenna type indicated. Antenna types not included in this list, having a gain greater than the maximum gain indicated for that type, are strictly prohibited for use with this device.

Conformément à la réglementation d'Industrie Canada, le présent émetteur radio peut fonctionner avec une antenne d'un type et d'un gain maximal (ou inférieur) approuvé pour l'émetteur par Industrie Canada. Dans le but de réduire les risques de brouillage radioélectrique à l'intention des autres utilisateurs, il faut choisir le type d'antenne et son gain de sorte que la puissance isotrope rayonnée équivalente (p.i.r.e.) ne dépasse pas l'intensité nécessaire à l'établissement d'une communication satisfaisante.

Immediately following the above notice, the manufacturer shall provide a list of all antenna types approved for use with the transmitter, indicating the maximum permissible antenna gain (in dBi) and required impedance for each.

6.2.2 APPROVED EXTERNAL ANTENNA TYPES

Transmitter Antenna (from Section 7.1.2 RSS-Gen, Issue 5, March 2019):

The RN2903 module can only be sold or operated with antennas with which it was approved. Transmitter may be approved with multiple antenna types. An antenna type comprises antennas having similar in-band and out-of-band radiation patterns. Testing shall be performed using the highest gain antenna of each combination of transmitter and antenna type for which approval is being sought, with the transmitter output power set at the maximum level. Any antenna of the same type having equal or lesser gain as an antenna that had been successfully tested with the transmitter, will also be considered approved with the transmitter, and may be used and marketed with the transmitter.

When a measurement at the antenna connector is used to determine RF output power, the effective gain of the device's antenna shall be stated, based on measurement or on data from the antenna manufacturer. For transmitters of output power greater than 10 milliwatts, the total antenna gain shall be added to the measured RF output power to demonstrate compliance to the specified radiated power limits.

Testing of the RN2903 module was performed with the antenna types listed in [Table 5-1 Tested External Antenna Types](#).

6.2.3 HELPFUL WEB SITES

Industry Canada: <http://www.ic.gc.ca/>

6.3 Australia

RN2903 module RF transmitter test reports can be used in part to demonstrate compliance in accordance with ACMA Radio communications "Short Range Devices" Standard 2004 (The Short Range Devices standard calls up the AS/NZS 4268:2008 industry standard). The MRF89XAM9A module test reports can be used as part of the product certification and compliance folder. For more information on the RF transmitter test reports, contact Microchip Technology Australia office.

AS/NZS 4268:2008 refers to the USA FCC 15.247 RF standards, the frequency limits of 915 - 928 MHz apply in Australia.

To meet overall Australian end product compliance, the integrator must construct a compliance folder containing all relevant compliance test reports e.g. RF, EMC, electrical safety and DoC (Declaration of Conformity) etc. It is the responsibility of the integrator to know what is required in the compliance folder for ACMA compliance. For more information on Australia compliance, refer to the Australian Communications and Media Authority web site <http://www.acma.gov.au/>.

6.3.1 HELPFUL WEB SITES

The Australian Communications and Media Authority: <http://www.acma.gov.au/>.

6.4 New Zealand

RN2903 module RF transmitter test reports can be used in part to demonstrate compliance against the New Zealand "General User Radio License for Short Range Devices". New Zealand Radio communications (Radio Standards) Notice 2010 calls up the AS / NZS 4268:2008 industry standard. The RN2903 module test reports can be used as part of the product certification and compliance folder. For more information on the RF transmitter test reports, contact Microchip Technology.

Information on the New Zealand short range devices license can be found in the following web links:

<http://www.rsm.govt.nz/cms/licensees/types-of-licence/general-user-licences/short-range-devices>

and

<http://www.rsm.govt.nz/about-rsm/spectrum-policy>

While the AS /NZS 4268:2008 refers to the USA FCC 15.247 and EN 300 220-1 V2.3.1 RF standards, the frequency limits of 921 MHz to 928 MHz apply in New Zealand.

To meet overall New Zealand end product compliance, the developer must construct a compliance folder containing all relevant compliance test reports e.g. RF, EMC, electrical safety and DoC (Declaration of Conformity) etc. It is the responsibility of the developer to know what is required in the compliance folder for New Zealand Radio communications. For more information on New Zealand compliance, refer to the web site <http://www.rsm.govt.nz/>.

6.4.1 HELPFUL WEB SITES

Radio Spectrum Ministry of Economic Development:
<http://www.rsm.govt.nz/>.

RN2903

NOTES:

APPENDIX A: REVISION HISTORY**Revision A (June 2015)**

This is the initial release of this document.

RN2903

NOTES:

THE MICROCHIP WEB SITE

Microchip provides online support via our WWW site at www.microchip.com. This web site is used as a means to make files and information easily available to customers. Accessible by using your favorite Internet browser, the web site contains the following information:

- **Product Support** – Data sheets and errata, application notes and sample programs, design resources, user's guides and hardware support documents, latest software releases and archived software
- **General Technical Support** – Frequently Asked Questions (FAQ), technical support requests, online discussion groups, Microchip consultant program member listing
- **Business of Microchip** – Product selector and ordering guides, latest Microchip press releases, listing of seminars and events, listings of Microchip sales offices, distributors and factory representatives

CUSTOMER CHANGE NOTIFICATION SERVICE

Microchip's customer notification service helps keep customers current on Microchip products. Subscribers will receive e-mail notification whenever there are changes, updates, revisions or errata related to a specified product family or development tool of interest.

To register, access the Microchip web site at www.microchip.com. Under "Support", click on "Customer Change Notification" and follow the registration instructions.

CUSTOMER SUPPORT

Users of Microchip products can receive assistance through several channels:

- Distributor or Representative
- Local Sales Office
- Field Application Engineer (FAE)
- Technical Support

Customers should contact their distributor, representative or Field Application Engineer (FAE) for support. Local sales offices are also available to help customers. A listing of sales offices and locations is included in the back of this document.

Technical support is available through the web site at: <http://microchip.com/support>

RN2903

NOTES:

PRODUCT IDENTIFICATION SYSTEM

To order or obtain information, e.g., on pricing or delivery, refer to the factory or the listed sales office.

<u>PART NO.</u>		<u>RM</u>	<u>XXX</u>	Examples:
Device	Temperature Range	Package	Firmware Revision Number	RN2903-I/RM: Industrial temperature
Device: RN2903: Low-Power Long Range LoRa™ Technology Transceiver module				
Temperature Range: I = -40°C to +85°C (Industrial)				
Package: RM = Radio Module				

RN2903

NOTES:

Note the following details of the code protection feature on Microchip devices:

- Microchip products meet the specification contained in their particular Microchip Data Sheet.
- Microchip believes that its family of products is one of the most secure families of its kind on the market today, when used in the intended manner and under normal conditions.
- There are dishonest and possibly illegal methods used to breach the code protection feature. All of these methods, to our knowledge, require using the Microchip products in a manner outside the operating specifications contained in Microchip's Data Sheets. Most likely, the person doing so is engaged in theft of intellectual property.
- Microchip is willing to work with the customer who is concerned about the integrity of their code.
- Neither Microchip nor any other semiconductor manufacturer can guarantee the security of their code. Code protection does not mean that we are guaranteeing the product as "unbreakable."

Code protection is constantly evolving. We at Microchip are committed to continuously improving the code protection features of our products. Attempts to break Microchip's code protection feature may be a violation of the Digital Millennium Copyright Act. If such acts allow unauthorized access to your software or other copyrighted work, you may have a right to sue for relief under that Act.

Information contained in this publication regarding device applications and the like is provided only for your convenience and may be superseded by updates. It is your responsibility to ensure that your application meets with your specifications. **MICROCHIP MAKES NO REPRESENTATIONS OR WARRANTIES OF ANY KIND WHETHER EXPRESS OR IMPLIED, WRITTEN OR ORAL, STATUTORY OR OTHERWISE, RELATED TO THE INFORMATION, INCLUDING BUT NOT LIMITED TO ITS CONDITION, QUALITY, PERFORMANCE, MERCHANTABILITY OR FITNESS FOR PURPOSE.** Microchip disclaims all liability arising from this information and its use. Use of Microchip devices in life support and/or safety applications is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless Microchip from any and all damages, claims, suits, or expenses resulting from such use. No licenses are conveyed, implicitly or otherwise, under any Microchip intellectual property rights.

Trademarks

The Microchip name and logo, the Microchip logo, dsPIC, FlashFlex, flexPWR, JukeBlox, KEELOQ, KEELOQ logo, Kleer, LANCheck, MediaLB, MOST, MOST logo, MPLAB, OptoLyzer, PIC, PICSTART, PIC³² logo, RightTouch, SpyNIC, SST, SST Logo, SuperFlash and UNI/O are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

The Embedded Control Solutions Company and mTouch are registered trademarks of Microchip Technology Incorporated in the U.S.A.

Analog-for-the-Digital Age, BodyCom, chipKIT, chipKIT logo, CodeGuard, dsPICDEM, dsPICDEM.net, ECAN, In-Circuit Serial Programming, ICSP, Inter-Chip Connectivity, KleerNet, KleerNet logo, MiWi, MPASM, MPF, MPLAB Certified logo, MPLIB, MPLINK, MultiTRAK, NetDetach, Omniscient Code Generation, PICDEM, PICDEM.net, PICkit, PICtail, RightTouch logo, REAL ICE, SQL, Serial Quad I/O, Total Endurance, TSHARC, USBCheck, VariSense, ViewSpan, WiperLock, Wireless DNA, and ZENA are trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

SQTP is a service mark of Microchip Technology Incorporated in the U.S.A.

Silicon Storage Technology is a registered trademark of Microchip Technology Inc. in other countries.

GestIC is a registered trademark of Microchip Technology Germany II GmbH & Co. KG, a subsidiary of Microchip Technology Inc., in other countries.

All other trademarks mentioned herein are property of their respective companies.

© 2015, Microchip Technology Incorporated, Printed in the U.S.A., All Rights Reserved.

ISBN:

Microchip received ISO/TS-16949:2009 certification for its worldwide headquarters, design and wafer fabrication facilities in Chandler and Tempe, Arizona; Gresham, Oregon and design centers in California and India. The Company's quality system processes and procedures are for its PIC® MCUs and dsPIC® DSCs, KEELOQ® code hopping devices, Serial EEPROMs, microperipherals, nonvolatile memory and analog products. In addition, Microchip's quality system for the design and manufacture of development systems is ISO 9001:2000 certified.

**QUALITY MANAGEMENT SYSTEM
CERTIFIED BY DNV
== ISO/TS 16949 ==**



MICROCHIP

Worldwide Sales and Service

AMERICAS

Corporate Office
2355 West Chandler Blvd.
Chandler, AZ 85224-6199
Tel: 480-792-7200
Fax: 480-792-7277
Technical Support:
<http://www.microchip.com/support>
Web Address:
www.microchip.com

Atlanta

Duluth, GA
Tel: 678-957-9614
Fax: 678-957-1455

Austin, TX

Tel: 512-257-3370

Boston

Westborough, MA
Tel: 774-760-0087
Fax: 774-760-0088

Chicago

Itasca, IL
Tel: 630-285-0071
Fax: 630-285-0075

Cleveland

Independence, OH
Tel: 216-447-0464
Fax: 216-447-0643

Dallas

Addison, TX
Tel: 972-818-7423
Fax: 972-818-2924

Detroit

Novi, MI
Tel: 248-848-4000

Houston, TX

Tel: 281-894-5983

Indianapolis

Noblesville, IN
Tel: 317-773-8323
Fax: 317-773-5453

Los Angeles

Mission Viejo, CA
Tel: 949-462-9523
Fax: 949-462-9608

New York, NY

Tel: 631-435-6000

San Jose, CA

Tel: 408-735-9110

Canada - Toronto

Tel: 905-673-0699
Fax: 905-673-6509

ASIA/PACIFIC

Asia Pacific Office
Suites 3707-14, 37th Floor
Tower 6, The Gateway
Harbour City, Kowloon
Hong Kong
Tel: 852-2943-5100
Fax: 852-2401-3431
Australia - Sydney
Tel: 61-2-9868-6733
Fax: 61-2-9868-6755

China - Beijing
Tel: 86-10-8569-7000
Fax: 86-10-8528-2104
China - Chengdu
Tel: 86-28-8665-5511
Fax: 86-28-8665-7889

China - Chongqing
Tel: 86-23-8980-9588
Fax: 86-23-8980-9500
China - Dongguan
Tel: 86-769-8702-9880
China - Hangzhou
Tel: 86-571-8792-8115
Fax: 86-571-8792-8116

China - Hong Kong SAR
Tel: 852-2943-5100
Fax: 852-2401-3431
China - Nanjing
Tel: 86-25-8473-2460
Fax: 86-25-8473-2470
China - Qingdao
Tel: 86-532-8502-7355
Fax: 86-532-8502-7205

China - Shanghai
Tel: 86-21-5407-5533
Fax: 86-21-5407-5066
China - Shenyang
Tel: 86-24-2334-2829
Fax: 86-24-2334-2393
China - Shenzhen
Tel: 86-755-8864-2200
Fax: 86-755-8203-1760

China - Wuhan
Tel: 86-27-5980-5300
Fax: 86-27-5980-5118
China - Xian
Tel: 86-29-8833-7252
Fax: 86-29-8833-7256

ASIA/PACIFIC

China - Xiamen
Tel: 86-592-2388138
Fax: 86-592-2388130
China - Zhuhai
Tel: 86-756-3210040
Fax: 86-756-3210049

India - Bangalore
Tel: 91-80-3090-4444
Fax: 91-80-3090-4123
India - New Delhi
Tel: 91-11-4160-8631
Fax: 91-11-4160-8632

India - Pune
Tel: 91-20-3019-1500
Japan - Osaka
Tel: 81-6-6152-7160
Fax: 81-6-6152-9310
Japan - Tokyo
Tel: 81-3-6880-3770
Fax: 81-3-6880-3771

Korea - Daegu
Tel: 82-53-744-4301
Fax: 82-53-744-4302
Korea - Seoul
Tel: 82-2-554-7200
Fax: 82-2-558-5932 or
82-2-558-5934

Malaysia - Kuala Lumpur
Tel: 60-3-6201-9857
Fax: 60-3-6201-9859

Malaysia - Penang
Tel: 60-4-227-8870
Fax: 60-4-227-4068
Philippines - Manila
Tel: 63-2-634-9065
Fax: 63-2-634-9069

Singapore
Tel: 65-6334-8870
Fax: 65-6334-8850
Taiwan - Hsin Chu
Tel: 886-3-5778-366

Taiwan - Kaohsiung
Tel: 886-3-5770-955
Taiwan - Taipei
Tel: 886-2-2508-8600
Fax: 886-2-2508-0102

Thailand - Bangkok
Tel: 66-2-694-1351
Fax: 66-2-694-1350

EUROPE

Austria - Wels
Tel: 43-7242-2244-39
Fax: 43-7242-2244-393

Denmark - Copenhagen
Tel: 45-4450-2828
Fax: 45-4485-2829

France - Paris
Tel: 33-1-69-53-63-20
Fax: 33-1-69-30-90-79

Germany - Dusseldorf
Tel: 49-2129-3766400

Germany - Munich
Tel: 49-89-627-144-0
Fax: 49-89-627-144-44

Germany - Pforzheim
Tel: 49-7231-424750

Italy - Milan
Tel: 39-0331-742611
Fax: 39-0331-466781

Italy - Venice
Tel: 39-049-7625286

Netherlands - Drunen
Tel: 31-416-690399
Fax: 31-416-690340

Poland - Warsaw
Tel: 48-22-3325737

Spain - Madrid
Tel: 34-91-708-08-90
Fax: 34-91-708-08-91

Sweden - Stockholm
Tel: 46-8-5090-4654

UK - Wokingham
Tel: 44-118-921-5800
Fax: 44-118-921-5820