

## RF Exposure Report

**Report No.:** SA160407E10A

**FCC ID:** WBV-AP550

**Test Model:** AP550

**Received Date:** Apr. 07, 2016

**Test Date:** May 04 ~ Jun. 22, 2016

**Issued Date:** Jun. 29, 2016

**Applicant:** Aerohive Networks Inc.

**Address:** 1011 McCarthy Blvd, Milpitas, CA 95035, USA

**Issued By:** Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch

**Lab Address:** E-2, No.1, Li Hsin 1st Road, Hsinchu Science Park, Hsinchu City 300, Taiwan R.O.C.

**Test Location (1):** E-2, No.1, Li Hsin 1st Road, Hsinchu Science Park, Hsinchu City 300, Taiwan R.O.C.

**Test Location (2):** No. 49, Ln. 206, Wende Rd., Shangshan Tsuen, Chiung Lin Hsiang, Hsin Chu Hsien 307, Taiwan R.O.C.



This report is for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specific mention, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification. The report must not be used by the client to claim product certification, approval, or endorsement by TAF or any government agencies.

## Table of Contents

<b>Release Control Record</b> .....	<b>3</b>
<b>1      Certificate of Conformity</b> .....	<b>4</b>
<b>2      RF Exposure</b> .....	<b>5</b>
2.1    Limits for Maximum Permissible Exposure (MPE).....	5
2.2    MPE Calculation Formula .....	5
2.3    Classification .....	5
<b>3      Calculation Result of Maximum Conducted Power</b> .....	<b>6</b>

### Release Control Record

Issue No.	Description	Date Issued
SA160407E10A	Original release	Jun. 29, 2016

## 1 Certificate of Conformity

**Product:** Access Point

**Brand:** Aerohive

**Test Model:** AP550

**Sample Status:** Engineering sample

**Applicant:** Aerohive Networks Inc.

**Test Date:** May 04 ~ Jun. 22, 2016

**Standards:** FCC Part 2 (Section 2.1091)

KDB 447498 D01 (October 23, 2015)

IEEE C95.1

The above equipment has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's EMC characteristics under the conditions specified in this report.

**Prepared by :** Celine Chou, **Date:** Jun. 29, 2016  
Celine Chou / Specialist

**Approved by :** May Chen, **Date:** Jun. 29, 2016  
May Chen / Manager

## 2 RF Exposure

### 2.1 Limits for Maximum Permissible Exposure (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm <sup>2</sup> )	Average Time (minutes)
Limits For General Population / Uncontrolled Exposure				
300-1500	...	...	F/1500	30
1500-100,000	...	...	1.0	30

F = Frequency in MHz

### 2.2 MPE Calculation Formula

$$Pd = (Pout * G) / (4 * \pi * r^2)$$

where

Pd = power density in mW/cm<sup>2</sup>

Pout = output power to antenna in mW

G = gain of antenna in linear scale

Pi = 3.1416

R = distance between observation point and center of the radiator in cm

### 2.3 Classification

The antenna of this product, under normal use condition, is at least 37cm away from the body of the user. So, this device is classified as **Mobile Device**.

### 3 Calculation Result of Maximum Tune up Power

Frequency Band (MHz)	Max Tune up Power per chain (dBm)	Max total Tune up Power (dBm)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm <sup>2</sup> )	Limit (mW/cm <sup>2</sup> )
Radio 1						
2412-2462	22.00	28.02	9.80	37	0.352	1
5180-5240	20.00	26.02	11.71	37	0.345	1
5260-5320	16.00	22.02	11.69	37	0.137	1
5500-5720	18.00	24.02	11.55	37	0.210	1
5745-5825	22.00	28.02	11.81	37	0.559	1
Radio 2						
5180-5240	20.00	26.02	11.40	37	0.321	1
5260-5320	16.00	22.02	11.58	37	0.133	1
5500-5720	18.00	24.02	11.62	37	0.213	1
5745-5825	22.00	28.02	11.70	37	0.545	1
Radio 3						
BT EDR	5.00	5.00	5.83	37	0.001	1
BT LE	9.00	9.00	5.83	37	0.002	1

Note:

Radio 1

2412-2462MHz: Directional gain =  $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/4] = 9.80 \text{dBi}$

5180-5240MHz: Directional gain =  $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/4] = 11.71 \text{dBi}$

5260-5320MHz: Directional gain =  $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/4] = 11.69 \text{dBi}$

5500-5700MHz: Directional gain =  $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/4] = 11.55 \text{dBi}$

5745-5825MHz: Directional gain =  $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/4] = 11.81 \text{dBi}$

Radio 2

5180-5240MHz: Directional gain =  $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/4] = 11.40 \text{dBi}$

5260-5320MHz: Directional gain =  $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/4] = 11.58 \text{dBi}$

5500-5700MHz: Directional gain =  $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/4] = 11.62 \text{dBi}$

5745-5825MHz: Directional gain =  $10 \log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2/4] = 11.70 \text{dBi}$

Radio 3

BT EDR/BT LE: Gain = 5.83dB

**CONCLUSION:**

Both of the Radio 1 & Radio 2 & Radio 3 can transmit simultaneously, but Radio 1 & Radio 2 will not simultaneously in the same sub-band, the formula of calculated the MPE is:

$$CPD1 / LPD1 + CPD2 / LPD2 + \dots \text{etc.} < 1$$

CPD = Calculation power density

LPD = Limit of power density

**Mode 1:**

Radio 1 2.4G (2412-2462MHz) & Radio 2 5G (5745-5825MHz) & Radio 3 BT LE is  $0.352/1 + 0.545/1 + 0.002/1 = 0.899$ , which is less than "1".

**Mode 2:**

Radio 1 5G (5180-5240MHz) & Radio 2 5G (5745-5825MHz) & Radio 3 BT LE is  $0.345/1 + 0.545/1 + 0.002/1 = 0.892$ , which is less than "1".

**Mode 3:**

Radio 1 5G (5745-5825MHz) & Radio 2 5G (5180-5240MHz) & Radio 3 BT LE is  $0.559/1 + 0.321/1 + 0.002/1 = 0.882$ , which is less than "1".

This confirmed that the device comply with FCC 1.1310 MPE limit.

**---END---**