

December 25, 2008

Gadget Lab International Co., Ltd. 21K, Building 5, Time City Tower, Chuangye Road, Nanshan District Shenzhen, China

Dear Victor Chen:

Enclosed you will find your file copy of a Part 15 report (FCC ID: WVDMECHRC001A).

For your reference, TCB will normally take another 15-20 days for reviewing the report. Approval will then be granted when no query is sorted.

Please contact me if you have any questions regarding the enclosed material.

Sincerely,

Shawn Xing

**Assistant Manager** 

**Enclosure** 



### Gadget Lab International Co., Ltd.

Application
For
Certification
(FCC ID: WVDMECHRC001A)

**Computer Peripheral** 

Birly li

SZ08110084-1 Billy Li December 25, 2008

- The test results reported in this test report shall refer only to the sample actually tested and shall not refer or be deemed to refer to bulk from which such a sample
  may be said to have been obtained.
- This report is for the exclusive use of Intertek's Client and is provided pursuant to the agreement between Intertek and its Client. Intertek's responsibility and liability are limited to the terms and conditions of the agreement. Intertek assumes no liability to any party, other than to the Client in accordance with the agreement, for any loss, expense or damage occasioned by the use of this report. Only the Client is authorized to copy or distribute this report. Any use of the Intertek name or one of its marks for the sale or advertisement of the tested material, product or service must first be approved in writing by Intertek. The observations and test results referenced from this report are relevant only to the sample tested. This report by itself does not imply that the material, product, or service is or has ever been under an Intertek certification program.
- For Terms And Conditions of the services, it can be provided upon request.
- The evaluation data of the report will be kept for 3 years from the date of issuance.

TRF no.: FCC 15C\_PC\_a FCC ID: WVDMECHRC001A

#### **LIST OF EXHIBITS**

#### INTRODUCTION

EXHIBIT 1: General Description

EXHIBIT 2: System Test Configuration

EXHIBIT 3: Emission Results

EXHIBIT 4: Equipment Photographs

EXHIBIT 5: Product Labeling

EXHIBIT 6: Technical Specifications

EXHIBIT 7: Instruction Manual

EXHIBIT 8: Miscellaneous Information

i

TRF no.: FCC 15C\_PC\_a

#### **MEASUREMENT / TECHNICAL REPORT**

Gadget Lab International Co., Ltd. – MODEL: MRC001A

**FCC ID: WVDMECHRC001A** 

**December 25, 2008** 

This report concerns (check one:)	Original Grant X	Class II	Change	
Equipment Type: Class B Computing modem, etc.)	Device Peripheral (e	example: cor	nputer, prin	ter,
Deferred grant requested per 47 CFR 0.	457(d)(1)(ii)?	Yes	No	X
	If yes, defer u	ıntil:		
	•		date	
Company Name agrees to notify the Cor	mmission by:			
	,	date		
of the intended date of announcement of	of the product so that	the grant ca	n be issued	on
that date.				
Transition Rules Request per 15.37?		Yes	No	X
		<u> </u>		
Transition Rules Request per 15.37?  If no, assumed Part 15, Subpart C for		<u> </u>		

TRF no.: FCC 15C\_PC\_a

## **Table of Contents**

1.0	Ger	neral Description	2
	1.1	Product Description	
	1.2	Related Submittal(s) Grants	
	1.3		
	1.4	Test Facility	
2.0	Sys	stem Test Configuration	5
	2.1	Justification	
	2.2	EUT Exercising Software	5
	2.3	Special Accessories	5
	2.4	Equipment Modification	5
	2.5	Measurement Uncertainty	6
	2.6	Support Equipment List and Description	
3.0	Emi	ssion Results	8
	3.1	Field Strength Calculation	9
		Radiated Emission Configuration Photograph	
		Radiated Emission Data	
		Conducted Emission Configuration Photograph	
		Conducted Emission Data	
4.0 <u>l</u>	Equip	oment Photographs	18
5.0 <u>l</u>	Produ	uct Labelling	20
6.0	<u> Techi</u>	nical Specifications	22
7.0 <u>l</u>	<u>nstru</u>	uction Manual	24
8.0 I	Misce	ellaneous Information	26
-		Emissions Test Procedures	

TRF no.: FCC 15C\_PC\_a
FCC ID: WVDMECHRC001A

## List of attached file

Exhibit Type	File Description	Filename
Test Report	Test Report	report.pdf
Test Setup Photo	Radiated Emission	radiated photos.pdf
Test Setup Photo	Conducted Emission	conducted photos.pdf
External Photo	External Photo	external photos.pdf
Internal Photo	Internal Photo	internal photos.pdf
Block Diagram	Block Diagram	block.pdf
ID Label / Location	Label Artwork and Location	label.pdf
User Manual	User Manual	manual.pdf
Cover Letter	Letter of Agency	agency.pdf

TRF no.: FCC 15C\_PC\_a
FCC ID: WVDMECHRC001A

WVDMECHRC001A iv

# EXHIBIT 1 GENERAL DESCRIPTION

TRF no.: FCC 15C\_PC\_a

### 1.0 **General Description**

#### 1.1 Product Description

The Equipment under Test (EUT) is a MechRC Robot System with model: MRC001A. This robot can be controlled by an IR controller and can be programmed its motions via Serial port or USB port by a PC. The device is powered by DC 7.2V (rechargeable battery).

#### 1.2 Related Submittal(s) Grants

This is an application for certification of a computer peripheral.

TRF no.: FCC 15C\_PC\_a

#### 1.3 Test Methodology

Both AC mains line-conducted and radiated emission measurements were performed according to the procedures in ANSI C63.4 (2003). Radiated emission measurement was performed in semi-anechoic chamber and conducted emission measurement was performed in shield room. For radiated emission measurement, preliminary scans were performed in the semi-anechoic chamber only to determine the worst case modes. All radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the "Justification Section" of this Application.

#### 1.4 Test Facility

The Semi-chamber facility used to collect the radiated data is **Interterk Testing Services Shenzhen Ltd. Kejiyuan Branch** and located at 6F, D Block, Huahan Building, Langshan Road, Nanshan District, Shenzhen, P. R. China. This test facility and site measurement data have been fully placed on file with the FCC.

TRF no.: FCC 15C\_PC\_a

# EXHIBIT 2 SYSTEM TEST CONFIGURATION

TRF no.: FCC 15C\_PC\_a

FCC ID: WVDMECHRC001A

4

#### 2.0 **System Test Configuration**

#### 2.1 Justification

The system was configured for testing in a typical fashion (as a customer would normally use it), and in the confines as outlined in ANSI C63.4 (2003).

The device is powered by DC 7.2V (rechargeable battery) when controlled by an IR controller and download & upload data via Serial port or USB port by a PC.

For maximizing emissions, the EUT was rotated through 360°, the antenna height was varied from 1 meter to 4 meters above the ground plane, and the antenna polarization was changed. The step by step procedure for maximizing emissions led to the data reported in Exhibit 3.0.

The rear of unit shall be flushed with the rear of the table.

The equipment under test (EUT) was configured for testing in a typical fashion (as a customer would normally use it). The EUT was placed on turntable, which enabled the engineer to maximize emissions through its placement in the three orthogonal axes.

The frequency range from 30MHz to 1GHz was searched for spurious emissions from the device. Only those emissions reported were detected. All other emissions were at least 20 dB below the applicable limits.

#### 2.2 EUT Exercising Software

The test software was provided by Gadget Lab International Co., Ltd..

#### 2.3 Special Accessories

The device is tested with an Serial Cable with ferrite bead attached. They are marketed together with the device.

#### 2.4 Equipment Modification

Any modifications installed previous to testing by Gadget Lab International Co., Ltd. will be incorporated in each production model sold / leased in the United States.

No modifications were installed by Intertek Testing Services.

TRF no.: FCC 15C\_PC\_a

## 2.5 Measurement Uncertainty

When determining the test conclusion, the Measurement Uncertainty of test has been considered.

#### 2.6 Support Equipment List and Description

This product was tested in the following configuration:

#### Refer List:

Description	Manufacturer	Model No.	
Test PC	HP	RL487AV	
Hard Disk	Smart.drive	HD3-SU2FW	
1394 Cable	Smart.drive	Length 180cm	
USB Line Smart.drive		Length 155cm	

All the items listed under section 2.0 of this report are

### Confirmed by:

Shawn Xing Assistant Manager Intertek Testing Services Shenzhen Ltd. Kejiyuan Branch Agent for Gadget Lab International Co., Ltd.

\_\_\_\_\_ Signature

6

December 25, 2008 Date

TRF no.: FCC 15C\_PC\_a
FCC ID: WVDMECHRC001A

## **EXHIBIT 3**

# **EMISSION RESULTS**

TRF no.: FCC 15C\_PC\_a

FCC ID: WVDMECHRC001A

7

## 3.0 **Emission Results**

Data is included worst case configuration (the configuration which resulted in the highest emission levels). A sample calculation, configuration photographs and data tables of the emissions are included.

TRF no.: FCC 15C\_PC\_a

#### 3.1 Field Strength Calculation

The field strength is calculated by adding the reading on the Spectrum Analyzer to the factors associated with preamplifiers (if any), antennas, cables, pulse desensitization and average factors (when specified limit is in average and measurements are made with peak detectors). A sample calculation is included below.

$$FS = RA + AF + CF - AG + PD + AV$$

where FS = Field Strength in  $dB\mu V/m$ 

RA = Receiver Amplitude (including preamplifier) in dBμV

CF = Cable Attenuation Factor in dB

AF = Antenna Factor in dB AG = Amplifier Gain in dB

PD = Pulse Desensitization in dB

AV = Average Factor in -dB

In the radiated emission table which follows, the reading shown on the data table may reflect the preamplifier gain. An example of the calculations, where the reading does not reflect the preamplifier gain, follows:

$$FS = RA + AF + CF - AG + PD + AV$$

TRF no.: FCC 15C\_PC\_a

#### 3.1 Field Strength Calculation (cont'd)

#### **Example**

Assume a receiver reading of  $62.0dB\mu V$  is obtained. The antenna factor of 7.4dB and cable factor of 1.6dB is added. The amplifier gain of 29dB is subtracted. The pulse desensitization factor of the spectrum analyzer was 0dB, and the resultant average factor was -10dB. The net field strength for comparison to the appropriate emission limit is  $32dB\mu V/m$ . This value in  $dB\mu V/m$  was converted to its corresponding level in  $\mu V/m$ .

 $RA = 62.0dB\mu V$  AF = 7.4dB CF = 1.6dB

AG = 29.0dB

PD = 0dB

AV = -10dB

 $FS = 62 + 7.4 + 1.6 - 29 + 0 + (-10) = 32dB\mu V/m$ 

Level in  $\mu V/m$  = Common Antilogarithm [(32dB $\mu V/m$ )/20] = 39.8 $\mu V/m$ 

TRF no.: FCC 15C\_PC\_a

## 3.2 Radiated Emission Configuration Photograph

Worst Case Radiated Emission At 191.999MHz

For electronic filing, the worst case radiated emission configuration photograph is saved with filename: radiated photos.pdf.

TRF no.: FCC 15C\_PC\_a

#### 3.3 Radiated Emission Data

The data on the following page lists the significant emission frequencies, the limit and the margin of compliance. Numbers with a minus sign are below the limit.

Judgement: Passed by 5.4dB margin

IEST PERSONNEL:
Zivy li
Signature
Billy Li, Engineer
Typed / Printed Name
December 25, 2008
Date

TRF no.: FCC 15C\_PC\_a

FCC ID: WVDMECHRC001A

12

Company: Gadget Lab International Co., Ltd. Date of Test: December 25, 2008

Model: MRC001A

Worst Case Operating Mode: Download Data to Robot via USB port

Table 1
Radiated Emissions

Polarization	Frequency	Reading	Pre-	Antenna	Net	Limit	Margin
	(MHz)	(dBµV)	Amp	Factor	at 3m	at 3m	(dB)
			Gain	(dB)	(dBµV/m)	(dBµV/m)	
			(dB)				
Horizontal	191.999	46.5	20.0	11.6	38.1	43.5	-5.4
Horizontal	255.980	43.6	20.0	14.0	37.6	46.0	-8.4
Horizontal	320.000	41.1	20.0	16.6	37.7	46.0	-8.3
Vertical	57.850	41.0	20.0	8.5	29.5	40.0	-10.5
Vertical	127.998	46.6	20.0	8.8	35.4	43.5	-8.1
Vertical	498.018	38.1	20.0	19.8	37.9	46.0	-8.1

NOTES: 1. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distances were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.

- 2. Negative value in the margin column shows emission below limit.
- 3. All emissions are below the QP limit.

Test Engineer: Billy Li

TRF no.: FCC 15C\_PC\_a
FCC ID: WVDMECHRC001A

## 3.4 Conducted Emission Configuration Photograph

Worst Case Neutral-Conducted Configuration at 0.150 MHz

For electronic filing, the worst case conducted emission configuration photograph is saved with filename: conducted photos.pdf.

TRF no.: FCC 15C\_PC\_a

#### 3.5 Conducted Emission Data

Judgement: Passed by 9.7 dB margin

#### **TEST PERSONNEL:**

Birly li

Signature

Billy Li, Engineer

Typed / Printed Name

December 25, 2008

Date

TRF no.: FCC 15C\_PC\_a

Company: Gadget Lab International Co., Ltd. Date of Test: December 25, 2008

Model: MRC001A

Worst Case Operating Mode: Download Data to Robot via USB port

Table 3

Conducted Emissions

#### Live Line Data

Frequency (MHz)	Quasi-Peak		Average	
	Disturbance level dB(μV)	Permitted limit dB(μV)	Disturbance level dB(μV)	Permitted limit dB(μV)
0.154	50.7	65.8	41.7	55.8
0.202	45.6	63.5	40.9	53.5
3.386	33.7	56.0	23.1	
3.926	35.0	56.0	25.3	46.0
13.400	33.9	60.0	25.9	50.0
16.470	36.4	60.0	28.8 50.0	

#### **Neutral Line Data**

Frequency (MHz)	Quasi	-Peak	Average		
	Disturbance level dB(μV)	level limit		Permitted limit dB(μV)	
0.150	56.3	66.0	37.7	56.0	
0.202	47.4	63.5	41.8	53.5	
2.782	29.9	56.0	27.1	46.0	
3.393	32.2	56.0	22.1	46.0	
13.640	33.8	60.0	25.6	50.0	
17.067	36.2	60.0	31.4	50.0	

Test Engineer: Billy Li

TRF no.: FCC 15C\_PC\_a
FCC ID: WVDMECHRC001A

# EXHIBIT 4 EQUIPMENT PHOTOGRAPHS

TRF no.: FCC 15C\_PC\_a
FCC ID: WVDMECHRC001A

## 4.0 **Equipment Photographs**

For electronic filing, photographs of the tested EUT are saved with filename: external photos.pdf and internal photos.pdf.

TRF no.: FCC 15C\_PC\_a

# EXHIBIT 5 PRODUCT LABELLING

TRF no.: FCC 15C\_PC\_a

## 5.0 **Product Labelling**

For electronics filing, the FCC ID label artwork and the label location are saved with filename: label.pdf.

TRF no.: FCC 15C\_PC\_a

# EXHIBIT 6 TECHNICAL SPECIFICATIONS

TRF no.: FCC 15C\_PC\_a

## 6.0 <u>Technical Specifications</u>

For electronic filing, the block diagram of the tested EUT is saved with filename: block.pdf.

TRF no.: FCC 15C\_PC\_a
FCC ID: WVDMECHRC001A

# EXHIBIT 7 INSTRUCTION MANUAL

TRF no.: FCC 15C\_PC\_a

### 7.0 **Instruction Manual**

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf.

This manual will be provided to the end-user with each unit sold / leased in the United States.

TRF no.: FCC 15C\_PC\_a

## **EXHIBIT 8**

# **MISCELLANEOUS INFORMATION**

TRF no.: FCC 15C\_PC\_a

## 8.0 <u>Miscellaneous Information</u>

This miscellaneous information includes emission measuring procedure.

TRF no.: FCC 15C\_PC\_a
FCC ID: WVDMECHRC001A

#### 8.1 Emissions Test Procedures

The following is a description of the test procedure used by Intertek Testing Services in the measurements of computer peripheral operating under Part 15, Subpart B rules.

The test set-up and procedures described below are designed to meet the requirements of ANSI C63.4 – 2003.

The computer peripheral equipment under test (EUT) is placed on a wooden turntable which is four feet in diameter and approximately one meter in height above the ground plane. During the radiated emissions test, the turntable is rotated and any cables leaving the EUT are manipulated to find the configuration resulting in maximum emissions. The antenna height and polarization are varied during the testing to search for maximum signal levels. The height of the antenna is varied from one to four meters.

Detector function for radiated emissions is in QP mode from the frequency band 30MHz to 1GHz and RBW setting is 120kHz. Detector function for conducted emissions are in QP & AV mode and IFBW setting is 9kHz from the frequency band 150kHz to 30MHz.

For radiated emission, the frequency range scanned is 30MHz to 1GHz. For line-conducted emissions, the range scanned is 150kHz to 30MHz.

TRF no.: FCC 15C\_PC\_a

## 8.1 Emissions Test Procedures (cont'd)

The EUT is warmed up for 15 minutes prior to the test.

Conducted measurements are made as described in ANSI C63.4 – 2003.

TRF no.: FCC 15C\_PC\_a