






<Small RU & Large RU & Puncturing mode>

Maximum conducted output power

Test Result

Test Mode	Antenna	Freq (MHz)	MRU Type	MRU Index	Set Power	Channel Power [dBm]	Duty Cycle [%]	DC Factor [dBm]	Result [dBm]	Limit [dBm]	Gain [dBi]	EIRP [dBm]	EIRP Limit [dBm]	Verdict
11BE20MIMO	Ant7	5180	52+26_OFDMA	1	5	3.65	99.56	0.02	3.67	≤23.98	1.67	5.34	---	PASS
			106+26_OFDMA	1	6.5	5.50	99.32	0.03	5.53	≤23.98	1.67	7.20	---	PASS
	Ant6	5180	52+26_OFDMA	1	5	4.01	99.56	0.02	4.03	≤23.98	3.35	7.38	---	PASS
			106+26_OFDMA	1	6.5	6.22	99.32	0.03	6.25	≤23.98	3.35	9.60	---	PASS
	total	5180	52+26_OFDMA	1	---	---	---	---	6.86	≤23.98	3.35	10.21	---	PASS
			106+26_OFDMA	1	---	---	---	---	8.92	≤23.98	3.35	12.27	---	PASS
	Ant7	5240	52+26_OFDMA	3	5	4.28	100.00	0.00	4.28	≤23.98	1.67	5.95	---	PASS
			106+26_OFDMA	2	6.5	5.78	99.32	0.03	5.81	≤23.98	1.67	7.48	---	PASS
	Ant6	5240	52+26_OFDMA	3	5	4.50	100.00	0.00	4.50	≤23.98	3.35	7.85	---	PASS
			106+26_OFDMA	2	6.5	6.59	99.32	0.03	6.62	≤23.98	3.35	9.97	---	PASS
	total	5240	52+26_OFDMA	3	---	---	---	---	7.40	≤23.98	3.35	10.75	---	PASS
			106+26_OFDMA	2	---	---	---	---	9.24	≤23.98	3.35	12.59	---	PASS
	Ant7	5745	52+26_OFDMA	1	5	4.45	99.56	0.02	4.47	≤30.00	2.79	7.26	---	PASS
			106+26_OFDMA	1	6.5	6.08	99.32	0.03	6.11	≤30.00	2.79	8.90	---	PASS
	Ant6	5745	52+26_OFDMA	1	5	4.23	100.00	0.00	4.23	≤30.00	3.14	7.37	---	PASS
			106+26_OFDMA	1	6.5	6.38	99.66	0.01	6.39	≤30.00	3.14	9.53	---	PASS
	total	5745	52+26_OFDMA	1	---	---	---	---	7.36	≤30.00	3.14	10.50	---	PASS
			106+26_OFDMA	1	---	---	---	---	9.26	≤30.00	3.14	12.40	---	PASS
	Ant7	5825	52+26_OFDMA	3	5	3.97	100.00	0.00	3.97	≤30.00	2.79	6.76	---	PASS
			106+26_OFDMA	2	7	6.58	99.31	0.03	6.61	≤30.00	2.79	9.40	---	PASS
	Ant6	5825	52+26_OFDMA	3	5	3.74	99.34	0.03	3.77	≤30.00	3.14	6.91	---	PASS
			106+26_OFDMA	2	7	6.60	99.32	0.03	6.63	≤30.00	3.14	9.77	---	PASS
	total	5825	52+26_OFDMA	3	---	---	---	---	6.88	≤30.00	3.14	10.02	---	PASS
			106+26_OFDMA	2	---	---	---	---	9.63	≤30.00	3.14	12.77	---	PASS
11BE80MIMO	Ant7	5210	Large RU 484+242	4	6	6.66	98.80	0.05	6.71	≤23.98	1.67	8.38	---	PASS
			Puncturing 20M	4	7	7.14	100.00	0.00	7.14	≤23.98	1.67	8.81	---	PASS
	Ant6	5210	Large RU 484+242	4	6	7.68	97.59	0.11	7.79	≤23.98	3.35	11.14	---	PASS
			Puncturing 20M	4	7	7.49	99.63	0.02	7.51	≤23.98	3.35	10.86	---	PASS
	total	5210	Large RU 484+242	4	---	---	---	---	10.29	≤23.98	3.35	13.64	---	PASS
			Puncturing 20M	4	---	---	---	---	10.34	≤23.98	3.35	13.69	---	PASS
	Ant7	5775	Large RU 484+242	4	7	8.27	97.59	0.11	8.38	≤30.00	2.79	11.17	---	PASS
			Puncturing 20M	4	8	8.10	99.45	0.02	8.12	≤30.00	2.79	10.91	---	PASS
	Ant6	5775	Large RU 484+242	4	7	8.29	97.59	0.11	8.40	≤30.00	3.14	11.54	---	PASS
			Puncturing 20M	4	8	8.26	99.63	0.02	8.28	≤30.00	3.14	11.42	---	PASS
	total	5775	Large RU 484+242	4	---	---	---	---	11.40	≤30.00	3.14	14.54	---	PASS
			Puncturing 20M	4	---	---	---	---	11.21	≤30.00	3.14	14.35	---	PASS

Note: The Duty Cycle Factor is compensated in the graph.



Maximum power spectral density

Test Result


Test Mode	Antenna	Freq(MHz)	MRU Type	MRU Index	Result [dBm/MHz]	Limit [dBm/MHz]	Verdict
11BE20MIMO	Ant7	5180	52+26_OFDMA	1	-3.26	≤11.00	PASS
			106+26_OFDMA	1	-3.80	≤11.00	PASS
	Ant6	5180	52+26_OFDMA	1	-3.20	≤11.00	PASS
			106+26_OFDMA	1	-3.37	≤11.00	PASS
	total	5180	52+26_OFDMA	1	-0.38	≤11.00	PASS
			106+26_OFDMA	1	-0.68	≤11.00	PASS
	Ant7	5240	52+26_OFDMA	3	-3.49	≤11.00	PASS
			106+26_OFDMA	2	-3.13	≤11.00	PASS
	Ant6	5240	52+26_OFDMA	3	-2.71	≤11.00	PASS
			106+26_OFDMA	2	-2.88	≤11.00	PASS
	total	5240	52+26_OFDMA	3	-0.20	≤11.00	PASS
			106+26_OFDMA	2	-0.28	≤11.00	PASS
	Ant7	5745	52+26_OFDMA	1	-5.79	≤30.00	PASS
			106+26_OFDMA	1	-6.42	≤30.00	PASS
	Ant6	5745	52+26_OFDMA	1	-6.02	≤30.00	PASS
			106+26_OFDMA	1	-6.00	≤30.00	PASS
	total	5745	52+26_OFDMA	1	-2.89	≤30.00	PASS
			106+26_OFDMA	1	-3.19	≤30.00	PASS
	Ant7	5825	52+26_OFDMA	3	-6.49	≤30.00	PASS
			106+26_OFDMA	2	-6.22	≤30.00	PASS
	Ant6	5825	52+26_OFDMA	3	-6.35	≤30.00	PASS
			106+26_OFDMA	2	-5.48	≤30.00	PASS
11BE80MIMO	Ant7	5210	Large RU 484+242	4	-10.20	≤11.00	PASS
			Puncturing 20M	4	-9.77	≤11.00	PASS
	Ant6	5210	Large RU 484+242	4	-9.28	≤11.00	PASS
			Puncturing 20M	4	-9.51	≤11.00	PASS
	total	5210	Large RU 484+242	4	-6.95	≤11.00	PASS
			Puncturing 20M	4	-7.02	≤11.00	PASS
	Ant7	5775	Large RU 484+242	4	-11.55	≤30.00	PASS
			Puncturing 20M	4	-11.85	≤30.00	PASS
	Ant6	5775	Large RU 484+242	4	-11.63	≤30.00	PASS
			Puncturing 20M	4	-11.99	≤30.00	PASS
	total	5775	Large RU 484+242	4	-8.58	≤30.00	PASS
			Puncturing 20M	4	-8.91	≤30.00	PASS



Note: 1.The Result and Limit Unit is dBm/500 kHz in the band 5.725–5.85 GHz.


2.The Duty Cycle Factor and RBW Factor is compensated in the graph.







Test Graphs


















































<Partial Single RU>


Min emission bandwidth


Test Result

Test Mode	Antenna	Freq (MHz)	Ru Size	Ru Index	6db BW [MHz]	FL [MHz]	FH [MHz]	Limit [MHz]	Verdict
11BE20 MIMO	Ant7	5745	26Tone	RU0	2.04	5735.48	5737.52	0.5	PASS
	Ant6	5745	26Tone	RU0	2.08	5735.44	5737.52	0.5	PASS
	Ant7	5825	26Tone	RU8	2.08	5832.44	5834.52	0.5	PASS
	Ant6	5825	26Tone	RU8	2.08	5832.44	5834.52	0.5	PASS



Test Graphs







Maximum conducted output power

Test Result

Test Mode	Antenna	Freq (MHz)	Ru Size	Ru Index	Set Power	Channel Power [dBm]	Duty Cycle [%]	DC Factor [dBm]	Result [dBm]	Conducted Limit [dBm]	Gain [dBi]	EIRP [dBm]	EIRP Limit [dBm]	Verdict
11BE20MIMO	Ant7	5180	26Tone	RU0	-0.5	-0.95	99.45	0.02	-0.93	≤23.98	1.67	0.74	---	PASS
			52Tone	RU37	3	1.91	99.45	0.02	1.93	≤23.98	1.67	3.60	---	PASS
			106Tone	RU53	6	4.94	99.45	0.02	4.96	≤23.98	1.67	6.63	---	PASS
	Ant6	5180	26Tone	RU0	-0.5	-0.51	99.45	0.02	-0.49	≤23.98	3.35	2.86	---	PASS
			52Tone	RU37	3	2.06	99.45	0.02	2.08	≤23.98	3.35	5.43	---	PASS
			106Tone	RU53	6	5.63	99.45	0.02	5.65	≤23.98	3.35	9.00	---	PASS
	total	5180	26Tone	RU0	---	---	---	---	2.31	≤23.98	3.35	5.66	---	PASS
			52Tone	RU37	---	---	---	---	5.02	≤23.98	3.35	8.37	---	PASS
			106Tone	RU53	---	---	---	---	8.33	≤23.98	3.35	11.68	---	PASS
	Ant7	5240	26Tone	RU8	-1	-1.33	99.45	0.02	-1.31	≤23.98	1.67	0.36	---	PASS
			52Tone	RU40	2.5	1.90	99.45	0.02	1.92	≤23.98	1.67	3.59	---	PASS
			106Tone	RU54	5.5	4.92	99.45	0.02	4.94	≤23.98	1.67	6.61	---	PASS
	Ant6	5240	26Tone	RU8	-1	-0.51	99.45	0.02	-0.49	≤23.98	3.35	2.86	---	PASS
			52Tone	RU40	2.5	1.68	99.45	0.02	1.70	≤23.98	3.35	5.05	---	PASS
			106Tone	RU54	5.5	5.19	99.45	0.02	5.21	≤23.98	3.35	8.56	---	PASS
	total	5240	26Tone	RU8	---	---	---	---	2.13	≤23.98	3.35	5.48	---	PASS
			52Tone	RU40	---	---	---	---	4.82	≤23.98	3.35	8.17	---	PASS
			106Tone	RU54	---	---	---	---	8.09	≤23.98	3.35	11.44	---	PASS
	Ant7	5745	26Tone	RU0	-0.5	-0.36	99.45	0.02	-0.34	≤30.00	2.79	2.45	---	PASS
			52Tone	RU37	3	2.21	99.45	0.02	2.23	≤30.00	2.79	5.02	---	PASS
			106Tone	RU53	6	5.45	99.45	0.02	5.47	≤30.00	2.79	8.26	---	PASS
	Ant6	5745	26Tone	RU0	-0.5	-0.92	99.45	0.02	-0.90	≤30.00	3.14	2.24	---	PASS
			52Tone	RU37	3	2.57	99.45	0.02	2.59	≤30.00	3.14	5.73	---	PASS
			106Tone	RU53	6	5.93	99.45	0.02	5.95	≤30.00	3.14	9.09	---	PASS
	total	5745	26Tone	RU0	---	---	---	---	2.40	≤30.00	3.14	5.54	---	PASS
			52Tone	RU37	---	---	---	---	5.42	≤30.00	3.14	8.56	---	PASS
			106Tone	RU53	---	---	---	---	8.73	≤30.00	3.14	11.87	---	PASS
	Ant7	5825	26Tone	RU8	-0.5	-0.83	99.45	0.02	-0.81	≤30.00	2.79	1.98	---	PASS
			52Tone	RU40	3	1.55	99.45	0.02	1.57	≤30.00	2.79	4.36	---	PASS
			106Tone	RU54	6	4.88	99.45	0.02	4.90	≤30.00	2.79	7.69	---	PASS
	Ant6	5825	26Tone	RU8	-0.5	-1.07	99.45	0.02	-1.05	≤30.00	3.14	2.09	---	PASS
			52Tone	RU40	3	2.11	99.45	0.02	2.13	≤30.00	3.14	5.27	---	PASS
			106Tone	RU54	6	5.48	99.45	0.02	5.50	≤30.00	3.14	8.64	---	PASS
	total	5825	26Tone	RU8	---	---	---	---	2.08	≤30.00	3.14	5.22	---	PASS
			52Tone	RU40	---	---	---	---	4.87	≤30.00	3.14	8.01	---	PASS
			106Tone	RU54	---	---	---	---	8.22	≤30.00	3.14	11.36	---	PASS

Maximum power spectral density


Test Result



Test Mode	Antenna	Freq(MHz)	Ru Size	Ru Index	Result [dBm/MHz]	Limit [dBm/MHz]	Verdict
11BE20MIMO	Ant7	5180	26Tone	RU0	-3.22	≤11.00	PASS
			52Tone	RU37	-3.55	≤11.00	PASS
			106Tone	RU53	-3.04	≤11.00	PASS
	Ant6	5180	26Tone	RU0	-3.29	≤11.00	PASS
			52Tone	RU37	-3.71	≤11.00	PASS
			106Tone	RU53	-2.83	≤11.00	PASS
	total	5180	26Tone	RU0	-0.29	≤11.00	PASS
			52Tone	RU37	-0.62	≤11.00	PASS
			106Tone	RU53	-0.29	≤11.00	PASS
	Ant7	5240	26Tone	RU8	-3.71	≤11.00	PASS
			52Tone	RU40	-3.15	≤11.00	PASS
			106Tone	RU54	-3.09	≤11.00	PASS
	Ant6	5240	26Tone	RU8	-3.24	≤11.00	PASS
			52Tone	RU40	-3.00	≤11.00	PASS
			106Tone	RU54	-2.93	≤11.00	PASS
	total	5240	26Tone	RU8	-0.53	≤11.00	PASS
			52Tone	RU40	-0.28	≤11.00	PASS
			106Tone	RU54	-0.15	≤11.00	PASS
	Ant7	5745	26Tone	RU0	-5.28	≤30.00	PASS
			52Tone	RU37	-6.39	≤30.00	PASS
			106Tone	RU53	-6.01	≤30.00	PASS
	Ant6	5745	26Tone	RU0	-6.27	≤30.00	PASS
			52Tone	RU37	-5.65	≤30.00	PASS
			106Tone	RU53	-5.43	≤30.00	PASS
	total	5745	26Tone	RU0	-2.74	≤30.00	PASS
			52Tone	RU37	-2.99	≤30.00	PASS
			106Tone	RU53	-2.70	≤30.00	PASS
	Ant7	5825	26Tone	RU8	-6.16	≤30.00	PASS
			52Tone	RU40	-6.66	≤30.00	PASS
			106Tone	RU54	-6.37	≤30.00	PASS
	Ant6	5825	26Tone	RU8	-6.51	≤30.00	PASS
			52Tone	RU40	-6.03	≤30.00	PASS
			106Tone	RU54	-5.48	≤30.00	PASS
	total	5825	26Tone	RU8	-3.32	≤30.00	PASS
			52Tone	RU40	-3.32	≤30.00	PASS
			106Tone	RU54	-2.89	≤30.00	PASS



Note: 1.The Result and Limit Unit is dBm/500 kHz in the band 5.725–5.85 GHz.
2.The Duty Cycle Factor and is compensated in the graph.





Test Graphs




















































Appendix B. AC Conducted Emission Test Results





Test Engineer :	Nathon	Temperature :	22~24°C
		Relative Humidity :	44~50%
Test Voltage :	120Vac / 60Hz	Phase :	Neutral
Remark :	All emissions not reported here are more than 10 dB below the prescribed limit.		



Site : CO02-SZ
Condition : FCC 15E_QP LISN_2025-N NEUTRAL

	Freq	Level	Over	Limit	Read	LISN	Cable	Remark
	MHz	dBuV	Limit	Line	Level	Factor	Loss	
			dB	dBuV	dBuV	dB	dB	
1	0.17	34.03	-20.96	54.99	14.10	9.75	10.18	Average
2	0.17	41.93	-23.06	64.99	22.00	9.75	10.18	QP
3	0.20	32.02	-21.78	53.80	12.00	9.84	10.18	Average
4	0.20	40.92	-22.88	63.80	20.90	9.84	10.18	QP
5	0.27	33.01	-17.97	50.98	13.10	9.71	10.20	Average
6	0.27	39.21	-21.77	60.98	19.30	9.71	10.20	QP
7	0.39	31.50	-16.58	48.08	11.50	9.78	10.22	Average
8	0.39	39.30	-18.78	58.08	19.30	9.78	10.22	QP
9	0.52	28.96	-17.04	46.00	9.10	9.62	10.24	Average
10	0.52	36.86	-19.14	56.00	17.00	9.62	10.24	QP
11	0.61	30.58	-15.42	46.00	10.69	9.65	10.24	Average
12 *	0.61	37.98	-18.02	56.00	18.09	9.65	10.24	QP

Note:

- Level(dBμV) = Read Level(dBμV) + LISN Factor(dB) + Cable Loss(dB)
- Over Limit(dB) = Level(dBμV) – Limit Line(dBμV)



Appendix C. Radiated Spurious Emission

Test Engineer :	HuaCong Liang	Relative Humidity :	50%
		Temperature :	20-22°C

Radiated Spurious Emission Test Modes

Mode	Band	Band (GHz)	Antenna	Modulation	Channel	Frequency	Data Rate	RU	Remark
Mode 1	U-NII-1	5.15-5.25	CDD 7+6	802.11a	36	5180	6Mbps	-	-
Mode 2	U-NII-1	5.15-5.25	CDD 7+6	802.11a	44	5220	6Mbps	-	-
Mode 3	U-NII-1	5.15-5.25	CDD 7+6	802.11a	48	5240	6Mbps	-	-
Mode 4	U-NII-1	5.15-5.25	CDD 7+6	802.11n HT20	36	5180	MCS0	-	-
Mode 5	U-NII-1	5.15-5.25	CDD 7+6	802.11n HT20	44	5220	MCS0	-	-
Mode 6	U-NII-1	5.15-5.25	CDD 7+6	802.11n HT20	48	5240	MCS0	-	-
Mode 7	U-NII-1	5.15-5.25	CDD 7+6	802.11n HT40	38	5190	MCS0	-	-
Mode 8	U-NII-1	5.15-5.25	CDD 7+6	802.11n HT40	46	5230	MCS0	-	-
Mode 9	U-NII-1	5.15-5.25	CDD 7+6	802.11ac VHT80	42	5210	MCS0	-	-
Mode 10	U-NII-1	5.15-5.25	CDD 7+6	802.11be EHT20	36	5180	MCS0	Full RU	-
Mode 11	U-NII-1	5.15-5.25	CDD 7+6	802.11be EHT20	44	5220	MCS0	Full RU	-
Mode 12	U-NII-1	5.15-5.25	CDD 7+6	802.11be EHT20	48	5240	MCS0	Full RU	-
Mode 13	U-NII-1	5.15-5.25	CDD 7+6	802.11be EHT40	38	5190	MCS0	Full RU	-
Mode 14	U-NII-1	5.15-5.25	CDD 7+6	802.11be EHT40	46	5230	MCS0	Full RU	-
Mode 15	U-NII-1	5.15-5.25	CDD 7+6	802.11be EHT80	42	5210	MCS0	Full RU	-
Mode 16	U-NII-1	5.15-5.25	CDD 7+6	802.11be EHT20	36	5180	MCS0	Single RU_106/53	-
Mode 17	U-NII-1	5.15-5.25	CDD 7+6	802.11be EHT20	48	5240	MCS0	Single RU_106/54	-
Mode 18	U-NII-1	5.15-5.25	CDD 7+6	802.11be EHT20	36	5180	MCS0	Small RU_52+26	-
Mode 19	U-NII-1	5.15-5.25	CDD 7+6	802.11be EHT20	48	5240	MCS0	Small RU_52+26	-
Mode 20	U-NII-3	5.725-5.85	CDD 7+6	802.11a	149	5745	6Mbps	-	-
Mode 21	U-NII-3	5.725-5.85	CDD 7+6	802.11a	157	5785	6Mbps	-	-
Mode 22	U-NII-3	5.725-5.85	CDD 7+6	802.11a	165	5825	6Mbps	-	-
Mode 23	U-NII-3	5.725-5.85	CDD 7+6	802.11n HT20	149	5745	MCS0	-	-
Mode 24	U-NII-3	5.725-5.85	CDD 7+6	802.11n HT20	157	5785	MCS0	-	-
Mode 25	U-NII-3	5.725-5.85	CDD 7+6	802.11n HT20	165	5825	MCS0	-	-
Mode 26	U-NII-3	5.725-5.85	CDD 7+6	802.11n HT40	151	5755	MCS0	-	-
Mode 27	U-NII-3	5.725-5.85	CDD 7+6	802.11n HT40	159	5795	MCS0	-	-
Mode 28	U-NII-3	5.725-5.85	CDD 7+6	802.11ac VHT80	155	5775	MCS0	-	-
Mode 29	U-NII-3	5.725-5.85	CDD 7+6	802.11be EHT20	149	5745	MCS0	Full RU	-
Mode 30	U-NII-3	5.725-5.85	CDD 7+6	802.11be EHT20	157	5785	MCS0	Full RU	-
Mode 31	U-NII-3	5.725-5.85	CDD 7+6	802.11be EHT20	165	5825	MCS0	Full RU	-
Mode 32	U-NII-3	5.725-5.85	CDD 7+6	802.11be EHT40	151	5755	MCS0	Full RU	-
Mode 33	U-NII-3	5.725-5.85	CDD 7+6	802.11be EHT40	159	5795	MCS0	Full RU	-
Mode 34	U-NII-3	5.725-5.85	CDD 7+6	802.11be EHT80	155	5775	MCS0	Full RU	-
Mode 35	U-NII-3	5.725-5.85	CDD 7+6	802.11be EHT20	149	5745	MCS0	Single RU_106/53	-
Mode 36	U-NII-3	5.725-5.85	CDD 7+6	802.11be EHT20	165	5825	MCS0	Single RU_106/54	-
Mode 37	U-NII-3	5.725-5.85	CDD 7+6	802.11be EHT20	149	5745	MCS0	Small RU_52+26	-



Mode 38	U-NII-3	5.725-5.85	CDD 7+6	802.11be EHT20	165	5825	MCS0	Small RU_106+26	-
Mode 39	U-NII-1	5.15-5.25	CDD 7+6	802.11be EHT80	42	5210	MCS0	Large RU 484+242_4	-
Mode 40	U-NII-3	5.725-5.85	CDD 7+6	802.11be EHT80	155	5775	MCS0	Large RU 484+242_4	-
Mode 41	U-NII-1	5.15-5.25	CDD 7+6	802.11be EHT80	42	5210	MCS0	Puncturing 20M_4	-
Mode 42	U-NII-3	5.725-5.85	CDD 7+6	802.11be EHT80	155	5775	MCS0	Puncturing 20M_4	-
Mode 43	U-NII-1	5.15-5.25	CDD 7+6	802.11ac VHT80	42	5210	MCS0	-	LF
Mode 44	U-NII-3	5.725-5.85	CDD 7+6	802.11n HT40	151	5755	MCS0	-	LF

Summary of each worse mode

Mode	Modulation	Ch.	Freq. (MHz)	Level (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Pol.	Peak Avg.	Result	Remark
1	802.11a	36	5149.98	46.38	54.00	-7.62	V	AVERAGE	Pass	Band Edge
1	802.11a	36	7252.00	45.84	54.00	-8.13	V	AVERAGE	Pass	Harmonic
2	802.11a	44	-	-	-	-	-	-	-	Band Edge
2	802.11a	44	7308.00	46.24	54.00	-7.76	V	AVERAGE	Pass	Harmonic
3	802.11a	48	5103.34	43.19	54.00	-10.81	V	AVERAGE	Pass	Band Edge
3	802.11a	48	7336.00	45.83	54.00	-8.17	V	AVERAGE	Pass	Harmonic
4	802.11n HT20	36	5148.25	45.53	54.00	-8.47	V	AVERAGE	Pass	Band Edge
4	802.11n HT20	36	10360.00	57.78	68.30	-10.52	V	Peak	Pass	Harmonic
5	802.11n HT20	44	-	-	-	-	-	-	-	Band Edge
5	802.11n HT20	44	10440.00	58.78	68.30	-9.52	V	Peak	Pass	Harmonic
6	802.11n HT20	48	5129.43	43.24	54.00	-10.76	V	AVERAGE	Pass	Band Edge
6	802.11n HT20	48	10480.00	58.35	68.30	-9.95	V	Peak	Pass	Harmonic
7	802.11n HT40	38	5149.99	48.40	54.00	-5.60	V	Average	Pass	Band Edge
7	802.11n HT40	38	10380.00	52.50	68.30	-15.80	V	Peak	Pass	Harmonic
8	802.11n HT40	46	5125.93	44.18	54.00	-9.82	V	AVERAGE	Pass	Band Edge
8	802.11n HT40	46	-	-	-	-	-	-	-	Harmonic
9	802.11ac VHT80	42	5149.90	49.46	54.00	-4.54	V	Average	Pass	Band Edge
9	802.11ac VHT80	42	10420.00	48.62	68.30	-19.68	H	Peak	Pass	Harmonic
10	802.11be EHT20	36	5124.47	43.06	54.00	-10.94	V	AVERAGE	Pass	Band Edge
10	802.11be EHT20	36	10360.00	48.34	68.30	-19.96	V	Peak	Pass	Harmonic
11	802.11be EHT20	44	-	-	-	-	-	-	-	Band Edge
11	802.11be EHT20	44	10440.00	48.52	68.30	-19.78	V	Peak	Pass	Harmonic
12	802.11be EHT20	48	5061.34	42.97	54.00	-11.03	H	AVERAGE	Pass	Band Edge
12	802.11be EHT20	48	10480.00	48.78	68.30	-19.52	V	Peak	Pass	Harmonic
13	802.11be EHT40	38	5149.63	44.02	54.00	-9.98	V	AVERAGE	Pass	Band Edge
13	802.11be EHT40	38	-	-	-	-	-	-	-	Harmonic
14	802.11be EHT40	46	5455.06	42.85	54.00	-11.15	H	AVERAGE	Pass	Band Edge
14	802.11be EHT40	46	-	-	-	-	-	-	-	Harmonic
15	802.11ax HE80	42	5149.99	46.08	54.00	-7.92	V	Average	Pass	Band Edge
15	802.11be EHT80	42	-	-	-	-	-	-	-	Harmonic
16	802.11be EHT20	36	5147.89	42.91	54.00	-11.09	V	AVERAGE	Pass	Band Edge
16	802.11be EHT20	36	-	-	-	-	-	-	-	Harmonic
17	802.11be EHT20	48	5072.60	42.81	54.00	-11.19	V	AVERAGE	Pass	Band Edge
17	802.11be EHT20	48	-	-	-	-	-	-	-	Harmonic
18	802.11be EHT20	36	5128.27	42.97	54.00	-11.03	V	AVERAGE	Pass	Band Edge



18	802.11be EHT20	36	-	-	-	-	-	-	-	Harmonic
19	802.11be EHT20	48	5041.64	42.84	54.00	-11.16	V	AVERAGE	Pass	Band Edge
19	802.11be EHT20	48	-	-	-	-	-	-	-	Harmonic
20	802.11a	149	5648.65	54.36	68.30	-13.94	H	PEAK	Pass	Band Edge
20	802.11a	149	17235.00	47.41	68.30	-20.89	V	Peak	Pass	Harmonic
21	802.11a	157	-	-	-	-	-	-	-	Band Edge
21	802.11a	157	17355.00	47.49	68.30	-20.81	V	Peak	Pass	Harmonic
22	802.11a	165	5925.83	54.46	68.30	-13.84	H	PEAK	Pass	Band Edge
22	802.11a	165	17475.00	47.73	68.30	-20.57	V	Peak	Pass	Harmonic
23	802.11n HT20	149	5650.11	54.15	68.38	-14.23	V	PEAK	Pass	Band Edge
23	802.11n HT20	149	17235.00	47.99	68.30	-20.31	V	Peak	Pass	Harmonic
24	802.11n HT20	157	-	-	-	-	-	-	-	Band Edge
24	802.11n HT20	157	17355.00	48.61	68.30	-19.69	H	Peak	Pass	Harmonic
25	802.11n HT20	165	5942.19	53.51	68.30	-14.79	V	PEAK	Pass	Band Edge
25	802.11n HT20	165	17475.00	48.36	68.30	-19.94	V	Peak	Pass	Harmonic
26	802.11n HT40	151	5642.80	56.84	68.30	-11.46	V	Peak	Pass	Band Edge
26	802.11n HT40	151	17265.00	47.92	68.30	-20.38	H	Peak	Pass	Harmonic
27	802.11n HT40	159	5619.03	54.86	68.30	-13.44	V	PEAK	Pass	Band Edge
27	802.11n HT40	159	17385.00	46.89	68.30	-21.41	V	Peak	Pass	Harmonic
28	802.11ac VHT80	155	5633.36	53.70	68.30	-14.60	H	PEAK	Pass	Band Edge
28	802.11ac VHT80	155	-	-	-	-	-	-	-	Harmonic
29	802.11be EHT20	149	5616.10	54.62	68.30	-13.68	H	PEAK	Pass	Band Edge
29	802.11be EHT20	149	17235.00	47.42	68.30	-20.88	H	Peak	Pass	Harmonic
30	802.11be EHT20	157	-	-	-	-	-	-	-	Band Edge
30	802.11be EHT20	157	17355.00	47.86	68.30	-20.44	V	Peak	Pass	Harmonic
31	802.11be EHT20	165	5935.88	53.61	68.30	-14.69	V	PEAK	Pass	Band Edge
31	802.11be EHT20	165	17475.00	47.75	68.30	-20.55	V	Peak	Pass	Harmonic
32	802.11be EHT40	151	5627.59	55.12	68.30	-13.18	H	PEAK	Pass	Band Edge
32	802.11be EHT40	151	17265.00	48.15	68.30	-20.15	H	Peak	Pass	Harmonic
33	802.11be EHT40	159	5647.97	54.09	68.30	-14.21	H	PEAK	Pass	Band Edge
33	802.11be EHT40	159	17385.00	47.49	68.30	-20.81	H	Peak	Pass	Harmonic
34	802.11be EHT80	155	5616.63	54.58	68.30	-13.72	H	PEAK	Pass	Band Edge
34	802.11be EHT80	155	17325.00	47.53	68.30	-20.77	H	Peak	Pass	Harmonic
35	802.11be EHT20	149	5635.96	54.51	68.30	-13.79	V	PEAK	Pass	Band Edge
35	802.11be EHT20	149	-	-	-	-	-	-	-	Harmonic
36	802.11be EHT20	165	5944.50	54.40	68.30	-13.90	V	PEAK	Pass	Band Edge
36	802.11be EHT20	165	-	-	-	-	-	-	-	Harmonic
37	802.11be EHT20	149	5645.68	54.56	68.30	-13.74	V	PEAK	Pass	Band Edge
37	802.11be EHT20	149	-	-	-	-	-	-	-	Harmonic
38	802.11be EHT20	165	5938.25	53.80	68.30	-14.50	V	PEAK	Pass	Band Edge
38	802.11be EHT20	165	-	-	-	-	-	-	-	Harmonic
39	802.11be EHT80	42	5149.84	44.15	54.00	-9.85	H	AVERAGE	Pass	Band Edge
39	802.11be EHT80	42								Harmonic
40	802.11be EHT80	155	5649.18	54.08	68.30	-14.22	H	PEAK	Pass	Band Edge
40	802.11be EHT80	155	-	-	-	-	-	-	-	Harmonic
41	802.11be EHT80	42	5146.69	43.07	54.00	-10.93	V	AVERAGE	Pass	Band Edge



41	802.11be EHT80	42	-	-	-	-	-	-	-	Harmonic
42	802.11be EHT80	155	5634.48	54.58	68.30	-13.72	H	PEAK	Pass	Band Edge
42	802.11be EHT80	155	-	-	-	-	-	-	-	Harmonic
43	802.11ac VHT80	42	829.28	30.62	46.00	-15.38	H	PEAK	Pass	LF
44	802.11n HT40	151	44.55	21.91	40.00	-18.09	V	PEAK	Pass	LF





Co-location mode:**Radiated Spurious Emission Test Modes**

Mode	Band (MHz)	Antenna	Modulation	Channel	Frequency	Data Rate	RU	Remark
45	CO_TX	CDD 7+6	802.11b	01	2412	1Mbps	-	-
		CDD 7+6	802.11ac VHT80	42	5210	MCS0		
		4	LTE	Bnad14	-	-	-	-

Summary of each worse mode

Mode	Modulation	Ch.	Freq. (MHz)	Level (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Pol.	Peak Avg.	Result	Remark
45	CO-TX	-	5134.61	49.38	54.00	-4.62	V	AVERAGE	Pass	Band Edge
45		-	4824.00	49.54	54.00	-4.46	V	AVERAGE	Pass	Harmonic





		1																																																																																							
Mode		Band Edge																																																																																							
		U-NII-1_5.15-5.25_802.11a_CH36_5180MHz																																																																																							
ANT		CDD 7+6																																																																																							
Pol.		Horizontal					Fundamental																																																																																		
Peak	Level (dBuV/m) Date: 2025-03-26  Frequency (MHz)					Level (dBuV/m) Date: 2025-03-26  Frequency (MHz)																																																																																			
	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5149.31</td><td>53.52</td><td>74.00</td><td>-20.48</td><td>39.36</td><td>35.70</td><td>11.09</td><td>32.63</td><td>100 43 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5149.31	53.52	74.00	-20.48	39.36	35.70	11.09	32.63	100 43 PEAK	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5180.00</td><td>106.05</td><td>-----</td><td>-----</td><td>91.86</td><td>35.75</td><td>11.07</td><td>32.63</td><td>100 43 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5180.00	106.05	-----	-----	91.86	35.75	11.07	32.63
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1	5149.31	53.52	74.00	-20.48	39.36	35.70	11.09	32.63	100 43 PEAK																																																																																
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1	5180.00	106.05	-----	-----	91.86	35.75	11.07	32.63	100 43 PEAK																																																																																
Avg	Level (dBuV/m) Date: 2025-03-26  Frequency (MHz)					Level (dBuV/m) Date: 2025-03-26  Frequency (MHz)																																																																																			
	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5149.99</td><td>44.27</td><td>54.00</td><td>-9.73</td><td>30.12</td><td>35.70</td><td>11.08</td><td>32.63</td><td>100 43 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5149.99	44.27	54.00	-9.73	30.12	35.70	11.08	32.63	100 43 AVERAGE	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5180.00</td><td>98.34</td><td>-----</td><td>-----</td><td>84.15</td><td>35.76</td><td>11.07</td><td>32.64</td><td>100 43 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5180.00	98.34	-----	-----	84.15	35.76	11.07	32.64
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1	5149.99	44.27	54.00	-9.73	30.12	35.70	11.08	32.63	100 43 AVERAGE																																																																																
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																
1	5180.00	98.34	-----	-----	84.15	35.76	11.07	32.64	100 43 AVERAGE																																																																																



		1																																																																																						
Mode		Band Edge																																																																																						
		U-NII-1_5.15-5.25_802.11a_CH36_5180MHz																																																																																						
ANT		CDD 7+6																																																																																						
Pol.		Vertical					Fundamental																																																																																	
Peak	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5149.63</td><td>55.58</td><td>74.00</td><td>-18.42</td><td>41.42</td><td>35.70</td><td>11.09</td><td>32.63</td><td>260</td><td>101</td><td>PEAK</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5149.63	55.58	74.00	-18.42	41.42	35.70	11.09	32.63	260	101	PEAK	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5180.00</td><td>109.95</td><td>-----</td><td>-----</td><td>95.76</td><td>35.75</td><td>11.07</td><td>32.63</td><td>260</td><td>101</td><td>PEAK</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5180.00	109.95	-----	-----	95.76	35.75	11.07	32.63	260	101	PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																															
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																	
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																
1	5149.63	55.58	74.00	-18.42	41.42	35.70	11.09	32.63	260	101	PEAK																																																																													
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																	
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																
1	5180.00	109.95	-----	-----	95.76	35.75	11.07	32.63	260	101	PEAK																																																																													
Avg	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5149.98</td><td>46.38</td><td>54.00</td><td>-7.62</td><td>32.23</td><td>35.70</td><td>11.08</td><td>32.63</td><td>260</td><td>101</td><td>AVERAGE</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5149.98	46.38	54.00	-7.62	32.23	35.70	11.08	32.63	260	101	AVERAGE	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5180.00</td><td>101.60</td><td>-----</td><td>-----</td><td>87.41</td><td>35.75</td><td>11.07</td><td>32.63</td><td>260</td><td>101</td><td>AVERAGE</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5180.00	101.60	-----	-----	87.41	35.75	11.07	32.63	260	101	AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																															
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																	
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																
1	5149.98	46.38	54.00	-7.62	32.23	35.70	11.08	32.63	260	101	AVERAGE																																																																													
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																	
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																
1	5180.00	101.60	-----	-----	87.41	35.75	11.07	32.63	260	101	AVERAGE																																																																													



Mode	1																																																																																																																																																																						
	Harmonic																																																																																																																																																																						
	U-NII-1_5.15-5.25_802.11a_CH36_5180MHz																																																																																																																																																																						
ANT	CDD 7+6																																																																																																																																																																						
Pol.	Horizontal										Vertical																																																																																																																																																												
Peak Avg																																																																																																																																																																							
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>7252.00</td><td>49.18</td><td>74.00</td><td>-24.82</td><td>52.87</td><td>36.60</td><td>11.91</td><td>52.20</td><td>200</td><td>313</td><td>Peak</td></tr><tr><td>2</td><td>7252.00</td><td>43.07</td><td>54.00</td><td>-10.93</td><td>46.76</td><td>36.60</td><td>11.91</td><td>52.20</td><td>200</td><td>313</td><td>Average</td></tr><tr><td>3</td><td>10360.00</td><td>56.42</td><td>68.30</td><td>-11.88</td><td>55.16</td><td>38.10</td><td>14.59</td><td>51.43</td><td>200</td><td>170</td><td>Peak</td></tr><tr><td>4</td><td>15540.00</td><td>46.95</td><td>74.00</td><td>-27.05</td><td>41.37</td><td>40.60</td><td>17.17</td><td>52.19</td><td>---</td><td>---</td><td>Peak</td></tr></table>											Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg		1	7252.00	49.18	74.00	-24.82	52.87	36.60	11.91	52.20	200	313	Peak	2	7252.00	43.07	54.00	-10.93	46.76	36.60	11.91	52.20	200	313	Average	3	10360.00	56.42	68.30	-11.88	55.16	38.10	14.59	51.43	200	170	Peak	4	15540.00	46.95	74.00	-27.05	41.37	40.60	17.17	52.19	---	---	Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>7252.00</td><td>54.30</td><td>74.00</td><td>-19.70</td><td>57.99</td><td>36.60</td><td>11.91</td><td>52.20</td><td>113</td><td>338</td><td>Peak</td></tr><tr><td>2</td><td>7252.00</td><td>45.87</td><td>54.00</td><td>-8.13</td><td>49.56</td><td>36.60</td><td>11.91</td><td>52.20</td><td>113</td><td>338</td><td>Average</td></tr><tr><td>3</td><td>10360.00</td><td>58.21</td><td>68.30</td><td>-10.09</td><td>56.95</td><td>38.10</td><td>14.59</td><td>51.43</td><td>190</td><td>166</td><td>Peak</td></tr><tr><td>4</td><td>15540.00</td><td>47.44</td><td>74.00</td><td>-26.56</td><td>41.86</td><td>40.60</td><td>17.17</td><td>52.19</td><td>---</td><td>---</td><td>Peak</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg		1	7252.00	54.30	74.00	-19.70	57.99	36.60	11.91	52.20	113	338	Peak	2	7252.00	45.87	54.00	-8.13	49.56	36.60	11.91	52.20	113	338	Average	3	10360.00	58.21	68.30	-10.09	56.95	38.10	14.59	51.43	190	166	Peak	4	15540.00	47.44	74.00	-26.56	41.86	40.60	17.17	52.19	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																																																															
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																																																														
		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																																												
1	7252.00	49.18	74.00	-24.82	52.87	36.60	11.91	52.20	200	313	Peak																																																																																																																																																												
2	7252.00	43.07	54.00	-10.93	46.76	36.60	11.91	52.20	200	313	Average																																																																																																																																																												
3	10360.00	56.42	68.30	-11.88	55.16	38.10	14.59	51.43	200	170	Peak																																																																																																																																																												
4	15540.00	46.95	74.00	-27.05	41.37	40.60	17.17	52.19	---	---	Peak																																																																																																																																																												
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																																																																
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																																																															
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																																													
1	7252.00	54.30	74.00	-19.70	57.99	36.60	11.91	52.20	113	338	Peak																																																																																																																																																												
2	7252.00	45.87	54.00	-8.13	49.56	36.60	11.91	52.20	113	338	Average																																																																																																																																																												
3	10360.00	58.21	68.30	-10.09	56.95	38.10	14.59	51.43	190	166	Peak																																																																																																																																																												
4	15540.00	47.44	74.00	-26.56	41.86	40.60	17.17	52.19	---	---	Peak																																																																																																																																																												



		2																																																																												
Mode		Harmonic																																																																												
		U-NII-1_5.15-5.25_802.11a_CH44_5220MHz																																																																												
ANT		CDD 7+6																																																																												
Pol.		Horizontal																																																																												
Peak Avg		Date: 2025-05-14 <table><thead><tr><th></th><th>Freq</th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th colspan="2">Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>7308.00</td><td>51.49</td><td>74.00</td><td>-22.51</td><td>55.12</td><td>36.58</td><td>12.01</td><td>52.22</td><td>200</td><td>333 Peak</td></tr><tr><td>2</td><td>7308.00</td><td>43.82</td><td>54.00</td><td>-10.18</td><td>47.45</td><td>36.58</td><td>12.01</td><td>52.22</td><td>200</td><td>333 Average</td></tr><tr><td>3</td><td>10440.00</td><td>56.44</td><td>68.30</td><td>-11.86</td><td>55.12</td><td>38.14</td><td>14.59</td><td>51.41</td><td>200</td><td>177 Peak</td></tr><tr><td>4</td><td>15660.00</td><td>44.90</td><td>74.00</td><td>-29.10</td><td>39.56</td><td>40.60</td><td>17.19</td><td>52.45</td><td>---</td><td>---</td><td>Peak</td></tr></tbody></table>											Freq	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	7308.00	51.49	74.00	-22.51	55.12	36.58	12.01	52.22	200	333 Peak	2	7308.00	43.82	54.00	-10.18	47.45	36.58	12.01	52.22	200	333 Average	3	10440.00	56.44	68.30	-11.86	55.12	38.14	14.59	51.41	200	177 Peak	4	15660.00	44.90	74.00	-29.10	39.56	40.60	17.19	52.45	---	---	Peak
			Freq	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	7308.00	51.49	74.00	-22.51	55.12	36.58	12.01	52.22	200	333 Peak																																																																				
2	7308.00	43.82	54.00	-10.18	47.45	36.58	12.01	52.22	200	333 Average																																																																				
3	10440.00	56.44	68.30	-11.86	55.12	38.14	14.59	51.41	200	177 Peak																																																																				
4	15660.00	44.90	74.00	-29.10	39.56	40.60	17.19	52.45	---	---	Peak																																																																			
		Date: 2025-05-14 <table><thead><tr><th></th><th>Freq</th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th colspan="2">Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>7308.00</td><td>54.23</td><td>74.00</td><td>-19.77</td><td>57.86</td><td>36.58</td><td>12.01</td><td>52.22</td><td>111</td><td>336 Peak</td></tr><tr><td>2</td><td>7308.00</td><td>46.24</td><td>54.00</td><td>-7.76</td><td>49.87</td><td>36.58</td><td>12.01</td><td>52.22</td><td>111</td><td>336 Average</td></tr><tr><td>3</td><td>10440.00</td><td>57.53</td><td>68.30</td><td>-10.77</td><td>56.21</td><td>38.14</td><td>14.59</td><td>51.41</td><td>201</td><td>172 Peak</td></tr><tr><td>4</td><td>15660.00</td><td>45.50</td><td>74.00</td><td>-28.50</td><td>40.16</td><td>40.60</td><td>17.19</td><td>52.45</td><td>---</td><td>---</td><td>Peak</td></tr></tbody></table>											Freq	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	7308.00	54.23	74.00	-19.77	57.86	36.58	12.01	52.22	111	336 Peak	2	7308.00	46.24	54.00	-7.76	49.87	36.58	12.01	52.22	111	336 Average	3	10440.00	57.53	68.30	-10.77	56.21	38.14	14.59	51.41	201	172 Peak	4	15660.00	45.50	74.00	-28.50	40.16	40.60	17.19	52.45	---	---	Peak
	Freq	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																					
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	7308.00	54.23	74.00	-19.77	57.86	36.58	12.01	52.22	111	336 Peak																																																																				
2	7308.00	46.24	54.00	-7.76	49.87	36.58	12.01	52.22	111	336 Average																																																																				
3	10440.00	57.53	68.30	-10.77	56.21	38.14	14.59	51.41	201	172 Peak																																																																				
4	15660.00	45.50	74.00	-28.50	40.16	40.60	17.19	52.45	---	---	Peak																																																																			



Mode	3																																																																									
	Band Edge - L																																																																									
	U-NII-1_5.15-5.25_802.11a_CH48_5240MHz																																																																									
ANT	CDD 7+6																																																																									
Pol.	Horizontal	Fundamental																																																																								
Peak	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5080.52</td><td>52.92</td><td>74.00</td><td>-21.08</td><td>38.62</td><td>35.80</td><td>11.12</td><td>32.62</td><td>100 43 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5080.52	52.92	74.00	-21.08	38.62	35.80	11.12	32.62	100 43 PEAK	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5240.00</td><td>105.04</td><td>-----</td><td>-----</td><td>90.87</td><td>35.80</td><td>11.02</td><td>32.65</td><td>100 43 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5240.00	105.04	-----	-----	90.87	35.80	11.02	32.65	100 43 PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																			
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																		
1 5080.52	52.92	74.00	-21.08	38.62	35.80	11.12	32.62	100 43 PEAK																																																																		
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																			
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																		
1 5240.00	105.04	-----	-----	90.87	35.80	11.02	32.65	100 43 PEAK																																																																		
Avg	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5119.88</td><td>42.86</td><td>54.00</td><td>-11.14</td><td>28.62</td><td>35.76</td><td>11.10</td><td>32.62</td><td>100 43 AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5119.88	42.86	54.00	-11.14	28.62	35.76	11.10	32.62	100 43 AVERAGE	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5240.00</td><td>98.87</td><td>-----</td><td>-----</td><td>84.70</td><td>35.80</td><td>11.02</td><td>32.65</td><td>100 43 AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5240.00	98.87	-----	-----	84.70	35.80	11.02	32.65	100 43 AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																			
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																		
1 5119.88	42.86	54.00	-11.14	28.62	35.76	11.10	32.62	100 43 AVERAGE																																																																		
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																			
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																		
1 5240.00	98.87	-----	-----	84.70	35.80	11.02	32.65	100 43 AVERAGE																																																																		



Mode	3																																										
	Band Edge - R																																										
	U-NII-1_5.15-5.25_802.11a_CH48_5240MHz																																										
ANT	CDD 7+6																																										
Pol.	Horizontal	Fundamental																																									
Peak	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5371.47</td><td>52.35</td><td>74.00</td><td>-21.65</td><td>38.03</td><td>36.06</td><td>10.93</td><td>32.67</td><td>100</td><td>43 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5371.47	52.35	74.00	-21.65	38.03	36.06	10.93	32.67	100	43 PEAK	Blank
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5371.47	52.35	74.00	-21.65	38.03	36.06	10.93	32.67	100	43 PEAK																																	
Avg	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5365.51</td><td>42.62</td><td>54.00</td><td>-11.38</td><td>28.29</td><td>36.07</td><td>10.93</td><td>32.67</td><td>100</td><td>43 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5365.51	42.62	54.00	-11.38	28.29	36.07	10.93	32.67	100	43 AVERAGE	Blank
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5365.51	42.62	54.00	-11.38	28.29	36.07	10.93	32.67	100	43 AVERAGE																																	





Mode	3																																																																															
	Band Edge - L																																																																															
	U-NII-1_5.15-5.25_802.11a_CH48_5240MHz																																																																															
ANT	CDD 7+6																																																																															
Pol.	Vertical	Fundamental																																																																														
Peak	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5075.02</td><td>53.25</td><td>74.00</td><td>-20.75</td><td>38.94</td><td>35.80</td><td>11.13</td><td>32.62</td><td>256</td><td>97 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5075.02	53.25	74.00	-20.75	38.94	35.80	11.13	32.62	256	97 PEAK	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5240.00</td><td>109.35</td><td>-----</td><td>-----</td><td>95.17</td><td>35.80</td><td>11.03</td><td>32.65</td><td>256</td><td>97 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5240.00	109.35	-----	-----	95.17	35.80	11.03	32.65	256	97 PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																							
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																									
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																							
1	5075.02	53.25	74.00	-20.75	38.94	35.80	11.13	32.62	256	97 PEAK																																																																						
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																								
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																									
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																							
1	5240.00	109.35	-----	-----	95.17	35.80	11.03	32.65	256	97 PEAK																																																																						
Avg	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5103.34</td><td>43.19</td><td>54.00</td><td>-10.81</td><td>28.91</td><td>35.79</td><td>11.11</td><td>32.62</td><td>256</td><td>97 AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5103.34	43.19	54.00	-10.81	28.91	35.79	11.11	32.62	256	97 AVERAGE	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5240.00</td><td>102.17</td><td>-----</td><td>-----</td><td>87.99</td><td>35.80</td><td>11.03</td><td>32.65</td><td>256</td><td>97 AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5240.00	102.17	-----	-----	87.99	35.80	11.03	32.65	256	97 AVERAGE
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																								
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																									
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																							
1	5103.34	43.19	54.00	-10.81	28.91	35.79	11.11	32.62	256	97 AVERAGE																																																																						
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																								
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																									
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																							
1	5240.00	102.17	-----	-----	87.99	35.80	11.03	32.65	256	97 AVERAGE																																																																						



Mode	3	
	Band Edge - R	
	U-NII-1_5.15-5.25_802.11a_CH48_5240MHz	
ANT	CDD 7+6	
Pol.	Vertical	Fundamental
Peak	</	







Mode	3																																																																																								
	Harmonic																																																																																								
	U-NII-1_5.15-5.25_802.11a_CH48_5240MHz																																																																																								
ANT	CDD 7+6																																																																																								
Pol.	Horizontal																																																																																								
Peak Avg	Date: 2025-05-14 																																																																																								
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>7336.00</td><td>52.72</td><td>74.00</td><td>-21.28</td><td>56.42</td><td>36.53</td><td>12.00</td><td>52.23</td><td>200</td><td>300</td><td>Peak</td></tr><tr><td>2</td><td>7336.00</td><td>43.53</td><td>54.00</td><td>-10.47</td><td>47.23</td><td>36.53</td><td>12.00</td><td>52.23</td><td>200</td><td>300</td><td>Average</td></tr><tr><td>3</td><td>10480.00</td><td>55.92</td><td>68.30</td><td>-12.38</td><td>54.55</td><td>38.18</td><td>14.59</td><td>51.40</td><td>210</td><td>188</td><td>Peak</td></tr><tr><td>4</td><td>15720.00</td><td>45.69</td><td>74.00</td><td>-28.31</td><td>40.46</td><td>40.62</td><td>17.19</td><td>52.58</td><td>---</td><td>---</td><td>Peak</td></tr></table>												Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg		1	7336.00	52.72	74.00	-21.28	56.42	36.53	12.00	52.23	200	300	Peak	2	7336.00	43.53	54.00	-10.47	47.23	36.53	12.00	52.23	200	300	Average	3	10480.00	55.92	68.30	-12.38	54.55	38.18	14.59	51.40	210	188	Peak	4	15720.00	45.69	74.00	-28.31	40.46	40.62	17.19	52.58	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																
		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																														
1	7336.00	52.72	74.00	-21.28	56.42	36.53	12.00	52.23	200	300	Peak																																																																														
2	7336.00	43.53	54.00	-10.47	47.23	36.53	12.00	52.23	200	300	Average																																																																														
3	10480.00	55.92	68.30	-12.38	54.55	38.18	14.59	51.40	210	188	Peak																																																																														
4	15720.00	45.69	74.00	-28.31	40.46	40.62	17.19	52.58	---	---	Peak																																																																														
Pol.	Vertical																																																																																								
Peak Avg	Date: 2025-05-14 																																																																																								
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>7336.00</td><td>55.06</td><td>74.00</td><td>-18.94</td><td>58.76</td><td>36.53</td><td>12.00</td><td>52.23</td><td>126</td><td>338</td><td>Peak</td></tr><tr><td>2</td><td>7336.00</td><td>45.83</td><td>54.00</td><td>-8.17</td><td>49.53</td><td>36.53</td><td>12.00</td><td>52.23</td><td>126</td><td>338</td><td>Average</td></tr><tr><td>3</td><td>10480.00</td><td>57.61</td><td>68.30</td><td>-10.69</td><td>56.24</td><td>38.18</td><td>14.59</td><td>51.40</td><td>165</td><td>178</td><td>Peak</td></tr><tr><td>4</td><td>15720.00</td><td>46.16</td><td>74.00</td><td>-27.84</td><td>40.93</td><td>40.62</td><td>17.19</td><td>52.58</td><td>---</td><td>---</td><td>Peak</td></tr></table>												Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg		1	7336.00	55.06	74.00	-18.94	58.76	36.53	12.00	52.23	126	338	Peak	2	7336.00	45.83	54.00	-8.17	49.53	36.53	12.00	52.23	126	338	Average	3	10480.00	57.61	68.30	-10.69	56.24	38.18	14.59	51.40	165	178	Peak	4	15720.00	46.16	74.00	-27.84	40.93	40.62	17.19	52.58	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																
		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																														
1	7336.00	55.06	74.00	-18.94	58.76	36.53	12.00	52.23	126	338	Peak																																																																														
2	7336.00	45.83	54.00	-8.17	49.53	36.53	12.00	52.23	126	338	Average																																																																														
3	10480.00	57.61	68.30	-10.69	56.24	38.18	14.59	51.40	165	178	Peak																																																																														
4	15720.00	46.16	74.00	-27.84	40.93	40.62	17.19	52.58	---	---	Peak																																																																														





Mode	4																																																																																	
	Band Edge																																																																																	
	U-NII-1_5.15-5.25_802.11n HT20_CH36_5180MHz																																																																																	
ANT	CDD 7+6																																																																																	
Pol.	Horizontal	Fundamental																																																																																
Peak	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5120.71</td><td>53.26</td><td>74.00</td><td>-20.74</td><td>39.02</td><td>35.76</td><td>11.10</td><td>32.62</td><td>100</td><td>44</td><td>PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5120.71	53.26	74.00	-20.74	39.02	35.76	11.10	32.62	100	44	PEAK	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5180.00</td><td>104.42</td><td>-----</td><td>-----</td><td>90.23</td><td>35.76</td><td>11.07</td><td>32.64</td><td>100</td><td>44</td><td>PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5180.00	104.42	-----	-----	90.23	35.76	11.07	32.64	100	44	PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																											
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1	5120.71	53.26	74.00	-20.74	39.02	35.76	11.10	32.62	100	44	PEAK																																																																							
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																											
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1	5180.00	104.42	-----	-----	90.23	35.76	11.07	32.64	100	44	PEAK																																																																							
Avg	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5144.27</td><td>43.54</td><td>54.00</td><td>-10.46</td><td>29.37</td><td>35.71</td><td>11.09</td><td>32.63</td><td>100</td><td>44</td><td>AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5144.27	43.54	54.00	-10.46	29.37	35.71	11.09	32.63	100	44	AVERAGE	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5180.00</td><td>97.55</td><td>-----</td><td>-----</td><td>83.36</td><td>35.76</td><td>11.07</td><td>32.64</td><td>100</td><td>44</td><td>AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5180.00	97.55	-----	-----	83.36	35.76	11.07	32.64	100	44	AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																											
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1	5144.27	43.54	54.00	-10.46	29.37	35.71	11.09	32.63	100	44	AVERAGE																																																																							
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																											
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1	5180.00	97.55	-----	-----	83.36	35.76	11.07	32.64	100	44	AVERAGE																																																																							





		4																																																																														
Mode		Band Edge																																																																														
		U-NII-1_5.15-5.25_802.11n HT20_CH36_5180MHz																																																																														
ANT		CDD 7+6																																																																														
Pol.		Vertical					Fundamental																																																																									
Peak																																																																																
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5140.67	54.72	74.00	-19.28	40.54	35.72	11.09	32.63	245	97 PEAK	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5180.00</td><td>107.82</td><td>-----</td><td>-----</td><td>93.63</td><td>35.76</td><td>11.07</td><td>32.64</td><td>245</td><td>97 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5180.00	107.82	-----	-----	93.63	35.76	11.07	32.64	245
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																							
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																										
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																							
1 5140.67	54.72	74.00	-19.28	40.54	35.72	11.09	32.63	245	97 PEAK																																																																							
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																							
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																										
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																							
1 5180.00	107.82	-----	-----	93.63	35.76	11.07	32.64	245	97 PEAK																																																																							
Avg																																																																																
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5148.25	45.53	54.00	-8.47	31.37	35.70	11.09	32.63	245	97 AVERAGE	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5180.00</td><td>101.30</td><td>-----</td><td>-----</td><td>87.11</td><td>35.75</td><td>11.07</td><td>32.63</td><td>245</td><td>97 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5180.00	101.30	-----	-----	87.11	35.75	11.07	32.63	245
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																							
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																										
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																							
1 5148.25	45.53	54.00	-8.47	31.37	35.70	11.09	32.63	245	97 AVERAGE																																																																							
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																							
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																										
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																							
1 5180.00	101.30	-----	-----	87.11	35.75	11.07	32.63	245	97 AVERAGE																																																																							



Mode	4																																																																																																																			
	Harmonic																																																																																																																			
	U-NII-1_5.15-5.25_802.11n HT20_CH36_5180MHz																																																																																																																			
ANT	CDD 7+6																																																																																																																			
Pol.	Horizontal						Vertical																																																																																																													
Peak Avg																																																																																																																				
	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>10360.00</td><td>56.69</td><td>68.30</td><td>-11.61</td><td>55.87</td><td>38.10</td><td>14.15</td><td>51.43</td><td>177</td><td>122</td><td>Peak</td></tr><tr><td>2</td><td>15540.00</td><td>47.21</td><td>74.00</td><td>-26.79</td><td>41.95</td><td>40.60</td><td>16.85</td><td>52.19</td><td>---</td><td>---</td><td>Peak</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10360.00	56.69	68.30	-11.61	55.87	38.10	14.15	51.43	177	122	Peak	2	15540.00	47.21	74.00	-26.79	41.95	40.60	16.85	52.19	---	---	Peak	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>10360.00</td><td>57.78</td><td>68.30</td><td>-10.52</td><td>56.96</td><td>38.10</td><td>14.15</td><td>51.43</td><td>159</td><td>184</td><td>Peak</td></tr><tr><td>2</td><td>15540.00</td><td>47.55</td><td>74.00</td><td>-26.45</td><td>42.29</td><td>40.60</td><td>16.85</td><td>52.19</td><td>---</td><td>---</td><td>Peak</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10360.00	57.78	68.30	-10.52	56.96	38.10	14.15	51.43	159	184	Peak	2	15540.00	47.55	74.00	-26.45	42.29	40.60	16.85	52.19	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																												
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																																											
1	10360.00	56.69	68.30	-11.61	55.87	38.10	14.15	51.43	177	122	Peak																																																																																																									
2	15540.00	47.21	74.00	-26.79	41.95	40.60	16.85	52.19	---	---	Peak																																																																																																									
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																													
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																																											
1	10360.00	57.78	68.30	-10.52	56.96	38.10	14.15	51.43	159	184	Peak																																																																																																									
2	15540.00	47.55	74.00	-26.45	42.29	40.60	16.85	52.19	---	---	Peak																																																																																																									



Mode	5																																																																																															
	Harmonic																																																																																															
	U-NII-1_5.15-5.25_802.11n HT20_CH44_5220MHz																																																																																															
ANT	CDD 7+6																																																																																															
Pol.	Horizontal						Vertical																																																																																									
Peak Avg																																																																																																
	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th>Remark</th></tr></thead><tbody><tr><td>1</td><td>10440.00</td><td>57.35</td><td>68.30</td><td>-10.95</td><td>56.42</td><td>38.14</td><td>14.20</td><td>51.41</td><td>180</td><td>127</td><td>Peak</td></tr><tr><td>2</td><td>15660.00</td><td>45.98</td><td>74.00</td><td>-28.02</td><td>40.89</td><td>40.60</td><td>16.94</td><td>52.45</td><td>---</td><td>---</td><td>Peak</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss Factor		Remark	1	10440.00	57.35	68.30	-10.95	56.42	38.14	14.20	51.41	180	127	Peak	2	15660.00	45.98	74.00	-28.02	40.89	40.60	16.94	52.45	---	---	Peak	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th>Remark</th></tr></thead><tbody><tr><td>1</td><td>10440.00</td><td>58.78</td><td>68.30</td><td>-9.52</td><td>57.85</td><td>38.14</td><td>14.20</td><td>51.41</td><td>137</td><td>182</td><td>Peak</td></tr><tr><td>2</td><td>15660.00</td><td>46.57</td><td>74.00</td><td>-27.43</td><td>41.48</td><td>40.60</td><td>16.94</td><td>52.45</td><td>---</td><td>---</td><td>Peak</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss Factor		Remark	1	10440.00	58.78	68.30	-9.52	57.85	38.14	14.20	51.41	137	182	Peak	2	15660.00	46.57	74.00	-27.43	41.48	40.60	16.94	52.45	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																								
Freq	Level	Line	Margin	Level	Factor	Loss Factor		Remark																																																																																								
1	10440.00	57.35	68.30	-10.95	56.42	38.14	14.20	51.41	180	127	Peak																																																																																					
2	15660.00	45.98	74.00	-28.02	40.89	40.60	16.94	52.45	---	---	Peak																																																																																					
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																									
Freq	Level	Line	Margin	Level	Factor	Loss Factor		Remark																																																																																								
1	10440.00	58.78	68.30	-9.52	57.85	38.14	14.20	51.41	137	182	Peak																																																																																					
2	15660.00	46.57	74.00	-27.43	41.48	40.60	16.94	52.45	---	---	Peak																																																																																					







		6																																																																																						
Mode		Band Edge - L																																																																																						
		U-NII-1_5.15-5.25_802.11n HT20_CH48_5240MHz																																																																																						
ANT		CDD 7+6																																																																																						
Pol.		Horizontal					Fundamental																																																																																	
Peak	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5127.34</td><td>53.48</td><td>74.00</td><td>-20.52</td><td>39.26</td><td>35.75</td><td>11.10</td><td>32.63</td><td>100</td><td>43 PEAK</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5127.34	53.48	74.00	-20.52	39.26	35.75	11.10	32.63	100	43 PEAK	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5240.00</td><td>104.56</td><td>-----</td><td>-----</td><td>90.38</td><td>35.80</td><td>11.03</td><td>32.65</td><td>100</td><td>43 PEAK</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5240.00	104.56	-----	-----	90.38	35.80	11.03	32.65	100	43 PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																															
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																	
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																															
1	5127.34	53.48	74.00	-20.52	39.26	35.75	11.10	32.63	100	43 PEAK																																																																														
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																	
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																															
1	5240.00	104.56	-----	-----	90.38	35.80	11.03	32.65	100	43 PEAK																																																																														
Avg	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5093.96</td><td>42.89</td><td>54.00</td><td>-11.11</td><td>28.59</td><td>35.80</td><td>11.12</td><td>32.62</td><td>100</td><td>43 AVERAGE</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5093.96	42.89	54.00	-11.11	28.59	35.80	11.12	32.62	100	43 AVERAGE	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5240.00</td><td>97.31</td><td>-----</td><td>-----</td><td>83.13</td><td>35.80</td><td>11.03</td><td>32.65</td><td>100</td><td>43 AVERAGE</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5240.00	97.31	-----	-----	83.13	35.80	11.03	32.65	100	43 AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																															
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																	
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																															
1	5093.96	42.89	54.00	-11.11	28.59	35.80	11.12	32.62	100	43 AVERAGE																																																																														
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																	
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																															
1	5240.00	97.31	-----	-----	83.13	35.80	11.03	32.65	100	43 AVERAGE																																																																														



Mode	6									
	Band Edge - R									
	U-NII-1_5.15-5.25_802.11n HT20_CH48_5240MHz									
ANT	CDD 7+6									
Pol.	Horizontal					Fundamental				
Peak										





		6																																																																																								
Mode		Band Edge - L																																																																																								
		U-NII-1_5.15-5.25_802.11n HT20_CH48_5240MHz																																																																																								
ANT		CDD 7+6																																																																																								
Pol.		Vertical					Fundamental																																																																																			
Peak	Level (dBuV/m) Date: 2025-03-26  Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5053.88</td><td>53.21</td><td>74.00</td><td>-20.79</td><td>38.88</td><td>35.80</td><td>11.14</td><td>32.61</td><td>246</td><td>100</td><td>PEAK</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5053.88	53.21	74.00	-20.79	38.88	35.80	11.14	32.61	246	100	PEAK	Level (dBuV/m) Date: 2025-03-26  Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5240.00</td><td>106.98</td><td>-----</td><td>-----</td><td>92.80</td><td>35.80</td><td>11.03</td><td>32.65</td><td>246</td><td>100</td><td>PEAK</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5240.00	106.98	-----	-----	92.80	35.80	11.03	32.65	246	100	PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																			
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5053.88	53.21	74.00	-20.79	38.88	35.80	11.14	32.61	246	100	PEAK																																																																															
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																			
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5240.00	106.98	-----	-----	92.80	35.80	11.03	32.65	246	100	PEAK																																																																															
Avg	Level (dBuV/m) Date: 2025-03-26  Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5129.43</td><td>43.24</td><td>54.00</td><td>-10.76</td><td>29.03</td><td>35.74</td><td>11.10</td><td>32.63</td><td>246</td><td>100</td><td>AVERAGE</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5129.43	43.24	54.00	-10.76	29.03	35.74	11.10	32.63	246	100	AVERAGE	Level (dBuV/m) Date: 2025-03-26  Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5240.00</td><td>100.49</td><td>-----</td><td>-----</td><td>86.31</td><td>35.80</td><td>11.03</td><td>32.65</td><td>246</td><td>100</td><td>AVERAGE</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5240.00	100.49	-----	-----	86.31	35.80	11.03	32.65	246	100	AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																			
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5129.43	43.24	54.00	-10.76	29.03	35.74	11.10	32.63	246	100	AVERAGE																																																																															
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																			
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5240.00	100.49	-----	-----	86.31	35.80	11.03	32.65	246	100	AVERAGE																																																																															



Mode	6																																																			
	Band Edge - R																																																			
	U-NII-1_5.15-5.25_802.11n HT20_CH48_5240MHz																																																			
ANT	CDD 7+6																																																			
Pol.	Vertical	Fundamental																																																		
Peak	Date: 2025-03-26 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5366.81</td><td>52.47</td><td>74.00</td><td>-21.53</td><td>38.14</td><td>36.07</td><td>10.93</td><td>32.67</td><td>246</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>100 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5366.81	52.47	74.00	-21.53	38.14	36.07	10.93	32.67	246										100 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																												
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																											
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																											
1	5366.81	52.47	74.00	-21.53	38.14	36.07	10.93	32.67	246																																											
									100 PEAK																																											
Avg	Date: 2025-03-26 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5354.97</td><td>42.70</td><td>54.00</td><td>-11.30</td><td>28.34</td><td>36.09</td><td>10.94</td><td>32.67</td><td>246</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>100 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5354.97	42.70	54.00	-11.30	28.34	36.09	10.94	32.67	246										100 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																												
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																											
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																											
1	5354.97	42.70	54.00	-11.30	28.34	36.09	10.94	32.67	246																																											
									100 AVERAGE																																											





Mode	6																																																																																																																							
	Harmonic																																																																																																																							
	U-NII-1_5.15-5.25_802.11n HT20_CH48_5240MHz																																																																																																																							
ANT	CDD 7+6																																																																																																																							
Pol.	Horizontal								Vertical																																																																																																															
Peak Avg																																																																																																																								
	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>10480.00</td><td>56.97</td><td>68.30</td><td>-11.33</td><td>55.96</td><td>38.18</td><td>14.23</td><td>51.40</td><td>175</td><td>125</td><td>Peak</td></tr><tr><td>2</td><td>15720.00</td><td>47.09</td><td>74.00</td><td>-26.91</td><td>42.06</td><td>40.62</td><td>16.99</td><td>52.58</td><td>---</td><td>---</td><td>Peak</td></tr></tbody></table>									Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	10480.00	56.97	68.30	-11.33	55.96	38.18	14.23	51.40	175	125	Peak	2	15720.00	47.09	74.00	-26.91	42.06	40.62	16.99	52.58	---	---	Peak	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>10480.00</td><td>58.35</td><td>68.30</td><td>-9.95</td><td>57.34</td><td>38.18</td><td>14.23</td><td>51.40</td><td>144</td><td>185</td><td>Peak</td></tr><tr><td>2</td><td>15720.00</td><td>47.41</td><td>74.00</td><td>-26.59</td><td>42.38</td><td>40.62</td><td>16.99</td><td>52.58</td><td>---</td><td>---</td><td>Peak</td></tr></tbody></table>									Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	10480.00	58.35	68.30	-9.95	57.34	38.18	14.23	51.40	144	185	Peak	2	15720.00	47.41	74.00	-26.59	42.38	40.62	16.99	52.58	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																															
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																															
1	10480.00	56.97	68.30	-11.33	55.96	38.18	14.23	51.40	175	125	Peak																																																																																																													
2	15720.00	47.09	74.00	-26.91	42.06	40.62	16.99	52.58	---	---	Peak																																																																																																													
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																	
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																															
1	10480.00	58.35	68.30	-9.95	57.34	38.18	14.23	51.40	144	185	Peak																																																																																																													
2	15720.00	47.41	74.00	-26.59	42.38	40.62	16.99	52.58	---	---	Peak																																																																																																													



Mode	7																																																																																																	
	Band Edge - L																																																																																																	
	U-NII-1_5.15-5.25_802.11n HT40_CH38_5190MHz																																																																																																	
ANT	CDD 7+6																																																																																																	
Pol.	Horizontal	Fundamental																																																																																																
Peak	Level (dBuV/m) Date: 2025-05-14 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th></tr></thead><tbody><tr><td>1 5148.72</td><td>55.58</td><td>74.00</td><td>-18.42</td><td>41.42</td><td>35.70</td><td>11.09</td><td>32.63</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>236 310 Peak</td></tr></tbody></table>	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	1 5148.72	55.58	74.00	-18.42	41.42	35.70	11.09	32.63								236 310 Peak	Level (dBuV/m) Date: 2025-05-14 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th></tr></thead><tbody><tr><td>1 5190.00</td><td>98.80</td><td>-----</td><td>-----</td><td>84.60</td><td>35.78</td><td>11.06</td><td>32.64</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>236 310 Peak</td></tr><tr><td>2 5190.00</td><td>92.80</td><td>-----</td><td>-----</td><td>78.60</td><td>35.78</td><td>11.06</td><td>32.64</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>236 310 Average</td></tr></tbody></table>	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	1 5190.00	98.80	-----	-----	84.60	35.78	11.06	32.64								236 310 Peak	2 5190.00	92.80	-----	-----	78.60	35.78	11.06	32.64								236 310 Average
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																										
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm																																																																																											
1 5148.72	55.58	74.00	-18.42	41.42	35.70	11.09	32.63																																																																																											
							236 310 Peak																																																																																											
Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																											
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm																																																																																											
1 5190.00	98.80	-----	-----	84.60	35.78	11.06	32.64																																																																																											
							236 310 Peak																																																																																											
2 5190.00	92.80	-----	-----	78.60	35.78	11.06	32.64																																																																																											
							236 310 Average																																																																																											
Avg	Level (dBuV/m) Date: 2025-05-14 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th></tr></thead><tbody><tr><td>1 5149.99</td><td>44.91</td><td>54.00</td><td>-9.09</td><td>30.76</td><td>35.70</td><td>11.08</td><td>32.63</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>236 310 Average</td></tr></tbody></table>	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	1 5149.99	44.91	54.00	-9.09	30.76	35.70	11.08	32.63								236 310 Average	Blank																																																								
Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																											
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm																																																																																											
1 5149.99	44.91	54.00	-9.09	30.76	35.70	11.08	32.63																																																																																											
							236 310 Average																																																																																											





Mode	7																																																	
	Band Edge - R																																																	
	U-NII-1_5.15-5.25_802.11n HT40_CH38_5190MHz																																																	
ANT	CDD 7+6																																																	
Pol.	Horizontal										Fundamental																																							
Peak	Level (dBuV/m) Date: 2025-05-14  <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5446.28</td><td>52.90</td><td>74.00</td><td>-21.10</td><td>38.62</td><td>35.91</td><td>11.06</td><td>32.69</td><td>236</td><td>310</td><td>Peak</td></tr></table> Blank											Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	5446.28	52.90	74.00	-21.10	38.62	35.91	11.06	32.69	236	310	Peak
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																											
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																									
1	5446.28	52.90	74.00	-21.10	38.62	35.91	11.06	32.69	236	310	Peak																																							
Avg	Level (dBuV/m) Date: 2025-05-14  <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5353.04</td><td>41.39</td><td>54.00</td><td>-12.61</td><td>27.03</td><td>36.09</td><td>10.94</td><td>32.67</td><td>236</td><td>310</td><td>Average</td></tr></table> Blank											Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	5353.04	41.39	54.00	-12.61	27.03	36.09	10.94	32.67	236	310	Average
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																											
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																										
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																									
1	5353.04	41.39	54.00	-12.61	27.03	36.09	10.94	32.67	236	310	Average																																							



Mode	7																																																																																											
	Band Edge - L																																																																																											
	U-NII-1_5.15-5.25_802.11n HT40_CH38_5190MHz																																																																																											
ANT	CDD 7+6																																																																																											
Pol.	Vertical	Fundamental																																																																																										
Peak	Level (dBuV/m) Date: 2025-05-13 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5148.98</td><td>59.03</td><td>74.00</td><td>-14.97</td><td>44.87</td><td>35.70</td><td>11.09</td><td>32.63</td><td>235</td><td>166</td><td>Peak</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	5148.98	59.03	74.00	-14.97	44.87	35.70	11.09	32.63	235	166	Peak	Level (dBuV/m) Date: 2025-05-14 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5190.00</td><td>104.03</td><td>-----</td><td>89.83</td><td>35.78</td><td>11.06</td><td>32.64</td><td>235</td><td>166</td><td>Peak</td></tr><tr><td>2</td><td>5190.00</td><td>97.47</td><td>-----</td><td>83.27</td><td>35.78</td><td>11.06</td><td>32.64</td><td>235</td><td>166</td><td>Average</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	5190.00	104.03	-----	89.83	35.78	11.06	32.64	235	166	Peak	2	5190.00	97.47	-----	83.27	35.78	11.06	32.64	235	166	Average
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																			
1	5148.98	59.03	74.00	-14.97	44.87	35.70	11.09	32.63	235	166	Peak																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																			
1	5190.00	104.03	-----	89.83	35.78	11.06	32.64	235	166	Peak																																																																																		
2	5190.00	97.47	-----	83.27	35.78	11.06	32.64	235	166	Average																																																																																		
Avg	Level (dBuV/m) Date: 2025-05-14 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5149.99</td><td>48.40</td><td>54.00</td><td>-5.60</td><td>34.25</td><td>35.70</td><td>11.08</td><td>32.63</td><td>235</td><td>166</td><td>Average</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	5149.99	48.40	54.00	-5.60	34.25	35.70	11.08	32.63	235	166	Average	Blank																																																		
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																				
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																			
1	5149.99	48.40	54.00	-5.60	34.25	35.70	11.08	32.63	235	166	Average																																																																																	



Mode	7																																																																																													
	Harmonic																																																																																													
	U-NII-1_5.15-5.25_802.11n HT40_CH38_5190MHz																																																																																													
ANT	CDD 7+6																																																																																													
Pol.	Horizontal							Vertical																																																																																						
Peak Avg																																																																																														
	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th></tr></thead><tbody><tr><td>1</td><td>10380.00</td><td>51.30</td><td>68.30</td><td>-17.00</td><td>50.46</td><td>38.10</td><td>14.16</td></tr><tr><td>2</td><td>15570.00</td><td>47.58</td><td>74.00</td><td>-26.42</td><td>42.36</td><td>40.60</td><td>16.87</td></tr></tbody></table>								Limit	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	1	10380.00	51.30	68.30	-17.00	50.46	38.10	14.16	2	15570.00	47.58	74.00	-26.42	42.36	40.60	16.87	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th></tr></thead><tbody><tr><td>1</td><td>10380.00</td><td>52.50</td><td>68.30</td><td>-15.80</td><td>51.66</td><td>38.10</td><td>14.16</td></tr><tr><td>2</td><td>15570.00</td><td>47.08</td><td>74.00</td><td>-26.92</td><td>41.86</td><td>40.60</td><td>16.87</td></tr></tbody></table>								Limit	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	1	10380.00	52.50	68.30	-15.80	51.66	38.10	14.16	2	15570.00	47.08	74.00	-26.92	41.86	40.60	16.87
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																						
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																						
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB																																																																																							
1	10380.00	51.30	68.30	-17.00	50.46	38.10	14.16																																																																																							
2	15570.00	47.58	74.00	-26.42	42.36	40.60	16.87																																																																																							
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																							
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																							
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB																																																																																							
1	10380.00	52.50	68.30	-15.80	51.66	38.10	14.16																																																																																							
2	15570.00	47.08	74.00	-26.92	41.86	40.60	16.87																																																																																							
<table><thead><tr><th></th><th>Remark</th></tr></thead><tbody><tr><td>1</td><td>232 Peak</td></tr><tr><td>2</td><td>---</td></tr></tbody></table>								Remark	1	232 Peak	2	---	<table><thead><tr><th></th><th>Remark</th></tr></thead><tbody><tr><td>1</td><td>143 185 Peak</td></tr><tr><td>2</td><td>---</td></tr></tbody></table>								Remark	1	143 185 Peak	2	---																																																																					
	Remark																																																																																													
1	232 Peak																																																																																													
2	---																																																																																													
	Remark																																																																																													
1	143 185 Peak																																																																																													
2	---																																																																																													



Mode	8																																																																											
	Band Edge - L																																																																											
	U-NII-1_5.15-5.25_802.11n HT40_CH46_5230MHz																																																																											
ANT	CDD 7+6																																																																											
Pol.	Horizontal	Fundamental																																																																										
Peak	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5002.65</td><td>53.27</td><td>74.00</td><td>-20.73</td><td>38.92</td><td>35.80</td><td>11.15</td><td>32.60</td><td>100 44 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5002.65	53.27	74.00	-20.73	38.92	35.80	11.15	32.60	100 44 PEAK	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5230.00</td><td>99.50</td><td>-----</td><td>-----</td><td>85.33</td><td>35.80</td><td>11.02</td><td>32.65</td><td>100 44 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5230.00	99.50	-----	-----	85.33	35.80	11.02	32.65	100 44 PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	5002.65	53.27	74.00	-20.73	38.92	35.80	11.15	32.60	100 44 PEAK																																																																			
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	5230.00	99.50	-----	-----	85.33	35.80	11.02	32.65	100 44 PEAK																																																																			
Avg	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5147.80</td><td>43.19</td><td>54.00</td><td>-10.81</td><td>29.03</td><td>35.70</td><td>11.09</td><td>32.63</td><td>100 44 AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5147.80	43.19	54.00	-10.81	29.03	35.70	11.09	32.63	100 44 AVERAGE	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5230.00</td><td>92.99</td><td>-----</td><td>-----</td><td>78.82</td><td>35.80</td><td>11.02</td><td>32.65</td><td>100 44 AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5230.00	92.99	-----	-----	78.82	35.80	11.02	32.65	100 44 AVERAGE
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	5147.80	43.19	54.00	-10.81	29.03	35.70	11.09	32.63	100 44 AVERAGE																																																																			
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	5230.00	92.99	-----	-----	78.82	35.80	11.02	32.65	100 44 AVERAGE																																																																			



Mode	8									
	Band Edge - R									
	U-NII-1_5.15-5.25_802.11n HT40_CH46_5230MHz									
ANT	CDD 7+6									
Pol.	Horizontal					Fundamental				
Peak										



		8																																																																																		
Mode		Band Edge - L																																																																																		
		U-NII-1_5.15-5.25_802.11n HT40_CH46_5230MHz																																																																																		
ANT		CDD 7+6																																																																																		
Pol.		Vertical					Fundamental																																																																													
Peak	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5121.10</td><td>55.51</td><td>74.00</td><td>-18.49</td><td>41.27</td><td>35.76</td><td>11.10</td><td>32.62</td><td>218 157 PEAK</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5121.10	55.51	74.00	-18.49	41.27	35.76	11.10	32.62	218 157 PEAK	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5230.00</td><td>103.50</td><td>-----</td><td>-----</td><td>89.30</td><td>35.80</td><td>11.04</td><td>32.64</td><td>218 157 PEAK</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5230.00	103.50	-----	-----	89.30	35.80	11.04	32.64	218 157 PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																												
1	5121.10	55.51	74.00	-18.49	41.27	35.76	11.10	32.62	218 157 PEAK																																																																											
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																												
1	5230.00	103.50	-----	-----	89.30	35.80	11.04	32.64	218 157 PEAK																																																																											
Avg	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5125.93</td><td>44.18</td><td>54.00</td><td>-9.82</td><td>29.96</td><td>35.75</td><td>11.10</td><td>32.63</td><td>218 157 AVERAGE</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5125.93	44.18	54.00	-9.82	29.96	35.75	11.10	32.63	218 157 AVERAGE	Level (dBuV/m) Date: 2025-03-26 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5230.00</td><td>96.58</td><td>-----</td><td>-----</td><td>82.38</td><td>35.80</td><td>11.04</td><td>32.64</td><td>218 157 AVERAGE</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5230.00	96.58	-----	-----	82.38	35.80	11.04	32.64	218 157 AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																												
1	5125.93	44.18	54.00	-9.82	29.96	35.75	11.10	32.63	218 157 AVERAGE																																																																											
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																												
1	5230.00	96.58	-----	-----	82.38	35.80	11.04	32.64	218 157 AVERAGE																																																																											



Mode	8																																									
	Band Edge - R																																									
	U-NII-1_5.15-5.25_802.11n HT40_CH46_5230MHz																																									
ANT	CDD 7+6																																									
Pol.	Vertical	Fundamental																																								
Peak	Date: 2025-03-26 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5403.77</td><td>52.85</td><td>74.00</td><td>-21.15</td><td>38.64</td><td>35.99</td><td>10.90</td><td>32.68</td><td>218 157 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5403.77	52.85	74.00	-21.15	38.64	35.99	10.90	32.68	218 157 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																	
1	5403.77	52.85	74.00	-21.15	38.64	35.99	10.90	32.68	218 157 PEAK																																	
Avg	Date: 2025-03-26 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5353.63</td><td>43.16</td><td>54.00</td><td>-10.84</td><td>28.80</td><td>36.09</td><td>10.94</td><td>32.67</td><td>218 157 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5353.63	43.16	54.00	-10.84	28.80	36.09	10.94	32.67	218 157 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																	
1	5353.63	43.16	54.00	-10.84	28.80	36.09	10.94	32.67	218 157 AVERAGE																																	



Mode	9																																																																																													
	Band Edge - L																																																																																													
	U-NII-1_5.15-5.25_802.11ac VHT80_CH42_5210MHz																																																																																													
ANT	CDD 7+6																																																																																													
Pol.	Horizontal	Fundamental																																																																																												
Peak	Level (dBuV/m) Date: 2025-05-14 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5136.24</td><td>58.61</td><td>74.00</td><td>-15.39</td><td>44.42</td><td>35.73</td><td>11.09</td><td>32.63</td><td>353</td><td>264</td><td>Peak</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	5136.24	58.61	74.00	-15.39	44.42	35.73	11.09	32.63	353	264	Peak	Level (dBuV/m) Date: 2025-05-14 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5210.00</td><td>100.61</td><td>-----</td><td>-----</td><td>86.40</td><td>35.80</td><td>11.05</td><td>32.64</td><td>353</td><td>264</td><td>Peak</td></tr><tr><td>2</td><td>5210.00</td><td>94.34</td><td>-----</td><td>-----</td><td>80.13</td><td>35.80</td><td>11.05</td><td>32.64</td><td>353</td><td>264</td><td>Average</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	5210.00	100.61	-----	-----	86.40	35.80	11.05	32.64	353	264	Peak	2	5210.00	94.34	-----	-----	80.13	35.80	11.05	32.64	353	264	Average
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																						
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																						
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																					
1	5136.24	58.61	74.00	-15.39	44.42	35.73	11.09	32.63	353	264	Peak																																																																																			
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																							
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																						
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																					
1	5210.00	100.61	-----	-----	86.40	35.80	11.05	32.64	353	264	Peak																																																																																			
2	5210.00	94.34	-----	-----	80.13	35.80	11.05	32.64	353	264	Average																																																																																			
Avg	Level (dBuV/m) Date: 2025-05-14 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5138.58</td><td>48.14</td><td>54.00</td><td>-5.86</td><td>33.96</td><td>35.72</td><td>11.09</td><td>32.63</td><td>353</td><td>264</td><td>Average</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	5138.58	48.14	54.00	-5.86	33.96	35.72	11.09	32.63	353	264	Average	Blank																																																				
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																							
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																						
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																					
1	5138.58	48.14	54.00	-5.86	33.96	35.72	11.09	32.63	353	264	Average																																																																																			



Mode	9																																								
	Band Edge - R																																								
	U-NII-1_5.15-5.25_802.11ac VHT80_CH42_5210MHz																																								
ANT	CDD 7+6																																								
Pol.	Horizontal	Fundamental																																							
Peak	Date: 2025-05-14 <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5417.52</td><td>52.69</td><td>74.00</td><td>-21.31</td><td>38.47</td><td>35.96</td><td>10.94</td><td>32.68</td><td>353</td><td>264 Peak</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	5417.52	52.69	74.00	-21.31	38.47	35.96	10.94	32.68	353	264 Peak	Blank
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																	
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																
1	5417.52	52.69	74.00	-21.31	38.47	35.96	10.94	32.68	353	264 Peak																															
Avg	Date: 2025-05-14 <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5357.04</td><td>41.97</td><td>54.00</td><td>-12.03</td><td>27.61</td><td>36.09</td><td>10.94</td><td>32.67</td><td>353</td><td>264 Average</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	5357.04	41.97	54.00	-12.03	27.61	36.09	10.94	32.67	353	264 Average	Blank
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																	
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																
1	5357.04	41.97	54.00	-12.03	27.61	36.09	10.94	32.67	353	264 Average																															



Mode	9																																																																																													
	Band Edge - L																																																																																													
	U-NII-1_5.15-5.25_802.11ac VHT80_CH42_5210MHz																																																																																													
ANT	CDD 7+6																																																																																													
Pol.	Vertical	Fundamental																																																																																												
Peak	Level (dBuV/m) Date: 2025-05-14 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5132.08</td><td>59.83</td><td>74.00</td><td>-14.17</td><td>45.62</td><td>35.74</td><td>11.10</td><td>32.63</td><td>220</td><td>329</td><td>Peak</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	5132.08	59.83	74.00	-14.17	45.62	35.74	11.10	32.63	220	329	Peak	Level (dBuV/m) Date: 2025-05-14 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5210.00</td><td>100.35</td><td>-----</td><td>-----</td><td>86.14</td><td>35.80</td><td>11.05</td><td>32.64</td><td>220</td><td>329</td><td>Peak</td></tr><tr><td>2</td><td>5210.00</td><td>94.32</td><td>-----</td><td>-----</td><td>80.11</td><td>35.80</td><td>11.05</td><td>32.64</td><td>220</td><td>329</td><td>Average</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	5210.00	100.35	-----	-----	86.14	35.80	11.05	32.64	220	329	Peak	2	5210.00	94.32	-----	-----	80.11	35.80	11.05	32.64	220	329	Average
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																						
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																						
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																					
1	5132.08	59.83	74.00	-14.17	45.62	35.74	11.10	32.63	220	329	Peak																																																																																			
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																							
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																						
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																					
1	5210.00	100.35	-----	-----	86.14	35.80	11.05	32.64	220	329	Peak																																																																																			
2	5210.00	94.32	-----	-----	80.11	35.80	11.05	32.64	220	329	Average																																																																																			
Avg	Level (dBuV/m) Date: 2025-05-14 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5149.90</td><td>49.46</td><td>54.00</td><td>-4.54</td><td>35.30</td><td>35.70</td><td>11.09</td><td>32.63</td><td>220</td><td>329</td><td>Average</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	5149.90	49.46	54.00	-4.54	35.30	35.70	11.09	32.63	220	329	Average	Blank																																																				
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																							
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																						
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																					
1	5149.90	49.46	54.00	-4.54	35.30	35.70	11.09	32.63	220	329	Average																																																																																			