

FCC RF EXPOSURE REPORT

FCC ID: X4YVEK2400GWP

Project No. : 2105C153
Equipment : VEKTOR G2400AC Whole Home Mesh WiFi System
Brand Name : NEXXT SOLUTIONS
Test Model : NCM-G2400P
Series Model : N/A
Applicant : NEXXT SOLUTIONS
Address : 3505 N.W 107TH AVE. MIAMI, FL 33178
Manufacturer : NEXXT SOLUTIONS
Address : 3505 N.W 107TH AVE. MIAMI, FL 33178
Date of Receipt : May 24, 2021
Date of Test : May 24, 2021~Jun. 15, 2021
Issued Date : Jun. 24, 2021
Report Version : R00
Test Sample : Engineering Sample No.: DG2021052493
Standard(s) : FCC Part 2.1091
FCC Title 47 Part 2.1091
KDB 447498 D01 General RF exposure guidance v06

The above equipment has been tested and found compliance with the requirement of the relative standards by BTL Inc.

Maker Qi

Prepared by : Maker Qi

Issac Song.

Approved by : Issac Song



TESTING CERT #5123.03

Add: No. 29, Jintang Road, Tangzhen Industry Park, Pudong New Area, Shanghai 201210, China

TEL: +86-021-61765666

Web: www.newbtl.com

REPORT ISSUED HISTORY

Report Version	Description	Issued Date
R00	Original Issue.	Jun. 24, 2021

1. MPE CALCULATION METHOD

Calculation Method of RF Safety Distance:

$$S = \frac{PG}{4\pi r^2} = \frac{EIRP}{4\pi r^2}$$

where:

S = power density

P = power input to the antenna

G = power gain of the antenna in the direction of interest relative to an isotropic radiator

R = distance to the center of radiation of the antenna

Table for Filed Antenna

For 2.4G

Ant.	Brand	Model Name	Antenna Type	Connector	Gain(dBi)
1	N/A	N/A	PCB	N/A	3
2	N/A	N/A	PCB	N/A	3

Note:

1. This EUT supports Beamforming and CDD, all antennas have the same gain, any transmit signals are correlated with each other, so

1) Beamforming:

$$\text{Directional gain} = 10\log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2 / N_{\text{ANT}}] \text{dBi},$$

$$\text{that is Directional gain} = 10\log[(10^{G1/20} + 10^{G2/20} + \dots + 10^{GN/20})^2 / N_{\text{ANT}}] \text{dBi} = 6.01;$$

$$\text{So output power limit is } 30 - 6.01 + 6 = 29.99, \text{ the power spectral density limit is } 8 - 6.01 + 6 = 7.99.$$

2) CDD:

For power spectral density measurements, For power spectral density measurements, the Directional gain = $G_{\text{ANT}} + \text{Array Gain}$, that is Directional gain = $3 + 10\log(2/1) = 6.01$;

$$\text{So power spectral density limit is } 8 - 6.01 + 6 = 7.99.$$

For power measurements, Directional gain = $G_{\text{ANT MAX.}} + \text{Array Gain}$, Array Gain = 0dB ($N_{\text{ANT}} \leq 4$), so the Directional gain = 3.

2. The antenna gain and beamforming gain are provided by the manufacturer.

Operating Mode TX Mode	Ant. 1	Ant. 2	Ant. 1+2
IEEE 802.11b	✓	✓	✗
IEEE 802.11g	✓	✓	✗
IEEE 802.11n(HT20)	✓	✓	✓
IEEE 802.11n(HT40)	✓	✓	✓

For 5G

Ant.	Brand	Model Name	Antenna Type	Connector	Gain(dBi)
1	N/A	N/A	PCB	N/A	3
2	N/A	N/A	PCB	N/A	3

Note:

1. This EUT supports Beamforming and CDD, all antennas have the same gain, any transmit signals are correlated with each other, so

1) Beamforming:

Directional gain = $10\log[(10^{G1/20}+10^{G2/20}+\dots+10^{GN/20})^2/N_{ANT}]$ dB_i,
that is Directional gain= $10\log[(10^{G1/20}+10^{G2/20}+\dots+10^{GN/20})^2/N_{ANT}]$ dB_i = 6.01;

Then, the UNII-1, UNII-3 output power limit is 30-6.01+6=29.99.

The UNII-1 power spectral density limit is 17-6.01+6=16.99,
the UNII-3 power spectral density limit is 30-6.01+6=29.99.

2) CDD:

For power spectral density measurements, the Directional gain= $G_{ANT} + \text{Array Gain}$,
that is Directional gain= $3 + 10\log(2/1)$ = 6.01;

Then, the UNII-1 power spectral density limited is 17-6.01+6=16.99,
the UNII-3 power spectral density limit is 30-6.01+6=29.99.

For power measurements, Directional gain= $G_{ANT\ MAX} + \text{Array Gain}$.

Array Gain=0dB($N_{ANT} \leq 4$), so the Directional gain=3.

2. The antenna gain and beamforming gain are provided by the manufacturer.

Operating Mode TX Mode	Ant. 1	Ant. 2	Ant. 1+2
IEEE 802.11a	✓	✓	✗
IEEE 802.11n(HT20)	✓	✓	✓
IEEE 802.11n(HT40)	✓	✓	✓
IEEE 802.11ac(VHT20)	✓	✓	✓
IEEE 802.11ac(VHT40)	✓	✓	✓
IEEE 802.11ac(VHT80)	✓	✓	✓

2. TEST RESULTS

For 2.4GHz:

Beamforming

Antenna Gain (dBi)	Antenna Gain (numeric)	Max. tune up Power (dBm)	Max. tune up Power (mW)	Power Density (S) (mW/cm ²)	Limit of Power Density (S) (mW/cm ²)	Test Result
6.01	3.99020	29.00	794.3282	0.630556	1	Complies

CDD:

Antenna Gain (dBi)	Antenna Gain (numeric)	Max. tune up Power (dBm)	Max. tune up Power (mW)	Power Density (S) (mW/cm ²)	Limit of Power Density (S) (mW/cm ²)	Test Result
3.00	1.9953	29.00	794.3282	0.315310	1	Complies

For 5GHz :

Beamforming

Antenna Gain (dBi)	Antenna Gain (numeric)	Max. tune up Power (dBm)	Max. tune up Power (mW)	Power Density (S) (mW/cm ²)	Limit of Power Density (S) (mW/cm ²)	Test Result
6.01	3.9902	20.00	100.0000	0.079382	1	Complies

CDD:

Antenna Gain (dBi)	Antenna Gain (numeric)	Max. tune up Power (dBm)	Max. tune up Power (mW)	Power Density (S) (mW/cm ²)	Limit of Power Density (S) (mW/cm ²)	Test Result
3.00	1.9953	21.00	125.8925	0.049973	1	Complies

For the max simultaneous transmission MPE:

2.4G+5G

Power Density (S) (mW/cm ²)	Power Density (S) (mW/cm ²)	Total	Limit of Power Density (S) (mW/cm ²)	Test Result
2.4GHz	5GHz			
0.630556	0.079382	0.709938	1	Complies

Note: The calculated distance is 20 cm.

Output power including tune up tolerance.

End of Test Report