# BLUETOOTH AUDIO RECEIVER

# QUICK INSTALL GUIDE

MODEL DC-5BT

Thank you for your purchase of the MANHATTAN® Bluetooth Audio Receiver, Model 161091.

Quickly installed with a 3.5 mm stereo plug, it pairs with PCs, MP3 players, mobile phones and other Bluetooth-enabled media sources to convert most speakers into a wireless entertainment system.

(Instructions on back of this sheet.)

- Built-in rechargeable battery provides up to 6.5 hours of listening almost anywhere
- Compact, integrated design requires no external antenna
- Lifetime Warranty







Designed and produced by JUNGLEREX Electronics CO., LTD.

Made in China www.junglerex.com

MH-DC-5BT-miniQIG-1109-02



## **SETUP & OPERATING INSTRUCTIONS**





Prior to the initial use of the Bluetooth Audio Receiver, its built-in battery needs to be fully charged. The first charge can take up to 4 hours, while subsequent recharging may take less than 3 hours.

### Charging the Battery

- Plug the included power adapter/recharger into an AC outlet, then connect it to the In DC 5V jack on the receiver (above-left image).
- The middle LED (between the On/Off buttons) will light green to indicate the battery is charging, then turn off to indicate a full charge (aboveright image).

#### **Bluetooth Pairing and Operation**

- Connect your speakers to the 3.5 mm stereo Line Out jack on the Bluetooth Audio Receiver.
- 2. Power on the receiver by pressing the On button, and keep it pressed (for approximately 4 seconds) until the red and blue LEDs (between the On/Off buttons) flash back and forth. The receiver is now in its pairing mode. NOTE: Whenever the pairing between devices is not maintained for a full minute or so, the pairing function will stop and need to be re-established.
- Turn on your Bluetooth-enabled device (mobile phone, PC, notebook, etc.) and activate its Bluetooth pairing per the device's BT instructions. NOTE: To play music using a Bluetooth-enabled mobile phone, the phone needs to support A2DP and AVRCP profiles.
- When your Bluetooth-enabled device locates the receiver and displays it (as "BT Speakers") in its Devices list, select the receiver for pairing.
- 5. When the display of your Bluetooth-enabled device prompts you to enter a PIN code, enter 0000 (zeroes). This should complete the pairing process — indicated by the flashing blue LED — and place the receiver in standby mode, automatically connecting to your Bluetoothenabled device.
- At this point, the receiver is ready to relay sound to your speakers.
   NOTE: To avoid unwanted syncing, turn the receiver off when it's not in use

161091\_02\_miniQ16.indd 2 1/4/10 10:02:26 AM

FCC NOTE: THE MANUFACTURER IS NOT RESPONSIBLE FOR ANY RADIO OR TV INTERFERENCE CAUSED BY UNAUTHORIZED MODIFICATIONS TO THIS EQUIPMENT. SUCH MODIFICATIONS COULD VOID THE USER'S AUTHORITY TO OPERATE THE EQUIPMENT.

Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

The carrier frequency of transmitter is 2400 MHz-2483.5 and the Worst field strength is 94.6 dBuV/M at 3 meter measured.