

USB Plus 5lb

DATA SHEET

FEATURES

- Highly-accurate weighing and/or postal scale (5lb/0.1oz)
- USB power from PC – plug and play (no software needed)
- USB connection (USB cable supplied)
- Can be used with online postage system such as Stamps.com, USPS, Endicia, and USA PC Postal Calculator to capture weight reading to PC

SPECIFICATIONS

Range	: 0-5lb Mechanical overload protection
Accuracy	: $\pm 0.1\%$ of reading ± 1 digit
Resolution	: 0.1oz
Minimum Weight	: >0.2oz
Min. Add-on Wt.	: >0.1oz
Power Working Current	: USB power DC 5V : 10 mA
Warm-up time	: 2 seconds or less.
User Calibration	: Using 5lb weights (not supplied)
Temperature	: Good performance within 30 degree to 100 degree Fahrenheit. The scale is designed to operate in normal room temperatures. If subjected to cold or warm temperatures, it should be allowed to reach room temperature before operating.
Case & Platform	: Fine texture ABS plastic
Load Cell Technology	: Four element single strain gage with temperature compensation
Load Cell Body	: Material: 2024 – T4/T351 Aluminum Alloy
Interface	: Includes USB cable to connect to PC

PHYSICAL FEATURES

Dimensions : 16.5 X 16.5 X 4.7 cm

4th floor, #10 of Ai-De Air Industry Park,

Gao Qi South 12th Road, Xiamen, Fujian 361006, China

Tel: (86) 592-602-3169 Fax: (86)592-566-5162

Email: sales@elane.net

Website: www.elane.net

Platform Size : 15.7 X 15.7 cm
Weight : 507g Without Cable

PACKAGING

Box Dimension : 20.5 X 18.4 X6.0 cm
Packaged Weight : 570g
Master Carton Dimension : 43 X 38 X 38 cm
Quantity: 24 boxes per Master carton
Volume: 0.05 cbm
Gross Weight: 14.6kg

WARRANTY

1 year from date of sale to end-user against defect in manufacturing and materials.

FCC NOTE

NOTE

THE MANUFACTURER IS NOT RESPONSIBLE FOR ANY RADIO OR TV INTERFERENCE CAUSED BY UNAUTHORIZED MODIFICATIONS TO THIS EQUIPMENT. SUCH MODIFICATIONS COULD VOID THE USER AUTHORITY TO OPERATE THE EQUIPMENT.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.
- Modifications not expressly approved by the manufacturer could void the user's authority to operate the equipment under FCC rules.