# Content

1	Ge	etting started3
	1.1	Installing the SIM Cards and the Battery
	1.2	Charging the Battery
	1.3	Linking to the Network
2	In	put method5
	2.1	To Shift Entry Methods
	2.2	Numeric and English Input
	2.3	Inserting a Symbol
3	Us	ing the Menus6
	3.1	Phonebook6
	3.2	Multimedia6
	3.3	Messages7
	3.4	Call History7
	3.5	Profiles8
	3.6	Organizer8

3.7	Settings	9
3.8	Games	12
39	STK	12

# Phone Specifications









Dimensions (H×W×D): 102.5\*44.5\*15 MM

Weight: 70g

Camera: 0.08Mpixel Lithium battery

Rated capacity: 3.7V 600mAh

Continuous standby duration: (Relates to network status) 96-144 hours Continuous conversation duration: (Relates to network status) 3 hours

Please refer to their labels for other data related to the battery and the charger.

# 1 Getting started

# 1.1 Installing the SIM Cards and the Battery

An SIM card carries useful information, including your mobile phone number, PIN (Personal Identification Number), PUK (PIN Unlocking Key), IMSI (International Mobile Subscriber Identity), network information, contacts data, and short messages data.

# 1.2 Charging the Battery

The lithium battery delivered with the mobile phone can be put into use immediately after being unpacked. Your mobile phone can monitor and display the battery state.

- ◆ Normally the remaining energy of the battery is indicated by the battery level icon at the upper right corner of the display screen.
- ♦ When the battery energy is insufficient, the mobile phone prompts "Battery low". If you have set an alert tone, an alert tone will be given off when the battery level is too low.
- ◆ A charging animation appears when the battery is being charged. When the charging is complete, the animation disappears.
- ◆ It is normal of the battery to become hot during the charging period.
- ◆ The battery icon does no longer flicker when the charging process ends.
- ◆ Use only the battery provided by the vendor. Otherwise, damages or even injuries could be caused during the charging.
- Power off the mobile phone before removing the battery.
- ◆ The charging process lasts a longer time for a new battery or a battery not in use for a long time. If the battery voltage is too low to enable the mobile phone to be powered on, charge the battery for a longer time.
- ◆ During the charging, ensure the battery is placed in a room temperature environment or in an environment close to room temperature.

Immediately stop using the battery if the battery produces odor, overheats, cracks, distorts or has other damage, or if the electrolyte leaks.

◆ The battery wears out with use. A longer charging time is required as the battery is put into use for a long time.

# Warning:

- (1) There may be the risk of explosion if the battery is replaced by the wrong type.
- (2)Dispose of used batteries according to the guidelines.
- (3)The socket-outlet shall be installed near the equipment and shall be easily accessible.

Provides charging temperature range -5  $^{\circ}$ C to 55  $^{\circ}$ C, over this range, please do not use the charging equipment. And be sure to use the charger provided by the supplier. Use of an unapproved charger may be dangerous and breach of warranty of the equipment approval and terms.

# 1.3 Linking to the Network

After the SIM card and the mobile phone are successfully unlocked, the mobile phone automatically searches for an available network.

# 2 Input method

This mobile phone provides multiple input methods, including English input in both upper and lower case, and numeric input method.

# 2.1 To Shift Entry Methods

Press # key to switch between input methods.

# 2.2 Numeric and English Input

You can input numbers with the numeric input method. Press a number key to input the corresponding number.

.

# 2.3 Inserting a Symbol

Press the \* key to enter the **Select symbol** interface and select a symbol you want.

# 3 Using the Menus

# 3.1 Phonebook

In this menu you can **Add, view, Copy, Delete** and **Speed dial** telephone numbers. The mobile phone can store up to 500 telephone numbers. You can also view the **Owner number** choose the **Preferred storage** where the numbers will be saved in and check the **Memory status** of the phone.

# 3.2 Multimedia

# **FM Radio**

You can use the application as a traditional FM radio with automatic tuning and saved channels. ▲ or ▼keys to tune volume.

# Video Player

Use this function to play video files.

# **Audio Player**

Use this function to play audio files. In audio player interface, you can press ▲ or ▼keys to tune volume.

#### **Sound Recorder**

Use this function to record audio files. The phone supports WAV and AMR format.

#### Camera

Use this function to capture pictures.

# Video Recorder

Use this function to record video files.

# File manager

The phone provides a certain space for users to manage files and supports the Micro SD card. You can use the file manager to conveniently manage various directories and files on the phone and the Micro SD card.

## 3.3 Messages

NA

# 3.4 Call History

# Missed Calls / Dialed Calls / Received Calls / All Calls / Clear logs

You can view a list of the above.

#### 3.5 Profiles

The mobile phone provides multiple user profiles, General, Meeting, Outdoor, Indoor, Headset, Bluetooth.

When you insert an earpiece to the mobile phone, the mobile phone automatically enters the Headset mode. There is no option for activating the Headset mode on the screen. For details on operation, refer to **General**. If you set **Headset** > **Customize** > **Answer mode** to **Auto**, incoming calls will be automatically answered.

# 3.6 Organizer

#### To do list

This feature lists out all your tasks you have added. You can view, add, edit, delete, and delete all.

#### Alarm

Five alarm clocks are set but deactivated by default.. For each alarm clock, the ringing date and the ringing time can be set.

# **Stopwatch**

Typical stopwatch: Split timing, Lap timing, and View records, nWay stopwatch.

#### Calendar

Once you enter this menu, there is a monthly-view calendar for you to keep track of important appointments, etc.

# World clock

Access this menu to view time of main cities in various time zones.

#### Calculator

This calculator provides limited precision and is only applicable to simple arithmetic calculation.

# 3.7 Settings

# Time and date

Set the date format, the time format, and detail time of the location.

# **Display settings**

Users can access this item to set wallpaper, screen saver, power on/off display, etc.

#### **Bluetooth**

With Bluetooth, you can make a wireless connection to other compatible devices

## **Phone Settings**

- ◆ **Select Language:** Select the display language for the mobile phone.
- ◆ Schedule power on/off: Set the time when the mobile phone will be automatically powered on or off.
- Greeting text: Sets a greeting message when the phone is turned on.
- ♦ **Home city:** Sets the time of the current city on the mobile phone.
- ◆ Auto keypad lock: On/Off.
- ◆ **Input method settings:** Select one of the input methods as the prior. So while you write SMS, it will automatically display the selected input method by default.

## **Call Settings**

- ◆ **Dual-SIM:** Dual-SIM refers to two SIM card slots, and the two cards can standby at the same time or set one of them to display on the idle screen.
- ◆ Caller ID: Allows you to **Send** or **Hide** your phone number when you call someone.
- ◆ Call waiting: Network dependent.
- ◆ Call divert: this network function enables you to forward incoming calls to another number you have previously specified.
- ◆ Call barring: The call barring function enables you to bar calls as needed. When setting this function, you need to use a network barring code, which can be obtained from the network operator.
- ◆ **Line switching**: Switch to Line 1 or Line 2. By default, Line 1 is used.
  - **Note:** If you choose Line 2, dialing may fail. This depends on the implementation of the network operator.

◆ Others: Through this function, you can set IP shortcut key, 50 seconds voice tone, connect prompt, answer/reject mode and auto redial status..

#### **Network settings**

You can search the network again. Select your favorite network and choose to register the network automatically or manually.

#### **Network status**

View the current networks on the SIM cards inserted on the phone.

# **Security Settings**

This function provides you with related settings about safety use

- ◆ PIN: The PIN (Personal identification number, 4 to 8 digits) code prevents your SIM card from being used by unauthorized people. In general, the PIN is supplied with SIM card by the network operator. If PIN check is enabled, you need to input the PIN each time when you power on your mobile phone. The SIM card will be locked if you input wrong PIN code for three times
- ◆ PIN2: The PIN2 code (4 to 8 digits), supplied with SIM card, is required to access some functions such as "call costs setup" and "fixed dialing setup". Please contact the network operator to verify whether your SIM card supports these functions. If you input wrong PIN2 for three times, the PIN2 will be locked.
- ◆ **Privacy**: the initial password is 1234. After accessing this function, you can select some items. Once an item is selected, you need to input correct password whenever you want to enter there items to perform

further operations.

- ◆ **Auto keypad lock**: The function enables you to lock the keypad. Set the auto locking time, 5s, 30s, 1min or 5mins is available.
- ◆ Lock screen by end-key: Users can activate/deactivate this function as needed.
- ◆ Power-on password: Once this function is activated, password is required when powering on the phone. Guard lock: When the guard lock is on, once your SIM card is replaced, the phone will automatically send stolen information to the number you've set

#### 3.8 Games

Access this menu, it provides with an embedded game (F1 race). For specific operation about game, please refer to 'Game help' option of the game.

# 3.9 STK

◆ Here you can use the value-added services provided by your network operator.

# **Connection management**

Through this function, you can set network account related parameters.

## **Certification Information (SAR)**

This device meets guidelines for exposure to radio waves.

the independent scientific organization International Commission on Non-Ionizing Radiation Protection (ICNIRP) and include safety measures designed to ensure safety for all users, regardless of age and health. The Specific Absorption Rate (SAR) is the unit of measurement for the amount of radio frequency energy absorbed by the body when using a device. The SAR value is determined at the highest certified power level in laboratory conditions, but the actual SAR level of the device when being operated can be well below the value. This is because the device is designed to use the minimum power required to reach the network. The SAR limit adopted by USA and Canada is 1.6 watts/kilogram (W/kg) averaged over one gram of tissue.

Your device is a low-power radio transmitter and receiver. As recommended by international guidelines, the device is designed not to exceed the limits for exposure to radio waves. These guidelines were developed by

Device Type

The highest SAR value when tested at the ear is...(W/kg)

The highest SAR value when properly worn on the body is...(W/kg)

#### **FCC Statement**

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.


**Warning**: Changes or modifications made to this device not expressly approved by BLU Technologies Co., Ltd. may void the FCC authorization to operate this device.

#### **Federal Communication Commission Interference Statement**

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that



# ▶ RF Exposure Information (SAR)

This mobile phone meets the government's requirements for exposure to radio waves.

This phone is designed and manufactured not to exceed the emission limits for exposure to radio frequency (RF) energy set by the Federal Communications Commission of the U.S. Government.

The exposure standard for wireless mobile phones employs a unit of measurement known as the Specific Absorption Rate, or SAR. The SAR limit set by the FCC is 1.6W/kg. 'Tests for SAR are conducted using standard operating positions accepted by the FCC with the phone transmitting at its highest certified power level in all tested frequency bands. Although the SAR is determined at the highest certified power level, the actual SAR level of the phone while operating can be well below the maximum value. This is because the phone is designed to operate at multiple power levels so as to use only the poser required to reach the network. In general, the closer you are to a wireless base station antenna, the lower the power output.

-16-

The highest SAR value for the model phone as reported to the FCC when tested for use at the ear is 1.16 W/kg and when worn on the body, as described in this user guide, is 0.279 W/kg (Body-worn measurements differ among phone models, depending upon available accessories and FCC requirements.)

While there may be differences between the SAR levels of various phones and at various positions, they all meet the government requirement.

The FCC has granted an Equipment Authorization for this model phone with all reported SAR levels evaluated as in compliance with the FCC RF exposure guidelines. SAR information on this model phone is on file with the FCC and

can be found under the Display Grant section of <a href="www.fcc.gov/oet/ea/fccid">www.fcc.gov/oet/ea/fccid</a> after searching on FCC ID: <a href="https://www.fcc.gov/oet/ea/fccid">YHLBLUCLICKPUS</a>.

For body worn operation, this phone has been tested and meets the FCC RF exposure guidelines for use with an accessory that contains no metal and that positions the handset a minimum of 1.5 cm from the body. Use of other accessories may not ensure compliance with FCC RF exposure guidelines. If you do not use a body-worn accessory and are not holding the phone at the ear, position the handset a minimum of 1.5 cm from your body when the phone is switched on.

# **★**Warning

The operating temperature of this mobile phone is -10  $^{\circ}$ C  $\sim$  +50  $^{\circ}$ C.