

**\*\* MPE Calculations \*\***

The MPE calculation for this exposure is shown below.

The peak radiated output power (EIRP) is calculated as follows:

$EIRP = P + G$	Where,
$EIRP = 22.09 \text{ dBm} + 3.75 \text{ dBi}$	$P = \text{Power input to the antenna (mW)}$
$EIRP = 25.84 \text{ dBm}$	$G = \text{Power gain of the antenna (dBi)}$

**Power density at the specific separation:**

$S = PG/(4R^2 \pi)$	Where,
$S = (161.81 * 2.37) / (4 * 20^2 * \pi)$	$S = \text{Maximum power density (mW/cm}^2\text{)}$ $P = \text{Power input to the antenna (mW)}$ $G = \text{Numeric power gain of the antenna}$
$S = 0.0764 \text{ mW/cm}^2$	$R = \text{Distance to the center of the radiation of the antenna}$ (20cm = limit for MPE)

The Maximum permissible exposure (MPE) for the general population is 1 mW/cm<sup>2</sup>.

The power density does not exceed the 1 mW/cm<sup>2</sup> limit.

Therefore, the exposure condition is compliant with FCC rules.

**Estimated safe separation:**

$R = \sqrt{(PG / 4\pi)}$	Where,
$R = \sqrt{(161.81 * 2.37 / 4\pi)}$	$P = \text{Power input to the antenna (mW)}$ $G = \text{Numeric power gain of the antenna}$
$R = 5.53 \text{ Cm}$	$R = \text{Distance to the center of the radiation of the antenna}$ (20cm = limit for MPE)

The numeric gain(G) of the antenna with a gain specified in dB is determined by:

$$G = \text{Log}^{-1} (\text{dB antenna gain} / 10)$$

$$G = \text{Log}^{-1} (3.75 / 10)$$

$$G = 2.37$$