



FCC TEST REPORT

FOR

Phonetone Technology (Shenzhen) Co., Ltd.

Cell Phone Signal booster

Test Model: N70AN-US59

Prepared for : Phonetone Technology (Shenzhen) Co., Ltd.
Address : Room 404, Building 12, Qianlong Garden, Minzhi Street, Bao'an District, Shenzhen, China

Prepared by : Shenzhen LCS Compliance Testing Laboratory Ltd.
Address : 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Shajing Street, Baoan District, Shenzhen, China
Tel : (+86)755-82591330
Fax : (+86)755-82591332
Web : www.LCS-cert.com
Mail : webmaster@LCS-cert.com

Date of receipt of test sample : March 11, 2023
Number of tested samples : 2
Serial number : Prototype
Date of original test : March 11, 2023 ~ April 24, 2024
Date of difference test : February 24, 2025 ~ February 26, 2025
Date of Report : February 26, 2025



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



FCC TEST REPORT	
FCC CFR 47 PART 20.21	
Report Reference No. : LCSA02245060EA	
Date of Issue..... : February 26, 2025	
Testing Laboratory Name..... : Shenzhen LCS Compliance Testing Laboratory Ltd.	
Address.....	101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Shajing Street, Baoan District, Shenzhen, China
Testing Location/ Procedure.....	Full application of Harmonised standards ■ Partial application of Harmonised standards □ Other standard testing method □
Applicant's Name..... : Phonetone Technology (Shenzhen) Co., Ltd.	
Address.....	Room 404, Building 12, Qianlong Garden, Minzhi Street, Bao'an District, Shenzhen, China
Test Specification	
Standard.....	FCC CFR Title 47 Part 20.21
Test Report Form No.....	LCSEMC-1.0
TRF Originator.....	Shenzhen LCS Compliance Testing Laboratory Ltd.
Master TRF.....	Dated 2011-03
Shenzhen LCS Compliance Testing Laboratory Ltd. All rights reserved.	
This publication may be reproduced in whole or in part for non-commercial purposes as long as the Shenzhen LCS Compliance Testing Laboratory Ltd. is acknowledged as copyright owner and source of the material. Shenzhen LCS Compliance Testing Laboratory Ltd. takes no responsibility for and will not assume liability for damages resulting from the reader's interpretation of the reproduced material due to its placement and context.	
Test Item Description..... : Cell Phone Signal booster	
Trade Mark.....	INVCALL, INVCALL , ANNTLENT, ANNTLENT , PHONETONE, PHONETONE , CELSGN, CELSGN
Test Model.....	N70AN-US59
	For AC Adapter(model: SK02T-0500200U):
Ratings.....	Input: 100-240V~50/60Hz 0.35A Max Output: 5V~2A
Result	Positive

Compiled by:

Kevin Huang/ Administrator

Supervised by:

Cary Luo/ Technique principal

Approved by:

Gavin Liang / Manager



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity

**FCC -- TEST REPORT**

Test Report No. :	LCSA02245060EA	<u>February 26, 2025</u> Date of issue
--------------------------	-----------------------	---

Test Model.....	: N70AN-US59
EUT.....	: Cell Phone Signal booster
Applicant.....	: Phonetone Technology (Shenzhen) Co., Ltd.
Address.....	: Room 404, Building 12, Qianlong Garden, Minzhi Street, Bao'an District, Shenzhen, China
Telephone.....	: /
Fax.....	: /
Manufacturer.....	: Phonetone Technology (Shenzhen) Co., Ltd.
Address.....	: Room 404, Building 12, Qianlong Garden, Minzhi Street, Bao'an District, Shenzhen, China
Telephone.....	: /
Fax.....	: /
Factory.....	: Phonetone Technology (Shenzhen) Co., Ltd.
Address.....	: Room 404, Building 12, Qianlong Garden, Minzhi Street, Bao'an District, Shenzhen, China
Telephone.....	: /
Fax.....	: /

Test Result	Positive
--------------------	-----------------

The test report merely corresponds to the test sample.

It is not permitted to copy extracts of these test result without the written permission of the test laboratory.



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Revision History

Revision	Issue Date	Revisions	Revised By
000	February 26, 2025	Initial Issue	---

At the customer's request, the adapter was updated, the radiation emission spurious was tested for difference, and the result was pass, the rest of the test items were unchanged.

The revised report was submitted to LCSA02245060EA applicant by quoting the RF test data of LCSA02284033EA original report, the original report is invalid.

Adapter parameter change:

For AC Adapter(model: SK03T1-1200200U):

Input: 100-240V~50/60Hz 0.6A

Output: 12V=2A

Change to

For AC Adapter(model: SK02T-0500200U):

Input: 100-240V~50/60Hz 0.35A Max

Output: 5V=2A



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



TABLE OF CONTENTS

Description	Page
1. GENERAL INFORMATION	6
1.1 Description of Device (EUT)	6
1.2 Support equipment List	9
1.3 External I/O Cable	9
1.4 Description of Test Facility	9
1.5 Statement of the Measurement Uncertainty	10
1.6 Measurement Uncertainty	10
1.7 Operation Band	10
2. TEST METHODOLOGY	11
2.1 EUT Configuration	11
2.2 General Test Procedures	11
3. SYSTEM TEST CONFIGURATION	12
3.1 Justification	12
3.2 EUT Exercise Software	12
3.3 Special Accessories	12
3.4 Block Diagram/Schematics	12
3.5 Equipment Modifications	12
3.6 Test Setup	12
4. SUMMARY OF TEST RESULTS	13
5. SUMMARY OF TEST EQUIPMENT	14
6. MEASUREMENT RESULTS	16
6.1 Noise Limits	16
6.2 Authorized Frequency Band Verification	26
6.3 Maximum power measurement	29
6.4 Gain Limits and Bidirectional Capability&Variable Gain&Variable Uplink Gain Timing	36
6.5 Anti-Oscillation	43
6.6 Intermodulation Limits	55
6.8. Conducted Spurious Emission	86
6.9 Uplink Inactivity	117
6.10 Occupied Bandwidth	120
7. RADIATION SPURIOUS EMISSION	134
8. TEST SETUP PHOTOGRAPHS OF EUT	138
9. EXTERIOR PHOTOGRAPHS OF THE EUT	138
10. INTERIOR PHOTOGRAPHS OF THE EUT	138





1. GENERAL INFORMATION

1.1 Description of Device (EUT)

EUT	: Cell Phone Signal booster
Equipment Type	: Fixed Wideband Consumer Zone Enhancers
Test Model	: N70AN-US59
Power Supply	For AC Adapter(model: SK02T-0500200U): : Input: 100-240V~50/60Hz 0.35A Max Output: 5V=2A
Hardware Version	: N70AN-CA60 V1.0
Software Version	: N70AN-CA60 V1.0
Frequency Range	Lower 700MHz Band (B12) Uplink: 698~716MHz, Downlink: 728~746MHz Upper 700MHz Band (B13) Uplink: 777~787MHz, Downlink: 747~757MHz Cellular Band (B5) Uplink: 824~849MHz, Downlink: 869~894MHz PCS Band (B2, B25) Uplink: 1850~1915MHz, Downlink: 1930~1995MHz AWS Band(B4, B66) Uplink: 1710~1780MHz, Downlink: 2110~2200MHz
Max Gain	Uplink: ≤67dB Downlink: ≤64dB
Mobile Antenna Gain	: 8dBi
Max Antenna Port Output Power	Uplink: ≤20dBm Downlink: ≤7dBm
Emission Designator	: F9W, G7D, G7W, GXW, W7D
FCC Classification	: B2W/Wideband Consumer Booster(CMRS)
Operating Temperature	: -20°C~+65°C

Note: For a more detailed antenna description, please refer to the antenna specifications or the antenna report provided by the customer.





Antenna Information:

Mode	Frequency (MHz)	Outdoor Antenna Gain (dBi) (Log Periodic Antenna, Model: AN201)	Cable loss (dB)
Uplink	698-716	6	1.80
	777-787	6	1.80
	824-849	6	2.00
	1850-1915	8	2.95
	1710-1780	8	2.70
Mode	Frequency (MHz)	Indoor Antenna Gain (dBi) (Indoor Panel Antenna, Model: AN101)	Cable loss (dB)
Downlink	728-746	7	1.80
	747-757	7	1.80
	869-894	7	2.00
	1930-1995	7	2.95
	2110-2200	7	3.20





MSCL Calculations N70AN-CA60:




Figure 1

Remark: $MSCL = \text{Path loss} + \text{Indoor Cable Loss} - \text{Mobile Antenna Gain} - \text{Indoor Antenna Gain} + \text{Polarity Loss}$

Path loss=20Logf+20LogD-27.56				
Operation Band	Frequency (MHz)	D (m)	Constant (dB)	Path loss (dB)
Lower 700 Band (698-716)	698	2	27.56	35.34
Upper 700 Band (777-787)	777	2	27.56	36.30
Cellular Band (824-849)	824	2	27.56	36.78
PCS Band (1850-1915)	1850	2	27.56	43.80
AWS Band (1710-1780)	1710	2	27.56	43.12

Path loss=20Logf+20LogD-27.56						
MSCL Calculations of fixed booster N70AN-CA60						
MSCL						
Operation Band	Path loss (dB)	Indoor Cable Loss (dB)	Mobile Antenna Gain (dBi)	Indoor Antenna Gain (dBi)	Polarity Loss (dB)	MSCL (dB)
Lower 700 Band (698-716)	35.34	1.80	8	7	3	25.14
Upper 700 Band (777-787)	36.30	1.80	8	7	3	26.10
Cellular Band (824-849)	36.78	2.00	8	7	3	26.78
PCS Band (1850-1915)	43.80	2.95	8	7	3	34.75
AWS(1710-1780)	43.12	2.70	8	7	3	33.82





1.2 Support equipment List

Manufacturer	Description	Model	Serial Number	Certificate
Shenzhen Simsukian Electronics Technology Co., Ltd.	AC/DC Adapter	SK02T-0500200U	---	FCC

1.3 External I/O Cable

I/O Port Description	Quantity	Cable
Antenna Port	2	N/A
DC IN Port	1	N/A

1.4 Description of Test Facility

FCC Registration Number is 254912.

NVLAP Accreditation Code is 600167-0.

FCC Designation Number is CN5024.

CAB identifier is CN0071.

CNAS Registration Number is L4595.

Industry Canada Registration Number is 9642A.

The 3m-Semi anechoic test site fulfils CISPR 16-1-4 according to ANSI C63.10:2013 and CISPR 16-1-4:2010 VSWR requirement for radiated emission above 1GHz.



Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity



1.5 Statement of the Measurement Uncertainty

The data and results referenced in this document are true and accurate. The reader is cautioned that there may be errors within the calibration limits of the equipment and facilities. The measurement uncertainty was calculated for all measurements listed in this test report acc. To CISPR 16 – 4 “Specification for radio disturbance and immunity measuring apparatus and methods – Part 4: Uncertainty in EMC Measurements” and is documented in the LCS quality system acc. To DIN EN ISO/IEC 17025. Furthermore, component and process variability of devices similar to that tested may result in additional deviation. The manufacturer has the sole responsibility of continued compliance of the device.

1.6 Measurement Uncertainty

Test Item	Frequency Range	Uncertainty	Note
Radiation Uncertainty	9KHz~30MHz	3.10dB	(1)
	30MHz~200MHz	2.96dB	(1)
	200MHz~1000MHz	3.10dB	(1)
	1GHz~26.5GHz	3.80dB	(1)
	26.5GHz~40GHz	3.90dB	(1)
Conduction Uncertainty	150kHz~30MHz	1.63dB	(1)
Power disturbance	30MHz~300MHz	1.60dB	(1)

(1). This uncertainty represents an expanded uncertainty expressed at approximately the 95% confidence level using a coverage factor of k=2.

1.7 Operation Band

Uplink Band Frequency (MHz)	Downlink Band Frequency (MHz)
Lower 700 Band (698-716MHz)	Lower 700 Band (728-746MHz)
Upper 700 Band (777-787MHz)	Upper 700 Band (747-757MHz)
Cellular Band (824-849MHz)	Cellular Band (869-894MHz)
PCS Band (1850-1915MHz)	PCS Band (1930-1995MHz)
AWS Band (1710-1780MHz)	AWS Band (2110-2200MHz)





2. TEST METHODOLOGY

All tests and measurements indicated in this document were performed in accordance with:

- 1) The Code of federal Regulations Title 47, Part 2, Part 22, Part 24, Part 27, Part 20.21;
- 2) ANSI C63.26-2015, American National Standard for Compliance Testing of Transmitters Used in Licensed Radio Services;
- 3) KDB 935210 D03 Signal Booster Measurements v04r04.

2.1 EUT Configuration

The EUT configuration for testing is installed on RF field strength measurement to meet the Commissions requirement and operating in a manner that intends to maximize its emission characteristics in a continuous normal application.

2.2 General Test Procedures

2.2.1 Radiated spurious emissions

The EUT is placed on the turntable, which is 1.5 m above ground plane. The turntable shall rotate 360 degrees to determine the position of maximum emission level. EUT is set 3m away from the receiving antenna. And also, each emission was to be maximized by changing the polarization of receiving antenna both horizontal and vertical. In order to find out the maximum emissions, exploratory radiated spurious emissions measurements were made according to the requirements in Section 6.3 of ANSI C63.10-2013





3. SYSTEM TEST CONFIGURATION

3.1 Justification

The system was configured for testing in a continuous transmits condition.

3.2 EUT Exercise Software

N/A

3.3 Special Accessories

Manufacturer	Description	Model	Serial Number	Certificate
--	--	--	--	--

3.4 Block Diagram/Schematics

Please refer to the related document.

3.5 Equipment Modifications

Shenzhen LCS Compliance Testing Laboratory Ltd. has not done any modification on the EUT.

3.6 Test Setup

Please refer to the test setup photo.



Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity



4. SUMMARY OF TEST RESULTS

Requirement	CFR 47 Section	Result
Noise Limits	§20.21(e)(8)(i)(A) §20.21(e)(8)(i)(H)	PASS
Authorized Frequency Band Verification Test	§20.21(e)(3)	PASS
Maximum Power Measurement	§20.21(e)(8)(i)(D) §20.21(e)(8)(i)(B)&§20.21(e)(4)	PASS
Gain Limits and Bidirectional Capability &Variable Gain &Variable Uplink Gain Timing	§20.21(e)(8)(i)(C)(2) §20.21(e)(8)(i)(B) §20.21(e)(8)(i)(C) (1) §20.21(e)(8)(i)(H)	PASS
Anti-Oscillation	§20.21(e)(8)(ii)(A)&§20.21(e)(4)	PASS
Intermodulation Limits	§20.21(e)(8)(i)(F)	PASS
Out of Band Emission	§20.21(e)(8)(i)(E)	PASS
Conducted Spurious Emission	§2.1051	PASS
Uplink inactivity	§20.21(e)(8)(i)(I)	PASS
Occupied Bandwidth	§2.1049	PASS
Radiated Spurious Emission	§2.1053	PASS
RF Exposure	RSS-102: 2.5.2	PASS
Spectrum Block Filter	N/A	N/A

Note:

1. PASS: Test item meets the requirement.
2. Fail: Test item does not meet the requirement.
3. N/A: Test case does not apply to the test object.
4. The test result judgment is decided by the limit of test standard.





5. SUMMARY OF TEST EQUIPMENT

Date of original test: March 11, 2023 ~ April 24, 2024

Item	Equipment	Manufacturer	Model No.	Serial No.	Cal Date	Due Date
1	Power Meter	R&S	NRVS	100444	2023-06-09	2024-06-08
2	Power Sensor	R&S	NRV-Z81	100458	2023-06-09	2024-06-08
3	Power Sensor	R&S	NRV-Z32	10057	2023-06-09	2024-06-08
4	LTE Test Software	Tonscend	JS1120-1	N/A	N/A	N/A
5	RF Control Unit	Tonscend	JS0806-1	158060009	2023-10-18	2024-10-17
6	MXA Signal Analyzer	Agilent	N9020A	MY51250905	2023-10-18	2024-10-17
7	WIDEBAND RADIO COMMUNICATION TESTER	R&S	CMW 500	103818	2023-06-09	2024-06-08
8	DC Power Supply	Agilent	E3642A	N/A	2023-10-18	2024-10-17
9	EMI Test Software	AUDIX	E3	/	N/A	N/A
10	3m Semi Anechoic Chamber	SIDT FRANKONIA	SAC-3M	03CH03-HY	2023-06-09	2024-06-08
11	Positioning Controller	Max-Full	MF7802BS	MF780208586	N/A	N/A
12	Active Loop Antenna	SCHWARZBECK	FMZB 1519B	00005	2021-08-29	2024-08-28
13	By-log Antenna	SCHWARZBECK	VULB9163	9163-470	2021-09-12	2024-09-11
14	By-log Antenna	SCHWARZBECK	VULB9163	9163-471	2021-09-12	2024-09-11
15	Horn Antenna	SCHWARZBECK	BBHA 9120D	9120D-1925	2021-09-05	2024-09-04
16	Horn Antenna	SCHWARZBECK	BBHA 9120D	9120D-1926	2021-09-05	2024-09-04
17	Broadband Horn Antenna	SCHWARZBECK	BBHA 9170	791	2021-08-29	2024-08-28
18	Broadband Horn Antenna	SCHWARZBECK	BBHA 9170	792	2021-08-29	2024-08-28
19	Broadband Preamplifier	SCHWARZBECK	BBV9719	9719-025	2021-08-29	2024-08-28
20	EMI Test Receiver	R&S	ESR 7	101181	2023-08-15	2024-08-14
21	RS SPECTRUM ANALYZER	R&S	FSP40	100503	2023-07-17	2024-07-16
22	Low-frequency amplifier	SchwarzZBECK	BBV9745	00253	2023-10-18	2024-10-17
23	High-frequency amplifier	JS Denki Pte	PA0118-43	JSPA21009	2023-10-18	2024-10-17
24	6dB Attenuator	/	100W/6dB	1172040	2023-06-09	2024-06-08
26	3dB Attenuator	/	2N-3dB	/	2023-10-18	2024-10-17
27	Temperature & Humidity Chamber	GUANGZHOU GOGNWEN	GDS-100	70932	2023-10-05	2024-10-04
28	EMI Test Software	Farad	EZ	/	N/A	N/A
29	RADIO COMMUNICATION TESTER	R&S	CMU 200	105988	2023-06-09	2024-06-08



Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity

**Date of difference test: February 24, 2025 ~ February 26, 2025**

Item	Equipment	Manufacturer	Model No.	Serial No.	Cal Date	Due Date
1	Power Meter	R&S	NRVS	100444	2024-06-06	2025-06-05
2	Power Sensor	R&S	NRV-Z81	100458	2024-06-06	2025-06-05
3	Power Sensor	R&S	NRV-Z32	10057	2024-06-06	2025-06-05
4	LTE Test Software	Tonscend	JS1120-1	N/A	N/A	N/A
5	RF Control Unit	Tonscend	JS0806-1	158060009	2024-11-08	2025-11-07
6	MXA Signal Analyzer	Agilent	N9020A	MY51250905	2024-10-08	2025-10-07
7	WIDEBAND RADIO COMMUNICATION TESTER	R&S	CMW 500	103818	2024-06-06	2025-06-05
8	DC Power Supply	Agilent	E3642A	N/A	2024-10-08	2025-10-07
9	EMI Test Software	AUDIX	E3	/	N/A	N/A
10	3m Semi Anechoic Chamber	SIDT FRANKONIA	SAC-3M	03CH03-HY	2024-06-06	2025-06-05
11	Positioning Controller	Max-Full	MF7802BS	MF780208586	N/A	N/A
12	Active Loop Antenna	SCHWARZBECK	FMZB 1519B	00005	2024-07-13	2027-07-12
13	By-log Antenna	SCHWARZBECK	VULB9163	9163-470	2024-08-03	2027-08-02
14	By-log Antenna	SCHWARZBECK	VULB9163	9163-471	2024-08-03	2027-08-02
15	Horn Antenna	SCHWARZBECK	BBHA 9120D	9120D-1925	2024-07-13	2027-07-12
16	Horn Antenna	SCHWARZBECK	BBHA 9120D	9120D-1926	2024-07-13	2027-07-12
17	Broadband Horn Antenna	SCHWARZBECK	BBHA 9170	791	2024-07-13	2027-07-12
18	Broadband Horn Antenna	SCHWARZBECK	BBHA 9170	792	2024-07-13	2027-07-12
19	Broadband Preamplifier	SCHWARZBECK	BBV9719	9719-025	2024-07-30	2025-07-29
20	EMI Test Receiver	R&S	ESR 7	101181	2024-06-06	2025-06-05
21	RS SPECTRUM ANALYZER	R&S	FSP40	100503	2024-06-06	2025-06-05
22	Low-frequency amplifier	SchwarzZBECK	BBV9745	00253	2024-10-08	2025-10-07
23	High-frequency amplifier	JS Denki Pte	PA0118-43	JSPA21009	2024-10-08	2025-10-07
24	6dB Attenuator	/	100W/6dB	1172040	2024-06-06	2025-06-05
26	3dB Attenuator	/	2N-3dB	/	2024-10-08	2025-10-07
27	Temperature & Humidity Chamber	Baro	/	/	2024-06-12	2025-06-11
28	EMI Test Software	Farad	EZ	/	N/A	N/A
29	RADIO COMMUNICATION TESTER	R&S	CMU 200	105988	2024-06-06	2025-06-05
30	Antenna Mast	Max-Full	MFA-515BSN	1308572	N/A	N/A





6. MEASUREMENT RESULTS

6.1 Noise Limits

6.1.1 Applicable Standard

According to §20.21(e)(8)(i)(A) Noise Limits (uplink); §20.21(e)(8)(i)(H) Transmit Power Off Mode (uplink and downlink noise power):

1. The transmitted maximum noise power in dBm/MHz of consumer boosters at their uplink and downlink ports shall not exceed the following limits:

Fixed booster maximum noise power shall not exceed $-102.5 \text{ dBm/MHz} + 20 \text{ Log}_{10}(\text{Frequency})$, where Frequency is the uplink mid-band frequency of the supported spectrum bands in MHz.

2. The transmitted noise power in dBm/MHz of consumer boosters at their uplink port shall not exceed $-103 \text{ dBm/MHz} - \text{RSSI}$.

6.1.2 Test Procedure

Maximum transmitter noise power level

According to section 7.7.1 of KDB 935210 D03 Signal Booster Measurement v04r04:

- Connect the EUT to the test equipment as shown in Figure 2. Begin with the uplink output (donor) port connected to the spectrum analyzer. When measuring downlink noise, connect the downlink output (server) port to the spectrum analyzer.
- Set the spectrum analyzer RBW to 1 MHz with the VBW ≥ 3 RBW.
- Select the power averaging (rms) detector and trace average over at least 100 traces.
- Set the center frequency of the spectrum analyzer to the center of the CMRS band under test with the span ≥ 2 the CMRS band.
- Measure the maximum transmitter noise power level.
- Save the spectrum analyzer plot as necessary for inclusion in the final test report.
- Repeat 7.7b) to 7.7f) for all operational uplink and downlink bands.
- Connect the EUT to the test equipment as shown in Figure 3 for uplink noise power measurement in the presence a downlink signal. Affirm the coupled path of the RF coupler is connected to the spectrum analyzer.
 - Configure the signal generator for AWGN operation with a 99% OBW of 4.1 MHz.
 - Set the spectrum analyzer RBW for 1 MHz, VBW ≥ 3 RBW, with a power averaging (rms) detector with at least 100 trace averages.
 - Set the center frequency of the spectrum analyzer to the center of the CMRS band under test, with the span ≥ 2 the CMRS band. This shall include all spectrum blocks in the particular CMRS band under test (see Appendix A).
 - For uplink noise measurements, set the spectrum analyzer center frequency for the uplink band under test, and tune the signal generator to the center of the paired downlink band.
 - Measure the maximum transmitter noise power level while varying the downlink signal generator output level from -90 dBm to -20 dBm , as measured at the input port (i.e., downlink signal level at the booster donor port node of Figure 3), in 1 dB steps inside the



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



RSSI-dependent region, and in 10 dB steps outside the RSSI-dependent region. Report the six values closest to the limit, with at least two points within the RSSI-dependent region of the limit. See Appendix D for noise limits graphs.

n) Repeat 7.7.1h) through 7.7.1m) for all operational uplink bands.

NOTE—Some signal boosters will require a signal generator input because they will not operate unless a signal is received at the input terminals. If this is the case, for the setups shown in Figure 2 and Figure 3 connect a second signal generator at the server port, then cycle the RF output of the second signal generator to simulate this function.

NOTE—Some signal boosters have a maximum transmitter noise power level that is less than the Transmit Power Off Mode of -70 dBm. For these boosters it is still necessary to confirm that the uplink noise power limits are met in the presence of a downlink signal. Test reports should show measurement data demonstrating compliance. Alternatively the applicant may provide attestation with detailed design information and explanation justifying the omission of the variable uplink testing.

Variable uplink noise timing

According to section 7.7.2 of KDB 935210 D03 Signal Booster Measurement v04r04:

Variable uplink noise timing is to be measured as follows, using the test setup shown in Figure 3.

- Set the spectrum analyzer to the uplink frequency to be measured.
- Set the span to 0 Hz, with a sweep time of 10 seconds.
- Set the power level of signal generator to the lowest level of the RSSI-dependent noise [see 7.7.1m)].
- Select MAX HOLD and increase the power level of signal generator by 10 dB for mobile boosters, and 20 dB for fixed boosters.
- Confirm that the uplink noise decreases to the specified level within 1 second for mobile devices, and within 3 seconds for fixed devices.¹⁸
- Repeat 7.7.2a) to 7.7.2e) for all operational uplink bands.
- Include plots and summary table in test report.




Figure 2 – Noise limit test setup






Figure 3 – Test setup for uplink noise power measurement in the presence of a downlink signal

6.1.3 Test Data

Temperature	23.6℃	Humidity	52.3%
Test Engineer	Nick Peng	Test Mode	Transmitting

Max Noise Power				
Operation Band		Measured (dBm/MHz)	Limit (dBm/MHz)	Result (dB)
Uplink	Lower 700 Band	-46.975	-45.51	PASS
	Upper 700 Band	-45.847	-44.64	PASS
	Cellular Band	-45.568	-44.05	PASS
	PCS Band	-41.997	-37.00	PASS
	AWS Band	-42.093	-37.73	PASS
Downlink	Lower 700 Band	-46.435	-45.15	PASS
	Upper 700 Band	-45.865	-44.98	PASS
	Cellular Band	-46.372	-43.60	PASS
	PCS Band	-37.922	-36.64	PASS
	AWS Band	-41.807	-35.92	PASS





Variable Uplink Noise				
Operation Band	RSSI dBm	Measured dBm/MHz	Limit dBm/MHz	Results
Lower 700 Band	-81	-41.16	-22	PASS
	-82	-43.78	-21	PASS
	-83	-44.58	-20	PASS
	-84	-44.73	-19	PASS
	-85	-46.63	-18	PASS
	-86	-47.57	-17	PASS
Upper 700 Band	-81	-41.73	-22	PASS
	-82	-42.88	-21	PASS
	-83	-43.13	-20	PASS
	-84	-44.62	-19	PASS
	-85	-45.78	-18	PASS
	-86	-47.39	-17	PASS
Cellular Band	-81	-40.15	-22	PASS
	-82	-40.49	-21	PASS
	-83	-41.75	-20	PASS
	-84	-43.46	-19	PASS
	-85	-45.54	-18	PASS
	-86	-46.69	-17	PASS
PCS Band	-82	-38.57	-21	PASS
	-83	-39.05	-20	PASS
	-84	-40.67	-19	PASS
	-85	-40.78	-18	PASS
	-86	-41.43	-17	PASS
	-87	-42.86	-16	PASS
AWS Band	-83	-37.11	-20	PASS
	-84	-38.58	-19	PASS
	-85	-39.05	-18	PASS
	-86	-40.16	-17	PASS
	-87	-41.29	-16	PASS
	-88	-43.35	-15	PASS






Variable Uplink Noise Timing			
Operation Band	Measured (s)	Limit (s)	Results
Lower 700 Band	0.120	3	PASS
Upper 700 Band	0.130	3	PASS
Cellular Band	0.060	3	PASS
PCS Band	0.120	3	PASS
AWS Band	0.030	3	PASS







Test Graphs



Lower 700 Band UL



Lower 700 Band DL



Lower 700 Band Variable Uplink Noise Timing




Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Upper 700 Band UL



Upper 700 Band DL



Upper 700 Band Variable Uplink Noise Timing





Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity









6.2 Authorized Frequency Band Verification

6.2.1 Applicable Standard

According to § 20.21(e)(3) Frequency Bands.

This test is intended to confirm that the signal booster only operates on the CMRS frequency bands authorized for use by the NPS. In other words, the signal booster shall reject amplification of other signals outside of its passband. In addition, this test will identify the frequency at which the maximum gain is realized within each CMRS operational band, which then serves as a basis for subsequent tests.

6.2.2 Test Procedure

According to section 7.1 of KDB 935210 D03 Signal Booster Measurement v04r04:

- Connect the EUT to the test equipment as shown in Figure 4. Begin with the uplink output (donor) port connected to the spectrum analyzer.
- Set the spectrum analyzer resolution bandwidth (RBW) for 100 kHz with the video bandwidth (VBW) ≥ 3 the RBW, using a PEAK detector with the MAX HOLD function.
- Set the center frequency of the spectrum analyzer to the center of the operational band under test with a span of 1 MHz.
- Set the signal generator for CW mode and tune to the center frequency of the operational band under test.
- Set the initial signal generator power to a level that is at least 6 dB below the AGC level specified by the manufacturer.
- Slowly increase the signal generator power level until the output signal reaches the AGC operational level.
- Reduce the signal generator power to a level that is 3 dB below the level noted above, then manually reset the EUT (e.g., cycle ac/dc power).
- Reset the spectrum analyzer span to 2 the width of the CMRS band under test. Adjust the tuned frequency of the signal generator to sweep 2 the width of the CMRS band using the sweep function. The AGC must be deactivated throughout the entire sweep.
- Using three markers, identify the CMRS band edges and the frequency with the highest power. Affirm that the values of all markers are visible on the display of the spectrum analyzer (e.g., marker table set to on).
- Capture the spectrum analyzer trace for inclusion in the test report.
- Repeat 7.1c) to 7.1j) for all operational uplink and downlink bands.




Figure 4 – Band verification test instrumentation setup





6.2.3 Test Data

Temperature	23.6°C	Humidity	52.3%
Test Engineer	Nick Peng	Test Mode	Transmitting

Test Graphs-Uplink



Shenzhen LCS Compliance Testing Laboratory Ltd.



Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity





Test Graphs-Downlink




Lower 700 Band

Upper 700 Band



Cellular Band

PCS Band



AWS Band



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



6.3 Maximum power measurement

6.3.1 Applicable Standard

According to §20.21(e)(8)(i)(D) Power Limits; §20.21(e)(8)(i)(B) Bidirectional Capability (uplink minimum conducted power output); §20.21(e)(4) Self-monitoring:

1. A booster's uplink power must not exceed 1 watt composite conducted power and equivalent isotropic radiated power (EIRP) for each band of operation. Composite downlink power shall not exceed 0.05 watt (17 dBm) conducted and EIRP for each band of operation.

2. Consumer Boosters must be able to provide equivalent uplink and downlink gain and conducted uplink power output that is at least 0.05 watts

This procedure shall be used to demonstrate compliance to the signal booster power limits and requirements as specified in Sections 20.21(e)(8)(i)(D) and 20.21(e)(8)(i)(B) for wideband consumer signal boosters.

6.3.2 Test Procedure

According to section 7.2.1 of KDB 935210 D03 Signal Booster Measurement v04r04:

Compliance to applicable EIRP limits must be shown using the highest gains from the list of antennas, cabling, and coupling devices declared by the manufacturer for use with the consumer booster.

a) In addition, the maximum power levels measured in this procedure will be used in calculating the maximum gain as described in the next subclause.

b) The frequency with the highest power level in each operational band as determined in 7.1 is to be measured discretely by applying the following procedure using the stated emission and power detector types independently.

c) Use a signal generator to create a pulsed CW or GSM signal with a pulse width of 570 μ s and a duty cycle of 12.5% (i.e., one GSM timeslot), then measure using the burst power function of the measuring instrument.

d) Use a signal generator to create an AWGN signal with a 99% occupied bandwidth (OBW) of 4.1 MHz, then measure using the channel power or band power function of the measuring instrumentation.

f) All modes of operation must be verified to maintain operation within applicable limits at the maximum uplink and downlink test levels per device type as defined in 5.5, by increasing the power level in 2 dB steps from the AGC level to the maximum input level specified in 5.5.

According to section 7.2.2 of KDB 935210 D03 Signal Booster Measurement v04r04:

a) Connect the EUT to the test equipment as shown in Figure 5. Begin with the uplink output (donor) port connected to the spectrum analyzer.

b) Configure the signal generator and spectrum analyzer for operation on the frequency determined in 7.1 with the highest power level, but with the center frequency of the signal no closer than 2.5 MHz from the band edge. The spectrum analyzer span shall be set to at least 10 MHz.

c) Set the initial signal generator power to a level well below that which causes AGC activation.

d) Slowly increase the signal generator power level until the output signal reaches the AGC operational limit (from observation of signal behavior on the spectrum analyzer; i.e., no further increase in output power as input power is increased).

e) Reduce power sufficiently on the signal generator to ensure that the AGC is not controlling the power output.



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



- f) Slowly increase the signal generator power to a level just below (and within 0.5 dB of) the AGC limit without triggering the AGC. Note the signal generator power level as P_{in} .
- g) Measure the output power, P_{out} , with the spectrum analyzer as follows.
- 1) Set RBW = 100 kHz for AWGN signal type, or 300 kHz for CW or GSM signal type.
 - 2) Set VBW ≥ 3 RBW.
 - 3) Select either the BURST POWER or CHANNEL POWER measurement mode, as required for each signal type. For AWGN, the channel power integration bandwidth shall be the 99% OBW of the 4.1 MHz signal.
 - 4) Select the power averaging (rms) detector.
 - 5) Affirm that the number of measurement points per sweep $\geq (2 \text{ span})/\text{RBW}$.
NOTE—This requirement does not apply for BURST power measurement mode.
 - 6) Set sweep time = auto couple, or as necessary (but no less than auto couple value).
 - 7) Trace average at least 100 traces in power averaging (i.e., rms) mode.
 - 8) Record the measured power level P_{out} , with one set of results for the GSM or CW input stimulus, and another set of results for the AWGN input stimulus.

6.3.3 Test Data

Temperature	23.6°C	Humidity	52.3%
Test Engineer	Nick Peng	Test Mode	Transmitting

Max Output Power									
Mode	Operation Band	Signal Type	Conducted Output Power (dBm)	Conducted Output Power limit(dBm)	Antenna Gain (dBi)	Cable Loss (dB)	EIRP (dBm)	EIRP Limit (dBm)	Verdict
Uplink	Lower 700	CW	17.435	17-30	6	1.80	21.635	≤ 30	PASS
		AWGN	17.750		6	1.80	21.950		PASS
	Upper 700	CW	17.849		6	1.80	22.049		PASS
		AWGN	17.750		6	1.80	21.950		PASS
	Cellular	CW	17.662		6	2.00	21.662		PASS
		AWGN	17.440		6	2.00	21.440		PASS
	PCS	CW	17.330		8	2.95	22.380		PASS
		AWGN	17.590		8	2.95	22.640		PASS
	AWS	CW	17.820		8	2.70	23.120		PASS
		AWGN	17.530		8	2.70	22.830		PASS
Downlink	Lower 700	CW	-4.644	/	7	1.80	0.556	≤ 17	PASS
		AWGN	6.17		7	1.80	11.370		PASS
	Upper 700	CW	1.281		7	1.80	6.481		PASS
		AWGN	6.88		7	1.80	12.08		PASS
	Cellular	CW	1.988		7	2.00	6.988		PASS
		AWGN	6.690		7	2.00	11.690		PASS
	PCS	CW	-2.934		7	2.95	1.116		PASS
		AWGN	5.970		7	2.95	10.020		PASS
	AWS	CW	1.259		7	3.20	5.059		PASS
		AWGN	5.800		7	3.20	9.600		PASS

Note: EIRP = Conducted Output Power + Antenna Gain - Cable Loss






Max Input test level						
Mode	Operation Band	Signal Type	AGC Level (dBm)	Max Input Level (dBm)	Max Input Level limit (dBm)	Verdict
Uplink	Lower 700 Band	CW	-34	-17	≤27	PASS
		AWGN	-35	-18		PASS
	Upper 700 Band	CW	-35	-18		PASS
		AWGN	-36	-19		PASS
	Cellular Band	CW	-34	-17		PASS
		AWGN	-35	-18		PASS
	PCS Band	CW	-38	-21		PASS
		AWGN	-36	-24		PASS
	AWS Band	CW	-46	-30		PASS
		AWGN	-48	-33		PASS
Downlink	Lower 700 Band	CW	-55	-37	≤-20	PASS
		AWGN	-56	-38		PASS
	Upper 700 Band	CW	-54	-38		PASS
		AWGN	-55	-39		PASS
	Cellular Band	CW	-48	-37		PASS
		AWGN	-52	-39		PASS
	PCS Band	CW	-53	-48		PASS
		AWGN	-55	-50		PASS
	AWS Band	CW	-54	-50		PASS
		AWGN	-57	-52		PASS







Test Graphs




Lower 700 Band AWGN, UL




Lower 700 Band CW, UL




Lower 700 Band AWGN, DL



Lower 700 Band CW, DL



Upper 700 Band AWGN, UL



Upper 700 Band CW, UL




Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity




Upper 700 Band AWGN, DL




Upper 700 Band CW, DL




Cellular Band AWGN, UL



Cellular Band CW, UL



Cellular Band AWGN, DL



Cellular Band CW, DL




Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity




PCS Band AWGN, UL




PCS Band CW, UL




PCS Band AWGN, DL



PCS Band CW, DL





AWS Band AWGN, UL



AWS Band CW, UL





Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



6.4 Gain Limits and Bidirectional Capability&Variable Gain&Variable Uplink Gain Timing

6.4.1 Applicable Standard

According to §20.21(e)(8)(i)(C)(2) Booster Gain Limits (maximum gain); §20.21(e)(8)(i)(B) Bidirectional Capability (equivalent uplink and downlink gain):

The uplink and downlink maximum gain of a Consumer Booster referenced to its input and output ports shall not exceed the following limits:

- (i) Fixed Booster maximum gain shall not exceed $6.5 \text{ dB} + 20 \log_{10}(\text{Frequency})$;
- (ii) Where, Frequency is the uplink mid-band frequency of the supported spectrum bands in MHz.

6.4.2 Test Procedure

According to section 7.3 of KDB 935210 D03 Signal Booster Measurement v04r04:

This subclause provides guidance for the calculation of the maximum gain, based on the results obtained from the 7.1 and 7.2 measurements. The NPS limits on maximum gain for fixed and mobile wideband consumer signal boosters are provided in §20.21(e)(8)(i)(C)(2). Additionally, §20.21(e)(8)(i)(B) requires that wideband consumer signal boosters be able to provide equivalent uplink and downlink gain, i.e., within 9 dB.

- a) Calculate the maximum gain of the booster as follows to demonstrate compliance to the applicable gain limits as specified.
- b) For both the uplink and downlink in each supported frequency band, use each of the POUT and PIN result pairs for all signal types used in 7.2 in the following equation to obtain the maximum gain, G:

$$G \text{ (dB)} = \text{POUT(dBm)} - \text{PIN(dBm)}.$$

- c) Record the maximum gain of the uplink and downlink paths for each supported frequency band, and verify that the each gain value complies with the applicable limit.
- d) Provide tabulated results in the test report

6.4.3 Test Data

Temperature	23.6°C	Humidity	52.3%
Test Engineer	Nick Peng	Test Mode	Transmitting





Max Gain							
Mode	Operation Band	Signal Type	Pre AGC Input Level (dBm)	Conducted Output Level (dBm)	Max Gain (dB)	Gain Limit (dB)	Verdict
Uplink	Lower 700 Band	CW	-34	18.82	52.82	≤63.49	PASS
		AWGN	-35	18.73	53.73		PASS
	Upper 700 Band	CW	-35	18.72	53.72	≤64.02	PASS
		AWGN	-36	18.64	54.64		PASS
	Cellular Band	CW	-34	19.20	53.20	≤64.94	PASS
		AWGN	-35	19.11	54.11		PASS
	PCS Band	CW	-38	19.07	57.07	≤71.99	PASS
		AWGN	-36	19.23	55.23		PASS
Downlink	Lower 700 Band	CW	-46	18.46	64.46	≤71.27	PASS
		AWGN	-48	18.31	66.31		PASS
	Upper 700 Band	CW	-55	5.36	60.36	≤63.85	PASS
		AWGN	-56	5.05	61.05		PASS
	Cellular Band	CW	-54	5.21	59.21	≤64.36	PASS
		AWGN	-55	5.01	60.01		PASS
	PCS Band	CW	-48	7.56	55.56	≤65.40	PASS
		AWGN	-52	6.32	58.32		PASS
	AWS Band	CW	-53	7.34	60.34	≤72.34	PASS
		AWGN	-55	6.72	61.72		PASS
	AWS Band	CW	-54	6.49	60.49	≤73.08	PASS
		AWGN	-57	6.22	63.22		PASS

Note: Fixed Booster maximum gain shall not exceed $6.5 \text{ dB} + 20 \log_{10}(\text{Frequency})$, where Frequency is the uplink mid-band frequency of the supported spectrum bands in MHz.

Uplink Gain VS Downlink Gain						
Band	Signal Type	Uplink Gain (dB)	Downlink Gain (dB)	Calculated (dB)	Limit (dB)	Verdict
Lower 700 Band	CW	52.82	60.36	-7.54	≤9	PASS
	AWGN	53.73	61.05	-7.32		PASS
Upper 700 Band	CW	53.72	59.21	-5.49		PASS
	AWGN	54.64	60.01	-5.37		PASS
Cellular Band	CW	53.20	55.56	-2.36		PASS
	AWGN	54.11	58.32	-4.21		PASS
PCS Band	CW	57.07	60.34	-3.27		PASS
	AWGN	55.23	61.72	-6.49		PASS
AWS Band	CW	64.46	60.49	3.97		PASS
	AWGN	66.31	63.22	3.09		PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



6.4.4 Variable Gain Test Procedure

According to §20.21(e)(8)(i)(C)(1) Booster Gain Limits (variable gain); §20.21(e)(8)(i)(H) Transmit Power Off Mode (uplink gain):

The uplink gain in dB of a consumer booster referenced to its input and output ports shall not exceed $-34 \text{ dB} - \text{RSSI} + \text{MSCL}$.

(i) Where RSSI is the downlink composite received signal power in dBm at the booster donor port for all base stations in the band of operation. RSSI is expressed in negative dB units relative to 1 mW.

(ii) Where MSCL (Mobile Station Coupling Loss) is the minimum coupling loss in dB between the wireless device and input port of the consumer booster. MSCL must be calculated or measured for each band of operation and provided in compliance test reports.

According to section 7.9.1 of KDB 935210 D03 Signal Booster Measurement v04r04:

- a) Connect the EUT to the test equipment as shown in Figure 5 with the uplink output (donor) port connected to signal generator #1. Affirm that the coupled path of the RF coupler is connected to the spectrum analyzer.
- b) Configure downlink signal generator #1 for AWGN operation with a 99% OBW of 4.1 MHz, tuned to the center of the operational band.
- c) Set the power level and frequency of signal generator #2 to a value that is 5 dB below the AGC level determined from 7.2. The signal type is AWGN with a 99% OBW of 4.1 MHz.
- d) Set RBW = 100 kHz.
- e) Set VBW $\geq$ 300 kHz.
- f) Select the CHANNEL POWER measurement mode.
- g) Select the power averaging (rms) detector.
- h) Affirm that the number of measurement points per sweep $\geq (2 \text{ span})/\text{RBW}$.
- i) Sweep time = auto couple or as necessary (but no less than auto couple value).
- j) Trace average at least 10 traces in power averaging (i.e., rms) mode.
- k) Measure the maximum channel power and compute maximum gain when varying the signal generator #1 output to a level from -90 dBm to -20 dBm , as measured at the input port (i.e., downlink signal level at the booster donor port node of Figure 5), in 1 dB steps inside the RSSI-dependent region, and 10 dB steps outside the RSSI-dependent region. Report the six values closest to the limit, including at least two points from within the RSSI-dependent region of operation. See gain limit in charts in Appendix D for uplink gain requirements. Additionally, document that the EUT provides equivalent uplink and downlink gain, and when operating in shutoff mode that the uplink and downlink gain is within the transmit power off mode gain limits.
- l) Repeat 7.9.1b) to 7.9.1k) for all operational uplink bands.





6.4.5 Variable uplink gain timing Test Procedure

According to section 7.9.2 (Variable uplink gain timing) of KDB 935210 D03 Signal Booster Measurement v04r04:

- m) Connect the EUT to the test equipment as shown in Figure 5 with the uplink output (donor) port connected to signal generator #1. Affirm that the coupled path of the RF coupler is connected to the spectrum analyzer.
- n) Configure downlink signal generator #1 for AWGN operation with a 99% OBW of 4.1 MHz, tuned to the center of the operational band.
- o) Set the power level and frequency of signal generator #2 to a value that is 5 dB below the AGC level determined from 7.2. The signal type is AWGN with a 99% OBW of 4.1 MHz.
- p) Set RBW = 100 kHz.
- q) Set VBW $\geq$ 300 kHz.
- r) Select the CHANNEL POWER measurement mode.
- s) Select the power averaging (rms) detector.
- t) Affirm that the number of measurement points per sweep $\geq$ (2 span)/RBW.
- u) Sweep time = auto couple or as necessary (but no less than auto couple value).
- v) Trace average at least 10 traces in power averaging (i.e., rms) mode.
- w) Measure the maximum channel power and compute maximum gain when varying the signal generator #1 output to a level from -90 dBm to -20 dBm, as measured at the input port (i.e., downlink signal level at the booster donor port node of Figure 5), in 1 dB steps inside the RSSI-dependent region, and 10 dB steps outside the RSSI-dependent region. Report the six values closest to the limit, including at least two points from within the RSSI-dependent region of operation. See gain limit in charts in Appendix D for uplink gain requirements. Additionally, document that the EUT provides equivalent uplink and downlink gain, and when operating in shutoff mode that the uplink and downlink gain is within the transmit power off mode gain limits.
- x) Repeat 7.9.1b) to 7.9.1k) for all operational uplink bands.




Figure 5 – Variable gain instrumentation test setup



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



6.4.6 Test data

Temperature	23.6℃	Humidity	52.3%
Test Engineer	Nick Peng	Test Mode	Transmitting

Variable booster Uplink gain								
Operation Band	Max Gain (dB)	Isolation (dB)	Difference (dB)	Variable booster gain (dB)	RSSI (dBm)	MSCL	Limit (dB)	Results
Lower 700 Band	53.73	+5	-6.54	47.19	-60	25.14	51.14	PASS
		+4	-5.49	48.24	-61	25.14	52.14	PASS
		+3	-4.59	49.14	-62	25.14	53.14	PASS
		+2	-3.72	50.01	-63	25.14	54.14	PASS
		+1	-3.50	50.23	-64	25.14	55.14	PASS
		0	-2.05	51.68	-65	25.14	56.14	PASS
Upper 700 Band	54.64	+5	-3.21	51.43	-61	26.10	53.10	PASS
		+4	-2.63	52.01	-62	26.10	54.10	PASS
		+3	-1.85	52.79	-63	26.10	55.10	PASS
		+2	-1.76	52.88	-64	26.10	56.10	PASS
		+1	-1.02	53.62	-65	26.10	57.10	PASS
		0	-0.85	53.79	-66	26.10	58.10	PASS
Cellular Band	54.11	+5	-4.26	49.85	-60	26.78	52.78	PASS
		+4	-3.03	51.08	-61	26.78	53.78	PASS
		+3	-2.46	51.65	-62	26.78	54.78	PASS
		+2	-2.37	51.74	-63	26.78	55.78	PASS
		+1	-2.24	51.87	-64	26.78	56.78	PASS
		0	-1.09	53.02	-65	26.78	57.78	PASS
PCS Band	57.07	+5	2.58	59.65	-61	34.75	61.75	PASS
		+4	2.47	59.54	-62	34.75	62.75	PASS
		+3	1.87	58.94	-63	34.75	63.75	PASS
		+2	1.70	58.77	-64	34.75	64.75	PASS
		+1	1.51	58.58	-65	34.75	65.75	PASS
		0	0.63	57.70	-66	34.75	66.75	PASS
AWS Band	66.31	+5	-5.55	60.76	-63	33.82	62.82	PASS
		+4	-4.47	61.84	-64	33.82	63.82	PASS
		+3	-3.36	62.95	-65	33.82	64.82	PASS
		+2	-3.21	63.10	-66	33.82	65.82	PASS
		+1	-3.13	63.18	-67	33.82	66.82	PASS
		0	-1.11	65.20	-68	33.82	67.82	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China


Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Variable Uplink Gain Timing			
Operation Band	Measured (s)	Limit (s)	Result
Lower 700 Band	0.600	3.0	PASS
Upper 700 Band	0.600	3.0	PASS
Cellular Band	0.400	3.0	PASS
PCS Band	0.700	3.0	PASS
AWS Band	0.500	3.0	PASS

Variable Uplink Gain Timing-Test Graphs




Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity





6.5 Anti-Oscillation

6.5.1 Applicable Standard

According to §20.21(e)(8)(ii)(A) Anti-Oscillation:

1. Consumer boosters must be able to detect and mitigate (i.e., by automatic gain reduction or shut down), any oscillations in uplink and downlink bands. Oscillation detection and mitigation must occur automatically within 0.3 seconds in the uplink band and within 1 second in the downlink band. In cases where oscillation is detected, the booster must continue mitigation for at least one minute before restarting. After five such restarts, the booster must not resume operation until manually reset.
2. Use of two EUTs is permitted for this measurement, which can greatly reduce the test time required. One EUT shall operate in a normal mode, and the second EUT shall operate in a test mode that is capable of disabling the uplink inactivity function and/or allows a reduction to 5 seconds of the time between restarts.

The procedures in 7.11.3 and 7.11.4 do not apply for devices that operate only as direct-connection mobile boosters having gain of less than or equal to 15 dB.

6.5.2 Test Procedure

Oscillation restart tests

According to section 7.11.2 of KDB 935210 D03 Signal Booster Measurement v04r04:

- a) Connect the normal-operating mode EUT to the test equipment as shown in Figure 6 beginning with the spectrum analyzer on the uplink output (donor) port. Confirm that the RF coupled path is connected to the spectrum analyzer.
NOTE—The band-pass filter shall provide sufficient out-of-band rejection to prevent oscillations from occurring in bands not under test.
- b) Spectrum analyzer settings:
 - 1) Center frequency at the center of the band under test
 - 2) Span equal or slightly exceeding the width of the band under test
 - 3) Continuous sweep, max-hold
 - 4) $RBW \geq 1$ MHz, $VBW > 3$ RBW
- c) Decrease the variable attenuator until the spectrum analyzer displays a signal within the band under test. Using a marker, identify the approximate center frequency of this signal on the max-hold display, increase the attenuation by 10 dB, then reset the EUT (e.g., cycle ac/dc power).
- d) Repeat 7.11.2c) twice to ensure that the center of the signal created by the booster remains within 250 kHz of the spectrum analyzer display center frequency. If the frequency of the signal is unstable, confirm that the spectrum analyzer display is centered between the frequency extremes observed. If the signal is wider than 1 MHz, ensure that the spectrum analyzer display is centered on the signal by increasing the RBW. Reset the EUT (e.g., cycle ac/dc power) after each oscillation event, if necessary. Set the spectrum analyzer sweep trigger level to just below the peak amplitude of the displayed EUT oscillation signal.
- e) Set the spectrum analyzer to zero-span, with a sweep time of 5 seconds, and single-sweep with max-hold. The spectrum analyzer sweep trigger level in this and the subsequent steps shall be the level identified in 7.11.2d).
- f) Decrease the variable attenuator until the spectrum analyzer sweep is triggered, increase the attenuation by 10 dB, then reset the EUT (e.g., cycle ac/dc power).



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



- g) Reset the zero-span trigger of the spectrum analyzer, then repeat 7.11.2f) twice to ensure that the spectrum analyzer is reliably triggered, resetting the EUT (e.g., cycle ac/dc power) after each oscillation event if necessary.
- h) Reset the zero-span sweep trigger of the spectrum analyzer, and reset the EUT (e.g., cycle ac/dc power).
- i) Force the EUT into oscillation by reducing the attenuation.
- j) Use the marker function of the spectrum analyzer to measure the time from the onset of oscillation until the EUT turns off, by setting Marker 1 on the leading edge of the oscillation signal and Marker 2 on the trailing edge. The spectrum analyzer sweep time may be adjusted to improve the time resolution of these cursors.
- k) Capture the spectrum analyzer zero-span trace for inclusion in the test report. Report the power level associated with the oscillation separately if it can't be displayed on the trace.
- l) Repeat 7.11.2b) to 7.11.2k) for all operational uplink and downlink bands.
- m) Set the spectrum analyzer zero-span sweep time for longer than 60 seconds, then measure the restart time for each operational uplink and downlink band.
- n) Replace the normal-operating mode EUT with the EUT that supports an anti-oscillation test mode.
- o) Set the spectrum analyzer zero-span time for a minimum of 120 seconds, and a single sweep.
- p) Manually trigger the spectrum analyzer zero-span sweep, and manually force the booster into oscillation as described in 7.11.2i).
- q) When the sweep is complete, place cursors between the first two oscillation detections, and save the plot for inclusion in the test report. The time between restarts must match the manufacturer's timing for the test mode, and there shall be no more than 5 restarts.
- r) Repeat 7.11.2m) to 7.11.2q) for all operational uplink and downlink bands.

Oscillation mitigation or shutdown

According to section 7.11.3 of KDB 935210 D03 Signal Booster Measurement v04r04:

- a) Connect the normal-operating mode EUT to the test equipment as shown in Figure 7.
- b) Set the spectrum analyzer center frequency to the center of band under test, and use the following settings:
 - 1) RBW=30 kHz, VBW $\geq 3 \times$ RBW,
 - 2) power averaging (rms) detector,
 - 3) trace averages ≥ 100 ,
 - 4) span $\geq 120\%$ of operational band under test,
 - 5) number of sweep points $\geq 2 \times$ Span/RBW.
- c) Configure the signal generator for AWGN operation with a 99% OBW of 4.1 MHz, tuned to the frequency of 2.5 MHz above the lower edge or below the upper edge of the operating band under test. Adjust the RF output level of the signal generator such that the measured power level of the AWGN signal at the output port of the booster is 30 dB less than the maximum power of the booster for the band under test. Affirm that the input signal is not obstructing the measurement of the strongest oscillation peak in the band, and is not included within the span in the measurement.
 - 1) Boosters with operating spectrum passbands of 10 MHz or less may use a CW signal source at the band edge rather than AWGN.
 - 2) For device passbands greater than 10 MHz, standard CMRS signal sources (i.e., CDMA, W-CDMA, LTE) may be used instead of AWGN at the band edge.
- d) Set the variable attenuator to a high attenuation setting such that the booster will operate at maximum gain when powered on. Reset the EUT (e.g., cycle ac/dc power). Allow the EUT to



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity




complete its boot-up process, to reach full operational gain, and to stabilize its operation.

e) Set the variable attenuator such that the insertion loss for the center of the band under test (isolation) between the booster donor port and server port is 5 dB greater than the maximum gain, as recorded in the maximum gain test procedure (see 7.3), for the band under test.

f) Verify the EUT shuts down, i.e., to mitigate the oscillations. If the booster does not shut down, measure and verify the peak oscillation level as follows.

- 1) Allow the spectrum analyzer trace to stabilize.
- 2) Place the marker at the highest oscillation level occurring within the span, and record its output level and frequency.
- 3) Set the spectrum analyzer center frequency to the frequency with the highest oscillation signal level, and reduce the span such that the upper and lower adjacent oscillation peaks are within the span.
- 4) Use the Minimum Search Marker function to find the lowest output level that is within the span, and within the operational band under test, and record its output level and frequency.
- 5) Affirm that the peak oscillation level measured in 7.11.3f2), does not exceed by 12.0 dB the minimal output level measured in 7.11.3f4). Record the measurement results of 7.11.3f2) and 7.11.3f4) in tabular format for inclusion in the test report.
- 6) The procedure of 7.11.3f1) to 7.11.3f5) allows the spectrum analyzer trace to stabilize, and verification of shutdown or oscillation level measurement must occur within 300 seconds.20
- g) Decrease the variable attenuator in 1 dB steps, and repeat step 7.11.3f) for each 1 dB step. Continue testing to the level when the insertion loss for the center of band under test (isolation) between the booster donor port and server port is 5 dB lower than the maximum gain (see 7.3).
- h) Repeat 7.11.3a) to 7.11.3g) for all operational uplink and downlink bands.



NOTE—This figure shows the test setup for uplink bands transmission path tests; i.e., signal flow is out from the donor port into the directional coupler. For downlink bands transmission path tests, the feedback signal flow path direction and equipment connections shall be reversed, i.e., signal flow is out from the server port into the directional coupler, and signal flow is into the donor port from the variable RF attenuator.

Figure 6 – Oscillation detection (7.11.2) test setup






Figure 7 – Oscillation mitigation/shutdown test setup

6.5.3 Test data

Temperature	23.6℃	Humidity	52.3%
Test Engineer	Nick Peng	Test Mode	Transmitting


Test Results Of Detection Time				
Operation Band		Detection Time (s)	Limit (s)	Result
Uplink	Lower 700 Band	0.255	0.300	PASS
	Upper 700 Band	0.255	0.300	PASS
	Cellular Band	0.200	0.300	PASS
	PCS Band	0.260	0.300	PASS
	AWS Band	0.200	0.300	PASS
Downlink	Lower 700 Band	0.255	1.000	PASS
	Upper 700 Band	0.200	1.000	PASS
	Cellular Band	0.215	1.000	PASS
	PCS Band	0.260	1.000	PASS
	AWS Band	0.280	1.000	PASS


Test Results Of Restarting Time						
Operation Band		Restarting Time (s)	Limit (s)	Restarting Counts	Limit	Result
Uplink	Lower 700 Band	See Test Graphs of Restarting Time	60	4	5	PASS
	Upper 700 Band		60	4	5	PASS
	Cellular Band		60	4	5	PASS
	PCS Band		60	3	5	PASS
	AWS Band		60	4	5	PASS
Downlink	Lower 700 Band		60	4	5	PASS
	Upper 700 Band		60	4	5	PASS
	Cellular Band		60	4	5	PASS
	PCS Band		60	3	5	PASS
	AWS Band		60	4	5	PASS




Test Graphs of Detection Time

Detection Time-Cellular Band DL







Detection Time-PCS Band UL



Detection Time-PCS Band DL



Detection Time-AWS Band UL



Detection Time-AWS Band DL



Shenzhen LCS Compliance Testing Laboratory Ltd.



Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com



Scan code to check authenticity





Test Graphs of Restarting Time



Restarting Time-Lower 700 Band UL



Restarting Time-Upper 700 Band UL



Restarting Time-Cellular Band UL

Restarting Time-Cellular Band DL




Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity




Restarting Time-PCS Band UL



Restarting Time-PCS Band DL



Restarting Time-AWS Band UL



Restarting Time-AWS Band DL



**Oscillation mitigation or shutdown:**

Lower 700 Band	Uplink		
Signal Type	AWGN		
Isolation	Deffrence	Limit	Result
dB	dB	dB	
+5	6.26	<12	Pass
+4	7.94	<12	Pass
+3	7.59	<12	Pass
+2	9.42	<12	Pass
+1	10.11	<12	Pass
0	shutdown		

Lower 700 Band	Downlink		
Signal Type	AWGN		
Isolation	Deffrence	Limit	Result
dB	dB	dB	
+5	6.35	<12	Pass
+4	7.07	<12	Pass
+3	7.86	<12	Pass
+2	9.49	<12	Pass
+1	10.23	<12	Pass
0	11.19	<12	Pass
-1	shutdown		

Upper 700 Band	Uplink		
Signal Type	AWGN		
Isolation	Deffrence	Limit	Result
dB	dB	dB	
+5	6.32	<12	Pass
+4	7.10	<12	Pass
+3	8.35	<12	Pass
+2	9.10	<12	Pass
+1	9.77	<12	Pass
0	10.65	<12	Pass
-1	shutdown		



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Upper 700 Band	Downlink		
Signal Type	AWGN		
Isolation	Deffrence	Limit	Result
dB	dB	dB	
+5	6.37	<12	Pass
+4	7.32	<12	Pass
+3	8.51	<12	Pass
+2	9.24	<12	Pass
+1	10.86	<12	Pass
0	shutdown		

Cellular Band	Uplink		
Signal Type	AWGN		
Isolation	Deffrence	Limit	Result
dB	dB	dB	
+5	7.18	<12	Pass
+4	8.67	<12	Pass
+3	9.39	<12	Pass
+2	10.28	<12	Pass
+1	shutdown		

Cellular Band	Downlink		
Signal Type	AWGN		
Isolation	Deffrence	Limit	Result
dB	dB	dB	
+5	5.22	<12	Pass
+4	7.85	<12	Pass
+3	8.45	<12	Pass
+2	9.37	<12	Pass
+1	10.16	<12	Pass
0	shutdown		



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



PCS Band	Uplink		
Signal Type	AWGN		
Isolation	Deffrence	Limit	Result
dB	dB	dB	
+5	5.88	<12	Pass
+4	6.37	<12	Pass
+3	7.05	<12	Pass
+2	7.75	<12	Pass
+1	9.46	<12	Pass
0	10.09	<12	Pass
-1	shutdown		

PCS Band	Downlink		
Signal Type	AWGN		
Isolation	Deffrence	Limit	Result
dB	dB	dB	
+5	7.32	<12	Pass
+4	8.78	<12	Pass
+3	9.59	<12	Pass
+2	10.22	<12	Pass
+1	11.05	<12	Pass
0	shutdown		

AWS Band	Uplink		
Signal Type	AWGN		
Isolation	Deffrence	Limit	Result
dB	dB	dB	
+5	7.25	<12	Pass
+4	8.57	<12	Pass
+3	9.35	<12	Pass
+2	9.76	<12	Pass
+1	10.57	<12	Pass
0	shutdown		



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



AWS Band	Downlink		
Signal Type	AWGN		
Isolation	Deffrence	Limit	Result
dB	dB	dB	
+5	6.69	<12	Pass
+4	7.76	<12	Pass
+3	8.31	<12	Pass
+2	9.42	<12	Pass
+1	10.37	<12	Pass
0	shutdown		





6.6 Intermodulation Limits

6.6.1 Applicable Standard

According to §20.21(e)(8)(i)(F) Intermodulation Limits:

The transmitted intermodulation products of a consumer booster at its uplink and downlink ports shall not exceed the power level of -19 dBm for the supported bands of operation.

6.6.2 Test Procedure

According to section 7.4 of KDB 935210 D03 Signal Booster Measurement v04r04:

- a) Connect the signal booster to the test equipment as shown in Figure 9. Begin with the uplink output (donor) port connected to the spectrum analyzer.
 - b) Set the spectrum analyzer RBW = 3 kHz.
 - c) Set the VBW ≥ 3 RBW.
 - d) Select the rms detector.
 - e) Set the spectrum analyzer center frequency to the center of the supported operational band under test.
 - f) Set the span to 5 MHz. Affirm that the number of measurement points per sweep $\geq (2 \times \text{span})/\text{RBW}$.
 - g) Configure the two signal generators for CW operation with generator #1 tuned 300 kHz below the operational band center frequency and generator #2 tuned 300 kHz above the operational band center frequency. If the maximum output power is not at the operational-band (booster pass band) center frequency, configure the test signal pair around the frequency with maximum output power as determined per 7.2.
 - h) Set the signal generator amplitudes so that the power from each into the EUT is equivalent, then turn on the RF output.
 - i) Simultaneously increase each signal generators' amplitude equally until just before the EUT begins AGC, then affirm that all intermodulation-product emissions (if any occur) are below the specified limit of -19 dBm.
 - j) Use the trace averaging function of the spectrum analyzer, and wait for the trace to stabilize. Place a marker at the highest amplitude intermodulation-product emission.
 - k) Record the maximum intermodulation product amplitude level that is observed.
 - l) Capture the spectrum analyzer trace for inclusion in the test report.
 - m) Repeat 7.4e) to 7.4l) for all uplink and downlink operational bands.
- NOTE—If using a single signal generator with dual outputs, affirm that intermodulation products are not the result of the generator.
- n) Increase the signal generator amplitude in 2 dB steps to 10 dB above the AGC threshold determined in 7.4i), but not exceeding the maximum input level of 5.5, to affirm that the EUT maintains compliance with the intermodulation limit. The test report shall include either a statement describing that the device complies at 10 dB above AGC or at the 5.5 power levels, or a table showing compliance at the additional input power(s) required.



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity





Figure 9 – Intermodulation product instrumentation test setup


6.6.3 Test Data

Temperature	23.6℃	Humidity	52.3%
Test Engineer	Nick Peng	Test Mode	Transmitting


Test Graphs




Lower 700 Band Pre AGC, UL



Lower 700 Band AGC+10dB, UL



Upper 700 Band Pre AGC, UL



Upper 700 Band AGC+10dB, UL




Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity




Cellular Band Pre AGC, UL




Cellular Band AGC+10dB, UL




PCS Band Pre AGC, UL



PCS Band AGC+10dB, UL



AWS Band Pre AGC, UL



AWS Band AGC+10dB, UL




Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity




Lower 700 Band Pre AGC, DL




Lower 700 Band AGC+10dB, DL




Upper 700 Band Pre AGC, DL



Upper 700 Band AGC+10dB, DL



Cellular Band Pre AGC, DL



Cellular Band AGC+10dB, DL




Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: + (86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity




PCS Band Pre AGC, DL



PCS Band AGC+10dB, DL



AWS Band Pre AGC, DL



AWS Band AGC+10dB, DL





6.7 Out of Band Emission

6.7.1 Applicable Standard

According to § 20.21(e)(8)(i)(E) Out of Band Emission Limits:

Booster out of band emissions (OOBE) shall be at least 6 dB below the FCC's mobile emission limits for the supported bands of operation. Compliance to OOBE limits will utilize high peak-to-average CMRS signal types.

For B2: Per FCC §24.238 the power of any emission outside of the authorized operating frequency ranges must be attenuated below the transmitting power (P) by a factor of at least $43 + 10\log(P)$ dB.

For B4: Per §27.53(h): For operations in the 1710–1755 MHz and 2110–2155 MHz bands, the power of any emission outside a licensee's frequency block shall be attenuated below the transmitter power (P) by at least $43 + 10 \log_{10}(P)$ dB.

For B5: Per FCC §22.917 the power of any emission outside of the authorized operating frequency ranges must be attenuated below the transmitting power (P) by a factor of at least $43 + 10\log(P)$ dB.

For B12: Per §27.53 (g): For operations in the 698–746 MHz band, the power of any emission outside a licensee's frequency band(s) of operation shall be attenuated below the transmitter power (P) within the licensed band(s) of operation, measured in watts, by at least $43 + 10 \log (P)$ dB.

For B13: Per §27.53 (c): For operations in the 776-788 MHz band, the power of any emission outside the licensee's frequency band(s) of operation shall be attenuated below the transmitter power (P) within the licensed band(s) of operation, measured in watts, in accordance with the following: On any frequency outside the 776-788 MHz band, the power of any emission shall be attenuated outside the band below the transmitter power (P) by at least $43 + 10 \log (P)$ dB.

Calculation: Limit (dBm) = $[P - 43 + 10 \log (P)] - 6 = -19$ dBm

6.7.2 Test Procedure

According to section 7.5 of KDB 935210 D03 Signal Booster Measurement v04r04:

a) Connect the EUT to the test equipment as shown in Figure 1. Begin with the uplink output (donor) port connected to the spectrum analyzer.

b) Configure the signal generator for the appropriate operation for all uplink and downlink bands:

- 1) GSM: 0.2 MHz from upper and lower band edges.
- 2) LTE (5 MHz): 2.5 MHz from upper and lower band edges.
- 3) CDMA: 1.25 MHz from upper and lower band edges, except for cellular band as follows (only the upper and lower frequencies need to be tested):

824.88 MHz, 845.73 MHz, 836.52 MHz, 848.10 MHz,
869.88 MHz, 890.73 MHz, 881.52 MHz, 893.10 MHz.

NOTE 1—Alternative test modulation types:

- CDMA (alternative 1.25 MHz AWGN)
- LTE 5 MHz (alternative W-CDMA or 4.1 MHz AWGN)

NOTE 2—For LTE, the signal generator should use the uplink and downlink signal types for these modulations in uplink and downlink tests, respectively. LTE shall use 5 MHz signal, 25 resource blocks transmitting.



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



- NOTE 3—When using an AWGN test signal, the bandwidth shall be the measured 99% OBW.
- c) Set the signal generator amplitude to the maximum power level prior to AGC similar to 7.2.2e) to 7.2.2f) of the power measurement procedures for the appropriate modulations.
 - d) Set RBW = measurement bandwidth specified in the applicable rule section for the supported frequency band (see Appendix A for cross-reference to applicable rule section).
 - e) NOTE 3—Within 300 kHz and 3 MHz away from band edge, if smaller RBW is used (i.e., $RBW < 100$ kHz or 1 MHz, for above and below 1 GHz, respectively), per Parts 24 and 27 the smaller RBW is applicable only for frequencies within 100 kHz or 1 MHz (for above and below 1 GHz, respectively) away from the band edge.
 - f) Set VBW = 3 RBW.
 - g) Select the power averaging (rms) detector.
 - h) Sweep time = auto-couple.
 - i) Set the analyzer start frequency to the upper band/block edge frequency and the stop frequency to the upper band/block edge frequency plus: 300 kHz (when operational frequency is < 1 GHz), or 3 MHz (when operational frequency is ≥ 1 GHz).
 - j) Trace average at least 100 traces in power averaging (i.e., rms) mode.
 - k) Use peak marker function to find the maximum power level.
 - l) Capture the spectrum analyzer trace of the power level for inclusion in the test report.
 - m) Increase the signal generator amplitude in 2 dB steps until the maximum input level per 5.5 is reached. Affirm that the EUT maintains compliance with the OOB limits. The test report shall include either a statement describing that the device complies at 10 dB above AGC or at the 5.5 power levels, or a table showing compliance at the additional input power(s) required.
 - n) Reset the analyzer start frequency to the lower band/block edge frequency minus: 300 kHz (when operational frequency is < 1 GHz), or 3 MHz (when operational frequency is ≥ 1 GHz), and the stop frequency to the lower band/block edge frequency, then repeat 7.5i) to 7.5l). Repeat 7.5b) through 7.5m) for each uplink and downlink operational band.






6.7.3 Test data

Temperature	23.6°C	Humidity	52.3%
Test Engineer	Nick Peng	Test Mode	Transmitting

Test Graphs-Uplink-GSM



Upper 700 Band UL-GSM Left Side Pre AGC

Upper 700 Band UL-GSM Left Side AGC+10dB




Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity




Upper 700 Band UL-GSM Right Side Pre AGC




Upper 700 Band UL-GSM Right Side AGC+10dB




Cellular Band UL-GSM Left Side Pre AGC



Cellular Band UL-GSM Left Side AGC+10dB



Cellular Band UL-GSM Right Side Pre AGC



Cellular Band UL-GSM Right Side AGC+10dB




Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: + (86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity




PCS Band UL-GSM Left Side Pre AGC




PCS Band UL-GSM Left Side AGC+5.5dB




PCS Band UL-GSM Right Side Pre AGC



PCS Band UL-GSM Right Side AGC+10dB



AWS Band UL-GSM Left Side Pre AGC



AWS Band UL-GSM Left Side AGC+10dB




Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



AWS Band UL-GSM Right Side Pre AGC



AWS Band UL-GSM Right Side AGC+10dB






Test Graphs-Downlink-GSM



Lower 700 Band DL-GSM Left Side Pre AGC




Lower 700 Band DL-GSM Left Side AGC+10dB




Lower 700 Band DL-GSM Right Side Pre AGC



Lower 700 Band DL-GSM Right Side AGC+10dB



Upper 700 Band DL-GSM Left Side Pre AGC



Upper 700 Band DL-GSM Left Side AGC+10dB




Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Upper 700 Band DL-GSM Right Side Pre AGC




Upper 700 Band DL-GSM Right Side AGC+10dB



Cellular Band DL-GSM Left Side Pre AGC



Cellular Band DL-GSM Left Side AGC+10dB



Cellular Band DL-GSM Right Side Pre AGC



Cellular Band DL-GSM Right Side AGC+10dB




Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity




PCS Band DL-GSM Left Side Pre AGC




PCS Band DL-GSM Left Side AGC+10dB




PCS Band DL-GSM Right Side Pre AGC



PCS Band DL-GSM Right Side AGC+10dB



AWS Band DL-GSM Left Side Pre AGC



AWS Band DL-GSM Left Side AGC+10dB




Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



AWS Band DL-GSM Right Side Pre AGC



AWS Band DL-GSM Right Side AGC+10dB



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity