

Slide Bluetooth Keyboard

Model: KB-6135

FCC ID: ZW7KB-6135

User Manual

IPhone4 Wireless Bluetooth Keyboard User Guide

Packing Contents:

1. Plastics shell W/Keyboard
2. USB Power Charging Cable
3. User Guide

1.0 Product Features:

1. Built-in Wireless Bluetooth 2.0 Silicone keyboard.
2. Stylish protective Plastics shell designed for iphone4.
3. Rechargeable lithium battery lasts for approximately 30 Hours per charge.
4. Special ipad home screen key for one-touch access to variety of applications.
5. Energy saving keyboard sleep mode

2.0 Keyboard Specifications

1. Bluetooth V2.0 interface Standard
2. Operating Distance : 10meters
3. Modulation System: GFSK 2.4G
4. Transmitting Power : Class 2
5. Operating Voltage:3.0-5.0
6. Working Current : <5.0MA
7. Standby Current :2.5MA
8. Sleeping Current: <200 μ A

9. Charging Current :>100MA
10. Standby time : 45 days
11. uninterrupted working time: 30hours
12. Lithium Battery Life :3 years
13. Lithium Battery Specifications : 03*16*45
14. Charging time :2-2.5hours
15. Lithium Battery Capacity :200MA
16. Key Dynamics : $80 \pm 10g$
17. Key Life : 1 million strokes
18. Operating Temperature : $-10^{\circ}\text{C} - +55^{\circ}\text{C}$
19. Humidity :20%-50%

3.0 Bleutooth Keyboard Pairing Operations

Step1: Turn on the power switch .the Power and Bluetooth indicator light will be on for 5 seconds ,then the lights will go off

Step2: Press on the “Connect” button ,The Bluetooth indicator light will be blinking ,and the power indicator will be on.The Keyboard is now ready to be connected to iphone4

Step3: Turn on and unlock iphone4 .click on the iphone4 “setting”icon.

Step4: On the setting menu ,item “General” to access “bluetooth”to turn on the connection . iphone4 will automatically search for a Bluetooth_enabled device.

Step5: Wireless keyboard found .click on the device to connect .

Step6: Enter the Password code displayed on screen. And press “Enter”key.

Step7: Wireless Keyboard connected successfully .”power”indicator light will stay on until the keyboard is switched off.

special application:

The wireless keyboard can be connected to iphone,4 ipad, and ipod Touch that had installed iOS 4.0 or later. For other Bluetooth enabled device ,please verify the Bluetooth standard&compatibility before attempting to connect to the keyboard.

4.0 Charging

When the battery power is low ,the “power” indicator light will start blinking .it is time to recharge the keyboard.

Step1: Connect the USB power cable to the keyboard charging interface

Step2: Connect the charging cable A port into USB power or USB Power Adapter.

The “charge”red indicator light will stay on ,when the keyboard is charging. Once it finished charging, the “charge”indicator light will turn off.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device is charged by USB port, but it can't communicate informations with PC through USB port.

FCC ID: ZW7KB-6135

IMPORTANT REGULATORY INFORMATION

This device complies with Part 15 of the FCC Rules: Operation is subject to the

following two conditions:

1. This device may not cause harmful interference and
2. This device must accept any interference that is received, including any interference that may cause undesired operation.

WARNING:

Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.