



TEST REPORT

Subject: Processing Gain For the ORINOCO IEEE802.11b products

Ref.: FCC Rules 47 CFR Part 15, Section 5.247d

Report Prepared by:

Maarten Visser
Name



Signature

July 28, 2000
Date

Concurrence:

1. Director of Engineering

Bruce Tuch
Name


Signature

August 10, 2000
Date


Name

Signature

Date

2. Team Captain

Frans Hoekstra
Name


Signature

August 10, 2000
Date

Name

Signature

Date



TEST REPORT

Subject: Processing Gain For the ORiNOCO IEEE802.11b products

Ref.: FCC Rules 47 CFR Part 15, Section 5.247d

Report Prepared by:

Maarten Vissee
Name

Signature

July 28, 2000
Date

Concurrence:

1. Director of Engineering

Bruce Tuch

Name

Signature

August 10, 2000

Date

2. Team Captain

Frans Hoekstra

Name

Signature

August 10, 2000

Date

1. Summary:

This document describes the Receiver Processing Gain verification measurements performed at the WaveLAN-II PC-Card Type 2, according to Ref.[2].

2. Conclusion:

The Lucent WaveLAN-II PC-Card Type 2 product confirms to the minimum required 10 dB processing gain, as set forth by the FCC for operation in the 2.4 GHz ISM band.

3. References:

- 1- Document FCC 97-114, Appendix C, Guidance on Measurements for Direct Sequence Spread Spectrum Systems.
- 2- Hardware Functional Specification for WaveLAN-II Embedded, High Speed, Doc. No. 011735, Rev. A, Source Organization Lucent Technologies WCND Utrecht.
- 3- Viterbi, A. J., Principles of Coherent Communications, New York, McGraw-Hill 1966.
- 4- Proakis, J.G., Digital Communications, New York, McGraw-Hill 1989, page 270.

4. Measurement description:

4.1 Test introduction - FCC requirements:

Part of FCC certification for the Lucent WaveLAN IEEE 802.11 High Speed compliant Network Interface Card (NIC) is a processing gain test. This test proves that the receiver of the tested product employs a true spread spectrum device receiver structure, taking full advantage of the direct sequence spread spectrum modulation technique.

This test verifies the receiver processing gain to be 10 dB or more for a data rate of 1, 2, 5.5 and 11 Mbit/s, by monitoring the Bit Error Rate (BER) of the product under test for each data rate, while operating under strict defined received signal conditions.

Several methods of showing compliance to the rules are possible, from a stepped CW jammer to a continuous sweeping CW interferer. For this test the discrete stepped CW jammer method was chosen, as described in Ref.[1].

Therefore a receiver input signal is applied to the product under test, in the presence of a Continuous Wave (CW) interference source, also referred to as CW jammer.

The test takes place at the product Functional Specification (Ref.[2]) specified conditions for BER rate measurements, specifying a BER equal or better than 10^{-8} at a receiver input level of -55 dBm. For practical reasons these test are performed at -55 dBm or -53 dBm. This small deviation from the Functional Specification should not cause any deviation from the specified Bit Error Rate, since the received levels are well above the thermal noise.

The test criteria for meeting the minimal processing gain is such that it takes the theoretical calculated SNR for the applied modulation technique and specified BER as a reference. From this given SNR the processing gain is subtracted, yielding the CW Jammer to Signal ratio J/S. From Ref. [4], likewise as Ref.[3] consulted in Ref. [1], it is determined that for a BER of 10^{-8} the SNR (S/N) equals:

13 dB @ 1 Mbit/s,
15 dB @ 2 Mbit/s,
15 dB @ 5.5 Mbit/s,
18 dB @ 11 Mbit/s.

Thus the J/S ratio for a processing gain of 10 dB that must be met is calculated as:

-13 + 10 = -3 dB @ 1 Mbit/s (DBPSK),
-15 + 10 = -5 dB @ 2 Mbit/s (DQPSK),
-15 + 10 = -5 dB @ 5.5 Mbit/s (CCK),
-18 + 10 = -8 dB @ 11 Mbit/s (CCK).

Two types of measurement corrections are allowed for as described in Ref.[1]. The first taking into account 2 dB implementation losses, thus increasing the absolute J/S ratio by 2 dB.

The second correction allows for deleting the 20% worst-case frequencies in the processing gain test that causes the test at that CW interference to fail. This implies that for the considered 14 MHz wide measurement interval the worst case 57 CW jammer frequencies can be ignored, being those that result in received data errors/missing frames (20% of 14 MHz * (1 MHz/50 KHz) + 1 = (20% * 281) + 1 = 57).

4.2 Test sequence:

The measurements are performed at a 50 KHz CW jammer raster. For each CW jammer frequency 10^8 bits are transmitted by the reference transmitter, and received by the product under test. For practical reasons 50.000 messages are transmitted. After blanking out frame overhead 1927 bits per frame are monitored. This results in $50.000 * 1927 = 9650000$ transmitted bits for a BER test, which is a mere 1.4% less than the targeted 10^8 bits. Though it would be more elegant to show BER compliance for at least say ten times 10^8 transmitted/received bits, the time involved with this grows significantly. Since the CW interferer is stepped in a 50 KHz raster, covering the receiver bandwidth of 14 MHz, it is considered that the BER requirement is sufficiently met since such a multitude of measurements are taken.

The total measurement is being performed under computer control, hereafter referred to as controller. It involves the control over the reference transmitter, CW-interference generator, receiver under test and received data error-checker/frame counter. The controller is programmed by a configuration file, that lists the CW jammer frequencies and CW jammer signal levels. The controller program flow chart is given in Annex A, WaveLAN-II FCC Processing Gain Measurements, Controller Flow Chart.

The transmitted data pattern is fixed, and known at the receiver. Therefore the error checker compares the known transmitted data sequence with received data sequence. Received data errors and missing received frames information is retrieved by the controller.

In the receiver at the inter-connection between the received data demodulator output at the DSP and the digital interface the demodulated received RF signal is made available to an error checker. This error checker is a dedicated piece of hardware that monitors real-time the received data, gating-out any other non-relevant information that is present in the received data (message header, message length field, CRC field, diagnostic information field etc.). For a chosen Tx message length of 230 bytes this yields 1927 useable bits.

The test sequence is as follows: the controller issues a request to the transmitter for 1000 frames to be transmitted. Once this number of frames has been transmitted the transmitter signals to the controller the completion of this. The controller reads the number of received frames and number of erroneous received frames. If there are no missing frames or received data errors detected, the controller increases the CW interference level by 1 dB. Consequently it re-issues a

FCC Processing Gain Measurements Results,
for the OriNOCO IEEE802.11b products, Report No. 015127, Rev. A.

Lucent WCND Confidential ©2000

1000 frames transmit request, and the test is re-started. This sequence is repeated until received data errors or missing frames are detected.

Now instead of a quick error scan using 1000 frames, 50000 frames (equals 10^8 bits) are transmitted to verify the BER. For this test the CW jammer level is lowered 1 dB, compared to the CW jammer level at which the first receive data errors and/or missing frames were detected. All the measurement results are recorded for later use.

After completion of the 50000 frames BER test, the spreading gain verification test continues by raising the CW jammer frequency by 50 KHz and re-setting the CW jammer level to the start value, taken from the controller configuration file. For this new CW frequency the measurements are repeated as described above (see Annex A).

All CW frequencies and power levels are listed in a command-file that is read by the controller at start up.

Before measurements are started, the receiver input level and CW jammer level need to be calibrated. See figure 1 for the test set-up.

The test takes place at an arbitrarily chosen channel, being channel two (2417 MHz).

4.3 Receiver level calibration:

The receiver input level is calibrated using the RF power meter. For this purpose, the reference transmitter output attenuator is set to 0 dB. The CW jammer is disabled during the calibration. Using the RF power meter at the receiver input of the device under test, the received level at the receiver input is measured for a continuous active reference transmitter. The attenuator value is calculated to achieve a received level of -55 dBm. Finally the attenuator is adjusted to this value.

4.4 CW level calibration:

The reference transmitter is disabled during this calibration. The CW jammer generator output level is set to 0 dBm, and the RF power meter value is read. The difference in CW output level setting and RF power meter measured at receiver input of the device under test is the attenuation of the test set-up. This is the correction factor that needs to be applied for analysis of the measurements results.

5. Equipment used:

# Item needed	Description
1	Portable PC with WaveLAN-II NIC, Zenith Z-lite, SN-3GSAZW000061, for receiver.
1	Portable PC with WaveLAN-II NIC, NCR 3150, SN 17-26106224, for transmitter.
1	Software 'Testware, V5.09', Rev. 0, <TW.EXE>, 141456 bytes, 12-13-1998. Used for the transmitter and receiver.
2	WaveLAN IEEE Turbo NIC.
1	PC + IEEE interface card, NCR PC6, SN 17-17039925 and CEC PC<>488 interface card.
1	Received error checker, wire-wrap prototype, Lucent WCND designed and built.
1	Power supply, Delta D030-1, for error checker.
1	Spectrum Analyzer, HP 9592B SN 3009U00102.
1	Power Meter, Rohde & Schwarz, Millivolt meter URV5, SN 893430/070.
1	Power Sensor, Rhode & Schwarz, type NRV-Z2 828218.02, SN 860925/005.
1	CW jammer generator, Gigatronics 7200, SN 746604.
1	Variable attenuator, 0-70 dB, Midwest Microwave, Model 1044.
2	Fixed attenuator, 10 dB, Inmet Corp., model 18AH-10.
1	RF power splitter, ARRA 3-9200-2, SN 2001.
1	Misc. IEEE cabling.
1	Misc. SMA cabling.
1	RF shielded cage.

6. Measurement set_up:

The test setup is given below in Figure 1, measurement test set-up. To avoid interference that can disrupt the measurement, the whole test is performed within a RF shielded cage.




Figure 1, measurement test set-up.

7. Measurement results:

7.1 Calibrations:

Receiver calibration 1, 2, 5.5 and 11 Mbit/s: For 0 dB total attenuator setting the received level at the receiver input equals +10 dBm.

Test setting: the fixed attenuator is chosen to be 20 dB, the variable attenuator is set to 45, respectively 43 dB attenuation.

CW jammer generator calibration: For a 0 dBm output level at the generator the received level at the receiver input is -6 dBm.

7.2 Processing Gain Measurement Results:

For each CW jammer frequency between $F_c \pm 7$ MHz, being the receiver bandwidth, a BER measurement is taken.

For each CW measurement frequency the jammer level is varied from -66 dBm to -58 dBm at the receiver input, yielding a J/S ratio of -11 to -3 dB, respectively -13 to -5 dB.

For some CW frequencies received data errors/missing frames are detected while performing the BER test.

Applying the allowed margin of 2 dB implementation losses for 1 Mbit/s, a 1 dB implementation loss for 5.5 and 11 Mbit/s, and no implementation loss for 2 Mbit/s, together with the rule of discarding the 20% worst-case jamming/signal points (Ref.[1]), results in meeting the specified BER for which less than 20% of the measured CW interference frequencies were found to cause received data errors and/or missing frames.


These percentage numbers are respectively 16% @ 1 Mbit/s, 3% @ 2 Mbit/s, 17% @ 5.5 Mbit/s and 18% @ 11 Mbit/s.

Therefore, a J/S ratio better or equal to -5 dB @ 1 Mbit/s, -5 dB @ 2 Mbit/s, -7 dB @ 5.5 Mbit/s and -9 dB @ 11 Mbit/s is measured.

7.3 Measurement Conclusion:

The tested product complies to the required Processing Gain of 10 dB for a data rate of 1, 2, 5.5 and 11 Mbit/s, as set forth in Ref.[1].

Annex A: Flow-Chart IEEE control program



Annex B : Process gain data at 11Mbps and 2Mbps

- Tests were performed at Spreading gain 10.4 dB. Engineering took extra margin.
- At 11Mbps S/N may be 18 dB, 2Mbps S/N may be 15 dB.
- SIR (Signal Interference Ratio) = S/N + Spreading gain + Lsys. (= -Mj)
We take only 1 dB Lsys for 11Mb/s or 0 dB Lsys for 2Mb/s into account so that :
11Mbps SIR = 18 dB - 10.4 dB + 1 = 8.6 (round of f upwards to 9) dB = (-)Mj
With this 9 dB SIR (= -9 dB Mj) we test unit and check for less than 20% errors
(Acutually 18.57%),

2Mbps SIR = 15 dB - 10.4 dB + 0 = 4.6 (round of f upwards to 5) dB = (-)Mj
With this 5 dB SIR (= -5 dB Mj) we test unit and check for less than 20% errors,
(Acutually 3.21%).

Thus in principle exact calculations in this case are :

Processing gain for **11Mbps** = S/N + Mj + Lsys = 18 + (-)8.6 + 1 = **10.4** dB

Processing gain for **2Mbps** = S/N + Mj + Lsys = 15 + (-)4.6 + 0 = **10.4** dB

[illegible]

Measurement file output name is: 1.1mbit.crd

Input command file name is: INPUT.CMD

Input CW correction level: 6 dB

Lowcount is: 1000 messages

Highcount is: 50000 messages

Rx level DUT is: -53 dBm

Note: 11 Mbit, 9 dB SIR tested for (18 dB SNR - 10.4 + 1 impl. losses).

Takes into account 1 dB of implementation loss (allowed 2 dB).

Only RxD errors are taken into account since these need better SIR then preamble at 1 MBit

Attention: Input the red cells for correct spreadsheet calculations!

total errors 52

percentage 18.57%

OK? <=20%, OK

Number of received data errors as a function of frequency and interference level																		
Not measured combinations listed as "-1"																		
J/S ratio (dB)	Uncorrected Interference level dialled at CW generator					H	I	J	K	L	M	N	O	P	Q	R	S	
	-60	-59	-58	-57														
	True CW Interference level at receiver input (dBm)																	
	-66	-65	-64	-63														
	-13	#PDA	-12	#PDA	-11	#PDA	-10	#PDA	-9	#PDA	-8	#PDA	-7	#PDA	-6	#PDA	-5	#PDA
Frequency (Hz)																		
2409000000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49987
2409050000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49993
2409100000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49984
2409150000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49988
2409200000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49988
2409250000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49990
2409300000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49991
2409350000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	999	0	49983
2409400000	0	1000	0	1000	0	1000	0	1000	0	1000	0	999	0	1000	0	1000	0	49985
2409450000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49987
2409500000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49986
2409550000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49989
2409600000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49988
2409650000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	999	0	49991
2409700000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49993
2409750000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49986
2409800000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49981
2409850000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49984
2409900000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49989
2409950000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49990
2410000000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49983
2410050000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	999	0	49984
2410100000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	999	0	49988
2410150000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	999	0	49989
2410200000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49992
2410250000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49984
2410300000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49990
2410350000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49992
2410400000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49986
2410450000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49989
2410500000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49992
2410550000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49990
2410600000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49985
2410650000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49987
2410700000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49984
2410750000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49992
2410800000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49993
2410850000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49986
2410900000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49989
2410950000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49988
2411000000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49991
2411050000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49983
2411100000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49984
2411150000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49988
2411200000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49988
2411250000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49990
2411300000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49991
2411350000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49983
2411400000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49984
2411450000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49988
2411500000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49988
2411550000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49990
2411600000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49991
2411650000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49983
2411700000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49984
2411750000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49988
2411800000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49988
2411850000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49990
2411900000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49991
2411950000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49983
2412000000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49984
2412050000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49988
2412100000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49988
2412150000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49990
2412200000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49991
2412250000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49983
2412300000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49984
2412350000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49988
2412400000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49988
2412450000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49990
2412500000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49991
2412550000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49983
2412600000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49984
2412650000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49988
2412700000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49988
2412750000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0	49990
2412800000	0	1000	0	1000	0	1000	0	1000	0	1000	0	1000	0					

Rx Errors detected full test range				PDA missing full test range				RxD Errors detected up to CW =< -62 dBm (J/S = -9dB)				PDA missing up to CW =< -62 dBm (J/S = -9 dB)				Both error RxD and PDA =<-62 dBm			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			
OK, 0 RxD errors				OK, No PDA errors				0				0				0			

[illegible]