

CIRCUIT DESCRIPTION

A general description of the overall circuit is not covered in an instruction manual. This section provides the description of circuits required by subpart 2.983 of the Commissions' Rules. Circuits not described in the manual are covered in this exhibit.

The following are included:

- | | |
|--|----|
| 1. Means for Frequency Stabilization | 8A |
| 2. Means for Modulation Limiting
and Low Pass Filter* | 8B |
| 3. Means for Harmonic Suppression | 8C |
| 4. Means for Limiting Power* | 8D |

* From currently Type Accepted Transmitter FCC ID: ABZ99FT4070.

EXHIBIT 8

CARRIER FREQUENCY GENERATION AND STABILIZATION**CIRCUIT DESCRIPTION:**

The carrier frequency is generated using a fractional-N frequency synthesizer inside the ULTZif(U801). This consist of a phase-locked loop circuit with a voltage controlled oscillator (VCO) whose output is fed back to a programmable divider chain. The divide ratios are determined from information stored in the microcomputer and bussed to the synthesizer via a microcomputer. The microcomputer extracts the data for the division ratios as determined by the system select switch or by loading data stored in the memory ICs. Using a time averaged algorithm a combination of divide ratios are used so that the reference frequency can be a much higher value than the value of the frequency resolution. Modulation occurs by a combination of directly coupling the modulation signal to the low pass filter in the loop and by processing the digitized analog modulation signal to alter the divider values. A temperature compensated crystal oscillator at 16.8 MHz and stable to 2.5 parts per million over temperature extremes is used for the frequency reference. The 16.8 MHz reference is further divided into one of three reference frequencies which is compared to the divided down VCO output in a phase detector which in turn provides a DC steering voltage back to the VCO.

EXHIBIT 8A

MODULATION LIMITING AND LOW PASS FILTER**CIRCUIT DESCRIPTION**

The pre-emphasis modulation limiting and low pass filtering of this transmitter are in integrated circuit form on the Audio/Signaling Filter section of the ULTZif(U801). Audio from the microphone initially enters the ULTZif(U801) where it is amplified, filtered and pre-emphasized. The limited, filtered audio is then fed through digitally programmable attenuators to the modulation port on the synthesizer module.

EXHIBIT 8B

HARMONIC SUPPRESSION CIRCUIT

CIRCUIT DESCRIPTION:

Attenuation for harmonics is provided by the Harmonic Filter after the Antenna Switch. The Harmonic Filter is a fifth order Low Pass Chebyshev with 0.1 dB of ripple composed of C104, L102, C105, L103, and C106.

For Circuit Diagram refer to the Schematic in Exhibit 6. (100- Harmonic Filter)

MEANS FOR LIMITING POWER**CIRCUIT DESCRIPTION**

The transmit power Amplifier is an RF IC Chip amplifier with a specified maximum output of 0.5 Watts. An antenna switch(SW-391) controls the RF signal flow. In transmit mode, the RF signal flow is directed to the Harmonic filter. The output of the harmonic filter is connected to a helical antenna. The antenna is permanently attached to the radio and cannot be removed.

For Circuit Diagram refer to the Schematic in Exhibit 6. (500- Tx PA)

EXHIBIT 8D