

Rhein Tech Laboratories, Inc.  
360 Herndon Parkway  
Suite 1400  
Herndon, VA 20170  
<http://www.rheintech.com>

Client: M/A-Com, Inc.  
Model: MultiLink Station  
Standards: FCC Part 90/IC RSS-111  
ID's: BV8MLINK/3670A-MLINK  
Report Number: 2008219

## **Appendix A: RF Exposure Compliance**

Please refer to the following page.

## MPE Calculation

The Limit for **Uncontrolled Exposure Power Density ( $P_d$ )** is 10 W/m<sup>2</sup> for fixed mounted device.

The M/A-COM 4.9 GHz VIDA MultiLink is a fixed mounted radio. After installation and commissioning, the safe distance from the 9 dBi omni-directional antenna is greater than 20 cm (8-inches).

### MPE calculation for omni-directional antenna

This MPE Minimum Distance Calculation is based on using a 9 dBi gain omni-directional antenna mounted directly to the MultiLink RF port.

Basic M/A-COM 4.9 GHz Client specifications:

**P:** Maximum Peak Conducted Power = 27 dBm

**G:** Maximum Omni Antenna Gain = 9 dBi

Frequency Range = 4.94 to 4.99 GHz

**R:** Minimum Distance between User and Antenna = 0.2 m

### Equation from FCC:

$$P_d = P * G / (4 * \pi * R^2)$$

$$P_d = 0.5 \text{ W} * 7.94 / (4 * 3.1415926 * 0.2^2) = 7.9 \text{ W} / \text{m}^2 < 10 \text{ W} / \text{m}^2$$

The calculation indicates that the minimum 0.2 meter distance between user and the omni-directional antenna (directly mounted to the MultiLink RF port) is required when operating the M/A-COM 4.9 GHz VIDA MultiLink.

### MPE Calculation for Directional Antenna

This MPE Minimum Distance Calculation is based on using a directional antenna with more than 9 dBi antenna gain.

Basic M/A-COM 4.9 GHz VIDA MultiLink specifications:

**P:** Maximum Peak Conducted Power = 27 dBm;

**G:** Maximum Antenna Gain – Cable Loss = 27 dBi – 1 dB = 26 dBi; (Use numerical  $G_N$  value for the calculation):  $G_N = 10^{(G/10)}$ ; For  $G = 26$  dBi,  $G_N = 10^{(26/10)} = 398$

Frequency Range = 4.94 to 4.99 GHz;

**R<sub>min</sub>:** Minimum Distance between user and antenna to comply with FCC MPE Level (10 W / m<sup>2</sup>);

### Equation from FCC:

$$P_d = P * G / (4 * \pi * R_{min}^2)$$

$$R_{min} = \text{SQRT}(0.5 \text{ W} * G_N / (4 * 3.1415926 * 10 \text{ W/m}^2))$$

$$R_{min} = 1.26 \text{ m, for } G = 26 \text{ (i.e., } G_N = 398)$$