AlarmPath ECHO AP-4700 WIRELESS SUBSCRIBER UNIT INSTALLATION INSTRUCTIONS

IMPORTANT! Failure to Read and Follow These Installation Instructions May Jeopardize Subscriber Security

INTRODUCTION: The AP-4700 is a 2-way, fully supervised Wireless Subscriber Unit for use on the nationwide (50 United States plus Puerto Rico and the US Virgin Islands) AlarmPath Network. The AlarmPath Control Center Processors forward these wireless signals to ANY Central Station via standard communicator techniques. The AlarmPath Control Center Processors will generate and report a Communications Failure signal in the event that the network does not receive the expected supervisory test signal from the Wireless Subscriber Unit during the scheduled period.

WARNING: To ensure user's safety and to satisfy FCC RF exposure requirements, this unit must be installed so that a minimum separation distance of 40 cm or 60 cm is always maintained between the antenna of the transmitting device and nearby persons. Operation closer than this distance is not recommended. Use ONLY the following antenna supplied by AlarmPath to comply with this warning. Colinear Antenna, PN: HG3DB – 60 cm or 1/4 Wave Rigid Whip Antenna, PN: G0DB – 40 cm.

NOTE: This equipment has been tested and found to comply with the limits for a Class B Unintentional Radiator, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction Manual, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. It this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one of more of the following measures: 1. Reorient or relocate the receiving antenna, 2. Increase the separation between the equipment and receiver, 3. Connect the equipment into an outlet on a circuit different from that to which the receiver is connected, 4. Consult the dealer or an experienced radio/TV technician for help.

GENERAL INSTALLATION GUIDELINES

- Since the mounting location can **ONLY** be selected based on RF performance, it is **HIGHLY** recommended that the installer follow the STEP 1 below **BEFORE** any wires are run.
- Generally, high locations are best. DO NOT mount radio in basement or below grade as unpredictable performance may result.
- Whenever possible, DO NOT mount the AP-1 in non-climate controlled environments (i.e. attics may become extremely hot in summer, garages may become extremely cold in winter).
- Avoid mounting locations within 3 feet of large metal objects (air conditioners, metal garage doors, etc.), AC power lines, and fluorescent light fixtures.
- A fair amount of care may be required to mount the AP-1 so as to achieve an optimal RF path. The installer should spend additional time as needed to obtain the highest signal level possible.
- The AP-1 draws a substantial amount of current approximately 2 AMPS during transmit. Therefore, follow the instructions for powering the AP-1 carefully!

STEP 1

SELECT A MOUNTING LOCATION


- Temporarily connect power to the AP-4700 from a fully charged 12V (4AH minimum) battery. DO NOT mount the AP-4700 at this time. Position the unit in the desired mounting location.
- Press the button (S1), under the coverage LED, the unit will transmit one long blink. After the unit transmits observe Coverage LED and count the number of blinks. Move the unit as required to achieve the best Coverage (signal strength) possible based on the chart below. As needed, reposition the unit, transmit and watch the Coverage LED to indicate change. The unit will not transmit if 15 seconds has not passed. There is a 2 second delay between blink cycles.
- Once a location has been selected based on Coverage, permanently and securely mount the unit using #6 screws (not supplied)
 in at least 2 of the 4 mounting holes.

# BLINKS	COVERAGE
0 BLINKS	NO NETWORK-DO NOT INSTALL, Try Re-positioning Unit
1 BLINK	VERY WEAK COVERAGE-DO NOT INSTALL, Try Re-positioning Unit
2 BLINKS	MARGINAL COVERAGE – Try Re-positioning Unit or High-Gain Antenna – INSTALL with CAUTION
3 BLINKS	GOOD COVERAGE SIGNAL-OK TO INSTALL
4 BLINKS	VERY GOOD COVERAGE SIGNAL-OK TO INSTALL
5 BLINKS	EXCELLENT COVERAGE-OK TO INSTALL

STEP2

APPLY POWER

- The AP-4700 requires 12VDC. It draws less than 20mA during standby, and almost 2 AMPS during Transmit (for less than 1 second). It is recommended that the AP-4700 be powered directly from the battery (4AH Minimum) of the alarm control panel, with a 3 AMP fuse in series. As the standby current is very low, the alarm control panel charging circuit will not be affected, and the battery is capable of supplying the 2 AMP current on transmit.
- 22-gauge wire can be used up to 50 feet in length, and 18-gauge wire can be used up to 100 feet in length.
- Connect power to
 + & screw
 terminals. DO NOT
 short wires to metal case.



STEP3

CONNECT INPUTS – CHANNEL TRIGGERING


NOTE: Use any *ONE* method to trigger INPUT #1. Use method "P" or "N" for INPUT 2 and/or 3. All channels triggered by "P" or "N" method have a 1 SEC integration delay. "SC" (SmartChannel) will analyze Bell or Siren Driver output to determine if trigger is BURG or FIRE, and has a 4 SEC integration delay. After triggering channels, use Signal Verification online at www.alarmpath.com or call AlarmPath and access Automated Operator System (Touch-Tone option 5)

SC-BP

SmartChannel (INPUT Terminal 1) "BELL POSITIVE" TRIGGER

e.g. ADEMCO, NAPCO and others with switched "BELL POSITIVE" terminals

- CUT resistor R100 to convert INPUT #1 to SmartChannel
- Make sure resistor R1 has NOT been cut.
- Run wire from AP-4700 INPUT #1 screw terminal to Alarm Control Panel BELL + terminal
- Steady Voltage (+4.5 to +14.5VDC) on INPUT #1 sends code 1D (BURG), pulsating Voltage (~800mS – 8 SEC/cycle) sends code 1C (FIRE)



SC-BN

SmartChannel (INPUT Terminal 1) "BELL NEGATIVE" TRIGGER

e.g. DSC and others with switched "BELL NEGATIVE" terminals

- CUT resistor R100 to convert INPUT #1 to SmartChannel
- CUT resistor R1 to convert INPUT #1 to Low/Negative/Pull-toground trigger
- Run wire from AP-4700 INPUT #1 screw terminal to Alarm Control Panel BELL – terminal
- Constant Ground on INPUT #1 sends code 1D (BURG), pulsating Ground (~800mS – 8 SEC/cycle) sends code 1C (FIRE)



P

"POSITIVE" TRIGGER (INPUT #1, 2 or 3)

e.g. Any "POSITIVE" voltage (+4.5 to 14.5VDC) trigger

- To use this method for INPUT #1, make sure resistor R100 has NOT been cut
- Make sure resistor R1, R2, R3 (INPUT #1, 2, 3 respectively) has
 NOT been cut, as applicable
- Run wire from AP-4700 INPUT #1, 2, 3 screw terminal (as applicable) to Positive trigger (Positive Voltage on alarm)
- INPUT # 1, 2, 3 send codes 1, 2, 3, respectively

N

"NEGATIVE" TRIGGER (INPUT #1, 2 or 3)

e.g. Any "NEGATIVE" or "Pull-to-Ground" trigger

- To use this method for INPUT #1, make sure resistor R100 has NOT been cut
- **CUT** resistor R1, R2, R3 (INPUT #1, 2, 3 respectively), as applicable
- Run wire from AP-4700 INPUT #1, 2, 3 screw terminal (as applicable) to Negative/Pull-to-Ground trigger (Goes Negative / "Pulls-to-Ground" on alarm)
- INPUT # 1, 2, 3 send codes 1, 2, 3, respectively

SC-S

SmartChannel (INPUT 1)
"SIREN DRIVER" TRIGGER

e.g. CADDX and other Alarm Control Panels with builtin siren drivers

USE THIS METHOD <u>ONLY</u> IF METHOD SC-BP OR SC-BN <u>CANNOT</u> BE USED

- CUT resistor R100 to convert INPUT #1 to SmartChannel
- Run wire from AP-4700 INPUT #1 screw terminal to Alarm Control Panel Built-In Siren Driver terminal. See NOTE below
- Warble Siren Audio Tone (~500hz to 2khz) on INPUT #1 sends code 2D (BURG), Steady Siren Audio Tone (~1khz) sends code 2C (FIRE)

NOTE:

Observe LED
D2 to
determine
correct polarity.
D2 will light
(steady or
blinking) when
connected to
the correct
SIREN terminal



HSO

HIGH-SECURITY OPTION

The AlarmPath HSO-KIT includes detailed instructions for wiring the HSO terminal, which provides an output if the AP-4700 loses coverage.