

FCC ID: NTAFP100RA1W

FP100RA 1W reader circuitry description

1. The power amplifier is an RF Micro Devices' IC type RF2192. It has 4.8 V supply voltage and draws 340 mA @ +30.5 dBm maximum power at power amplifier output.
 2. a. The TX data modulates an ASK modulator at 70 MHz. The modulator output frequency is filtered by a SAW filter (FL6) with a 3 dB bandwidth of 2.5 MHz and up-converted to 912-918 MHz by a PLL synthesizer of 842-848 MHz. Both oscillators are locked to a 16 MHz TCXO with a frequency stability of ± 5 PPM.
The TX frequency is filtered by a SAW filter (FL5) with a 3 dB bandwidth of 10 MHz.
The modulation is ASK with an on-to-off ratio of at least 20 dB. The voltage applied to Q13 together with an RC network at the base of Q13 are used as a spectrum shaper.
 - b. The receiver frequency is down-converted to a 10 MHz IF by mixing it with a 925 MHz oscillator based on a SAW resonator with a frequency stability of ± 200 kHz.
3. The device is categorized as fixed.

Sincerely yours,



Roman Sternberg
VP Marketing