



FM Wireless Stereo Transmitter


Scope

This product is used for sending your personal music sources (CD, MP3...) through FM radio waves to your home audio with built-in FM receiving tuner.

Circuitry Description

1. Battery Supply.

There are two ways of supply, Battery 3V (1.5V x 2) or DC 6V 25mA adaptor. The battery voltage will be step up to DC 5V via IC2. There are no harmful of battery even the DC adaptor connected at the same time.



2. Signal Input, Pre-emphasis, Frequency Adjust, Deviation Adjust


- a. Signal sources were passing through stereo audio plug to audio filter circuitry (C1/C4, R26/R28, C32/C31, R27/R29), then to IC inputs.
 - b. A Pre-emphasis of 75us was introduced (C14/C21) as well as LPF (C15/C22) was used to remove unwanted several kHz beat sounds.
 - c. Switch S2 was used to select transmitted frequency.
 - d. Deviation level was affected by setting the resistance of (R30/R31).



In-Tech

Electronics

精達科技研發(深圳)有限公司



3. PLL and RF

- a. PLL was formed by VCO (L1/C28/VD1) and LPF (Q1/R9/C13/C29/R15).


Composite signal from pin 5 with pre-adjusted modulation rate was injected to FM modulator.



In-Tech


Electronics

精達科技研發(深圳)有限公司



b. RF

Modulated FM was transmitted from pin 11 through attenuator network (R5/R7/R8) and antenna coil.



End

九龍市塘海橋道143號
航太科技中心6字603室
電話: 2755 5022-4
傳真: 2796 8049

合華實業有限公司
HOPWAH INDUSTRIAL LTD
TEL: 2755 5022-4


Unit 603, 6/F., China Aerospace Centre,
143 Hoi Bun Road, Kowloon, Kowloon
TEL: 2755 5022-4
Fax: 2796 8049

To: In - Tech (精進) Date: 28 - 12 - 2004
Attn: 林小姐 (採購部) Spec No.: HP040076


SPECIFICATION

Air antenna (ANT 1)

4033 (FM transmitter 20041209)



Notes:
 1) Please reel 18 turns with average pitch on Ø 9 mm * L: 45 mm paper roll.
 2) Please use adhesive fix it between coil and paper roll for preventing loose.
 3) Should be soldered at the tip.
 4) Material: 2UEW Ø 0.7 mm AWG 22.
 5) All dimension are in: mm



Winding Specification

Turns	18T
Wire	Enamelled Copper Wire 0.70mm (#22) (2UEW) (Gold)
Paper Diameter	Inner: Ø 9.0mm x 44.5mm
Length	1 x 11mm +0/-0.5mm (2.5mm ± 2mm Solder)

SAMPLE NO	APPROVED BY	REMARKS
12020/04		紙筒兩邊只可以留2mm ± 1mm 錫頭濶角90°c
CUSTOMER APPROVED		

Wireless Audio Link IC

BH1417F

The BH1417F is a FM stereo transmitter IC that transmits simple configuration. The IC consists of a stereo modulator for generating stereo composite signals and a FM transmitter for broadcasting a FM signal on the air. The stereo modulator generates a composite signal which consists of the MAIN, SUB, and pilot signal from a 38kHz oscillator.

The FM transmitter radiates FM wave on the air by modulating the carrier signal with a composite signal. Frequency is set for North America.

●Applications

Wireless speakers, Personal computer(sound board), Game machine, CD changer, Car TV, Car navigation

●Features

- 1) It is possible to improve the timbre because it has the pre-emphasis circuit, limiter circuit, and the low-pass filter circuit.
- 2) Built-in pilot-tone system FM stereo modulator circuit.
- 3) The transmission frequency is stable because it has a PLL system FM transmitter circuit.
- 4) PLL controls data input in parallel (4bits, 14ch for North America).

●Absolute maximum ratings (Ta = 25°C, In measurement circuit.)


Parameter	Symbol	Limits	Unit	Conditions
Supply voltage	Vcc	+7.0	V	Pin8,12
Date input voltage	V _{IN-D}	-0.3 to Vcc+0.3	V	Pin15,16,17,18
Phase comparator output voltage	V _{OUT-P}	-0.3 to Vcc+0.3	V	Pin7
Power dissipation	Pd	450 [*]	mW	
Storage temperature	T _{STG}	-55 to +125	°C	

* Derating : 4.5mW/°C for operation above Ta=25°C.

●Recommended operating conditions (Ta = 25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Operating supply voltage	Vcc	4.0	—	6.0	V	Pin8,12
Operating temperature	T _{OPR}	-40	—	+85	°C	
Audio input level	V _{IN-A}	—	—	-10	dBV	Pin1,22
Audio input frequency band	f _{IN-A}	20	—	15k	Hz	Pin1,22
Pre-emphasis time constant set up range	τ _{PRE}	—	—	155	μs	Pin2,21
Transmission frequency(200kHz step)	f _{TX}	87.7 106.7	—	88.9 107.9	MHz	Pin9,11
Control terminal "H" level input voltage	V _{IH}	0.8Vcc	—	Vcc	V	Pin15,16,17,18
Control terminal "L" level input voltage	V _{IL}	GND	—	0.2Vcc	V	Pin15,16,17,18


● Block diagram




Multimedia ICs

●Application circuit

US BAND (88.0MHz~89.2MHz)



● **External dimensions (Units : mm)**



Appendix

Notes

- No technical content pages of this document may be reproduced in any form or transmitted by any means without prior permission of ROHM CO.,LTD.
 - The contents described herein are subject to change without notice. The specifications for the product described in this document are for reference only. Upon actual use, therefore, please request that specifications to be separately delivered.
 - Application circuit diagrams and circuit constants contained herein are shown as examples of standard use and operation. Please pay careful attention to the peripheral conditions when designing circuits and deciding upon circuit constants in the set.
 - Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
 - Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or otherwise dispose of the same, no express or implied right or license to practice or commercially exploit any intellectual property rights or other proprietary rights owned or controlled by
 - ROHM CO., LTD. is granted to any such buyer.
 - Products listed in this document use silicon as a basic material.
- Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).

Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

About Export Control Order in Japan

Products described herein are the objects of controlled goods in Annex 1 (Item 16) of Export Trade Control Order in Japan.

In case of export from Japan, please confirm if it applies to "objective" criteria or an "informed" (by MITI clause) on the basis of "catch all controls for Non-Proliferation of Weapons of Mass Destruction.

ROHM

FCC ID: NV6-CS4033

Appendix1-Rev1.0