

EBU*M* series electronic ballast operating principle**

This series of electronic ballast has six models, power 22W~72W. The circuit of the unit comprises EMC filter & AC/DC transfer circuit, DC/AC high frequency transfer circuit, High frequency booster circuit, Control circuit and Protection circuit for lamp abnormality.

EMC filter & AC/DC transfer circuit: It comprises C3, L2, D1, D2, C4, and C6; The EMC filter remove high frequency noise and interferences which were from network supply and this ballast. In the AC/DC transfer circuit a 120VAC input is rectified by the diode D1~D4 to a DC voltage.

DC/AC high frequency transfer circuit: It comprises Q1, R8, Q2 and R9; it converts the DC voltage into a high frequency AC voltage that is 20-30 kHz.

High frequency booster circuit: It comprises L3, L2 and C9; it boosts the high frequency AC voltage high enough to start the lamp, it stabilizes the lamp current when the lamp is operating.

Control circuit: It comprises T1 (A, B, C), R2 and R5; It supplies high frequency control signal for DC/AC high frequency transfer circuit.

Protection circuit for lamp abnormality: It comprises C12,C13,R12,D10,R10,C10, TH1,C7, and Z1; it supplies signal for control circuit to let the DC/AC high frequency transfer circuit stop working when the lamp become abnormal (end of life, dropout or break).