




Intelligent Cloud Film Cutting Machine


(Bluetooth version)

User Manual


Packing list




Blade holder



Blade



Intelligent cutter



① Cutter carriage

Control the knife to cut the film sheet

② Rubber wheels

Work with steel axis to keep cutting without slip

③ Steel axis

Work with rubber wheels to fix and protect film sheet

④ Power switch

Turn on the machine . Press it lightly to turn back the films during stand-by

⑤ Switch for blade holder installation

Press lightly to open the cover

⑥ Film feeding sensor

Auto feeding the film after detecting it

⑦ Film pasting guide

Please paste the films based on the guide

⑧ Blade holder installatin port

Open the port to take out or install the blade holder

⑨ High definition screen


6 inch touch screen , built in operation system

⑩ Power connection port

External 24v power port

—. Blade installation

Intelligent cutter



⑪ Handle

Press it to get the blade

⑫ Gear

Adjust the blade tip length

⑬ Blade handle holder

To be fixed by the hole in
cutting head

⑭ Cutting Blade

Cutting film sheet

Notes:

Ajust the blade:

Twist the gear to adjust the blade tip

Value bigger, tip longer

Value smaller, tip shorter

Factory setting is gear 6

Change blade:


Press handle

take out the old blade


put a new one in it

二. Blade holder installation


Intelligent cutter




Press the button to open the enhance



Open the fixed handle




Insert the holder to hole straightly




Fix the handle

三. Power on / off



Connect the cable and adapter. 110-240V AC power for the plug connection. The adapter connects the machine. Press the power button, machine power on. It takes 30s for starting.

四. Material installation



Put the material on the table flatly and align left based on the feeding guide


The material will be feed automatically after the cutter detect it. .

(If the film shift, press the switch in 1 second and the film will be returned back automatically)

四. Connect bluetooth



Scan it by browser




Choose the related phone system



APP Installed

Note: Suggest to scan the QR code to download APP by web browser

五. Loggin account





Please allow all access persion during installing the APP, otherwise it may abnormal, detailed operation as below:

1. Login App and choose language.
2. Insert the account and password.
3. Choose count / Monethly fee.
4. Default is Line:1 , if the internet not good , please change to Line:2.
5. Click LOGIN.
6. Register (This function only for the user who without account)

Note: Please change the password in "My Account" after the first login.

五. Choose Cutting Data




Choose a cutting data



Cutting finished

Intelligent cutter



The sheet will be dropped out automatically
after cutting finished, please take out the
finished parts and paste on the phone.

六. Parameters and precautions

Parameters	
Connection	wifi or Bluetooth
Internal Power	DC24V 1. 75A
Machine size	420*123*163mm
Machine weight	4. 3kg

Don't touch the knife tip by finger

The finger may be hurt by the knife tip

Don't seep into liquid

This may cause fire or electric shock

Don't use non-original power supply

This may damage the circuit or electric shock

Don't use in thunderstorm days

This may damage the machine

Don't use the non-standard materials

Please cut the standard size of material to reach the perfect result

Product parameters and precautions

-  Press power switch for emergency stop during working.
-  Forbid moving the carriage by hand after connecting the power to avoid machine damage.
-  Knife is a consumable part, please change to a new one if it is dull.
-  Press the power switch in 3 seconds continually to turn off the cutter, forbid taking out the power cable directly to turn off the machine because it will damage the mainboard

FCC Warning

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) this device may not cause harmful interference, and (2) this device must accept any interference received including interference that may cause undesired operation.

FCC Warning

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules.

These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception,

which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

To maintain compliance with FCC's RF Exposure guidelines, This equipment should be installed and operated with minimum distance between 20cm the radiator your body: Use only the supplied antenna.