




<div><h3>WIRELESS EARBUDS USER MANUAL</h3><p>Ailun-E5</p><p>Ailun</p><p>Please read this manual carefully before use and keep it for future reference.</p></div>	<div><h3>Product Information</h3><p>Wireless earbuds Charging case LED indicator(White)..... Type-C charging port..... MFB button (Multi-function button) Answer / End call Play / Pause Previous song / Next song Microphone Submicrophone Charging points.....</p><p>... 1 ...</p></div>	<div><h3>Packing List</h3><p>Charging Case * 1 Wireless Earbuds * 2 Type-C Cable * 1 S/M/L Eartips * 3 pairs Manual * 1</p><p>Tip: The ear tips in medium size have been installed on the earbuds in advance.</p><p>... 2 ...</p></div>	<div><h3>Important Reminder!</h3><p>Important Reminder!</p><p>Please take the following steps before using the earbuds for the first time:</p><p>Step 1: Peel off the blue insulating films on the charging contacts of the earbuds.</p><p>Step 2: Put the earbuds back into the charging case.</p><p>Step 3: CLOSE THE LID and let the earbuds charge for about 10 minutes.</p><p>... 3 ...</p></div>	<div><h3>Wearing</h3><p>Choose a pair of earbuds that fit your ears</p><p>L M S</p><p>Insert the earbud into your ear and rotate it backward to fit comfortably.</p><p>... 4 ...</p></div>	<div><h3>Power On</h3><p>Automatic operation: Open the charging case and take the earbud(s) out.</p><p>Manual operation: When the earbud is in power-off status, please touch and hold the touch button on the left/right earbud for 2 seconds to power on. You will hear a voice prompt of "Power on" from the earbud, then the red and white lights on the earbuds will be ON for 1 second at the same time.</p><p>Note: When the earbuds are being charged in the charging case and the case is out of power, the earbuds will turn on automatically.</p><p>... 5 ...</p></div>	<div><h3>Pairing</h3><p>1. Turn on your phone's Bluetooth. 2. Open the charging case and take out the earbuds. 3. Select "Ailun-E5" pairing, pairing the primary earbud red and white lights alternately flash, the secondary earbud white light flashes once in SS, pairing success beep "Connected".</p><p>Reminder: 1. Earbuds Turn On will pair L and R earbuds automatically, L R pairing successful will prompt voice "DingDong"; 2. If the earbud has been connected to the mobile phone, the earbud will be connected to the mobile phone first when the earbud is turned on. If the connection fails, it will automatically enter the mobile phone pairing state. 3. When pairing, the primary earbud red and white lights alternately flash, the secondary earbud white light flashes once in SS, pairing success beep "Connected".</p><p>... 6 ...</p></div>	<div><h3>Voice assistant</h3><p>1: Three click L/R earbud MFB, Release your finger to activate your voice assistant; 2: The corresponding voice assistant screen pops up, and you can easily execute commands.</p><p>"How's the weather?" "Next song" "Set alarm reminders"</p><p>... 7 ...</p></div>
--	--	---	---	--	--	---	---

Incoming Call

Answer/hang up a call
Click the MFB button on the L or R earbud, the tone "Du".




Reject a call
Long press the MFB button on the L or R earbud for 2 seconds, the tone "Du" (in the incoming call state)



Music


Play/Pause/Previous/Next song
Pause/play: Click the MFB button on the L or R earbud (some phones need to turn on the Media player)
Previous song: Double click the left earbud MFB button (if you only use the left earbud, the earbud can only play the previous song)
Next song: Double click the right earbud MFB button (if only the right earbud is used, the earbud can only play the next song)



Cautions:
1. If music is playing when you call, the earbud will automatically play music after the call ends.
2. If the voice assistant is used, the music will be paused.

Charging

Insert one end of the adapted data cable into the charging port of the charging compartment, and connect the other end to the computer/adaptor/mobile power supply for charging.



Charge Charging Case


Method 1: [Diagram of charging case with cable]

Method 2: [Diagram of charging case with cable]


Charging the Case & LED Indicators

Charging status of the charging case: the LED white light of the charging compartment flashes, and when fully charged the white light always on.

Charging case low battery status: when the first LED light has 0%-5% power remaining, and when the white light flashes once per second, it needs to be charged in time.




Charging status: earbud red light is always on, the red light goes off after a full charge.
Low battery status: red light flashes 300ms on 300ms off 5 seconds a cycle, once per minute voice prompt "Please charge".




Power Off


Manual operation:
1. Tap and hold the touch button on the left/right earbud for 5 seconds.
2. After the earbuds are closed, put them back in the charging case and close the cover.



Automatic operation:
1. Put the earbud(s) back into the charging case and close the case.
2. Earbud(s) automatically turns off (and enters charging mode).



Reset the earbuds/clear all pairing information on the earbuds
Turn off the earbuds and hold the touch buttons of the left and right earbuds for 10 second.



Specifications

Model	Allun-E5
Bluetooth Version	V5.0
Battery	40mAh (each earbud) 400mAh (charging case)
Charging Time	Approximately 1.5 hour (earbuds) 2.5 hours (charging case)
Input	5V=1A
Playtime (varies by volume level and content)	4hours (Up to 16 hours with the charging case)
Bluetooth Range	10m / 33ft
Frequency range	20KHz-20KHz
Sensitivity	102±3dB

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different

from that to which the receiver is connected.

- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction

FCC ID: 2A4KI-E5