



**PAMBEE**  
Magnetic Wireless Power Bank  
User Manual




Model: M5

Thank you for choosing PAMBEE's portable, wireless, fast charging power bank! We are confident in our product's reliability and quality. Please carefully read through this manual before attempting to use the product and keep it handy for further reference.

**Product Description**



**Package Contents**




**Specifications**

Model	M5
USB-C Input	5V=3A
USB-C Output	5V=2.4A, 9V=2.22A, 12V=1.67A 20W(Max)
Wireless Output	5W / 7.5W / 10W / MPP 15W(Max)
Total	5V=3A
Battery Type	Lithium Polymer
Battery Capacity	5000mAh / 3.6V / 18Wh
Rated Capacity	3000mAh (5V=2.4A)
Size	4.06 x 2.6 x 0.36in / 103 x 66 x 9.3mm
Weight	3.77 oz / 107g


**Operating Instructions**

Note: When USB-C port and wireless charge output at the same time, wireless charge output automatically off mode, priority support for C port output.

**1. Charging the Power Bank**  
Connect the USB-C connector of the supplied cable to the Power Bank device. The two possibilities for the Power Bank device are: an AC charger as seen in picture (1), or a computer USB-C port as seen in picture (2). The other end of the supplied charging cable should be plugged into the USB-C port of the Power Bank.




Picture (1)



Picture (2)

**2. Power on**

① Auto positioning: Powered on. The mobile and the power bank are magnetically adsorbed and automatically positioned, then wireless charging is turned on with a snap.  
② Short-press: Power on (the light displays), then wireless charging starts.



**② Charging indicator status:**

Capacity	LED1	LED2	LED3	LED4
100%	ON	ON	ON	ON
75%~99%	ON	ON	ON	Flicker
50%~75%	ON	ON	Flicker	OFF
25%~50%	ON	Flicker	OFF	OFF
0%~25%	Flicker	OFF	OFF	OFF

**③ Wireless charging indicator:**

Wireless charger: Orange LED light is on  
Wireless charge Slow charge (5W): Orange LED light is on  
Wireless charging fast charge (7.5W / 10W / 15W): Orange LED light is on  
Wireless foreign object: Orange light flashing fast



**④ Description of power display**

① Discharge indicator status:

Capacity	LED1	LED2	LED3	LED4
75%~100%	ON	ON	ON	ON
50%~75%	ON	ON	ON	OFF
25%~50%	ON	ON	OFF	OFF
5%~25%	ON	OFF	OFF	OFF
1%~5%	Flicker	OFF	OFF	OFF
0%	OFF	OFF	OFF	OFF

● Both the protective phone case and the position of your device on the wireless charger will affect the charging speed. The farther it is placed from the center of the wireless charger, the slower the charging speed will be.

**Important Safety Instructions**

When using this product, basic precautions should always be followed, including the following:

- 1) Store the product in a cool, dry place.
- 2) Do not store the product in a hot or humid environment.
- 3) Do not dispose of the product in heat or fire.
- 4) Do not clean the product with harmful chemicals or detergents.
- 5) Operating temperature should be between 0°C to 45°C / 32°F to 113°F.
- 6) Do not disassemble the product. Take it to a qualified service person when service or repair is required. Incorrect reassembly may result in a risk of fire or injury to persons.
- 7) If the product is not used for long periods of time, you should charge and discharge it once every three months.
- 8) When charging a device, the product may feel warm. This is a normal operating condition and should not be a cause for concern.
- 9) In normal conditions, the battery performance will decline over several years.
- 10) Misuse, dropping, or excessive force may cause product damage.
- 11) When disposing of secondary cells or batteries, keep cells or batteries of different electrochemical systems separate from each other.
- 12) Be aware that a discharged battery may cause fire or smoke. Tape the terminals to insulate them.

**FAQs**

**Q: Can this be used with any phone other than an iPhone?**  
A: This magnetic power bank is designed specifically to charge the iPhone series phones. Only iPhone series phones support magnetic charging. Nevertheless, you can only use the USB-C port to charge other USB-C devices, or use the magnetic attraction ring to attach to other phone models that have wireless charging, however the charging speed will be slower.

**Q: What is the wattage of this power bank?**  
A: This wireless power bank charges the iPhone series phones with a maximum output of 15W.

**Q: Will the wireless magnetism work if the phone has a case?**  
A: This magnetic wireless charging mobile power can work well with the magsafe iPhone series phone case. If you use a normal case, the magnetic force will be very weak. For that reason, it is generally advised that it will not be effective with a thick protective case.

**Q: Is it normal for the battery to heat up when charging?**  
A: Compared to conventional charging devices, wireless technology charging devices tend to cause slight heat generation. However, this temperature is within the normal operating temperature range of the phone, so please feel free to use it despite it being slightly hotter.

**FCC Statement**

Warning: Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

**FCC Statement**  
This device has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:  
—Reorient or relocate the receiving antenna.  
—Increase the separation between the equipment and receiver.  
—Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.  
—Consult the dealer or an experienced radio/TV technician for help.

**RF exposure compliance statement:**  
1. The device has been evaluated to meet general RF exposure requirement.  
The device can be used in portable exposure condition without restriction.  
2. Equipment system maintenance is simple, please refer to the manual.  
3. The user can take simple measures to correct the interference.

**Customer Service:**  
✉ support@pambee.cn   🌐 www.pambee.cn

 Made in China