

Bluetooth Headphones Instruction

Product Parameters:

Bluetooth Version: V5.2

Support Profile: AVRCP1.3, A2DP1.0, HFP1.5, HSP1.0

Working Distance Range: 10m

Frequency Range: 2.402GHz-2.480GHz

Charging Voltage : DC4.2-5.5V

Charging Time: about 1.5 hours

Talking/Music time about 24 hours

Standby Time about 300 hours

Button Description:

Button M: ON/OFF/Three kinds of playback modes switch (TF Mode, Radio Mode, Bluetooth Mode)

Long press button M for more than 3seconds, the headset will start up and enter "Bluetooth Mode" automatically, LED indicator light turns to blue.

Long press button M for more 3 seconds, LED indicator light turns off.

Button with Phone icon: Play/Pause/FM Radio Searching/Answer Call/Hang up Call/ Make Call

Button V-: long press Reduce Volume/short press for Previous Song or Radio Station

Button V+: long press Increase Volume/short press for Next Song or Radio Station

Button Operation:

- 1) Answer Calls: Short press button with phone icon when calls coming;
- 2) Hang up phone calls: Short press button with phone icon after calling
- 3) Redial the last outgoing number: Double-click button with phone icon
- 4) Music Play: Short press button with phone icon after connected with the smart device.
- 5) Restart the music or FM: It will stop playing when calls coming, Short press button with phone icon to restart after hang up the call.

Mode:

Bluetooth Mode:

1. Pairing Operation:

a. For the first time pairing: Into "Bluetooth Mode" automatically. voice prompts "Bluetooth Mode" LED indicator light turns to blue. if can't search and pair with the last connected smart device within 3 seconds. it will automatically enter pairing mode. LED Indicator light rapidly alternating flashes with blue and green colors. Please open the smart device's Bluetooth searching function, and select the device "AH-806", no password required, after successful pairing, voice prompts "Connected", LED indicator light flash every two seconds while working.

b. Re-pairing: turn off the attached smart device's Bluetooth function, if the headset can't search and pair with the last connected smart device within 3 alternating flashes with blue and green, Open another smart device's Bluetooth searching function, and select the device "AH-806", no password required, after successful pairing. voice prompts "Connected", LED indicator light flash every two seconds while working.

c. Follow-up pairing: automatically pair the last connected device in 3 seconds after boot.

2. Maximum volume warning voice prompts "du du".

3. Power Saving Function if not no successful match for 5 minutes, the headset will automatic shutdown; insert Aux-in cable will cutoff the power supply to save power.
4. Supports MP3,WAV,WMA,FLAC format playback.
5. Battery indication no IOS.
6. Micro USB as common use charging port.

Micro SD Card Playback Mode:

- 1)When the slot is empty, inserted the Micro SD Card, LED indicator Light turns to green, voice prompts "Music". Then it plays media automatically,LED indicator light turns to green flashing every 4 seconds.
- 2)When the Micro SD Card is inside,switch to Micro SD Card Mode through MODE

FM Radio Mode:

- 1)When the headset is on, switch to FM Radio mode through MODE, voice prompts "Radio Mode", LED indicator light turns to green.
- 2)Usage Tips:long press:"Button with Phone icon" for 2 seconds to search and save stations automatically (it can be abort with another short press while searching). Once enter FM Radio mode again, it will play the first saved radio station automatically. If you want to re-scan, long press"Button with Phone icon" for 2 seconds again in the Radio mode.

AUX-in Mode:

When the headset is on, insert the AUX-in cable. Then it plays smart device's media automatically.

Note:

If no pairing connection after the Bluetooth headset enters the pairing mode. please turn off the headset as for power saving.

Do not perform other operations when searching Bluetooth to prevent the program error.

Please select the appropriate volume in use to prevent damage to your ears.

Please note that a good environmental for using the Bluetooth headset can avoid damage to the headphones.

Please charging the headset after a long time none-use.

FCC Statement

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.