

User Manual

RK · Bone Conduction Glasses



Nothing in or on your ears
A new way to listen. Stay connected to the world around you while discreetly listening to music with a revolutionary open-ear audio design.

One-button design has no access to multi-status operations through the glasses; under playback status, Operations like switching songs and adjusting volume can be operated through mobile phones.

(3) Light-Sensor Switch and Power Saving Mode: under playback status, taking off the glasses from your head will trigger light sensor, and music will automatically pause. When the light sensor triggers the music to pause, put on the glasses again within 5 seconds, and the music playback will automatically continue, but after 5 seconds, you need to click the button on either side to continue playing.

IV. Answer/Make Calls

▼ Follow the above instructions to turn on the glasses and pair them to a mobile phone or a desktop.

▼ Answer a Call: Single click the button on either side to pick up an incoming call

▼ Reject a Call: press and hold the button on either side for second and release

▼ End a Call: Single click the button on either side to hang up the call

▼ Radial the Last Number on call records only: press and hold the button of the main connection side with Bluetooth for 1 second.

1.Special Thanks

Thank you for your trust and support in purchasing our product. Please read the user manual carefully before using our product. In order to continuously enhance the performance and quality of the product and allow users to get a better experience in using our product, we will keep improving and optimizing this product. Thus design and specifications are subject to change without notice.

Note: Your satisfaction is our unremitting pursuit. In case you have any questions about using the product, please don't hesitate to contact us; we will provide timely and satisfactory solutions. **Contact:** us@youhegd.com

Should you have any using questions about the glasses, please scan the below QR or input the link in your browser, you will redirect to operation video with detailed instruction.

https://www.youtube.com/watch?v=wIRF_8YGzLk



V. Voice Assistant

▼ When glasses connected with Bluetooth, double clicking the button of the main connection side with Bluetooth to activate the Voice Assistant (also called Voice Recognition)

▼ After Voice Assistant is activated, human commands can be used to perform operations of mobile phones with Voice Assistant supported. Please refer to user manual of mobile phones for Voice Assistant operations.

VI. Charging

Use magnetic charging cable included and connect the glasses to a standard USB interface on PC or a standard 5V-1A USB charger. The LED indicator will show solid red when charging and will turn solid blue when charging is completed.

CAUTION: Please fully charge the glasses before the first use. Do not use any fast chargers to charge the glasses.

VII. Factory Reset

(1) In the OFF status, charge both sides of the glasses

(2) Press and hold the buttons of both sides for 15~20 seconds, do not release the buttons until the red light disappears and lights up again

(3) Unplug the charging cable, blue light will


2.Contents

1) Complied Standards-----	1
2) Product Overview and Accessories-----	1-2
3) Main Parameters-----	2-3
4) Operation Instructions-----	3-9
5) Troubleshooting-----	9-12
6) Federal Communications Commission (FCC) Statement-----	13-14

3.Complied Standards

1.This product is in compliance with the National Standard Food and Drug Administration (FDA) and Federal Communications Commission of United States of America.
2.This product complies with the regulation of myopia glasses and reading glasses.

4.Product Overview and Accessories



1

CAUTION: Do not put your fingers on the hingebar when open glasses for wearing, in case it will cause pinching.

Accessories:
Anti Blue Light&Photchromic Lenses; Lenses Templates; Magnetic Charging Cable; Cloth Pouch; User Manual

5.Main Parameters

I . Bluetooth System

- Bluetooth Version 5.0
- Connectable to Bluetooth competent mobile phones, desktops, laptops, etc. Compatible with profiles A2DP, APTX.
- Stand-by time: Around 7 days
- Continuous playback time: 3~4 hours (Different volume and sound source will be different.)
- Up to 10 meters barrier-free wireless range.
- Battery specifications: 90 mAh/3.7V on each frame side; Fully charge within 1 hour.
- Speaker type : Bone conduction speakers
- Power of speakers: 1W*2
- Speaker sensitivity : 102+3dB
- Microphone sensitivity : -40+3dB
- Frequency Range:20Hz ~ 20KHz

2

be not when you follow the instructions below. Please consult the after-sales team of the manufacturer who will provide you with recommendations and solutions for these problems.

Q1: Does not turn on

▼ Make sure the battery (both side frames) isn't dead and press ON/OFF button to check if there is any voice prompt saying "power on". If not, please press and hold ON/OFF button again for 3 secs to check whether there is any voice prompt saying "power off" or not. If neither of the voice prompts, it is concluded that the battery needs to be charged.

▼ It is recommended to reset the glasses to reset the glasses to factory reset if it still cannot be turned on after fully charged. Please follow previous steps for factory reset.

▼ If the problem still exists after factory reset, we assume it has something to do with the failure of the electric circuit. Please communicate with the after-sales team of the manufacturer to get a solution.

Q3: Does not charge

▼ Check whether there is electricity on the power outlet (check whether the socket switch is turned off etc.)

▼ Check whether the USB charger charges properly. (Try to charge other devices with this USB charger to make sure the USB charger is in good condition.)

▼ It is recommended to reset it to factory default if it still does not work.

▼ If the problem still exists after factory reset, we assume it has something to do with the failure of the electric circuit. Please communicate with the after-sales team of the manufacturer to get a solution.

Q2: Unable to pair

▼ Make sure the pairing mode is entered while LED light flashes red and blue alternately, and voice prompted "Pairing". If you see the intermittent red

II . Other technical specifications

- Product dimension:155mm* 146mm* 49mm
- Net weight: 38g(lenses included)
- Operating environment:Temperature:-10c ~ 50c Humidity:0~90%
- Waterproof rating:IP66
- Specification of charger: Charger port: Magnetic Input:AC 110V/220V. 50/60Hz Output:DC 5V. MAX 1A

Note: Always use PC USB port or 5V-1A charger for charging; using fast charger will damage battery life.

6.Operation Instructions

Voice prompts can be heard and the status of LED indicator shows differently as per different functions during the use of this product.

• Illustrations for voice prompts

Status/Function	Voice prompt
Power On	Power On
Power Off	Power Off
Enter Pairing Mode	Pairing
Bluetooth Connected	Connected
Bluetooth Disconnected	Disconnected

3

make sure the USB charger is in good condition.)

▼ Check whether the LED shows solid red. If not, it means charging isn't effective. LED turns blue when charging is finished.

▼ Check if the glasses have already been paired with another device within 10 meters. If yes, the solution is to delete the Bluetooth name "Rocklion" from the menu of the device paired and then follow the pairing steps to pair it with the new device.

▼ Try to remove all the Bluetooth names from the menu of your phone and put it back to pairing mode. Follow the correct steps of pairing described above.

▼ It is recommended to reset it to factory default if it still cannot get paired. Follow the correct steps of pairing described above.

▼ If the problem still exists after factory reset, we assume it has something to do with the failure of the electric circuit. Please communicate with the after-sales team of the manufacturer to get a solution.

▼ Check whether there is electricity on the power outlet (check whether the socket switch is turned off etc.)

▼ Check whether the USB charger charges properly. (Try to charge other devices with this USB charger to make sure the USB charger is in good condition.)

▼ It is recommended to reset it to factory default if it still does not work.

▼ If the problem still exists after factory reset, we assume it has something to do with the failure of the electric circuit. Please communicate with the after-sales team of the manufacturer to get a solution.

7.Troubleshooting

12

You may come across some unexpected problems during the use of this product. Some problems can be solved quickly by yourself while the others may

• Color of indicator and the corresponding status

Color of Indicator	Status
Red(Solid)	Charging
Blue(Solid)	Fully Charged
Blue and Red (Simultaneous Flash)	In Pairing Mode

I . Turn On/Off

In the OFF status, press and hold either side ON/OFF button for 3 sec to power on left or right frame only, followed by a voice prompt "Power On". While press and hold both side ON/OFF button for 3 sec to power on both left and right frames simultaneously, followed by a voice prompt "Power On".

In the ON status, press and hold the one side ON/OFF button for 3 sec to power off left or right frame only, followed by a voice prompt "Power Off". Press and hold both sides ON/OFF buttons for 3 sec to power off both left and right frames simultaneously, followed by a voice prompt "Power Off".

II . Bluetooth Connection

▼ In the OFF status, press and hold either side ON/OFF button for 3 sec to power on left or right frame only, e.g. turn on left side frame. After then, press and hold the ON/OFF button of the other side frame for 10 sec, till the blue

4

Federal Communications Commission (FCC) Statement

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful

interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit

13

and red light simultaneously flash and accompanied with voice prompt first "Power On" and then turn to "Pairing". **(The side in pairing status is the main connection side)**

▼ Locate the Bluetooth menu on the device you are using and select "Rocklion", then click it for Pairing.

▼ A voice prompt "connected" can be heard when pairing has succeeded.

1) For IOS system, when the main connection side connects successfully with Bluetooth, the other side frame will automatically interconnect with Bluetooth.

2) For Android system, after the main connection side connects successfully with Bluetooth, a new Bluetooth pairing request will pop up again in your device and you need to manually click "PAIR" to connect with Bluetooth.

III . Play/Pause Music

▼ Follow the above instructions to turn on the glasses and pair them to a mobile phone or a desktop.

▼ Start a music player from your mobile phone or desktop and wear the glasses to enjoy music.

▼ Music stops playing when the music player is closed from your mobile phone or desktop.

Operation instructions:

(1) Play/Pause: Single click On/Off button on either side to pause music under playback status. Single click On/Off button on either side to play music under pause status.

(2) Volume Adjustment and Song Switch:

5

menu of a connected device, please power off the glasses first and follow the previous steps of Bluetooth connection for pairing with a new device

(3) The glasses turn off automatically 14 minutes after they are unconnected or fail to connect to the device

(4) If out of range (more than 10 meters) when connected to a device, the glasses will disconnect from the device. Once back within range, it will automatically reconnect within 1 minutes. Single click On/Off button to make the glasses reconnect to the device if 5 minutes pass

IV . Notes

Notes:

(1) Pair the glasses to a standby device for the first use. After pairing, re-pairing is unnecessary for the connection to the same device if "Rocklion" isn't deleted from the Bluetooth menu of the device.

After the glasses are turned on, they will automatically reconnect to the device or you can select "Rocklion" for pairing from the Bluetooth menu of this device

(2) When you delete "Rocklion" from the Bluetooth

6

FCC Statement

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.