



Shenzhen Yingfeng antenna technology Co., LTD

D06 Test Report

Guest household Ling 'an Wireless

product	D06
engineer	Xu Yong
telephone	15195746167
mailbox	lyg@yingfengtianxian.com
date	2024-11-4



Report catalog

- ③ Test equipment
- ③ Prototype appearance
- ③ Matching parameter
- ③ Network debugging antenna S parameters
- ③ Free field efficiency of the whole machine
- ③ The whole machine free field type
- ③ Stretch test
- ③ Debugging summary





Test condition

- 1.S Parameter measurement
- 2.Equipment: Network analyzer (Agilent E5062A), Microwave darkroom, MT8852B
- 3.Item: Impedance, return loss, VSWR, Efficiency, gain, radiant field pattern, sensitivity, power, Frequency offset active data TRP TIS



Shenzhen Yingfeng antenna technology Co., LTD






Shenzhen Yingfeng antenna technology Co., LTD

Prototype appearance





Matching parameters (on-board ring)



ID	Model number	specification	manufacturer	Part number (P/N)	allowance	
1	onboard					
2	NC					
3	capacitance	1.5PF/0402	Murata		$\pm 0.1\text{NH}$	

4	inductance	4.3NH/0402	Murata		$\pm 0.1\text{NH}$	
5						

Network debugging antenna S parameters

Debugging waveform

ring



Free field efficiency of the whole machine

Ring efficiency




Freq (MHz)	Gain (dBi)	Efficiency (dB)	Efficiency (%)
2400	5.638819625	-9.082557591	12.35219789
2410	-5.525699349	-8.98747733	12.62560701
2420	-5.483687137	-8.97032589	12.67556746
2430	-5.470403454	-8.915894575	12.83543354
2440	-5.34501599	-8.763098944	13.295054
2450	-5.411438619	-8.776286544	13.25474404
2460	-5.590595727	-8.914002735	12.84102603
2470	-5.520103724	-8.812247635	13.14544331


2480	-5.28507728	-8.69594234	13.50223822
2490	-5.36207069	-8.765474855	13.28778261
2500	-5.25685849	-8.702283996	13.48253637



The whole machine free field type

Ring field pattern





Sum up

1. Ring the battery cable away from the antenna area.

Thanksfor Your Attention