

FEITUKEJI

Frequency ID	1	2	3	4	5	6	7	8	9	10	11
Frequency (MHz)	2400.0	2410.0	2420.0	2430.0	2440.0	2450.0	2460.0	2470.0	2480.0	2490.0	2500.0
Efficiency (dBi)	-2.21	-2.29	-2.19	-2.24	-1.91	-2.20	-2.24	-2.44	-2.74	-2.75	-2.90
Gain (dBi)	1.16	1.05	1.16	1.02	1.33	1.13	1.45	1.50	1.35	1.44	1.36
Efficiency (%)	60.12	59.08	60.37	59.71	64.49	60.20	59.73	57.05	53.22	53.09	51.30
Directivity (dB)	3.37	3.34	3.35	3.26	3.23	3.34	3.69	3.93	4.09	4.19	4.26
Peak Gain Position (Theta)	64.00	76.00	76.00	76.00	77.00	78.00	78.00	78.00	77.00	76.00	75.00
Peak Gain Position (Phi)	90.00	120.00	120.00	120.00	120.00	120.00	120.00	120.00	120.00	120.00	120.00
Efficiency ThetaPol (%)	51.75	50.57	51.98	51.82	56.02	52.25	52.12	49.98	46.33	45.85	44.63
Efficiency PhiPol (%)	8.37	8.50	8.39	7.89	8.46	7.95	7.61	7.08	6.89	7.24	6.67
Upper Hem. Efficiency (%)	35.14	34.50	35.47	35.49	38.63	36.35	36.45	35.03	32.57	32.36	31.73
Lower Hem. Efficiency (%)	24.98	24.58	24.90	24.22	25.86	23.85	23.28	22.02	20.65	20.73	19.58

Eff 15deg (dBi)											
Gain 15deg (dBi)											
Eff 15deg (%)											
Eff 30deg (dBi)											
Gain 30deg (dBi)											
Eff 30deg (%)											
Eff no SC											
Gain no SC											
Gain (dBi, ThetaPol)	1.10	1.04	1.14	1.01	1.32	1.13	1.45	1.49	1.35	1.44	1.35
Gain (dBi, PhiPol)	-3.34	-3.37	-3.49	-3.84	-3.56	-3.78	-3.77	-4.08	-4.30	-4.23	-4.80
Empty											



