无线蓝牙耳机

使用说明书

产品示意图



包装清单

- 89044蓝牙耳机主机
- 89044耳机充电盒
- Micro 5pin 充电线
- 备用大、小耳帽
- 使用说明书

产品规格

- 产品型号：89044
- 蓝牙版本：5.3
- 蓝牙名称：Wavelength-BT
- 电池规格：耳机3.7V 30mAh；充电仓3.7V 200mAh
- 支持模式：HFP/HSP/ A2DP/AVRCP
- 灵敏度：105dB ±3dB S.P.L at 1KHz
- 信号距离：10米（无任何较大障碍物的理想环境中）
- 播放时间：约 2 H
- 通话时间：约 2 小时
- 待机时间：约 80 小时
- 充电时间：给充电盒充电约1.5小时,充电盒给耳机充电约1小时
- 充电仓给耳机充电次数：约2.5次

功能操作说明

1、开机
将耳机从充电仓拿出自动开机或长按左右耳机多功能键3秒开机。

2、关机
将耳机放入充电仓自动关机/长按左右耳机多功能键5秒关机。

3、开机回连
当配对成功后，第二次开机时蓝牙耳机优先进入回连状态自动回连已连接过的手机。

4、播放/暂停
在待机状态下，单击左右耳机多功能键均可直接播放音乐，播放时单击左右耳机多功能键均可暂停播放。

5、切换歌曲
播放音乐时长按左耳机多功能键2秒同时响“嘟”一声切换到上一曲，长按右耳机多功能键2秒同时响“嘟”一声切换到下一曲。

6、音量加减
双击左耳机多功能键逐级加大音量，双击右耳机多功能键逐级减小音量

7、来电接听
手机来电时，单击左右耳机多功能键均可接听电话。

8、来电挂断
手机通话时，单击左右耳机多功能键均可挂断电话。

9、来电拒接
手机来电时，长按左右耳机多功能键2秒均可拒接来电。

10、末号重拨
在待机或者播放音乐时，三击左耳机多功能键即可拨打您通话记录中最后一个拨打过的电话。

11、启动语音助手
三击右耳机多功能键即可启动苹果Siri或谷歌语音助手进行语音控制手机操作。

12、低电量提示
当蓝牙耳机电池电量不足时，间隔30秒播放一次电量不足提示音直至耳机低电关机。

配对方式

普通配对方式

1.从充电仓取出或者同时长按左、右耳机多功能键3秒开机，直至红蓝灯交替闪烁，进入对耳搜索配对状态，进入对耳自动配对，配对成功后主耳（右耳）持续红蓝灯交替闪烁，副耳为蓝灯慢闪，同时播放对耳配对成功提示音。

2.启动手机或者其它设备的蓝牙功能，如果是安卓系统手机或者设备请点击手机“搜寻蓝牙设备”选项，如果是IOS系统的手机或者设备则会自动搜索设备；当搜寻到该蓝牙耳机的型号后，点击进入配对；当配对成功后，主（右）耳机会发出连接成功的提示音，左右耳机指示灯变为蓝灯慢闪，进入连接待机状态，配对成功后主耳为右声道，副耳为左声道。

3.两只耳机也可单独与手机进行配对使用，操作方法可按上步骤 2 操作手法进行操作。

充电操作

1， 将Micro USB充电线一头插上充电仓的USB口，一头插上充电器即可给充电盒充电，LCD会显示最新的电量。

2，给耳机充电：将耳机放入充电仓即可自动充电，充电时耳机指示灯为红色，充满电后熄灭；充电仓的LCD会显示剩余电量，当耳机充满电后，充电仓LCD会熄灭。

注意事项

1.请在安全的环境下充电。在给充电仓充电时当充电指示灯指示满电后请尽快将充电仓与USB充电线分开，以免在长时间插着充电对充电仓造成损伤。

2.在音乐播放时，请将音乐调至合适音量大小，以免长期在大音量状态下对听力造成损伤。

3.尽量避免在有干扰源的地方使用本耳机，否则有可能对耳机信号产生影响。

4.尽量避免在有腐蚀的环境中使用本耳机，以免对耳机的功能产生影响。

温馨提示:在您使用本蓝牙耳机听音乐或者通话时，请注意适当调节音量大小，以免过大的音量对您的听力造成影响!

该设备符合FCC规则第15部分。操作应符合以下两个条件：
（1）此设备可能不会造成有害干扰
（2）此设备必须接受接收到的任何干扰，包括可能导致意外操作的干扰。

未经合规责任方明确批准的任何变更或修改
可能会导致用户无权操作设备。

注：根据FCC规则第15部分的规定，该设备已测试并符合类数字设备的限制。这些限制旨在提供合理的保护，防止住宅安装中的有害干扰。本设备产生、使用和辐射射频能量。如果未按照说明安装和使用，可能会对无线电通信造成有害干扰。但是，无法保证在特定安装中不会发生干扰。

如果该设备确实对无线电或电视接收造成有害干扰，可通过关闭和打开设备来确定，鼓励用户尝试通过以下一种或多种措施来纠正干扰：

—重新定向或重新定位接收天线。
—增加设备和接收器之间的间隔。
—将设备连接到不同电路上的插座，从接收器连接的位置。
—请咨询经销商或有经验的无线电/电视技术人员以获得帮助。该设备经评估符合一般射频暴露声明。

该设备可在使用无曝光条件下使用，无限制
FCC ID: 2ATEF-89044

警告：未经负责合规性的器件明确批准，对本装置进行的更改或修改可能会导致用户无权操作设备

Wireless bluetooth headset

User's manual

Product schematic diagram



Package list

- Bluetooth earphone
- Endurance charging box
- Micro 5pin charging cable
- User's manual
- Earplug silicone cap

Product specifications

- Product number: 89044
- Bluetooth version: 5.3
- Bluetooth Name: Wavelength-BT
- Battery specification: Headset 3.7V/30mAh; Charging box 3.7V/200mAh
- Support mode: HFP/HSP/ A2DP/AVRCP
- Sensitivity: 105dB ±3dB S.P.L at 1KHz
- Transmission distance: 10 meters (in an ideal environment without any major obstacles)
- Play time: About 2 hours
- Call time: About 2 hours
- Standby time: About 80 hours
- Charging time: Charge the charging compartment for about 1.5 hours, and charge the headset for about 1 hour
- Charging box to charge the headset: About 2.5 times

Functional operation instructions

1. Boot
Take the headset out of the charging compartment and automatically turn it on or press and hold the left and right headset multifunction button for 3 seconds

2. Shut down
Put the headset into the charging compartment and turn it off automatically. Press and hold the left and right headset multifunction button for 5 seconds to shut down

3. Boot back:
When the pairing is successful, the Bluetooth headset preferentially enters the connected state when the second time is turned on, and automatically connects back to the connected mobile phone

4. Play / Pause
In the standby mode, click the left and right earphones multi-function keys to play music directly. When playing, click the left and right earphones multi-function keysto pause playback

5. Switch songs
When playing music, press and hold the left earphone multi-function button for 2 seconds while ringing "di" to switch to the previous song. Press and hold the right earphone multi-function button for 2 seconds while ringing "di" to switch to the next song

6. Volume addition and subtraction
Double-click the left earphone multi-function key to increase the volume step by step, double-click the right earphone multi-function key to gradually decrease the volume

7. Call answering
When the mobile phone calls, click the left and right earphones multi-function button to answer the call

8. Call hang up
When the phone is talking, click the left and right earphones multi-function button to hang up the phone

9. Call rejection
When the mobile phone calls, long press the left and right headphones multi-function button for 2 seconds to reject the call

10. Redial
While on standby or playing music, you can dial the last call you made in your call history by tapping the left headset multifunction button

11. Start voice assistant
Three-click the right headset multi-function button to start Apple Siri or Google Voice Assistant for voice control mobile phone operation

12. Low battery prompt
When the battery of the Bluetooth headset is low, the low battery tone will beplayed every 30 seconds until the headset is powered off

Pairing method

1.Take out from the charging bin or press and hold the left and right earphones multi-function button for 3 seconds to turn on until the red and blue lights flash alternately, enter the ear search pairing state, enter the ear pair automatic matching, and match the main ear (right ear) The red and blue lights are alternately flashing, the secondary ear is flashing slowly, and the paired ear is successfully played.

2.Start the Bluetooth function of the mobile phone or other devices. If it is an Android mobile phone or device, please click the "Search for Bluetooth device" option. If it is the IOS system mobile phone or device, it will automatically search for the device, when searching for the model of the Bluetooth headset After that, click to enter the pairing; when the pairing is successful, the main (right) earphone will make a prompt to connect successfully, and the left and right earphones will turn blue and flash slowly, and enter the connection standby state. After the pairing is successful, the main ear is the right channel. The secondary ear is the left channel.

3.The two earphones can also be paired with the mobile phone separately. The operation method can be operated according to the above step 2 operation method.

Charging operation

1. Plug the Micro USB charging cable into the USB port of the charging bay at one end, and plug the charger at the other end to charge the charging box. The LCD will display the latest power.

2, charge the earphone: put the earphone into the charging bin and it will automatically charge. The earphone indicator is red when charging, and it will be off when fully charged. The LCD of the charging bin will display the remaining power. When the earphone is fully charged, the LCD of the charging bin will go out.

Precautions

1. Please charge in a safe environment. When charging the charging compartment, please charge the charging compartment separately from the USB charging cable as soon as the charging indicator indicates full power, so as to avoid damage to the charging compartment after a long time of charging.

2. When playing music, please adjust the music to the appropriate volume to avoid hearing damage at high volume for a long time.

3. Try to avoid using the headset in a place with interference sources, otherwise it may affect the headphone signal.

4. Try to avoid using this headset in a corrosive environment to avoid affecting the function of the headset.

Tips: When you use this Bluetooth headset to listen to music or talk, please pay attention to adjust the volume properly, so as not to affect the hearing of excessive volume!

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.
Any changes or modifications not expressly approved by the party responsible for compliance
could void the user's authority to operate the equipment.
NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.
However, there is no guarantee that interference will not occur in a particular installation.
If this equipment does cause harmful interference to radio or television reception,
which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help. The device has been evaluated to meet general RF exposure statement. The device can be used in portable exposure condition without restriction.
FCC ID: 2ATEF-89044

Warning: Changes or modifications to this unit not expressly approved by the part responsible for compliance could void the user's authority to operate the equipment