


封面

Bluetooth Headset



01

02

03

04

05

06

07

08

09


10

11

Package Contents

- 1x Headset
- 1x USB Dongle
- 1x User Manual

Product Overview



Product Specification

Bluetooth Version: V5.2
Operation Range: 15 meters
Battery Capacity: 400mAh/3.7V
Charging Time: About 2 hours
Headset Dimensions: 173*173*75mm
CODEC Code: SBC, AAC
Bluetooth Protocols: HSP, HFP, AVRCP, A2DP
Working Time: About 60 hours (70% volume)
Talking Time: About 3.5 hours (70% volume)

** Some parameters may vary due to the environment and the mode of music played.*

Product Overview

- ① Microphone
- ② Multi-function Button (MFB)
- ③ Headset LED Indicator
- ④ Volume +
- ⑤ Volume -
- ⑥ Mute Button
- ⑦ Charge Port
- ⑧ USB Dongle

Product Specification

Bluetooth Version: V5.2
Operation Range: 15 meters
Battery Capacity: 400mAh/3.7V
Charging Time: About 2 hours
Headset Dimensions: 173*173*75mm
CODEC Code: SBC, AAC
Bluetooth Protocols: HSP, HFP, AVRCP, A2DP
Working Time: About 60 hours (70% volume)
Talking Time: About 3.5 hours (70% volume)

** Some parameters may vary due to the environment and the mode of music played.*

How to use

A. Bluetooth Pairing and Connection

1. In power off status, press and hold the MFB for 3 seconds to enter pairing mode with LED Blue & Red flash alternately.

B. How to pair with a computer

Pair with a computer via the USB Dongle

1. Plug the USB Dongle into the USB port of your computer and wait for your computer to recognize it. The LED indicator on the USB Dongle flashes blue.
2. On your PC, select Start > Settings > Bluetooth & other devices > Add Bluetooth or other device > Bluetooth > Click on the model number of DY101 > Your device. Pairing is successful when you hear "Your headset is connected".

Pair with a computer via Bluetooth

1. On your device, press and hold the MFB button of DY101 for 3 seconds to enter pairing mode. The LED indicator flashes blue and red alternately. You will hear the voice guidance say "Pairing".
2. On your PC, select Start > Settings > Bluetooth & other devices > Add Bluetooth or other device > Bluetooth > Click on the model number of DY101 > Your device. Pairing is successful when you hear "Your headset is connected".

A window will pop up indicating the Bluetooth connection is complete. If your computer asks for a Bluetooth driver, contact your computer manufacturer.

Check the sound settings to make sure sound is played via the correct output and input

The microphone and the speaker of the headset may be disabled or not set as the default device on your computer. 1. Right-click the Speakers icon at the bottom right, then click Open Sound settings.
2. Select [DY101] as your output device (speaker).
3. Select [DY101] as your input device (Microphone).

Pairing

1. In power off status, press and hold the MFB for 3 seconds to enter pairing mode with LED Blue & Red flash alternately.


Search and Connection

1. In power off status, press and hold the MFB for 3 seconds to enter pairing mode with LED Blue & Red flash alternately.

Search and Connection

1. In power off status, press and hold the MFB for 3 seconds to enter pairing mode with LED Blue & Red flash alternately.

Bluetooth Headset



01

02

03

04

05

06

07

08

09


10

11

Package Contents

- 1x Headset
- 1x USB Dongle
- 1x User Manual

Product Overview



Product Specification

Bluetooth Version: V5.2
Operation Range: 15 meters
Battery Capacity: 400mAh/3.7V
Charging Time: About 2 hours
Headset Dimensions: 173*173*75mm
CODEC Code: SBC, AAC
Bluetooth Protocols: HSP, HFP, AVRCP, A2DP
Working Time: About 60 hours (70% volume)
Talking Time: About 3.5 hours (70% volume)

** Some parameters may vary due to the environment and the mode of music played.*

How to use

A. Bluetooth Pairing and Connection

1. In power off status, press and hold the MFB for 3 seconds to enter pairing mode with LED Blue & Red flash alternately.

B. How to pair with a computer

Pair with a computer via the USB Dongle

1. Plug the USB Dongle into the USB port of your computer and wait for your computer to recognize it. The LED indicator on the USB Dongle flashes blue.
2. On your PC, select Start > Settings > Bluetooth & other devices > Add Bluetooth or other device > Bluetooth > Click on the model number of DY101 > Your device. Pairing is successful when you hear "Your headset is connected".

Pair with a computer via Bluetooth

1. On your device, press and hold the MFB button of DY101 for 3 seconds to enter pairing mode. The LED indicator flashes blue and red alternately. You will hear the voice guidance say "Pairing".
2. On your PC, select Start > Settings > Bluetooth & other devices > Add Bluetooth or other device > Bluetooth > Click on the model number of DY101 > Your device. Pairing is successful when you hear "Your headset is connected".

A window will pop up indicating the Bluetooth connection is complete. If your computer asks for a Bluetooth driver, contact your computer manufacturer.

Check the sound settings to make sure sound is played via the correct output and input

The microphone and the speaker of the headset may be disabled or not set as the default device on your computer. 1. Right-click the Speakers icon at the bottom right, then click Open Sound settings.
2. Select [DY101] as your output device (speaker).
3. Select [DY101] as your input device (Microphone).

Pairing

1. In power off status, press and hold the MFB for 3 seconds to enter pairing mode with LED Blue & Red flash alternately.


Search and Connection

1. In power off status, press and hold the MFB for 3 seconds to enter pairing mode with LED Blue & Red flash alternately.

Search and Connection

1. In power off status, press and hold the MFB for 3 seconds to enter pairing mode with LED Blue & Red flash alternately.

Bluetooth Headset



01

02

03

04

05

06

07

08

09


10

11

Package Contents

- 1x Headset
- 1x USB Dongle
- 1x User Manual

Product Overview



Product Specification

Bluetooth Version: V5.2
Operation Range: 15 meters
Battery Capacity: 400mAh/3.7V
Charging Time: About 2 hours
Headset Dimensions: 173*173*75mm
CODEC Code: SBC, AAC
Bluetooth Protocols: HSP, HFP, AVRCP, A2DP
Working Time: About 60 hours (70% volume)
Talking Time: About 3.5 hours (70% volume)

** Some parameters may vary due to the environment and the mode of music played.*

How to use

A. Bluetooth Pairing and Connection

1. In power off status, press and hold the MFB for 3 seconds to enter pairing mode with LED Blue & Red flash alternately.

B. How to pair with a computer

Pair with a computer via the USB Dongle

1. Plug the USB Dongle into the USB port of your computer and wait for your computer to recognize it. The LED indicator on the USB Dongle flashes blue.
2. On your PC, select Start > Settings > Bluetooth & other devices > Add Bluetooth or other device > Bluetooth > Click on the model number of DY101 > Your device. Pairing is successful when you hear "Your headset is connected".

Pair with a computer via Bluetooth

1. On your device, press and hold the MFB button of DY101 for 3 seconds to enter pairing mode. The LED indicator flashes blue and red alternately. You will hear the voice guidance say "Pairing".
2. On your PC, select Start > Settings > Bluetooth & other devices > Add Bluetooth or other device > Bluetooth > Click on the model number of DY101 > Your device. Pairing is successful when you hear "Your headset is connected".

A window will pop up indicating the Bluetooth connection is complete. If your computer asks for a Bluetooth driver, contact your computer manufacturer.

Check the sound settings to make sure sound is played via the correct output and input

The microphone and the speaker of the headset may be disabled or not set as the default device on your computer. 1. Right-click the Speakers icon at the bottom right, then click Open Sound settings.
2. Select [DY101] as your output device (speaker).
3. Select [DY101] as your input device (Microphone).

Pairing

1. In power off status, press and hold the MFB for 3 seconds to enter pairing mode with LED Blue & Red flash alternately.


Search and Connection

1. In power off status, press and hold the MFB for 3 seconds to enter pairing mode with LED Blue & Red flash alternately.

Search and Connection

1. In power off status, press and hold the MFB for 3 seconds to enter pairing mode with LED Blue & Red flash alternately.

Bluetooth Headset



01

02

03

04

05

06

07

08

09


10

11

Package Contents

- 1x Headset
- 1x USB Dongle
- 1x User Manual

Product Overview



Product Specification

Bluetooth Version: V5.2

<p>Charging Method</p> <p>Please charge the DY101 at once when the Red LED is lit up. Charging time is about 2 hours. Solid Red LED turn off and Blue LED turn on after fully charged.</p> <p>Tips:</p> <ol style="list-style-type: none"> Please charge the headset once every two months if you won't use it for a long time. The headphone need to be charged when prompts that the power is low, in order to ensure the charging quality, the earphone will automatically disconnect from the mobile phone when charging. 	<p>LED Indicator</p> <table border="1"> <thead> <tr> <th>Headset</th><th>LED Indicator</th><th>Status</th><th>Voice Prompt</th></tr> </thead> <tbody> <tr> <td>Power on</td><td>Blue LED flash 5 times</td><td>Power on</td><td>Power on</td></tr> <tr> <td>Pairing mode</td><td>Red LED on for first second</td><td>Enter pairing mode</td><td>Pairing</td></tr> <tr> <td>Pairing mode</td><td>Red & Blue LED flash alternately</td><td>Bluetooth connect success</td><td>Your headset is connected</td></tr> <tr> <td>Standby mode</td><td>Blue LED flash once every 10 seconds</td><td>Bluetooth disconnect</td><td>Your headset is disconnected</td></tr> <tr> <td>Playing Music</td><td>Blue LED flash twice every 10 seconds</td><td>Power off</td><td>Power off</td></tr> <tr> <td>Talking</td><td>Blue LED flash twice every 10 seconds</td><td>Mute on</td><td>Mute on</td></tr> <tr> <td>Delete pairing record</td><td>Red & Blue LED flash once at the same time</td><td>Mute off</td><td>Mute off</td></tr> <tr> <td>Charging</td><td>Solid Red LED</td><td></td><td></td></tr> <tr> <td>Full charged</td><td>Solid Blue LED</td><td></td><td></td></tr> <tr> <td>Low battery</td><td>Red LED flash</td><td></td><td></td></tr> </tbody> </table>	Headset	LED Indicator	Status	Voice Prompt	Power on	Blue LED flash 5 times	Power on	Power on	Pairing mode	Red LED on for first second	Enter pairing mode	Pairing	Pairing mode	Red & Blue LED flash alternately	Bluetooth connect success	Your headset is connected	Standby mode	Blue LED flash once every 10 seconds	Bluetooth disconnect	Your headset is disconnected	Playing Music	Blue LED flash twice every 10 seconds	Power off	Power off	Talking	Blue LED flash twice every 10 seconds	Mute on	Mute on	Delete pairing record	Red & Blue LED flash once at the same time	Mute off	Mute off	Charging	Solid Red LED			Full charged	Solid Blue LED			Low battery	Red LED flash			<p>Voice Prompt</p> <p>FAQs</p> <p>Q-How to reconnect and operate when failed to reconnect?</p> <p>A: When your PCs connected to your mobile phone successfully for the first time, it will search and reconnect the paired device automatically when power on. If the reconnection failed, please pair and connect again. The headset can be reconnected in 5 minutes. It will auto off automatically if disconnected over 10 minutes.</p> <p>Q-Is the active noise reduction technique applied in this headset?</p> <p>A: This headset is specially designed for call centre and has the noise reduction function for unplug calls, but it does not provide the local active-noise-reduction function.</p> <p>Q-How to delete pair record?</p> <p>A: In power-on status, long press VOLUME+ and MFB for 5 seconds to clear the headset's memory. The pair record was deleted. DY101 will not reconnect the device automatically. You need to connect it manually.</p> <p>Q-What's the password for pairing?</p> <p>A: Some devices require a password for pairing. Please try 0000, 8888, 1111 or 1234.</p> <p>Q-What devices could charge for the headset?</p> <p>A: Any car charger, power bank, PC etc. (DC 5V / above 500mA)</p>	<p>Q-What to do if I cannot turn the power on or fail to connect to devices?</p> <p>A: Please try to reset the headset. Connect the headset to the power supply. This will reset the headset and turn off the power, then turn on the power to test it. If you still cannot use it normally, you can ask customer service or manufacturer for technical support.</p> <p>Q-Why does the headset turn off automatically?</p> <p>A: If there is no connection for more than 5 minutes or the battery voltage is lower than 3.2V, the headset will automatically shut down. Please restart or charge the headset.</p> <p>Precautions</p> <p>Note on static electricity</p> <p>Static electricity accumulated in the body may cause mild tingling in your ears. To minimize the effect, wear clothes made from natural materials.</p> <p>Q-Can I use the headset to play music?</p> <p>A: The main application scenario of this headset is business calls and it focuses on the human voice frequency band. When used for music playback, the experience would be worse than that of a stereo headset.</p> <p>Q-How can I connect the headset to my computer?</p> <p>A: Plug the dongle to the USB port of your computer to connect the headset.</p>	<p>Limited 18-Month warranty</p> <p>What this warranty covers: SKY WING Consumer Electronics Co., Ltd SKY WING warrants to the original purchaser of this product that the product shall be free of defects in design, assembly, material or workmanship. What the period of coverage is: Skywing warrants the Product for 18 Months. What we like to do: correct problems? We do not warrant we will repair or replace an optionally defective product free of charge(except for shipping charges for the product). What is not covered by this warranty? All above warranties are null and void if the product is not provided to Skywing. For inspection upon Skywing's request to the sole expense of the purchaser. If Skywing determines that the product has been improperly installed/ altered in any way or tampered with, the Product Warranty does not protect against acts of God such as flood, earthquake, lightning, war, vandalism, theft, mold, water and fire arson/damage caused by negligence, damage due to low voltage disruption, s/brownouts or sagged/unauthorized power, or system equipment modification or alteration. Should any problem persist, please contact us. If you have any questions or problems concerning this headset that are not answered in this manual, please contact us by email at: DY_Business@outlook.com How to claim the warranty: Please contact retailers or visit DY_Business@outlook.com for more information. To extend the warranty period, please visit our website and register as a member within 1 month of purchasing the product.</p> <p>Disclaimer</p> <p>Every effort has been made to ensure that the information and procedures in this guide are accurate and complete. No liability can be accepted for any errors, omissions and we reserve the right to make changes without further notice to any products mentioned herein.</p> <p>Changes or modifications not expressly approved by the party responsible for compliance could void user's operation of the equipment.</p> <p>Bluetooth</p> <p>The Bluetooth mark and logos are registered trademarks owned by their proprietor and used by SKY WING under license. All other marks mentioned are those of their respective owners.</p> <p>FCC Statement</p> <p>This device complies with Part 15 of the FCC rules. Operation is subject to the following two conditions: 1) this device may not cause harmful interference, and 2) if interference is found, the user must stop using the equipment immediately.</p> <p>Correct Disposal of This Product</p> <p>(Waste Electrical/Electronic Equipment) This marking shows on the product or its literature, indicate that it should not be disposed with other household wastes at the end of its working life. To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate this from other types of waste and deliver it responsibly to an authorized collection point for the treatment of material resources. Household users should inform the retailer where they purchased the product, or their local authorities, of their intention to dispose of the goods and how they can take this item for environmentally safe recycling. Business users should refer to the applicable provisions in the terms and conditions of the purchase contract. This product should not be mixed with other commercial wastes for disposal.</p> <p>© 2016 SKY WING Consumer Electronics Co., Ltd All Rights Reserved. All Rights Reserved. Power Technology Co., Ltd Copyright © 2016</p> <p>FC Made in China</p>
Headset	LED Indicator	Status	Voice Prompt																																													
Power on	Blue LED flash 5 times	Power on	Power on																																													
Pairing mode	Red LED on for first second	Enter pairing mode	Pairing																																													
Pairing mode	Red & Blue LED flash alternately	Bluetooth connect success	Your headset is connected																																													
Standby mode	Blue LED flash once every 10 seconds	Bluetooth disconnect	Your headset is disconnected																																													
Playing Music	Blue LED flash twice every 10 seconds	Power off	Power off																																													
Talking	Blue LED flash twice every 10 seconds	Mute on	Mute on																																													
Delete pairing record	Red & Blue LED flash once at the same time	Mute off	Mute off																																													
Charging	Solid Red LED																																															
Full charged	Solid Blue LED																																															
Low battery	Red LED flash																																															

封底

成品尺寸： 70x80mm

材质：128g 双铜 4C印刷 双面印刷

过油 折叠 (手风琴式)