

# **User Manual**





### Caution

### Precautions and maintenance

- For indoor use only.
- $\bullet$  Do not expose the unit to moisture  $% \left( 1\right) =\left( 1\right) \left( 1\right) =\left( 1\right) \left( 1\right)$
- $\bullet$  Do not block the ventilation holes on the back of the digital photo frame.
- $\bullet$  Keep the digital photo frame out of direct sunlight.
- Do not dismantle the digital photo frame. There is a risk of electric shock and there are no user serviceable parts inside. Dismantling the digital photo frame will void your warranty.

#### Cleaning the LCD Screen

- Treat the screen carefully. Because the screen of the digital photo frame is made of glass and it
  would easily be broken or scratched.
- If fingerprints or dust accumulate on the LCD screen, we recommend using a soft, non-abrasive cloth such as a camera lens cloth to clean the LCD screen.
- Moisten the cleaning cloth with the gentle cleaning detergent and apply the cloth to the screen.

## WARNING:

Please power off the unit before inserting or removing a card or USB device. To avoid Causing any damage to the card/USB and the unit.

To reduce the risk of fire or electric shock, do not expose this frame to rain or moisture.  $\label{eq:condition}$ 

### Introduction:

- Thank you for the purchase of the digital photo frame. It is designed to allow quick and easy
  view of photos taken from your digital camera, mobile photo, or from a memory storage card.
- Please read this User Manual carefully to learn the correct way to use the digital photo frame.



## Features:

- 1. IPS screen and touch panel.
- 2. Support viewing pictures in thumbnail mode.
- 3. Support 1080P Full HD video display.
- 4. Sharing pictures, videos from FRAMEO APP.
- 5. Sturdy and removable bracket.
- 6. Built in G-Sensor support auto rotate function..
- 7. Support OTA version upgrade.

### Packaging Check List:

digital photo frame
 AC/DC adapter
 User Manual
 1 piece
 1 piece



## Contents

Contents		3
Getti	ing started	6
F	rameo app	6
Fram	eo quick setup	7
Start	using Frameo	8
C	Connecting a new friend	8
Navi	gating your Frameo	9
	Add friend	9
	Settings	9
	Power menu	9
	Hide photo	9
	Gallery	9
	Fit to frame/Fill frame	9
	Adjust photo	10
	Interacting with videos	10
	Power menu	10
Setti	ngs	11
N	Ny frame	11
	Frame name	11
	Frame location	11
	Set language	11
	Set time zone	11
	Enable/Disable 24-hour format	11
N	Manage photos	12
	Show/hide photos	12
	Delete photos	12



Import photos	12
Export photos	12
My Friends	13
Change options for a friend	13
Add person	13
Display	13
Brightness level	13
Sleep mode	13
Slideshow	13
Timer	13
Show caption	14
Fill frame	14
Photo display order	14
Autoplay	14
Video playback	14
Video volume	14
Wi-Fi	14
Wi-Fi details	15
Reset Wi-Fi	15
Notifications	15
Show notifications	15
Notification volume	15
Storage space	15
Backup	15
Network connection	15
New photos	15
New friends	15
Software update	15
Feature news	16



Backu	up and Restore	16
В	Backup frame to external storage (e.g. microSD card)	16
А	automatic backup	16
R	testore from backup	16
R	teset frame	16
Help		17
0	Open source libraries	17
SI	hare anonymous analytics data	17
G	Guide	17
About	ıt	17
А	android version	17
P	Peer ID	17
N	MAC	17
Fr	rameo version	17
U	Jp time	17
C	check for update	17
В	seta program	18
Privacy		18
Support		18
Warranty, Compliance, Support and Safety information		18



## **Getting started**

Congratulations with your brand new Frameo photo frame!
If you are new to using Frameo then start by following the Frameo quick setup or follow the onscreen guide when powering it on for the first time.

Once you have set up your Frameo frame, you can start connecting it to your friends and family.

### Frameo app

To send photos to your frame, use the Frameo app for iOS or Android.



Find the Frameo app by scanning this code:



For Android: Search for "Frameo" on <u>Google Play</u>.

For iOS: Search for "Frameo" on App Store.



## Frameo quick setup

When starting your frame for the first time, you will need to setup the frame.

- Select a language. This will be the language used on the Frameo.
   Connect your frame to the internet by connecting it to a Wi-Fi.
   Frameo may ask you to update to the latest version. It is recommended to update your frame before continuing if asked to.
   Enter your name, and the location where you have placed your frame e.g. "John Doe" and "Living room", "Kitchen" or "Office". Finally set the timezone if not already correct.



## **Start using Frameo**

Next step is to connect Frameo with your friends and family by providing them with a code from your frame.

If you want to be able to send photos to the frame yourself, start by downloading the app for iOS or Android on App Store or Google Play. Then use the code to connect your frame and app as described below.

### Connecting a new friend

Make sure that your friend has downloaded and installed the Frameo app.

Click the add friend icon on your frame \*\*. A dialog will appear showing a connection code, which is valid for 12 hours.

Now share this code in whatever fashion you prefer e.g. SMS, E-Mail, IM, phone call, to your friend.

Once your friends have added the code in their Frameo app, they will automatically appear on your frame and be able to send you photos.

Read chapter <u>Change options for a friend</u> to *allow* connected friends, to retrieve and share the connection code via the smartphone app.





## **Navigating your Frameo**

Swipe left or right to go through your photos.

To access the menu, simply tap once on the screen.



In the menu you will find the most used features.

\* Add friend
This will generate a code that you can share with your friends and family so they can connect and send photos to your frame.

## Settings

Opens the Settings.

## U Power menu

Opens the Power menu

## Nide photo

Hides the current photo. This means that the photo will no longer be shown in the slideshow. If needed the photo can be shown again through the settings menu.

## **Gallery**

Opens a gallery which allows for easy and fast navigation through your photos.

## Fit to frame/Fill frame

This toggles how the photo is shown.

The Fill frame option is the default. The photo is scaled so that it fills the whole screen. It will be centered around what is selected as the most important part. See the first picture below.

Fit to frame will make sure that the entire photo is shown on the screen. See the second picture







Allows you to adjust the position of the photo in the frame for an even better fit. Here you can also use to rotate C your photo.

Interacting with videos
When a video is shown two additional controls are shown. One for play/pause of the video and one to control the volume level for video sounds.



Press to open the volume slider. Use the slider to adjust the volume level for video sounds.

Pressing • will mute the video while pressing • will unmute the video.



Tap the power icon  ${}^{\mbox{$0$}}$  to access the power menu. Here you can power off using  ${}^{\mbox{$0$}}$  , restart your frame using  ${}^{\mbox{$0$}}$  or enter sleep mode using  ${}^{\mbox{$0$}}$  .





NB. Make sure to always use the power off button on the device or in the power menu to turn Frameo off. Never disconnect power when Frameo is running.

## Settings

Through the settings, you can personalize your frame to your needs.

 $Changes \ the \ name \ of \ your \ frame. \ This \ is \ also \ the \ name \ that \ connected \ friends \ and \ family \ will \ see$ in their list of connected frames in the smartphone app.

Frame location
Changes the location of your frame. This is the location displayed on your friends' and family's list of connected frames which can help to distinguish frames from each other.

**Set language**Sets the language used on the frame.

**Set time zone**Sets the time zone used on the frame.

## Enable/Disable 24-hour format

Enables, and disables, 24-hour time format.



### Manage photos

In the manage photos menu you can see how many photos are on your frame and the storage they use. You can also see the amount of storage left available on your device for storing new photos.

### Show/hide photos

Select which photos to hide by tapping them. Hidden photos will NOT be deleted from your frame and you can always select them to be shown again.

Use to hide or show all photos.

#### Delete photos

Select photos that you want to permanently delete from your frame by tapping the photo.

Use to select or deselect all and to permanently delete the selected photos.

#### Import photos

Allows you to import photos from an external storage (e.g. microSD card).

Before you try to import photos, make sure you have an external storage (e.g. microSD card) inserted into your frame with the photos you wish to import.

Start by selecting the photos that you want to import onto your frame. Once selected tap the import button  $\stackrel{\$}{=}$  to start the import process.

Use  $^{\square}$  to select or deselect all photos on the external storage (e.g. microSD card).

Use = to set the sort order of photos before import and to order by ascending/descending.

It is currently not possible to add a caption or define the most important part of the photo when using the import function. An alternative for this is to add yourself to your friend list and send the photos using the app.

### Export photos

Allows you to export photos from the frame to external storage (e.g. microSD card).

The export function will export all photos on the frame as well as profile pictures.



### My Friends

This list contains all the connected friends that are allowed to send photos to your frame.

#### Change options for a friend

Click the options icon to open the friend options menu. From here you can allow / disallow if a friend may share the code to the frame. If this is enabled the friend can retrieve and share the code to the frame from his/her app.

From the options menu you can also delete a friend, by pressing the DELETE FRIEND button. This will remove the friend from the list and thereby remove their permission to send photos to the frame. You will then be asked to confirm the removal and if you would like to remove all photos previously received from this friend.

### Add person

To allow a new person to send you photos, simply tap the add friend button  $^{*\pm}$  and share the presented code in whatever way you prefer.

#### Display

### Brightness level

Adjust the brightness level of the screen.

## Sleep mode

Frameo offers a sleep mode which turns off the screen to reduce power consumption. The default setting is to turn off the screen at 23:00 and turn on the screen again at 07:00. To change this just set the sleep mode start/end time.

Your frame is not powered down or in standby, so you will still be able to receive photos during sleep mode.

### Slideshow

### Timer

Set the duration that a photo should be displayed before showing the next photo.



#### Show caption

Sets whether or not to display the captions that your friends have sent with the photo. Check to display captions. Uncheck to hide captions.

#### Fill fram

Sets the default frame photo setting. Check to set default to fill which makes the photos fit the device screen according to the most important part of the photo. Uncheck to make the photo fit inside the screen of the device, adding blurred bars on the sides or top/bottom

### Photo display order

Sets the order in which your photos are displayed on the frame.

- By date: Photos are shown newest to latest.
- Shuffle: Photos are shuffled and shown in a random order.

#### Autoplay

Enables/disables autoplay of videos in the slideshow. Videos can always be manually started regardless of this setting.

### Video playback

Determines how videos should be played when autoplay is enabled.

- Loop videos: The video will loop until the slideshow timer is up.
- Play once: The video will play once and show it's thumbnail until the timer is up.
- Play once and continue: The video will play once and continue to the next photo, or video, once it completes.

### Video volume

Adjust the volume level for video sounds on the frames.

### Wi-Fi

Set which Wi-Fi the frame connects to. If you are connecting to a network with a captive portal

Connection status will say that Wi-Fi login is required and show . Tap this to open a login screen where you can enter credentials to access the network.



### Wi-Fi details

Use to show details about the current connected Wi-Fi.

#### Reset Wi-Fi

Use to delete all Wi-Fi information and restart your frame.

### Notifications

#### Show notifications

Enables/disables whether notifications are shown in the slideshow (e.g. when a new photo is received).

### Notification volume

Adjust the volume level for notification sounds.

### Storage space

Enables/disables notifications shown when frame storage is low.

### Backup

Enables/disables notifications shown if automatic backup has failed.

### Network connection

Enables/disables notifications showing network connection status.

### New photos

Enables/disables notifications shown when receiving new photos.

### New friend:

Enables/disables notifications shown when new friends are added.

### Software update

Enables/disables notifications shown when a software update has been installed.



#### Feature new

Enables/disables notifications shown when new exciting features are added.

#### Backup and Restore

### Backup frame to external storage (e.g. microSD card)

Tap to make a backup of your photos, friends and settings. The time of the latest successful backup is also displayed here.

Any existing backup on the external storage will be overridden!

#### Automatic backup

If checked, your frame will automatically take a backup within 30 hours of receiving new photos or making changes to your frame.

#### Restore from backup

Before you attempt to restore your frame, start by confirming that your backup is up-to-date. This is done by confirming the date under "Backup frame to external storage (e.g. microSD card)". If e.g. the last backup is too old or if no backup is made, then press the "Backup frame to external storage (e.g. microSD card)" button to make a new backup.

NB: To keep both the old and the new frame operational at the same time after restoring from backup, please make sure that both frames are updated to the latest version beforehand.

If you wish to restore a backup on a frame that has already been setup, then you must first reset the frame. This is done by pressing the "Reset frame" button. This will delete all data on the Frameo and reset the Frameo to its setup screen.

On the setup screen you can select the "Restore from backup" button which will restore your frame according to the backup.

If the "Restore from backup" button isn't visible, then confirm that the external storage (e.g. microSD card) is correctly mounted.

### Reset frame

Removes all data from your frame.

This will permanently remove all your photos, friends/connections and settings.



### Open source libraries

Opens a list of open source libraries used in the app and their licenses.

### Share anonymous analytics data

Sharing anonymous analytics data helps us tremendously to improve the Frameo software. We understand if you do not wish to share this data with us. Keep it checked if you wish to help us improve Frameo. Set unchecked to deny the sharing of anonymous analytics data.

#### Guide

Opens the quick start guide, that was shown when you first started the frame.

### Android version

See what version of Android that is installed on the frame.

Peer ID This is a unique ID for your photo frame. When contacting our support, please provide this ID with

### MAC

Shows the MAC address of your frame.

### Frameo version

Shows what version of the Frameo software is currently installed on your frame.

### Up time

Shows how long the photo frame has been powered on.

### Check for update

Check if an update is available for your frame.



Beta program
If checked the device will join the Beta program where it will receive updates more frequently and before normal release devices.

## Privacy

For more information regarding privacy, please visit <a href="http://privacy.frameo.net">http://privacy.frameo.net</a>

### Support

Please visit <a href="http://frameo.net/helpcenter">http://frameo.net/helpcenter</a> for FAQ, support and to provide feedback.

## Warranty, Compliance, Support and Safety information

For more information regarding warranty, hardware compliances, support and safety please refer to the material included in the package.

#### Warning statement

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- -Reorient or relocate the receiving antenna.
- -Increase the separation between the equipment and receiver.
- -Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- -Consult the dealer or an experienced radio/TV technician for help. This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator & your body.