

Operation “Wash Cycle”

Step:

1. Press the one touch button
2. Observe that the green LED came on, and Yellow LED began to blink
3. Wash Cycle has started
Wash cycle should be ~7 minutes long

At the end of the wash cycle unit will beep 5 times and leave the green LED blinking.



To place unit into sleep mode after wash cycle is done:

Step:

1. press the Play/Pause button
 1. Green LED should turn off

Operation “Reboot”

Step:

1. Press the “green leaf” Reset, Cups, Program button

You should observe the green LED coming on, yellow LED blink 3 times, then eventually beep and go into sleep mode

A reboot takes about 8 seconds



Operation “Reboot” with RFID Communication

Step:

1. Place RFID tag in the center of the HR logo on top cover.
2. Press the “green leaf” Reset, Cups, Program button.

You should observe the green LED coming on, yellow LED blink 3 times, then eventually beep and begin to blink LED's signaling the number of wash tokens loaded onto the unit (green LED = 100's, Yellow = 10's, red = 1s)

To get out of the “Token Read Out” you must press the “green leaf” Reset, Cups, Program button with no token tag near unit.

A reboot takes about 8 seconds

