

User's Manual

Guoya Bluetooth Headset E702

Features

1. Broadcom BCM20771 chip; support EDR 3.0 and 2.1+; ARM Cortex-M3 processor
2. RF Perf: +8dBm (Tx), -91dBm (Rx sensitivity)
3. A2DP 1.2, SBC decoder
4. Dual-channel stereo output
5. Voice reminder in English
6. Voice commander in English ("Answer": answer the call; "Ignore": ignore the call)
7. High-quality 96dB SNR DACs; support sample rate 44.1kHz and 48kHz
8. Integrated SmartAudio speech enhancement algorithms
9. Built-in ADC monitoring battery power, temperature and charging voltage
10. Support quick charging and auto power-saving mode

Profile

1. Previous;
2. Next;
3. Play/Pause/Resume Play/On/Off/Pair;
4. Volume +;
5. Micro USB Port (for charging);
6. (Audio) Line-in Port;
7. State Indicator;
8. Volume -;
9. State Indicator;



Keys

① : press it to play/pause/resume play the song or pair the headset; long press it to turn on/off the headset; when there is an incoming call, press it to answer the call and press it again to hang up; press and hold it for 2s to redial the last number you dialed.

▶ : press it to play the next song.

◀ : press it to play the previous song.

▼ : Long press it to reduce the volume.

▶ : Long press it to increase the volume.

Turn On/Off E702

1. Long press  for 2s to turn on the headset and enter the bluetooth mode by default with the indicator flashing quickly for three times in blue.
2. Long press  for 4s to turn off the headset with the indicator flashing quickly for three times in red.

Operations in Bluetooth Mode

Pair E702

Note: please pair the headset with your phone before using it to make or answer calls. (“Pair” is to associate the bluetooth headset with your phone and enable your phone to save the unique ID of the headset. When the headset is successfully paired with your phone, it will be auto connected to your phone.)

1. Put the headset and phone together (spacing $\leq 0.5\text{m}$) and make sure the headset is turned off. Long press  until the indicator flashes alternately in red and blue. Then you can proceed with pairing.
2. Enable the “Search Device” function of your phone (refer to the User’s Manual of your phone). The searching result “E702” will be shown in the device list.
3. Select and confirm “E702” in the device list.
4. Input the pairing code “0000” and confirm to pair the headset. In case of successful pairing, the headset will enter the standby state with the indicator flashing slowly in blue.
5. Now you can use the headset to make or answer calls. Note: as for some phone models, the bluetooth headset will be auto connected to the phone again next time when you turn on the phone.

Use E702 to Make/Answer Calls

1. When there is an incoming call, press  to answer it.
2. Press  again to hang up. If the other person hangs up, you do not need to press .
3. Press and hold  for 2s to redial the last number you dialed.
4. If there is an incoming or outgoing call when you play a song, the song will be paused until you or the other person hangs up.

Play/Pause

When you play a song, press  to pause and press it again to resume. (If you enable the line-in mode when you play a song, you will listen to both the song and line-in sound. You can press  to pause the song to listen to the line-in sound only.)

Previous

In song playing state, press  to play the previous song.

Next

In song playing state, press  to play the next song.

Volume -

In song playing state, press  to reduce the volume.

Volume +

In song playing state, press  to increase the volume.

Standby

When you turn on the bluetooth headset, it will be auto connected to the phone associated with it last time and enter the standby state.

Operations in Line-in Mode

Connect the bluetooth headset to the computer through the line-in cable to listen to the songs or make voice chats on the computer.

Note: when you insert the line-in cable to the line-in port, the bluetooth mode will be auto disabled; to enable the bluetooth mode, please remove the line-in cable and restart the headset.

About Charging

1. Fully charge the headset before the first use.
2. In case of low voltage, the indicator will flash quickly in red. The headset will be auto turned off if not charged in time.
3. Charge the headset through the charger.
4. The indicator will flash in red in charging and go out when charging is finished.

Note: you can also use the charging cable to connect the headset to the USB port of the computer for charging.

Charge E702:

The headset is equipped with a rechargeable battery. Please fully charge it before the first use.

1. Insert one end of the charger into the micro USB port and the other end into the power socket.

* Charging is finished when the indicator goes out.

* It will take about 3 hours for charging.

2. Remove the charger.

* It is for reference only if the salesclerk tells you to charge the headset for 5 hours for the first three times and 2 hours later.

Store E702:

- * Turn off the power before storing the headset.
- * Do not expose the headset to a temperature higher than 40°C (like in car or under direct sunlight), or its surface could be damaged and battery life shortened.
- * Do not expose the headset or its accessories to rainwater or any other liquid.

Basic Operations:

I. Turn On/Off E702:

Turn on: press and hold  for 4s until the indicator flashes for four times in blue.

Turn off: press and hold  for 4s until the indicator flashes for twice in blue.

II. Explanation for Indicator:

If the indicator flashes every 8s in blue, the headset is in working state: in a call, up to 4 hours.

If the indicator flashes every 3s in blue, the headset is in standby state: waiting calls, up to 70 hours.

If the indicator flashes in red, the headset supports call duration of 1 minute only and needs to be charged.

* The actual call duration and standby duration depend on the service condition and your phone model.

III. Pair E702:

In case of successful pairing, there will be a specially encoded wireless link between the headset and your phone.

1. Make sure the headset is turned off.

2. Press and hold  for 8s until the indicator remains in blue.

3. Enable the bluetooth function of your phone to search devices.

4. Your phone will auto find Samsung WEP200 and ask you whether to start pairing or not.

Please select "Yes" or "Ok".

5. Input the pairing code "0000" and select "Yes" or "Ok".

IV. Voice Dialing:

You need to enable the voice recognition/dialing function first.

1. Press , and you will hear a voice message indicating the activation of the voice dialing function.

2. Say the name of the other person.

* This function depends on your phone model.

V. Redial Last Number:

If the voice recognition/dialing function is disabled, double-press , 2s each.

If the voice recognition/dialing function is enabled:

1. Press  to activate the voice dialing function and press it again to cancel this function.
2. Press and hold  to check the call history.
3. Then long press  to dial the last number you dialed or received.

VI. Hang Up:

Press  to hang up.

VII. Answer Calls:

- * Press  to answer the call.
- * When answering a call with the phone, you can press  to answer it with the headset.

VIII. Ignore Calls:

When there is an incoming call, you can long press  for 2s to ignore it. This function depends on your phone model.

IX. Adjust Volume:

Press  to increase the volume or press  to reduce the volume.

Enhanced Function:

If there is another incoming call when you are making or answering a call, long press  for 2s to answer the second call and long press it for 2s again to answer the first call. Some phone models may not support this function.

Turn On/Off Microphone:

Long press  to turn on/off the microphone.

FCC STATEMENT:

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

Warning: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna.

Increase the separation between the equipment and receiver.

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician for help.

FCC Radiation Exposure Statement:

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment.