## *Using your KéNero*

✓ On rear of Thunderbird locate the pairing push button as marked

✓ On iPhone go "*Settings*" set "*Bluetooth On*"!

✓ Depress pairing button – Front Blue Light Flashes

✓ Select Thunderbird in *"Other Device"* set *"Pair"* see *"Connected"*

✓ Go to Notes app & check typing input

IPH6/6S SMART KEYBOARD
NOT FOR RESALE

PAIRING LOCATION

KéNero Features

Protective Case Fitting.
> The Thunderbird will snap fit to the Front & Rear of the included protective case.
> The case offers a rail system to easy slide the Keyboard on the front of the iPhone.
> The back rail system offers a Thunderbird storage location when not in use.

Screen Protection.
> A glass screen protector is included to be fitted to the iPhone using the Thunderbird.
> If you already have a screen protector fitted then keep the provided one as a spare.
> If fitting the supplied screen protector then follow the fitting instructions.

Function Fn Key.
> Single depression of Fn key sets next character to a symbol then reverts back to normal input.
> Fast double depression of the Fn key sets and locks input to numerical and symbol only.
> A fast double depression sets the Fn lock OFF mode.

Shift Key.
> Single depression of Shift key sets next input to capitalise then reverts to normal input.
> Fast double depression of the Shift key sets and locks character input to all capitalise input.
> A fast double depression sets the Shift lock OFF.

Power and Charging.
> The Thunderbird contains a rechargeable battery and a USB charging cable.
> Charge the Thunderbird using any USB charging port.
> On connecting to a USB port a Red light will be on at the most Selfie left key.
> Full charge takes around 45 mins with the Red light going to off when finished.
> When connected a % battery status in iPhone Notifications is shown (~ 10 seconds).
> Low battery at ~ 20% the Blue light will momentarily flash when using.

Quick Tips.
> Your iPhone unlock P/W – If a numeric p/w, set Function Lock to ON and start with a RETURN key.
> The keyboard layout is optimised for US QWERTY layout – Use US English Keyboard on iPhone
> Thunderbird snaps on and slides up and down the front of the iPhone supplied case.
> The keyboard can act as a remote Selfie Shutter in Camera and Video Mode (up to 10 meters).
> Thunderbird wake-up is by depression of any key.
> Fitting the Thunderbird onto the rear lower position of the case will instant sleep Thunderbird.
> Removing the Thunderbird from the case rear will wake Thunderbird and connect to iPhone.
> If asleep for inactivity, fitted to the rear of case - any key is needed to wakeup on removal.
> If backlight is on an independent 20 second off timer takes place for no keyboard activity.

KéNero Smart Commands

Note: The Smart Commands are dependant on the application running
     The backlight has a 20 second sleep timer for no keyboard activity
     The Thunderbird will sleep after 50 seconds of no keyboard activity

Capitalised a Character - Hold the required key down for a short duration to input uppercase

SPACE + SPACE Double space adds a period with capitalisation to end a sentence

CMD + SPACE   Toggle keyboard languages or Emoji choice as in the iPhone keyboard set up

CMD + Fn Key (Right) (one click) Go to iPhone HOME screen
CMD + Fn Key (Right) (two click) Go to iPhone apps screen
CMD + Fn Key (Right) (hold duration) Open Siri (Another click of CMD + Fn Right "Siri Off")
CMD + Fn Key (Left) Blank and Lock screen
CMD + Shift Key (Right) iPhone screen brightness up
CMD + Shift Key (Left) iPhone screen brightness down

CMD + A   Select All
CMD + C   Copy highlighted text
CMD + V   Paste copied text
CMD + Z   Undo last action
CMD + M   Hide / Show New Email – Email App

CMD + B   Set Bold text On/Off
CMD + I   Set Italic text On/Off
CMD + U   Set Underline text On/Off

CMD + D   (hold duration) Send Email
CMD + A   (hold duration) Attach File to Email
CMD + N   New Note, New Email
CMD + R   Reply to Email
CMD + R   (hold duration) Reply to All Email
CMD + F   (hold duration) Forward Email

CMD + DEL Delete all text to beginning of line
Fn + ☼   Turn Backlight On / Off
⌨   Hide or Show iPhone virtual keyboard
Shift + $ Input UK £ currency symbol

Shutter Key Shutter Key when in Camera App or Video Start /Stop
     Ringer Up – In Home Screen
     Volume Up – In Music/Video App

Shift + Shutter Key Ringer Down – In Home Screen
      Volume Down – In Music/Video App

FCC Warning

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions

(1) this device may not cause harmful interference, and

(2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

—Reorient or relocate the receiving antenna.

—Increase the separation between the equipment and receiver.

—Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

—Consult the dealer or an experienced radio/TV technician for help.

—The minimum separation generally be used is at least 20 cm.

FCC RF warning statement: The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.