

<p>Contents</p> <p>Thank you 1</p> <p>Introduction to Bluetooth Wireless Communication Technology 1</p> <p>Check the Items 1</p> <p>Product Specification, Parameters and Descriptions 1</p> <p>1. Produce Overview 2</p> <p>2. Charge the Headset 2</p> <p>3. Pair, Switch on off the Headset 3</p> <p>4. Pair the Headset with a Bluetooth Cell Phone 3</p> <p>5. Pair the Headset with Computer 4</p> <p>6. Pair the Headset with Multiple Devices 4</p> <p>7. Wear the Headset 4</p> <p>8. Play Music 5</p> <p>9. Make and Receive Calls through the Headset 5</p> <p>10. Meanings of Indicator Light and Warning Tones 6</p> <p>11. Toxic and Hazardous Substances or Elements 6</p>	<p>Thank you!</p> <p>Thank you for using Our Bluetooth wireless Stereo Headset . Please read this guide carefully before use.</p> <p>Introduction to Bluetooth Wireless Communication Technology</p> <p>Bluetooth is a wireless technology supporting short distance communication of devices (usually within 10m). It enables the wireless information to exchange among IT digital devices such as Bluetooth cell phones, bluetooth headsets and laptops, etc. "bluetooth" technology can effectively simplify the communication between devices, and through it the data transmission is consequently more rapidly and efficiently.</p> <p>Check the Items</p> <p>1. Headset body</p> <p>2. USB cable</p> <p>3. User Guide</p> <p>4. PC cable</p> <p>Product Specification</p> <p>Version of bluetooth</p> <p>Bluetooth v2.1 +edr</p> <p>Bluetooth protocol</p> <p>hfpv1.5/a2dpv1.2/avrcp v1.0</p> <p>Output power</p> <p>class II</p> <p>Effective distance</p> <p>10m</p> <p>*Working hours of the head</p> <p>Listening to music: about 8 hours</p> <p>Calling: about 9 hours</p> <p>Standby time of the headset</p> <p>About 250 hours</p> <p>Charging input voltage</p> <p>DC:2.8-4.2VA</p> <p>Charge time of the headset</p> <p>About 2.5 hours</p> <p>*Note:</p> <p>Due to the different pairing devices and using environment, the working hours of the headset are different.</p>	<p>1. Product Overview</p> <p>2. pair, Switch on or off the Headset</p> <table border="1"> <thead> <tr> <th>Function</th> <th>Operation</th> <th>indicator light</th> <th>warning tone</th> </tr> </thead> <tbody> <tr> <td>pairing mode</td> <td>Press and hold the multifunction key for about 5 seconds and release it until the alternative flash of red and green lights.</td> <td>Alternative flash of red and blue light</td> <td>one long "whistle", followed by two continuous short "honk"</td> </tr> <tr> <td>switch on the headset</td> <td>Press and hold the multifunction key for about 3 seconds and release it until the flash of the blue light</td> <td>Rapid flash of the blue light for four time</td> <td>one long "whistle"</td> </tr> <tr> <td>switch off the headset</td> <td>Press and hold the multifunction key for about 5 seconds and release it until the flash of the red light</td> <td>Rapid flash of the red light for four time</td> <td>one long "whistle"</td> </tr> </tbody> </table> <p>Note:</p> <p>The pairing mode lasts for 2 minutes. The headset will automatically switch to standby mode if no pair is made with any devices over 2 minutes.</p> <p>If no device connection is made 5 minutes the headset is switched on, the headset will automatically be switched off to save power.</p> <p>3. Pair the Headset with a computer</p> <p>First please make sure the computer is with Bluetooth function. Otherwise, you need to buy a stereo Bluetooth adapter. the pairing procedures for computer with Bluetooth function are follows:</p> <ol style="list-style-type: none"> 1.Keep the distance between the headset and the computer with in 1m. 2. Make the headset enter into the pairing mode (please refer to "how to enter the pairing mode"). 3. Active the Bluetooth option of the computer, click and select " add device" ,-- click "next" select "Tzumi BT" --click "next" --and click "close" . 4. After the pairing and connection are successful, the blue light of the headset will flash quickly twice every four seconds. <p>Notes:</p> <p>This pairing is based on Windows VISTA and Windows7 operation systems. Other versions should be operated according to system hints;</p> <p>If the Bluetooth version of the computer is lower than V2.1, the pairing "oooo" password will be required.</p> <p>4. Pair the Headset with Multiple Devices</p> <p>This headset can set up connection with two Bluetooth devices at the same time at most, and one of the connections is for hands-free profile(hfp). For multiple devices pairing and connection, please refer to the following procedures:</p> <ol style="list-style-type: none"> 1. First pair the headset with the Bluetooth transmitter (please refer to the "pairing with Bluetooth cell phone"). 2. Switch off the Bluetooth transmitter. 3. Pair and connect the headset with Bluetooth cell phone (refer to the "pairing with Bluetooth cell phone") 4. Switch on the transmitter again, and the transmitter will automatically initiate the connection to the headset. <p>The pairing procedures are as follows:</p> <ol style="list-style-type: none"> 1. Keep the distance between the cell phone and the headset with in 1m. 2. Make the headset enter into the pairing mode (please refer to the above mentioned "pairing mode") 3. Active the bluetooth function of the cell phone, to search for the Bluetooth devices. After finishing the search, select "Tzumi BT" in the device list displayed. 4. Press "yes" or "enter" key to confirm the successful pairing in accordance with the hint of the cell phone. 5. After the successful connection, the blue light of the headset will flash quickly twice every four seconds. <p>Cell phone which support both HSP and A2DP protocols can set up HSP and A2DP connection with the headset if it is started again.</p> <p>5. Make and Receive Calls through the Headset</p> <p>First, please make sure the bluetooth function is available for the cell phone. Specific pairing procedures shall be different depending on different cell phone. For detailed information, please read the Cell Phone User Guide concerning the pairing guidance of Bluetooth devices.</p> <p>6. Charge the Headset</p> <p>This headset has an internal rechargeable battery. The battery must be fully charged before you can start using the headset.</p> <p>By use of travel charger</p> <ol style="list-style-type: none"> 1. Connect the charger to the standard AC power socket. 2. Connect one end of the USB cable to the charger, and the other end to the charge interface of the headset. 3. Charge time with travel charger: about 2.5 hours. <p>By use of USB charging cable</p> <ol style="list-style-type: none"> 1. Connect the USB charging cable to the USB interface of the computer. 2. Connect the other end of the USB cable to the charger of the headset. 3. Charge time with travel charger: about 2.5 hours <p>Note:</p> <p>After a successful pairing devices will memorize each. Therefore, no pairing will be needed next time.</p> <p>Cell Phone will Bluetooth version lower than V2.1 will require for password or PIN code entry: "oooo"</p> <p>7. Wear the Headset</p> <p>Flexible design is used for the head are of this headset. Please adjust it according to the actual situation. On the headset, the mark "L" and the mark "R" correspond to the left ear and the right ear, respectively. Please wear the headset on the head according to the corresponding marks.</p>	Function	Operation	indicator light	warning tone	pairing mode	Press and hold the multifunction key for about 5 seconds and release it until the alternative flash of red and green lights.	Alternative flash of red and blue light	one long "whistle", followed by two continuous short "honk"	switch on the headset	Press and hold the multifunction key for about 3 seconds and release it until the flash of the blue light	Rapid flash of the blue light for four time	one long "whistle"	switch off the headset	Press and hold the multifunction key for about 5 seconds and release it until the flash of the red light	Rapid flash of the red light for four time	one long "whistle"	<p>8. Play Music</p> <p>When the headset connects with computer with support A2DP, a bluetooth cell phone or bluetooth transmitter, you can enjoy the wireless music through the headset.</p> <p>9. Meanings of Indicator Lights and Warning Tones</p> <table border="1"> <thead> <tr> <th>Indicator</th> <th>Headset Status</th> </tr> </thead> <tbody> <tr> <td>Alternative flash of red and blue light</td> <td>Pairing status</td> </tr> <tr> <td>Blue light turns red light when the battery is low</td> <td>Status (Not connected with device)</td> </tr> <tr> <td>Blue light turns red light when the battery is low</td> <td>Status (Already connected with device)</td> </tr> <tr> <td>Blue light turns red light when the battery is low</td> <td>Calling</td> </tr> <tr> <td>Blue light turns red light when the battery is low</td> <td>Comming</td> </tr> </tbody> </table> <p>10. Meanings of Indicator Lights and Warning Tones</p> <table border="1"> <thead> <tr> <th>Indicator Light</th> <th>Headset Status</th> </tr> </thead> </table>	Indicator	Headset Status	Alternative flash of red and blue light	Pairing status	Blue light turns red light when the battery is low	Status (Not connected with device)	Blue light turns red light when the battery is low	Status (Already connected with device)	Blue light turns red light when the battery is low	Calling	Blue light turns red light when the battery is low	Comming	Indicator Light	Headset Status
Function	Operation	indicator light	warning tone																														
pairing mode	Press and hold the multifunction key for about 5 seconds and release it until the alternative flash of red and green lights.	Alternative flash of red and blue light	one long "whistle", followed by two continuous short "honk"																														
switch on the headset	Press and hold the multifunction key for about 3 seconds and release it until the flash of the blue light	Rapid flash of the blue light for four time	one long "whistle"																														
switch off the headset	Press and hold the multifunction key for about 5 seconds and release it until the flash of the red light	Rapid flash of the red light for four time	one long "whistle"																														
Indicator	Headset Status																																
Alternative flash of red and blue light	Pairing status																																
Blue light turns red light when the battery is low	Status (Not connected with device)																																
Blue light turns red light when the battery is low	Status (Already connected with device)																																
Blue light turns red light when the battery is low	Calling																																
Blue light turns red light when the battery is low	Comming																																
Indicator Light	Headset Status																																
<p>11. Toxic and Hazardous Substances or Elements</p> <table border="1"> <thead> <tr> <th colspan="6">Toxic and Hazardous Substances or Elements</th> </tr> <tr> <th>Part name</th> <th>Lead(P)</th> <th>mercury(Hg)</th> <th>cadmium(Cd)</th> <th>hexavalent chromium(Cr⁶⁺)</th> <th>polybrominated diphenyl ethers(PBDE)</th> </tr> </thead> <tbody> <tr> <td>Parts with board assembly</td> <td>✗</td> <td>✗</td> <td>✗</td> <td>✗</td> <td>✗</td> </tr> <tr> <td>Plastic cement</td> <td>✗</td> <td>0</td> <td>0</td> <td>✗</td> <td>✗</td> </tr> <tr> <td>Metal</td> <td>✗</td> <td>✗</td> <td>✗</td> <td>✗</td> <td>0</td> </tr> </tbody> </table> <p>*Note:</p> <p>The content of the hazardous substances below is limited specified in SJ/T1136-2006: The content of the hazardous substances exceed the limit specified in SJ/T1136-2006. The information provided in this table is based on the supplier internal testing results of "Tzumi". Under current technology, some hazardous substances contained in some parts has been controlled by "Tzumi" to the minimum. Tzumi will keep making efforts to reduce using of various substances or elements through technology improvement.</p> <p>Environmental protection use period of the products shall be 10 years, and its mark is shown in the right figure. Environmental protection use period of replaceable parts or batteries may be different from that of the product. Environmental protection use period shall be valid only under normal using conditions specified in the user guide.</p>	Toxic and Hazardous Substances or Elements						Part name	Lead(P)	mercury(Hg)	cadmium(Cd)	hexavalent chromium(Cr ⁶⁺)	polybrominated diphenyl ethers(PBDE)	Parts with board assembly	✗	✗	✗	✗	✗	Plastic cement	✗	0	0	✗	✗	Metal	✗	✗	✗	✗	0			
Toxic and Hazardous Substances or Elements																																	
Part name	Lead(P)	mercury(Hg)	cadmium(Cd)	hexavalent chromium(Cr ⁶⁺)	polybrominated diphenyl ethers(PBDE)																												
Parts with board assembly	✗	✗	✗	✗	✗																												
Plastic cement	✗	0	0	✗	✗																												
Metal	✗	✗	✗	✗	0																												

FCC Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This device and its antenna(s) must not be co-located or operating in conjunction with any other antenna or transmitter.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules.

These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.