User manual

Bluetooth Headset BK 830

Pairing

- Before using the headset for the first time, you must pair it with a Bluetoothenbaled handset.
- To pair your headset with an additional handset, the headset must be placed in Pairing Mode.
- There are 2 Pairing Mode Methods with the BK 830.

Easy Pairing (First Time Pairing)

- 1.The BK 830 off hold the phone more than 4 seconds.
- 2. Using your handset, find the Bluetooth Menu and "search for "or "add" new devices.
 - Select"LG BK 830"form the list of devices and pair it with your handset.
- 3.If asked for the handset supports Secure Simple Pairing(SSP), you will not need to enter Pass/PIN code.
 - Once pairing has completed successfully, you will hear "your headset paired".
- 4.Some handsets might ask for permission to access the phone's contact list.If you receive a message from your handset,please select"OK"or "Allow access"
 - The BK 830 will automatically turn off if not paired within 3 minutes.

Manual Pairing(Pairing with another phone or re-pairing)

- With the Power off,press the CALL button and move the power Switch to the 'ON'side at the same time for 1 second.
- When the headset enters Pairing Mode, the LED indicator will show a solid blue light. After the procedure repeat Easy Pairing steps 2 through 4.

Multi-connection

Advanced Multipoint

The BK 830 is capable of having two devices connected to the headset at the same time. This will give you the freedom of using call waiting between calls on both of your connected phones. Connection

- Pair the headset with one of your Bluetooth-enabled handset.(per the pairing instructions on page 2).
- Turn off the headset.
- With the Power off, press the CALL button and move the power switch to the 'ON' side at the same time for 1 second to enter Manual Pairing mode.

- Now,pair and connect the headset with your other Bluetooth-enabled handset.(this will be your primary handset).
- Once this handset is paired and connected, go back and connect the originally paired handset to the headset. This will now be your secondary handset.
- * NOTE; When the BK 830 is connected to two handsets at the same time (Multipoint), the headset calling functions will with the primary handset.
- * NOTE; In case of failure to connect to the primary phone through Easy Pairing, BK 830 will enter pairing mode.

Auto Reconnect

- If the BK 830 is turned off (either accidentally of intentionally)while connected to a handset, the headset and handset will disconnect. The headset and handset will automatically reconnect when the BK 830 is turned back on while in range.
- Secondary handset need to be connected Via selecting "LG BK 830" from the list of devices at Bluetooth menu.

Out of range

- If the paired devices are separated by a range of 10 meters(33 feet)or more, the headset and handset will disconnect and BK 830 will vibrate to alert.
- If the headset and handset do not automatically reconnect when they are back within the required range, briefly press the CALL button on the BK 830 to reconnect manually.
- It is possible to use these functions only when your handset supports them. For further information about using these features, please consult your handset's user manual.
- While in multi-connection and streaming, non-streaming paired device which is out of range will be disconnected and BK 830 will alert once and not try to reconnect.

Controls

Power on / Power off

Hold down the "key" more than 4 seconds.

Volume Control

- Brigfly press the VOLUME button.

The external speaker

- Through the speaker/headset switches, switch to the external speaker, in order to easy to use, when the speaker work, headset or normal work

Charging

- When the charger is connected, with the power on or off ,the headset will turn
- While charging ,the LED indicator will show a solid red light.
- When charging is complete, the LED indicator will turn off.

Bettery status check

- Press and hold the VOLUME DOWN button for 1 second.
- There are 3 levels of battery status
- BK 830 battery status indicator will appear on the iPhone screen.

Low battery

- An announcement will be made once every 2 minutes.
- If the battery is not charged, the headset will turn off.

Answering a call / Ending a call

- When there is an incoming call, the headset will ring and vibrate.
- Briefly press the VILUME DOWN button to stop vibration.
- Briefly press the CALL button.

Last number redial

- Press and hold the CALL button for 1 second to activate "Last Number Redial". The headset will beep, and call the last number dialed.

Making a call

If you make a call from the handset, the call will(subject to phone settings)
automatically transfer to the headset. If the call is not automatically
transferred, you can manually transfer the call by press and hold VOLUME UP
button for 3 seconds.

Voice dialing

-Briefly press the call button to activate "Voice Command". Note: If the handset does not support Voice Dialing, it is possible that performing this action will activate Last Number Redial.

Transferring a call

 While on a call on your handset,press and hold VOLUME UP button for 3 seconds to transfer the audio either from headset to handset or from handset to headset.

Call waiting

- Answer a second call without hanging up the first call by pressing the CALL button for 1 second(you will hear a beep). Press the CALL button for 1 second to turn to the original call.
- Briefly press the CALL button to terminate the active call or both calls at once.(subject to handset's support)

Call Reject

- Press the CAll button for 1 second when the handset rings.

Mic Mute

 Press and hold the VOLUME UP and VOLUME DOWN buttons simultaneously for 1 second to mute/unmute the Mic during conversation.

Audio streaming

- PLAY:Briefly press the PLAY/PAUSE Button.
- PAUSE:Briefly press the PLAY/PAUSE button.
- STOP:Press and hold the PLAY/PAUSE button.
- NEXT SONG:Briefly press the FF button.
- PREVIOUS SONG:Briefly press the REW button.

- FAST FORWARD: Press and hold the FF button.
- REWIND: Press and hold the REW button.

Equalizer

- While playing music, press and hold VOLUME UP and VOLUME DOWN buttons simultaneously for 1 second to switch between EQ's (Bass Boost(Default) → Normal→Treble Boost)
- EQ is not changed if your hadset supports apt code and is enbaled.
- The bass coming from the speakers can vary as a result of the size of the Earbud that is being used.

apt

- BK 830 features apt technology that ensures audio content transmitted over Bluetooth is instant and crystal-clear.
- apt is automatically enabled as long as the source device supports it.

Precautions

Do not drop the unit from high places.

Do not modify, repair, or take apart.

Do not expose directly to water, alcohol, benzene, etc, for cleaning.

Do not expose directly to flammables.

Do not place or keep the unit near flammables.

Keep unit away from humidity & dust.

Do not place heavy objects on the unit.

Only use the headset with an original HANKER charger, otherwise it may be damaged.

- Changes or modifications not expressly approved by the party responsible for compli-ance could void the user's authority to operate the equipment.
- There is a risk of explosion if the battery is replaced by an in correct type.
- Dispose of used batteries according to the instructions.
- The neck strap is made of a shape memory alloy. However, bending the neck strap repeatedly is not recommended.

Declaration of Confirmation

FCC NOTICE TO USERS:

This device complies with part 15 of the FCC rules.

Operation is subject to the following two conditions.

- (1)This device may not cause harmful interference and
- (2)This device must accept any interference received, including interference that may cause undesired operation.

IMPORTANT NOTE:

To comply with the FCC PF exposure compliance requirements ,no change to the antenna or the

device is permitted. Any change to the antenna or the device could result in the device exceeding the RF exposure requirements and void user's authority to operate the device.

CE NOTICE TO USERS:

Hereby, LG Electronics Inc. declares that this BK 830 is in compliance with the essential requirements and other relevant provisions of Directive 1995/5/EC.

Addition Information

1. Radio frequency exposure

This Bluetooth Headset,BK 830,is a radio transmitter and receiver. When is operation,it communicates with a Bluetooth? equipped mobile device by receiving and transmitting radio frequency (RF) electromagnetic fields(microwaves)in the frequency range 2.4 to 2.4835 GHz. The output power of the Radio Transmitter is low,0.001 watt. Your Bluetooth? Headset is designed to operate in compliance with the RF exposure guidelines and limits set by national authorities and international health agencies when used any compatible HANKER Electronics mobile phone.

2. Potentially explosive atmoshpere

Turn off your electronic device when in any area with a potentially explosive atmosphere. It is rare, but your electronic device could generate sparks. Sparks in such areas could cause an explosion or fire resulting in bodily injury or even death. Areas with a potentially explosive atmosphere are often, but not always, clearly marked.

3. Battery information

A rechargeable battery has a long service life if treated properly. A mew battery or one that has not been used for a long period of time could have reduced capacity the first few times it is used. Do not expose the battery to extreme temperatures, never above $+60^{\circ}$ (140° F) or under -20° (-4° F). For maximum battery capacity, use the battery in room temperature. If the battery is used in low temperatures, the battery capacity will be reduced. The battery can only be charged in temperatures between $+10^{\circ}$ ($+50^{\circ}$ F) and $+45^{\circ}$ ($+113^{\circ}$ F). For your safety, do not remove the battery incorporated in the product.

If you need to replace the battery,take it to the nearest authorised HANLER Electronics service point or dealer for assistance.

4. Recycling the battery in your Bluetooth Headset

The battery in your Bluetooth Headset must be disposed of properly and should never be placed in municipal waste. The HANKER Electronics service partner removing battery will dispose of it according to local regulations.

5. Conditions

- The warranty is valid only if the original receipt issued to the original purchaser by the dealer, specifying the date of purchase and serial number, is presented with the product to be repaired or replaced. HANKER Electronics reserves the right to refuse warranty service if this information has been removed or changer after the original purchase of the product from the dealer.
- If HANKER Electronics repairs or replaces the product, the repaired or replaced

product shall be warranted for the remaining time of the original warranty period or for ninety(90)days from the date of repair, whichever is longer. Repair or replacement may involve the use of functionally equivalent reconditioned units. Replaced parts or components will become the property of HANKER Electronics.

- This Warranty does not cover any failure of the product due to normal wear and tear,or due to misuse,including but not limited to use in other than the normal and customary manner,in accordance with instructions for use and maintenance of the product.Not does the warranty cover any failure of the product due to accident,modification or adjustment,acts of God or damage resulting from liquid.
- This warranty does not cover product failures due to improper rapair installations, modifications or service performed by a non-HANKER Electronics authorized person. Tampering with any of the seals on the product will void the warranty.

Limited Warranty

SUBJECT TO THE CONDITIONS OF THIS LIMITED WARRANTY,LG ELECTRONICS WARRANTS THIS PRODUCT TO BE FREE FROM DEFECTS IN DESIGN.MATERIAL AND WORKMANSHIP AT THE TIME OF ITS ORIGINAL PURCHASE BY A CONSUMER,AND FOR A SUBSEQUENT PERIOD OF ONE(1)YEAR.SHOULD YOUR PRODUCT NEED WARRANTY SERVICE,PLEASE PETURN IT TO THE DEALER FROM WHOM IT WAS PURCHASED OR CONTACT YOUR LOCAL HANKER ELECTRONICS CONTACT CENTER TO GET FURTHER INFORMATION.

Important safety information

Avoiding hearing damage

Permanent hearing loss may occur if your use your Handsfree car kit at a high volume. Set the volume to a safe level. You can adapt over time to a higher volume of sound that may sound normal but can be damaging to your hearing.

If you experience ringing in your ears or muffled speech, stop listening and have your hearing checked. The louder the volume, the less time is required before your hearing could be affected. Hearing experts suggest that to protect your hearing:

- Limit the amount of time you use Headset at high volume.
- Avoid turning up the volume to block out noisy surroundings.
- Turn the volume down if you can't heat people speaking near you.

Please refer to your handset user guide for more information on how to adjust listening levels on your handset

Using Headset safely

Use of Headset to listen to music while operating a Vehicle is not recommended and is illegal in some areas. Be careful and attentive while driving. Stop using this device if you find it disruptive or distracting while operating any type of vehicle or performing and other activity that requites your full attention.

Warning

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment.