


ユーザーマニュアル


ケイデンスセンサーの取り付け

注：使用される前にプラスチック製バッテリーカバーを取り除いてください。マグネットは不要です。



Pro Speed Sensor

1. ラバーシムとセンサー底部の位置を合わせます。
2. 付属のOリングを用いて、Pro Speed Sensor をハブにしっかりと取り付けます。Oリングを、センサーが動かないよう、ハブの周りにきつくフィットさせてください。



Pro Cadence Sensor

1. ラバーシムとセンサー底部の位置を合わせます。
2. 付属のOリングを用いて、Pro Cadence Sensor をクランクアーム内側にしっかりと取り付けます。Oリングを、センサーが動かないよう、クランクアームの周りにきつくフィットさせてください。

はじめに

両センサーは、デュアルチャンネルのBluetooth 出力に対応します。これにより、2つのデバイスと同時に接続でき、ヘッドユニットと屋内型スマートトレーナーを一度にペアリングさせる場合に便利です。


Pro Cadence SensorとPro Speed Sensorは、Lezyne GPS デバイスや一般的なフィットネスアプリとペアリングができ、Bluetooth対応のスマートフォンと互換性があります。

Pro Cadence SensorおよびPro Speed Sensorを使用するには、これらのセンサーを接続させたいデバイスとペアリングさせます。両センサーを取り付けるホイールおよびまたはクランクアームは、センサーを起動させる際に数回回転させる必要があります。ペアリング情報について詳しくは、接続させるデバイスのユーザーマニュアルをご覧ください。

ホイール周長の入力

Pro Speed Sensorのみ: 速度を最も確実に読み取れるよう、お使いのホイールの周長を接続したデバイスに入力してください。ホイール周長の入力方法に関して詳しくは、Pro Speed Sensorとペアリングさせるデバイスのユーザーマニュアルを参照してください。

バッテリーの交換方法



注：使用される前にプラスチック製バッテリーカバーを取り除いてください。

1. 硬貨でバッテリーカバー ● を反時計方向に回して開けてください。
2. CR2032 ● バッテリーを交換してください。密閉用Oリング ● が溝内にあり、防水できていることを確認してください。
3. カバーを押し戻し、時計方向に回して閉めてください。

センサーとLezyne GPSとのペアリング

- Lezyne GPS
 - ▼ Main Menu
 - ▼ Sensors
 - ▼ Speed
 - ▼ Scan BTLEor
 - ▼ Cadence
 - ▼ Scan BTLE

仕様

Pro Speed Sensor Pro Cadence Sensor

サイズ：幅32.8x高さ36x奥行き14mm
重量：17g (バッテリー込み)
防水性：1m / 3ft
バッテリー：CR2032 (3ボルト)
およそのバッテリー寿命：250時間
システムの互換性：Bluetooth

FCC ID: 2AD4S-PROSV104
IC ID: 20084-PROSV104

さらに詳しくは

Lezyne製品に関して詳しくは、www.lezyne.comをご覧ください。

Wheel Size and Circumference

The wheel size can be found on the side of the tire. This is not exact list but a general guide. More specific wheel calculators can be found online. Or you can manual measured http://www.bikecalc.com/wheel_size_math

Wheel	Tire	CM
700c/29er	20mm	208
	23mm	209.9
	25mm	211.1
	28mm	213
650c	20mm	192
	23mm	193.8
	25mm	195.1
	28mm	197
20 inch Recumbent	20mm	154.3
	23mm	156.1
	25mm	157.4
	28mm	159.3
	32m	161.8
	35m	163.7
	1.00 inch	157.6
	1.25 inch	161.6
	1.50 inch	165.6
	1.75 inch	169.6
650b/27.5	1.90 inch	172
	1.95 inch	172.8
	2.00 inch	173.6
	20mm	196
	23mm	197.9
	25mm	199.2
	28mm	201.1
	32mm	203.6
	35mm	205.5
	38mm	207.3
	44mm	211.1
	50mm	214.9
	56mm	218.7
	1.00 inch	199.4

Wheel	Tire	CM
650b/27.5	1.25 inch	203.4
	1.50 inch	207.4
	1.75 inch	211.4
	1.90 inch	213.8
	1.95 inch	214.6
	2.00 inch	215.4
	2.10 inch	217
	2.125 inch	217.4
	2.20 inch	218.6
	2.25 inch	219.4
26 inch mtb	2.30 inch	220.2
	2.35 inch	221
	2.40 inch	221.6
	35mm	197.6
	38mm	199.5
	44mm	203.3
	50mm	207
	56mm	210.8
	1.00 inch	191.6
	1.25 inch	195.6
	1.50 inch	199.6
	1.75 inch	203.5
	1.90 inch	205.9
	1.95 inch	206.7
	2.00 inch	207.5
	2.10 inch	209.1
	2.125 inch	209.5
	2.20 inch	210.7
	2.25 inch	211.5
	2.30 inch	212.3
	2.35 inch	213.1
	2.40 inch	213.7

PRO SPEED SENSOR

PRO CADENCE SENSOR

NOTE

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
—Reorient or relocate the receiving antenna.
—Increase the separation between the equipment and receiver.
—Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
—Consult the dealer or an experienced radio/TV technician for help.

Labeling Requirement Notice:

Any Changes or modifications not expressly approved by the grantee of this device could void the users authority to operate the equipment This device complies with Part 15 of the FCC Rules and Industry Canada license-exempt RSS standards). Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation of the device.

Canada, Industry Canada (IC) Notices:

This device complies with Canada licence-exempt RSS standard(s).
Operation is subject to the following two conditions: (1) this device may not cause interference and (2) this device must accept any interference, including interference that may cause undesired operation of the device.
Canada, avis d'Industrie Canada (IC) Cet appareil est conforme avec Industrie Canada exceptes de licence RSS standard(s). Son fonctionnement est soumis aux deux conditions suivantes: (1) cet appareil ne doit pas causer d'interférence et (2) cet appareil doit accepter toute interférence, notamment les interférences qui peuvent affecter son fonctionnement

Radio Frequency (RF) Exposure Information

The radiated output power of the Wireless Device is below the Industry Canada (IC) radio frequency exposure limits.
The Wireless Device should be used in such a manner such that the potential for human contact during normal operation is minimized. This device has also been evaluated and shown compliant with the IC RF Exposure limits under mobile exposure conditions, (antennas are greater than 20cm from a person's body).

Informations concernant l'exposition aux frequences radio (RF)

La puissance de sortie émise par l'appareil de sans fil est inférieure a la limite d'exposition aux frequences radio d'Industrie Canada (IC). Utilisez l'appareil de sans fil de façon a minimiser les contacts humains lors du fonctionnement normal.
Ce peripherique a également ete évalué et demontre conforme aux limites d'exposition aux RF d'IC dans des conditions d'exposition a des appareils mobiles (antennes sont supérieures a 20 cm a partir du corps d'une personne).

SIMPLIFIED EU DECLARATION OF CONFORMITY

The simplified EU declaration of conformity referred to in Article 10(9) shall be provided as follows:
Hereby, Lezyne declares that the radio equipment of type, Information Technology Equipment, is in compliance with Directive 2014/53/EU.

FCC RF EXPOSURE MPE WARNING

This equipment must be installed and operated in accordance with provided instructions and the antenna(s) used for this transmitter must be installed to provide a separation distance of at least 20 cm from all persons and must not be co-located or operating in conjunction with any other antenna or transmitter. End-users and installers must be provide with antenna installation instructions and transmitter operating conditions for satisfying RF exposure compliance. Do not operate or store the GPS unit below -20° Celsius (-4° Fahrenheit) or above 60° Celsius (140° Fahrenheit). Storing the GPS unit in the direct sunlight or inside a parked vehicle can violate the temperature maximums. Battery life and battery health may be adversely affected at temperature extremes.