

User manual

Bluetooth Watch

Thank you for choosing our **SMART WATCH** devices. You can read the manual, a comprehensive understanding of the use of equipment, in fact, with a taste of the function and simple method of operation.

This device is used as long as the brand of intelligent machines are adapted to use intelligent machines can synchronize phonebook and provides a variety of useful features and services to facilitate your work and leisure activities in the smart machine operation.

The Company reserves the right to make any prior notice in the case of the contents of this manual for the right to amend, without notice.

When you get **SMART WATCH**, and install the APK program on the smart phone, realize SMS, and other instant messaging reminders.

APK Access mode 1 : Download the smart phone two-dimensional code scanner



APK Access mode 2: Downloaded from Web address

IP Address:  <ftp://211.144.196.251>

User: Smart watch

Password: Smart watch

Smart phone after installing APK, and smart phone to **SMART WATCH** connection ,First, open the Bluetooth feature on your smart phone, search **SMART WATCH** Equipment, smart phone will send "Bluetooth pairing request" and then press "confirm" ,After pairing

SMART WATCH will prompt " ** (Connected) " while there will be a standby interface "  " icon indicates a successful connection has been your smart phone, connect after the success you can follow the instructions below **SMART WATCH** operations:

Device explain:



一、Key Description: There are four buttons on the left upper and lower volume keys, page up and down keys, top right of the Enter key, the answer key, bottom right of the switch button, back button, hold button.

二、Standby screen displays: Time, day and date as the right




三、the main menu: Standby screen, press the Enter key to enter the main menu interface. Main menu interface: In this interface adjustment. Page up and down keys to select a different function, and then press the ENTER button to enter.


Main Menu Features:



1、Bluetooth : Turn on Bluetooth after the following



two menus, such as the right



(1) **Bluetooth settings**

1) Press the Enter key can be turned on or off Bluetooth, **SMART WATCH** Bluetooth turned off by default, Bluetooth is turned on if the status bar of the main menu screen will display a small icon "x";

2) The machine can be searched can be turned on or off, default is on.


3) The local device name display: **SMART WATCH**



(2) **Bluetooth sync**

1) You can search for Bluetooth devices;

2) Display can be connected Bluetooth device name, press the Enter key can connect / disconnect, remove, and help functions.



(3) **Anti lost**

Smart Watch will send alarm after leaving the mobile phone a certain distance, Open this function will see the following menu.

1) Enable

2) Set distance~can be long distance, mid-distance, close distance.



2、Phone book : If there is no sync phone book, press the Enter key displays "not connected", such as the right



, Now press the Enter key for phone book access, prompt "Loading", such as




the right , Loaded successfully, you can view the phone book down keys. Successful synchronization phone book, press the Enter key to enter the contact list screen: Tap the contact can be a phone call functionality.



3. Remote Notification : Enter the remote notification feature, you can see the latest mobile phone synchronization information, this feature only shows the latest news.



4. Bluetooth music : If a Bluetooth connection with



(1) another phone, press the Enter key to enter the interface. In this interface, the OK button to play or pause music, volume key up or down when the music player can switch songs; To adjust the volume, you can press the Back key to return to the idle screen

(2) Then press the volume key up or down to adjust the other smart phones connected thereto adjusting the volume also can increase or decrease the volume of **SMART WATCH** play music, and vice versa if not even prompt box will pop up on the "not connected."

NOTE: To ensure consistency with other phones Media Audio connection in order to play music!



5. Information : If the remote device supports the MAP protocol (such as Samsung GLAXY 2, millet, 2, etc.), press the Enter key to enter, you can see the In box and Sent two menu two menu message list; if the remote phone does not support MAP protocol (go to the In box and Sent messages prompt "remote device does not support MAP"), the remote device is installed "Bluetooth notice" APK, remote notification view the latest messages.



6. Call records : Press the Enter key to see: missed calls, dialed calls, received calls, and all calls, such as the

right



10. Toolbox : Open the Toolbox has the following



menus, such as the right



(1) Language Settings: Enter this interface, Support Chinese and English native default is Chinese, press the Enter key to select to select the appropriate language. Press the Return key to exit this function:

(2) Time setting: There are two ways to set the time




- 1) Press the Enter key to enter this interface, Switch button to jump to different locations numeric setting, each location can press the volume keys up or down to adjust the specific numbers, setting completed, press the Enter key to save the settings.
- 2) Installed on the smart machine "Bluetooth notification" APK, when connected to the phone dialer, the dialer client will prompt "with the remote device's date and time synchronization?", Then press the Enter key can be time synchronized to the phone dialer side , so there is no need to manually adjust the time.

(3) find your phone function:



Just choose the find your phone function on the watch, the phone will alarm and sound, let you find your phone.




(3) **Date Set:** There are two ways to set the date



- 1) Press the Enter key to enter this interface, Press the switch button to jump to different locations numeric setting, each location can press the volume keys up or down to adjust the specific numbers, setting completed, press the Enter button to save the settings;
- 2) Installed on the smart machine "Bluetooth notification" APK, when connected to the phone dialer, the dialer client will prompt "with the remote device's date and time synchronization?", Then press the Enter key can be synchronized to the phone dialer end date , so no need to manually adjust the date.

(4) **Ringtone:** enter ringtones function, vibration and ringtone 1-4 to select, simply choose the ringtone press the Enter key after the prompt above the "Saved" is set successfully.



(5) **Stopwatch** : Press OK to start timing or pause, press the return key to exit this function.


(6) Alarm: Press the Enter key to enter the alarm interface




, Alarm clock can be set to 5, press the volume up and down keys to select an option, press the Enter key to enter this list



1) Alarm status: Press the Enter key to enter the selection and preservation of the interface, the default is off, press the Enter key



you can choose to open or close, as the right , Setup is complete press the Enter key to save the settings, such as the right



(7) Power saving mode: use "confirmation" open or close

(8) About Bluetooth Watch: Enter this function to display **SMART WATCH** version information.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will

not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.