



# **Contents & Information**

#### WHAT'S IN THE BOX














- 2). Wireless USB Receiver
- 3). USB C Charging Cable 1.64 ft
- 4). User Guide

## **FEATURES**

- 1) Speaker Rated Input Power:10mw
- 2) Speaker Diameter: 50mm 3) Speaker Impedance: 32Ω±15%
- 4) Speaker Sensitivity: 103dB±3dB
- 5) USB C Charging cable: 1.64 ft
- 6) Wireless USB & Bluetooth Dual Mode Connection 7) Three Gaming EQ Pre-set
- 8) Cooling Gel-Infused Ear Cushions
- 9) Rechargeable with up to 26 hours of playtime per charge 10) Flip-to-mute bomm microphone
- 11) Connect via low-latency USB wireless receiver and Bluetooth Wireless Technology




SCAN HERE FOR MORE

PRODUCT INFORMATION AND LEAVE US A REVIEW!

## **Overview**

#### **Get To Know Your Gaming Headset**




50mm Gaming Driver ) Flip-Up to Mute Microphone

- 3) Adjustable Headband 4) Soft Cooling Gel Earpads 5) Power ON/OFF Button
- 6) Volume up/dowm Wheel 7) Wireless USB & Bluetooth Switch Mode Button
- 8) EQ Pre-set Switch Button 9) LED Indicator 10) USB-C Charging Port
- 11) Wireless USB Receiver 12) USB-C Charging Cable 1.64ft

# **Get to Know Panel**



- Charging LED Light status: Steady Red light During device search: Flash Red and Blue. After successful pairing: Steady Blue Light.
- When the headset powers off: Flash Twice Red Light



When the dongle is in Pairing: Flash Red and Blue. After the dongle successfully pairs: ·Steady Blue (Microphone Unmuted) ·Steady Red (Microphone Muted)

When the headset microphone is muted: Steady Red Light. When the headset microphone is active: Steady Blue Light.

# **Safety Precautions**

### **↑** CAUTION

Lithium-ion Battery Lithium-ion batteries, if used improperly, can be dangerous to users. Exercise caution when handling them, especially in adverse environments.

## **⚠ WARNING**



This symbol on the product or its packaging indicates that this product must not be disposed of with your other household waste. Instead, it is your responsibility to dispose of your waste equipment by handing it over to a designated collection point for the recycling of waste electrical and electronic equipment. The separate collection and recycling of your waste equipment at the time of disposal will help conserve natural resources and ensure that it is recycled in a manner that protects human health and the and it is lecycled in a maintee that products fundam health and ute provironment. For more information about where you can drop o your waste for recycling, please contact your local authority, or where you purchased your product.

# **Compliance Statement for** onn Wireless Gaming Headset

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Important: Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment


Note: This equipment has been tested and found to comply with the limits for a Class B digital Note: Insequipment has been tested and round to Compry with the limiter of a class is objected device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installetion. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

—Reorient or relocate the receiving antenna.

- Increase the separation between the equipment and receiver.
   Connect the equipment into an outlet on a circuit different from that to which the receiver is
- Consult the dealer or an experienced radio/TV technician for help.

# Let's Get Started!

# 1.First Time Set-up



as the audio source.

After a successful connection, the dongle LED will turn blue. Power ON/OFF

e headset defaults to USB Mode every time it is powered on

The dongle LED light will Flash Red and Blue when plugged in. Press and hold the Power button for 3 seconds. The LED light Make sure your headset is in USR MODE to use the USR-Receive


## 2.Connect Headset to the PC

If the headset doesn't automatically connect to your computer and play sound, please manually set the audio source. 1. Go to PC Settings, then select System






2. When the USB dongle is plugged into the Device, go to PC Setting > Sound > Volume Mixer.



3. Select both the Output Device and Input Device as "onn Wireless Gaming Headset

#### 3. Connect Headset to the PlayStation



When the USB Donale Receiver Plugged into the PlayStation Device.

Go to PlayStation Settings > Device > Select Audio Devices.

- Select both the Output Device and Input Device as "onn Wireless Gaming Headset."
- Set Output to Headset to ALL Audio
- Set Volume Control (Headset) level to maximum

Adjust your microphone levels by going to Settings > Sound > Microphone > Adjust Mic Level > Microphone Level

## 4. Bluetooth Set-up



Switch to Bluetooth Mode Press and hold the Bluetooth Button for 3 seconds to Bluetooth Mode.

EQ PRESET

Default

Chat Mode

Game Mode

1st

2<sup>nd</sup>

3rd

The LED will alternatively flash blue and red.

Open Bluetooth setting on your device and select "onn. Wireless Gaming Headset" to get it connected. After successful connection, you will hear "Bluetooth Connected"

The same operation can beapplied to connect with Bluetooth-enabled devices such as PC/Mobile/Console

3 Press the Blue button to enter Bluetooth pairing mode.


# **Operation** 1. Microphone Mute



· Microphone Status: Muted.

2. Microphone Down (Active Mode): · Microphone Status: Active.

When answering a call, press the Bluetooth button and flip down the microphone to



## 2. Select Different EQ Pre-Set



Switch to Default Gaming EQ -Balanced Gaming SoundPress the Mode Button once you will hear the sound prompt "Standard Mode"

Switch to Chat Mode EQ -Human Voice EnhancementPress the Mode Button once you will hear the sound prompt "Chat Mode".

Switch to FPS Gaming EQ -Full Frequency EnhancementPress the Mode Button once you will hear the sound prompt "Game Mode".

# Warranty

#### 1 YEAR LIMITED WARRANTY COVERING DEFECTIVE PARTS

Contact Manufacturer for Additional Information

This warranty is non- · All warranty coverage applies transferable and does not only if barricade is used in the cover failures due to misuse United States. of improper installation or maintenance.

> For product assistance & missing or replacement part s: WE CAN HELP

> > 7 DAYS/WEEK

7:00am - 9:00pm CST

IMPORTANT SAFETY INFORMATION. 1-888-516-2630 PLEASE READ AND

KEEP FOR FUTURE REFERENCE.

THIS GUIDE

CONTAINS

Find more at Walmart.com