

## RF EXPOSURE EVALUATION

### 1. PRODUCT INFORMATION

|                     |                   |
|---------------------|-------------------|
| Product Description | Bluetooth Speaker |
| Model Name          | BT081B            |
| FCC ID              | 2AI7L-BT081B      |

### 2. EVALUATION METHOD

According to 447498 D01 General RF Exposure Guidance v05

The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at test separation distances  $\leq$  50 mm are determined by:

$[(\text{max. power of channel, including tune-up tolerance, mW}) / (\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] \leq 3.0 \text{ for 1-g SAR and } \leq 7.5 \text{ for 10-g extremity SAR.}$

Where  $f(\text{GHz})$  is the RF channel transmit frequency in GHz

Power and distance are rounded to the nearest mW and mm before calculation

### 3. CALCULATION

$$P_t = 3.604 \text{ dBm} = 2.30 \text{ mW}$$

The value of the Maximum output power  $P_t$  is referred to the test report of the CFR47 §15.247.

The result for RF exposure evaluation SAR=  $(2.30 \text{ mW} / 5 \text{ mm}) \cdot [\sqrt{2.441 \text{ (GHz)}}] = 0.72 < 3.0$  for 1-g SAR and  $\leq 7.5$  for 10-g extremity SAR.

### 4. CONCLUSION

The SAR evaluation is not required.