

D06

True Wireless Stereo Bluetooth Headset

User Manual

(Binaural calls)

Preface

Thank you for purchasing the D06 True Wireless Stereo Bluetooth Headset. This manual will help you how to use your Bluetooth headset. Before using a Bluetooth headset, you must first understand and become familiar with the Bluetooth capabilities of your phone.

Product parameters

Bluetooth Protocol: A2DP/HFP/AVRCP/SPP

Bluetooth distance: 10 meters

Rechargeable battery capacity: 400 mA

Headphone battery capacity: 50 mA

Headphone charging time: 1 hour

Charger output voltage: 5V

Transmission frequency band: 2.4GHz----2.48GHz

Parts List:

Product illustration:

- 1: Charger
- 2: Micro USB
- 3: Charger LED indicator
- 4: Headphone charging case
- 5: Hidden button
- 6: Headphone LED indicator
- 7: Microphone
- 8: Charging metal contacts

Wear illustration

For the best audio experience, please do try each different size earbuds, When worn properly, feel tight, comfortable and stable inside the ear. When

used outdoors,

Please place the phone on the left side and the large ear cap will have a better bass effect.

Note: When wearing the ear cap, please press the ear cap to the tightest position, otherwise the headset may not be able to perfectly put into the charging case or affect charging.

Binaural operation

1: put in the earphone

Place the headset into the charging case. The headset indicator lights up in red to indicate that it is charging. After it is full, the blue light goes off after 5 seconds. About 45 minutes can be filled when the headphones are completely without electricity. If the charge capacity is insufficient, please charge the charging case first.

2: Remove the headset

After removing the L and R headsets from the charging case, the headset will automatically power on, wait for about 10 seconds, and automatically complete the connection between the headsets. After completing the connection, Lheadphone indicator lights alternately red and blue, and the R headset indicator light goes out.

Note: After you remove the headset, if the headset does not start up automatically, it is possible that during the removal process, repeated contact with the charging contacts will not result in the automatic turn on. It can be manually turned on or re-put into the charging case and removed again. The process of removing the headphones should be as steady as possible.

3: Open the mobile phone Bluetooth, click the pairing name D06-L, complete the pairing and start using.

4: Follow-up use.

After the pairing with the mobile phone is completed for the first time, subsequent use only needs to pick out the headset and automatically connect back to the mobile phone.

5: If the L and R headphones lose connection and only one ear has sound, please pair the L and R headphones first. The operating mode is: Off state, the left and right earphones are long pressed at the same time until the red and blue lights flash alternately, then release the buttons, waiting for about 5 seconds, the red and blue lights flash alternately, Pairing between headphones

is completed when when the R headphone light goes out. Then link the phone.

Monaural operation method

1: When using the L-headset alone, if the L-headphone has been paired with the phone before in the binaural mode, you only need to turn on the L-headphone to connect to the phone.

If the L headset was not paired with the phone before, remove the headset and wait for 10 seconds. When the red and blue lights are blinking, turn on the Bluetooth and select D06-L to pair.

2: When using the R headphones for the first time, remove the headphones and wait for 10 seconds. When the red and blue lights flash alternately, turn on the Bluetooth of the mobile phone and select D06-R to pair.

When using the R headset for the second time, remove the R headset and wait for 5-10 seconds to automatically connect to the phone.

Functional section

Boot: Remove the auto power on, or press the button for 3 seconds to turn on the red light flashes.

Turn off: Put yourself in the charging compartment to shut down, or press the button for 5 seconds to turn off the power when the red light is on.

Play music: click the button once.

Pause Music: Click the button once.

Answering the call: Click the button once when you call.

Hang up: Click the button once when talking.

Rejected: Press the button for 1 second.

Voice switch: Press 3 times when the red light starts flashing.

Last number replay: Double-click the button twice in standby mode.

Next song: In multimedia mode, double-click the button.

Clear pairing: Press and hold down the button for 15 seconds when the earphones power is off.

Charging instruction

Headphone section: When the power is low, the red light of the headphone indicator flashes.

During the charging process, the red light of the headphone indicator lights up.

When fullcharging, the red light of the headphone indicator flashes and then goes off.

Charging compartment: When the power is low, the blue lights of lights at No.1 hole and No.3 flash quickly.

During the charging process, the red light of the No. 2 lamp flashes.

When it is full, the red light of the No. 2 light is on.

The moment the headset is placed in the charging compartment, light No.1 or light No.3 will flash.

Flashing 4 times means that there is about 75%-100% of the charge

Flashing 3 times means that there is about 50%-75% of the charge in the charging compartment

Flashing 2 times means that there is about 25%-50% of charge in the charging chamber

Flashing 1 time means that there is about 0%-25% of power in the charging chamber

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.