

Instruction Manual

ENGLISH





Advanced Wireless Stereo Headset



- 1. Power Switch
- 2. Play/Pause/Stop Button
- 3. Fast Forward/Rewind Switch
- 4. Right Earbud Retraction Button
- 5. Retractable Earbuds
- 6. Microphone
- 7. Call Button
- 8. Left Earbud Retraction Button
- 9. LED Indicator
- 10. Charging Port
- 11. Volume Switch

CHARGING

Before using your Oracle headset, follow these steps:

Make sure that your Oracle headset is fully charged.

Use a fully charged Oracle headset with a Bluetooth-enabled mobile phone. To charge the Oracle headset, please insert the micro USB charge cable into the Oracle headset.

The red LED will light up to indicated the Oracle headset is charging and powered on.

ON/OFF

- 1. Use the power switch to turn the Oracle headset on or off. A bright red light will flash twice within a second, to indicate that the Oracle headset is on.
- 2. To turn the Oracle headset off, switch the power switch dial to "OFF". A bright red light will flash twice within a second, to indicate that the Oracle headset is off.

PAIRING THE ORACLE HEADSET WITH YOUR PHONE

- 1. To ensure a smooth pairing, your phone and Oracle headset should be less than 3 feet apart. Alternately flashing red and blue lights indicate the Oracle headset is in pairing mode.
- 2. Open the phone's Bluetooth function to scan for Bluetooth devices (please refer to the phone's manual operation). Once your phone completes scanning, it will display all the searched Bluetooth devices. tttSelect the appropriate device. Follow the prompt pairing.

Note: Your phone needs to be Bluetooth version 2.1 or later.

BLUETOOTH HEADSET MODE OPERATION

FUNCTION	DESCRIPTION
Last Number Redial	Double-click the ${\cal C}$
Answer a Call/End a Call	Click &
Back	Click ◄ ◀
Next	Click▶▶
Play/Pause	Click ▶
Volume + -	Click + -

LED INDICATOR OPERATION

FUNCTION	DESCRIPTION
Power OFF	All LED off
Bluetooth power ON/OFF	Red and Blue LED Light
Bluetooth pairing success	Blue LED with slow flash
Answering a call	Blue LED with fash flash
Charging	Red LED on
ON, OFF, calling	Vibrating alert

TROUBLESHOOTING

If you fail to successfully connect the Oracle headset with your phone on or in normal mode, try the following steps:

- Make sure you turn on the Bluetooth function on your phone.
- The distance between your phone and the Oracle headset should not be more than 30 feet. Make sure there is no electronic products between the two to remove any signal interference.
- •The Oracle headset can store eight paired devices, or when the Oracle headset pairing list is fulled.
- If the Oracle headset does not automatically connect or disconnect from the phone while listening to music, reboot your Oracle headset.
- When music is silent, please check whether your device is on muted or minimum volume.
- Ensure the battery is fully charged, in which the LED indicator will be red.

CARE AND MAINTENANCE

Consider turning the Oracle headset off before placing it in your pocket or bag. If the call button is accidentally activated, your mobile phone may place an unintended call. Do not expose the Oracle headset to liquid, moisture or humidity as it is not waterproof. Do not use abrasive cleaning solvents to clean the headset. Do not expose the headset to extreme temperature conditions. The best storage temperature range is from -10 to 60 degrees Fahrenheit. Otherwise, the life of the Oracle headset will be influenced. Do not dispose the Oracle headset in a fire as it may result in an explosion. Do not bring the headset into contact with sharp objects as this will cause scratches and damage. Do not attempt to disassemble the Oracle headset as it does not contact workable individual components. If you do not use the Oracle headset for long periods, be sure to store it in a dry place, free from extreme temperature condition and dust.

BOX CONTENTS

- 1 Oracle Advanced Wireless Stereo Headset
- 1 Micro USB Charge Cord
- 2 Pairs of Ear Gels
- User Manual

PRODUCT SPECIFICATIONS

Bluetooth® Version: V4.0+CSR

Support Profiles: HSP/HFP/A2DP/AVRCP
Distance Coverage: Up to 10 meters
Charging Time: Less than 2 hours

• Talk Time: Up to 17 hours

Play Music Time: Up to 14 hours

Power Rating: 17mWSpeaker: 32 oHM

• Standby Time: Up to 550 hours (or 23 days)

• Frequency Table: 2400.0-2480.0 MHz unlicensed ISM band

• Sensitivity: < -82dBm at < 0.1% BER

• Rechargeable 200 mA/h li-polymer battery

• Work Voletage: DC 3.3V to 4.2V

Charger: DC 5V (300mA)

• Weight: 54g

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- -- Reorient or relocate the receiving antenna.
- -- Increase the separation between the equipment and receiver.
- -- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- -- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.