

A5 Using instruction

Contents

Lewano R70D Overview	
Product Specifications	
Getting Started	
Charging Your Headset	
Indicator Light	
Pairing Your Headset with a Bluetooth Mobile Phone	
Using Your Headset	
Resetting Your Headset/ Removing the pairing History	
Troubleshooting	
Safety Information	
Care and Maintenance	
Declaration of Conformity	

Product Specifications

Bluetooth Specification: V4.1 + EDR Class 2

Bluetooth Profiles Supported: Headset, Handsfree

Range of Frequency : 2.4 GHz spectrum

Nominal Charging Time: Within 3 hours

Talk Time : up to 10 hours

Standby Time : up to 200 hours

Getting Started

To use your Lewano R70D bluetooth headset please follow the steps as below:

- 1.Ensure your headset is fully charged
- 2.Pair your charged headset with a Bluetooth-enabled mobile phone

Charging Your Headset

The headset comes with a built-in rechargeable battery ,Prior to using the headset for the first time, it is recommended to fully charge the battery, Insert the charger's Plug into the headset's DC charging socket and plug the mains charger to an AC wall outlet or plug to the PC/notebook. Use only the supported charge/ USB charging cable to charge the headset.

Indicator Light

Headset Status	Status Indicator Light
Standby	Flash blue
Charging(off mode)	Solid red
Fully charged (off mode)	Solid blue
Low battery	Flash red with short beep every minute
Out of battery	The loght turns off
Charging (standby mode)	Double flash red
Fully charged(standby mode)	Double flash blue
Out of Range	Solid purple for 5sec then flash blue

*Warning:

Do not use the headset while it is connected to the charger

Pairing Your Headset with a Bluetooth Mobile Phone

- 1) Ensure the headset is off.
- 2) To activate the pairing mode, press and hold the headset's MFB for 8 seconds without releasing your finger until its status indicator flashes blue and red light alternately.
- 3) Activate your mobile phone's Bluetooth, search Bluetooth devices, select "Lewano R70D" and enter the passcode "0000" when the pairing is completed, the headset status indicator will flash blue light rapidly 5 times and you can hear a long beep, if the pairing can not be completed within 3 minutes after pairing mode has been activated, the headset's status indicator will flash purple rapidly 5 times and then turns off. **Repeat steps 1 to 3 to do the pairing again for another Mobile phone.**

Using your headset

Function	Button	Beep/Buzzer	Status indicator
POWER ON	Press and hold the MFB for 2sec	Short beep	Flash blue light twice
When you turn on your headset for the first time, the headset proceeds into pairing mode, i.e. the status indicator flashes blue and red alternately, so that you can immediately pair it with your mobile phone.			
POWER OFF	Press and hold the MFB for 2sec	Long beep	Flash red light and then goes off
Incoming call		Ringtone through the earphone and buzzer ON (depends on buzzer pattern)	Flash purple
Answer/End a call		Press the MFB once	
When there is a 2nd incoming call, press MFB can hold the current call and answer the 2nd incoming call*			
Adjust Volume	Press Volume	Short beep at max. volume	
Last no. Redial*	In standby mode double click MFB		
Reject incoming call	Press MFB for 2 sec	Short beep	

Resetting your Headset/Removing the Pairing History

You may reset the headset to its default setting. Resetting will also remove the pairing history of your headset with the mobile phone.

1. During off mode, hold the Volume then plug the charging cable into

- the charging socket, The indicator will light in solid purple.
2. Release the volume.
 3. Hold the volume for 2 seconds until the status indicator blink in purple for 3 times.
 4. Release the Volume and headset will return to charge mode, now the headset is reset, Lewano Bluetooth headset is designed to work with Bluetooth devices, due to large variability between different Bluetooth devices from different manufacturers, interoperability between the headset and all Bluetooth-enabled products is not guaranteed.

Troubleshooting

I can hear crackling noise?

To receive the best audio quality, it is recommended to wear your headset on the same side of the body as your mobile phone.

I can't hear anything in my headset?

- Ensure the headset is turned on and is properly charged.
- Ensure the headset is properly paired with the mobile phone.
- Make sure that the mobile phone is connected with the headset - if it does not connect, either refer to the mobile phone's Bluetooth menu or by pressing the MFB once.

I can't connect my headset with mobile phone?

- Ensure your headset is turned off and is properly charged.
- Ensure the headset is properly paired with the mobile phone.
- Ensure your mobile phone's Bluetooth feature is activated, please refer to your phone user guide for specific instruction.
- Ensure the headset is within 10 meters range of your mobile phone and there are no obstructions, such as walls or other electronic devices in between.

If the above steps do not solve your problem, please recharge the headset and remove your mobile phone's battery for a while.

I can't turn off the headset or the headset does not response?

- you may do a "hardware reset" on your headset if you can't turn it off or it doesn't response.
- Press and hold Volume and MFB and plug the charging cable into the headset for 5 seconds.
- Release both buttons and the headset will return to charging mode and reset.

Safety Information

.Check and observe local laws regarding the use of a mobilephone and a headset while driving,if you use the headset while driving. Ensure your full attention and focus,it is your responsibility to drive safety, Consider to pull off the road before making or answering a call.

Safety information

.Observe all signs and displays that require an electrical device or RF radio product to be.
.Swithed off in designed areas.these could include hospitals,Blasting areas,and potentially explosive atmospheres.
.Turn off your headset prior to boarding an aircraft, do not set the listening volume too high.
.Do not attempt to modify the headset.
.Do not keep the headset near a wash basin or other wet places.
.Do not use the headset outdoors in the rain.
.Do not use the headset in stormy weather.
.Do not clean the headset while it is being charged, always disconnect the charger from the headset before cleaning..
.Do not attempt to force open the built-in battery.
.Only charge the headset's built-in battery in accordance with the instructions described in this user guide.

Care and Maintenance Headset

.Turn off your headset before placing t in your pocket or bag,f the MFB is accidentally depressed,your mobilephone may place an unintended call.
.Do not expose the headset to liquid,moisture or humidity,or rain as it is not waterproof.
.Do not use abrasive cleaners to clean the headset.
.Do not expose the headset to extremely high or low temperatures.
.Do not leave the headset in the direct sunlight for an extended period of time.
.Do not leave the headset near open flames such as cooking burners.
.Do not dispose of the headset in a fire as it will result in explosion.
.Do not bring the headset into contact with only sharp objects as this will cause scratches and damageds.
.Do not stick anything inside the headset as this may damage internal components.

- .Do not attempt to disassemble the headset as it does not contain serviceable components.
- .If you do not plan to use the headset for a long period,please store it in a dry place that is free from extreme temperatures and dust.
- .Avoidcharging the headset in extremely high or low temperatures.
- .Dispose of the battery and headset according to local regulations. Do not dispose of them as household waste.

Built-in Battery

- .Do not attempt to replace the headset's battery as it is in-built and is not changeable.
- .Dispose of the battery according to local regulations,do not dispose of the battery as household waste.
- .Charge the battery in accordance with the instructions supplied with this user guide.

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:(1) This device may not cause harmful interference, and (2) this device must

accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.