T9 user manual

Using steps:

- 1. Making sure the headset is in off state.
- 2. Press the power button for 7 seconds till the indicator light and the blue light is on , or the blue and red light is alternating flashing quickly.
- 3. According to the mobile module, then turn on the Bluetooth headset and set it into standby-search state (blue light on or blue and red light flashes alternately), then connect with the Bluetooth headset and the phone.

Important notes:

- 1 .Primitive pairing password of the Bluetooth headset is 00000.
- 2. When the indicating blue light flashes three times and then the red light flashes once time every seven seconds, it means docking successfully.
- 3.Standby search state for duration of 2 minutes, if paring with mobile phone is failed in 2 minutes, the Bluetooth headset will turn to the blue light and flash slowly for standby power -saving state, if you still need to search , please press the power button for 5 seconds to restart the equipment and repeat steps above

Summary

Thank you for choosing the Yuer brand, Yuer series Bluetooth headset combines fashion design elements, good compatibility, powerful. allowing you to truly experience the fun of wireless phone calls, listening to music It is the best choice for you to work, go out and drive!

Bluetooth wireless technology

With Bluetooth wireless technology, you do not need to use a cable to connect the headset to its compatible

communications equipment. Bluetooth connection without the need to keep the phone and the headset are mutually opposite each other, but the maximum distance between the two should not exceed 10 meters (about 30 feet). The Bluetooth wireless connection may be interfered by the wall and other obstacles or other electronic devices. Yuer series headset supports Bluetooth V4.0(Enhabced Data Rate) standard and supports the following Bluetooth profiles: 1.1 / 1.2 headphone profile and version 1.5 / 1.6 Handsfree profile/ support A2DP / AVRCP protocol, please consult other equipment manufacturers to determine whether the device can compatible with the headset. In some areas, the use of Bluetooth headset wireless technology may be some restrictions, please consult the local authorities or to the supplier.

Introduction to use

The headset is made of the following components (depending on the specific model)

- 1, Red, blue light
- 2, Multi-function button (MFB)
- 3. Volume plus and minus button
- 4. Charging jack. headphone cable jack
- 5, Microphone port
- 6, the Receiver

Please charge the Bluetooth headset for a full charge before use. charging method with the reference to the charging chapter of this manual. At the same time select the headset compatible with mobile phones and other Bluetooth terminal device pairing (Pairing method with the reference to the Basic Operation chapter of this manual).

Warm Tip: Please do not use credit cards or other magnetic storage media close to the headset, so as to avoid losing stored information due to demagnetization.

Basic Operations

(Note: short press is to press the button once. short press two times is to press button two times quickly. long press is:press and hold the botton more than I second.

Pairing:

Method 1, in the OFF state, long press MFB button until the red and blue alternately flash then loosen (a voice prompt tone), then the headset into pairing state.

Method 2, the second time use, press MFB button, see the blue lights flashing, or headset prompts "device connected" .the headset automatically goes into pairing state.

Connecting Headphones services : Open the phone's Bluetooth function, search for Bluetooth devices, when the search to the headset device, select the device to confirm, enter the 0000 matching code and confirm the matching connection (Note: when Bluetooth is V2.1 or above. no need to enter the matching code).

Answer a call: When there is an incoming call (there will be report number/ voice prompt), short press MFB button hear the beep beep and then answer the phone.

Reject the call: When there is an incoming call, long press MFB button for two seconds, hear beep / voice prompt and then loosen the button to achieve the function of refused to answer the phone.

Hang up the phone: During a call, short press MFB button that can hang up the call.

Volume Addition and Subtraction: During a call, short press the volume + can increase speaker sound. short press the volume - can decrease speaker sound.

Forward/backward: When listening to the music long press the volume+ button can get to previous song, Long press the volume- button can get to the next song.

Pause Play: short press MFB button can pause a song when playing a song, press again to realize the song is playing.

Music feature set: Some mobile phones and Bluetooth devices need to manually set on the audio transmission services. The sound need be sent to the headphones to play. Specific settings, please refer supporting mobile phone operating instructions.

Audio Switching: During a call, Long press MFB button for two seconds then loosen, the sound can be switched back to the phone, and then repeat the operation. the call can be switched to the headset.

Last call number redial: when you connect the headset phone standby, short press MFB button twice to be able to achieve the last call number redial function.

Voice dialing: headset when connected to the phone in standby, long press MFB button or short press MFB button twice to voice dialing (mobile phone needs to support this feature), and repeat the operation once to cancel voice dialing.

One with Two Operation:

Method 1 ,headset in the OFF state, long press MFB button headset is turned on, red and blue alternating flash when loosen hand, entering pairing status. Using A mobile phone paired connect the headset, turn off the headset after the connection is successful, turn the headset on again and make it into pairing status. At this time with B mobile phone is connected headset. turn off the headset again after connection is successful. Open again the headset see blue lights flashing three times then loosen hand, this time without the need to enter pairing status, the headset will automatically connect at the same time. to connect to the AB two phones. At this point either of AB phone calls can be answered.

Method 2 , the first Bluetooth headset and A mobile phone pairing connection. and then close the A mobile phone Bluetooth function. And then Bluetooth headset and B mobile phone pairing connection, and then open the Bluetooth function of A mobile phone, Bluetooth headset will automatically connect back A mobile phone (mobile phone should have automatic back function) or directly click the Bluetooth headset manually back to connect A mobile phone, Bluetooth headset can be connected on the AB two mobile phone at the same time, to achieve a headset with two mobile phone functions.

Three-way calling:

Method 1: In a call. there is a new call, short press MFB button once, hang up the current call (A-way) and turn on the B-way telephone; Long press MFB button for three seconds, refuse B line telephone and restore A way call. In a Call, a new call coming, double-click the MFB button once again to switch A/B two-way call into the three-way call, press MFB button once, hang up the current call and recover the call on hold.

Method 2: During a call, there are third-way call, short press MFB. hang up the current call. automatic answer/ press MFB to answer the third-way call, long press MFB button one second. the current call hold. call waiting call. Long press the MFB button one second, to retain third-way call, and return the current call.

Restore the Headset Factory Parameters Settings: Press and hold the MFB button under charging state until the blue light I red light flashing, restore the headset factory pa rameter settings.

Turn off: When the headset in the ON state, long press MFB button until the red light flashes or red and blue lights flashing simultaneously (voice prompts) to achieve turn off.

Charger and Battery: Before using any charger for the headset charging, check the specifications of the charger label whether meets the requirements (recommended charger output voltage: DC5V +1- 0.25V, output current: 100mA-500mA), the charging voltage is very high may damage the Bluetooth headset.

WARNING: Whenever possible, use an approved charger, the use of other types may invalidate any approval or warranty, and may be dangerous, if the factory is equipped with a charging cable to ship, need to be connected to the 3C certificated charger or computer to charge. Charge the Battery: The headset uses a built-in type of rechargeable battery, do not attempt to remove the battery from the headset, so as you not to damage the headset. When you do not use headphones for a long time, please store it in a dry, ventilated place, and charge it every two months.

- 1. when connected headset flashes red and the receiver have low electric beep beep, indicating that the headset battery is running low. If you continue to work will automatically shut down at this time needs to be charged Connect the charger cable plug into the headset jack.
- 2, Plug the charger into the AC outlet.
- 3, charging the red indicator is on, if the charging does not start, please disconnect the power supply with the headset connector, then re-insert the headset and try again, the battery fully charged may take two hours, after the battery fully charged, the red light will turn off, and blue light is on, then disconnect the charger from the electrical outlet and the headset.

Comon problems and their solutions

Problem Description	Cause	Problem-solving Method
Can not start	Battery drain	Whit changer full of electricity
	Long press the starting Press	Press the main button for 3
	the main button time is too	seconds to restart
	short	
Can not charge	Charging plug is not plugger in	The charging plug reinsert
	Long time not used, battery is	Use product charge for half an
	no electricity	hour or more
Can not shutdown	Errors caused by incorrect	Charging with charger can be
	operation of the headset	reset
Can not search or pairing	Headset does not enter	Enter the headset into pairing
failure	pairing procedure	state
		Restore factory settings
	Mobile phone Bluetooth	Turn off the phone and restart
	application error	pairing

FCC Statement:

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- —Reorient or relocate the receiving antenna.
- —Increase the separation between the equipment and receiver.
- —Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- —Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment.

This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.