# **BAPHILE B2 Sport Bluetooth Headset for Streaming** Music and Phone Call

User Manual

Introduction:

1

BAPHILE B2 is a stylish Bluetooth headset designed for sports. With this headset, you can enjoy music and make call freely when jogging running or on the go. All Bluetooth enabled devices, such as cellphone tablets, computers can be connected wirelessly.

Volume + / Previous Track Volume - / Next Track Microphone on the back Multi-function Button

Micro USB Charging Port Cover

### Bluetooth Connection:

LED

- 1. When the headset is powered off, long press the multi-function button for 5 seconds to active Bluetooth pairing mode until the LED flashes in red and blue alternately. Meanwhile a voice prompt "pairing" will be
- 2. Switch on your phone's Bluetooth settings, and scan for new Bluetooth devices until you have found "BAPHILE".

  3. Click the device ID "BAPHILE" for pairing until having
- succeeded. If your phone requires a pairing code, please enter "0000" and confirm.

Note 1: Besides step 1, you can also active the headset Bluetooth pairing mode like this. When the headset is powered off, long press the multifunction button for 3 seconds until the blue LED flashes three times quickly, and a voice prompt "Power on" will be heard. Now the headset is in power on mode. Then Short press the Vol+ & Vol- buttons concurrently to step into pairing mode.

Note 2: In power on mode, the headset will automatically connect with the latest connected Bluetooth device.

Note 3: In power on mode, the headset will automatically power off if no connection after 10 minutes

Note 4: The headset will quit pairing mode if no connection after 5 minutes.

Note 5: Follow the steps to connect with two phones at the same time.

Disconnect the first phone connection by phone.
 Short press Vol+ & Vol- concurrently to step into

pairing mode.

3). Pair with your second phone.

4). By operate on your first phone you can make it connect with the headset too.

### **Useful Function Operations:**

Power On

2

Long press the multi-function button for 3 seconds.

Long press the multi-function button for Power Of Short press the multi-function button to answer an incoming call. Short press again to end the call. / End a call Double click the multi-function button to Reject a call

Redial the Double press the multi-function button latest phone to redial. number Long press the multi-function button for 2

reject an incoming call.

seconds to active voice command if your phone supports. And you will hear the voice Voice Command prompt. Press for 2 seconds again to quit voice command mode.

Short press the multi-function button to pause when playing music. Short press Pause / Resume music again to resume Long Press Vol- for 2 seconds to play the track; Long press Vol+ for 2 seconds to

/ Previous track play the previous track. Short press Vol+ to increase volume; Short Volume control press Vol- to decrease volume. Reconnect Short press the multi-function button to

try to reconnect when losing connection

**Battery Charging:** 

4

Please charge the headset with the included charging cable timely. While charging, the red LED lights up. When charging finished, the blue LED will light up instead. When the battery voltage is less than 3.3V, (the power is less is less than 15%), the red LED will flash every 20 seconds, meanwhile, there will be a "battery low" voice prompt. When the voltage is less than 3.1V, (the power is less than 5%), the headset will power off automatically. Headset battery icon can be displayed on some smart phones

Basic specification: Length: 600mm Net Weight: 25g Ear tips: 2 sets in S/L size Main Material: Plastic, aluminum Buttons: 3 pcs Battery: Lithium 3.7V / 70 mAh Charging port: Micro USB Charging specification: 5V / 0.5~1A Charging time: about 1.5 hours Standby time: up to 100 hours Talk time: 4-5 hours Music time: 4-5 hours

Signal to Noise Ratio S / N: Distortion THD: ≤ 1%

Storage temperature: -20~40 C

Bluetooth specification: Bluetooth Chipset: V4.1 Profile Support: HSP / HFP / A2DP / AVRCP Signal Transmission Range: 2 40GHz~2 48GHz Transmission Distance:

**About Audio:** 

10 m / 33 feet Device ID: BAPHILE Pin code: 0000 (if needed)

Speaker: Φ10.0mm, 16Ω Audio Frequency Range: 20Hz-20KHz Noise reduction: CVC Microphone sensitivity:

Accessories:

5

1. 1 x Micro USB charging cable
 2. 1 x Set of ear tips

3. 1 x Cable clip

4. 1 x User manual

### Warranty:

Thanks for your purchase on our Basstyle Amazon store: www.amazon.com/shops/basstyle. Normally every item in our store deserves 18 months warranty after receiving. Your satisfaction is always our top priority. If you have any question or query, please don't hesitate to contact us. Our customer service team will always be ready to serve you 24 hours a day, 7 days a week. Three ways to ask for help: 1. "Ask a question" on our Amazon store. 2.Email to sales3@thinkano.com. 3.Call 1-6465685502.

## Warning:

Please do not expose your hearing to loud sound over a long period. Listen to loud music may cause damage to the hearing! This product should not be used if you actively participate in the road traffic.

# Precautions

1. Avoid this product from accidental drops, physical shocks, and any long exposure to the sun or rain.

2.Do not expose to moisture/liquids/ heat. Keep this device in a clean / dry environment of 0 C- 60 C in temperature. The ambient humidity of the device should not exceed 75% so as to avoid corrosion damage.

3.Do not use this product under thunder weather

4.Do not open/repair the device.

 Never dispose of any electrical or electronic waste in general circulation. Collect and dispose of such waste safely and separately

材质: 105g纸, 白底黑字, 双面打印, 3折叠

单页尺寸: 65.3\*90mm 三面尺寸: 196\*90mm

PS:虚线为折叠线,不用印刷

# FCC WARNING

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE 1: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.