


Front




TWS-T6

Specification


Specification of Earbuds

Product Name: True Wireless Bluetooth Earbuds
Bluetooth Version: Version 5.0 (BLE function from factory disabled)
Protocol: V5.0+EDR, supporting HSP/HFP/A2DP//
VRCP protocol can be downward compatible with other versions
Chipset: RTL8763BFR
Call Time: 5-6H (1 time full charged)
Play Music Time: 5-6H (1 time full charged)
Battery: 3.7V, >50mA Li Battery
Charging Time: 1-2H
Working Temperature: -10°-55°



Specification of Charging Case

Input: 5V ±0.25V/1A
Output: 5V ±0.25V/50MA
Battery Capacity: 450MA




How to operate

Auto-Turn on and Auto-Pair: Take out the two earbuds from the charging case, you will see the LED lights are twinkling (blue or red), 2-3s later, it hint "Power ON, Device connected", Right earbud hint "right channel" Left earbud hin "left channel", then the R/L earbuds paired successfully, ready for being searched by phone.

Pair to Phone: Turn on Bluetooth function on your phone, find Model NO. **T6-TWS** in the list of available devices, click to connect, it will show CONNECTED on your phone, and the LEFT earbud will hint "Device connected". Then it is paired successfully.

NEXT/PREV Songs: Double click on the LEFT earbud(R), it plays next song, double click on the left earbud, it plays previous song.



Volume +/-: Continuous press right earbud 3 times to turn up the volume; continuous press left earbud 3 times to turn down the volume, or you can adjust the volume on the phone directly.

Answer and Hangup Calls: Press the Right earbud 1 time to answer calls, press the Right earbud again 1 time to hang up when you finish the talk.

Start Siri: Long press Right earbud or Left earbud for 1s you will hear "voice dail", release and phone voice control is started. **Siri supported only.**

Power Off and Pause: Once put the earbuds back to charging case, the earbuds disconnects from phone, or press either earbuds for 3-5s, the RED lights is on for 1s then power off.

Auto pairing: Auto pair to the phone used last time when taking out earbuds from charging case

Special Note:


The two earbuds are well paired before packaged, but if they can not paired well due to some wrong operations, pls. do as following steps to re-pair the earbuds.
Power off the two earbuds, then press the button of the two earbuds at same time and do not release for about 20s, blue lights sparkled 3 times ----> red and blue lights sparkled 3 times alternatively ---> release ---> two earbuds are in the situation of paired, and they are ready for phone searching. Contact us if you have any question about this.

Single Earbud Mode


- Take out either one of the earbud from charging case, turn on Bluetooth function on your phone, you will find **T6-TWS** or **T6-TWS** on the list of available devices, click and connect, the earbud will hint "device connected" and it is ready to be used.
- Then the other earbud in charging case can be used to pair to another phone.
- Make sure the other earbud is in charging case when pairing the first one, or it will be recognized as a pair of earbuds not a single one.

Charging & Indicators

- Indicators on earbuds**
The earbuds will be charged automatically when putting them into charging case. Red for charging, Blue for fully charged.
- There is a micro USB port on the back of case for charging (see picture on next page)



- Indicators for charging case
Red is on when charging for the case, green is on when the case is fully charged.
- Indicator for charging earbuds
Green is on when earbuds are charged by the case, indicator is off when earbuds if fully charged.



Attention:

- Don't drop, crash, scrub, twist, beat, grind, or throw into water.
- Please make sure stay far away from magnet, electric appliance and loudspeaker when using bluetooth earbuds.
- Please don't put earbuds in extreme temperature.
- Please don't put earbuds exposed in moist environment.

FAQ and Solutions

Phenomenon	Failure Reason	Solution
Can not turn on / Turn off automatically	Low battery	Charge the earbuds for 2-5H
No hint after paired	Not paired correctly	Re-paired
Can talk but red light is on	Red light is on for lower battery	Charge for the earbuds
No lights on when charging	No output from power supply	Check the power supply if connected well
Echo	Too large volume or too noisy environmental	Turn down the volume or change the environmental
There is noise when talking	Environmental disturbance or too far away from device	Change the environment or move to place near the device
Low voice	Not wear earbuds correctly	Adjust the position of earbuds
Can not hear the music	The phone doesn't support	Need a phone support BT stereo

Thank you for purchasing our product!

Hope you enjoy your new true wireless Bluetooth earbuds.

If you have good experience of this pair of earbuds, we will be appreciated

you can share it to other customers.

T6-TWS-IB-180913-B

Warning Statement

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

The device is too small to label ID number, so, the ID number is adhered in the charger case.

Model:TWS-T6

FCC ID: 2ARMC-TWST6

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.