

# Ninebot Telematics Box specification

## 1. Product overview

Ninebot Telematics Box includes the functions of 4G networking, Bluetooth, mass storage and encryption. As the data transmission terminal of the electric motorcycle, Ninebot Telematics Box can control vehicle switch on / off through Bluetooth or remote network unlocking, and can realize the fast access unlocking function. It can also obtain the vehicle information through the serial port, and then report the vehicle status and position information to cloud server to realize the real-time monitoring of the whole vehicle.

## 2. Basic parameters

Item	parameters
Dimensions	85mm*85mm*43mm
Rated voltage	DC:40-110V
Rated current	working condition: 72V@70mA Low power state: 4V@4mA
working temperature	-20°C~+85°C
Charging temperature	<42°C

## 4. RF parameters

Item	parameters
Hardware version	EC25-EUX(Europe / Middle East / Africa / Korea / Thailand) EC25-AFX(North America) EC25-AUX(South America/ Australia,/New Zealand) EC25-J(Japan) EC21-KL(South Korea) EC25-MX (Mexico) EC20-CE(China / India)
technical characteristics	LTE CAT4/UMTS/EGPRS
Working frequency band	<b>EC25-EUX:</b> LTE FDD: B1/B3/B7/B8/B20/B28A LTE TDD:B38/B40/B41 WCDMA: B1/B8 GSM: B3/B8 <b>EC25-AFX:</b> LTE FDD: B2/B4/B5/B12/B13/B14/B66/B71 WCDMA: B2/B4/B5 <b>EC25-AUX:</b> LTE FDD: B1/B2/B3/B4/B5/B7/B8/B28 LTE TDD: B40 WCDMA: B1/B2/B4/B5/B8 GSM: B2/B3/B5/B8 <b>EC25-J:</b> LTE FDD: B1/B3/B8/B18/B19/B26 LTE TDD: B41 WCDMA: B1/B6/B8/B19 <b>EC21-KL:</b> LTE FDD:B1/B3/B5/B7/B8 <b>EC25-MX:</b> LTE FDD: B2/B4/B5/B7/B8/B66 WCDMA: B2/B4/B5 <b>EC20-CE:</b> LTE FDD: B1/B3/B5/B8 LTE TDD: B34/B38/B39/B40/B41 WCDMA: B1/B8 TD-SCDMA: B34/B39 CDMA: BC0 GSM: 900/1800MHz
GSM features	EDGE: 296Kbps (DL)/ 236.8Kbps (UL) GPRS: 107Kbps (DL)/ 85.6Kbps (UL)

UMTS features	DC-HSDPA: 42Mbps (DL) HSUPA: 5.76Mbps (UL) WCDMA: 384Kbps (DL)/ 384Kbps (UL)
LTE features	LTE FDD: 150Mbps (DL)/ 50Mbps (UL) LTE TDD: 130Mbps (DL)/ 30Mbps (UL)
Transmitting power	GSM850/GSM900: 33dBm±2dB DCS1800/PCS1900 :30dBm±2dB WCDMA:24dBm+1/-3dB LTE-FDD /LTE-TDD :23dBm±2dB
Receiving sensitivity	LTE:-102.5dB--99dB WCDMA:-110dB GSM850/EGSM900/DCS1800/PCS1900: -109dBm
Network protocol	TCP/UDP/PPP/FTP/FTPS/HTTP/HTTPS/NTP/PING/QMI/NITZ/ MMS/SMTP/SSL/MQTT/FILE

## 5. GPS parameters

Item	parameters
Model	UM220-IV NL
Frequency	BD2 B1 GPS L1 GLONASS L1
HDOP	<2.5m CEP

## 6. BLE parameters

Item	parameters
BLE Chip	NRF51802
Frequency	2.4GHz
Receiving sensitivity	-91dBm

## 7. Other technical parameters

Item	parameters
Main processor	STM32G070CBT6: Core: Cortex-M0+ Flash memory: 128K bytes Ram: 36k bytes
Serial port	115200bps

## Federal Communications Commission (FCC) Compliance Statement for USA

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator and your body. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

Nine Tech Co., Ltd. is not responsible for any changes or modifications not expressly approved by the party responsible for compliance. Such modifications could void the user's authority to operate the equipment.

Ninebot Telematics Box (model: N-A-LTEC72-A)

FCC ID:2AU2Y-JH0003

Contains FCC ID: XMR202006EC25AUX

## Important WEEE information



WEEE Disposal and Recycling Information Correct Disposal of this product. This marking indicates that this product should not be disposal with other household wastes through out the EU.

To prevent possible harm to the environment or human health from uncontrolled waste disposal, recycle it responsible to promote the sustainable reuse of materials resources. To return your used device, please use the return and collection systems or contact the retailer where the product was purchased. They can take this product for environmental safe recycling.

## Battery recycling information for the European Union



Batteries or packaging for batteries are labeled in accordance with European Directive 2006/66/EC and amendment 2013/56/EU concerning batteries and accumulators and waste batteries and accumulators. The

Directive determines the framework for the return and recycling of used batteries and accumulators as applicable throughout the European Union. This label is applied to various batteries to indicate that the battery is not to be thrown away, but rather reclaimed upon end of life per this Directive.

In accordance with the European Directive 2006/66/EC and amendment 2013/56/EU, batteries and accumulators are labeled to indicate that they are to be collected separately and recycled at end of life. The label on the battery may also include a chemical symbol for the metal concerned in the battery (Pb for lead, Hg for mercury, and Cd for cadmium). Users of batteries and accumulators must not dispose of batteries and accumulators as unsorted municipal waste, but use the collection framework available to customers for the return, recycling, and treatment of batteries and accumulators. Customer participation is important to minimize any potential effects of batteries and accumulators on the environment and human health due to the potential presence of hazardous substances.

Before placing electrical and electronic equipment (EEE) in the waste collection stream or in waste collection facilities, the end user of equipment containing batteries and/or accumulators must remove those batteries and accumulators for separate collection.

## Restriction of Hazardous Substances (RoHS) Directive

This Nine Tech Co., Ltd. product, with included parts (cables, cords, and so on) meets the requirements of Directive 2011/65/EU on the restriction of the use of certain hazardous substances in electrical and electronic equipment "( RoHS recast" or" RoHS 2").

## Radio Equipment Directive



Segway Europe BV, Hogehilweg 8, 1101 CC Amsterdam, The Netherlands.

Hereby, Nine Tech Co., Ltd., declares that the wireless equipment listed in this section are in compliance with the essential requirements and other relevant provisions of Directive 2014/53/EU.

Bluetooth	Frequency Band(s)	2.4000-2.4835GHz
	Max. RF Power	20mW