


感谢您选择并购买 蓝牙耳机

TWS 真无线耳机

产品展示



耳机参数

蓝牙版本： V5.0	蓝牙工作频率：2.402GHz~2.480GHz
接收距离： ≥10米	防水级别： IPX5级
电池： 聚合物电池5V、50mAh	充电仓： 300mAh
充电时间： 耳机充电1小时，充电仓1小时	
通话/播放时间约5小时(真实的使用时间取决于歌曲的类型和音量要求，80%音量)	
支持协议： AVRCP/A2DP/HFP/HSP	

基本操作

- 1.开机： 开盖自动开机或长按MFB键3秒。
- 2.双耳配对： 打开充电盒盖或关机状态下同时长按两耳机开机键3秒，打开手机蓝牙，搜索蓝牙设备名：“MOLDULL”后点击设备名连接完成配对
- 3.单击： 左耳（L）减音量，单击右耳（R）加音量。（音量加减有轻微的提示音，音量最大或最小有提示音）
- 4.双击： 播放/暂停、接听/挂断； 通话模式下长按2秒： 来电拒接。
- 5.三连击： 左耳(L)上一曲，右耳（R）下一曲。
- 6.语音助手： 连接模式长按左/右耳功能键2秒。
- 7.关机： 放入充电仓上充电仓盖自动关机或长按左右耳功能键5秒。
- 8.恢复出厂设置： 耳机连接手机后要恢复出厂设置，删除手机上的蓝牙配对信息，将耳机放回充电仓，拿出耳机后任意敲击L/R一边连续5下，耳机清除之前的配对信息，恢复出厂设置。

充电操作

- 1.首次使用确保2个耳机和充电仓的电是满的。

充电仓充电

- 1.用USB线连接充电仓一边上的Type C口，另一端连接插头适配器（或者将Type C）输出插入PC或电脑端，它将会开始充电，在充电时，充电仓显示屏显示当前电量比例，充满后显示屏灯灭。
- 2.确保充电仓的电是满的（或者连接着Type C线充电如说明提到的）
- 3.把耳机正确地放入充电仓，便会开始给耳机充电。（你可以同时给充电仓和耳机充电；你也可以先给充电仓充满，再使用充电仓给耳机充电。一旦耳机充满，充电仓会自动断电，耳机的LED灯也会灭）

开机/关机

- 1.开机： 按住耳机多功能键约3~5秒直到耳机LED灯闪烁蓝色，同时会有“开机”提示音；（或是从充电仓取出耳机，它会自动开机）
- 2.关机： 按住多功能键约5秒直到LED红灯闪烁2次，并伴随关机提示音关机（或者把耳机放回充电仓，它会自动关机）

蓝牙配对说明

- 1.在充电仓取出左右耳机，开机蓝灯，配对过程红蓝双闪。耳机配对后主耳红蓝灯交替闪亮，副耳蓝灯 呼吸一次组队成功，打开手机设备搜索耳机配对名称“MOLDULL”（部分手机需输入“0000”作为配对密码)点击连接配对完成。
- 2.手动打开蓝灯，配对过程红蓝交替，耳机配对后主耳红蓝灯交替闪亮，副耳蓝灯闪亮，连接上手机后，主副耳灯灭。打开手机设备搜索耳机配对名称“MOLDULL”(部分手机需输入“0000”作为配对密码)点击连接配对完成。
- 3.自动回连： 首次连接成功后默认连接最后配对的手机。

充电注意事项

- 1.使用 一段时间后，触点氧化，出现耳机充不了电或者开不了机，首先使用酒精和布清洗触点和充电仓两个顶针，就可以解决。
- 2.当你把耳机放回充电仓，它们会关机然后开始充电；如果再次把它拿出来，它们会自动开机并且自动互相配对。

存放与维护

- 1.存放
请存放于阴凉干燥处。
- 2.维护：
 - a.建议工作温度范围为：0~35℃；过冷，过热、或者高温环境会降低电池使用寿命，影响产品性能。
 - b.请勿在雷暴天气下使用。
 - c.长时间不使用后，请在使用前进行充电。
 - d.请使用干燥的软布对耳机进行清洁。
 - e.若槽口处有积水或汗水，用干布拭干即可，不影响正常使用。
 - f.请勿接近尖锐物体，易损伤产品。

附件清单


蓝牙耳机	X2
充电仓	X1
充电线	X1
备用耳帽	X2
说明书	X1

TRUE WIRELESS EARPHONES

FCC ID:2AXPW-MD002

User Manual

Product Display



Specification

Bluetooth version：V5.0	operating frequency:2.402GHz~2.480GHz
Bluetooth distance：≥10 M	Waterproof level： IPX5
Battery： Polymer battery5V,45mAh	charging box： 300mAh
Charging time： Earphones 1H,Charging box 1H	
Working time:5H depends on the type of song and the volume	
Support agreement：： AVRCP/A2DP/HFP/HSP	

Basic operation

- 1.Power on: Take out the earphone and start it automatically or press the MFB key for 3 seconds.
2. Binaural pairing: Open the charging box cover or press the power button of the two earphones for 3 seconds with the same duration when it is turned off, turn on the bluetooth of the mobile phone, search the Bluetooth device name: "MOLDULL" and click the device name to complete pairing.
- 3.Click: Lower volume in left ear (L), and increase volume in right ear (R). (The volume is increased or decreased with a slight hint, the volume is maximum or minimum.)
4. Double click: play/pause, answer/hang up;Long press 2 seconds in call mode: call rejected.
- 5.Triple play: left ear (L), last, right ear (R), next.
- 6.Voice assistant: In connection mode, long press the left/right ear function key for 2 seconds to open the voice assistant.
- 7.Power off: Put it in the charging box and close the charging box cover to automatically power off or long press the left and right ear function button for 5 seconds.
8. Restore factory Settings: After the earphone is connected, if you want to clear the pairing and restore factory Settings, first delete the Bluetooth pairing information on the phone, put the earphone back in the charging box and take out the earphone, tap any L/R side for 5 times in a row to clear the previous pairing information and restore factory Settings

Charging operation

- 1.For the first use, make sure that the power of the two headphones and the charging box are full.
Charging box charging
1.Connect the Type C port on one side of the charging box with a Type C cable, and connect the plug adapter at the other end.(Or plug the Type C output intothe PC or computer terminal, and it will start charging. When charging, the charging box display screen will display the current power ratio, and displayit after full charge.
2.Make sure the charge bin is fully charged (or plugged into a Type C cable to charge as the instructions indicate)
3. Put the earphones into the charging box correctly and it will start charging.(you can Charge the charging box and earphone simultaneously; You can also recharge the charging box and then use it to charge your earphones.Once earphones are full, the charging box will automatically power off and the earphones' LED will go off.)
Power on and off
1.Power on: Press and hold the multi-function button of the earphones for about 3~5 seconds until the LED light of the earphones flashes blue. At the same time, there will be a "boot" prompt sound;(Or take the earphones out of the charging box and it will boot up automatically.)
2. Power off: Hold down the multifunction button for about 5 seconds until the LED red light flashes twice and the power off is accompanied by the power off prompt (or put the earphones back in the charging compartment and it will automatically power off).

Bluetooth pairing instructions

- 1.Take out the left and right earphones in the charging box, turn on the blue light, and flash red and blue in the pairing process.The red and blue lights in the back main ear matched with the earphone alternately shine, and the blue lights in the second ear will breathe for a successful team. Open the mobile device to search for the headset pairing name "MOLDULL" (for some phones, enter "0000" as the pairing password) and click the connection to complete the pairing.
 - 2.Manually turn on the blue light, and the pairing process will be alternately red and blue. After pairing with the earphone, the red and blue light in the main ear will be alternately shining, and the blue light in the secondary ear will be shining.Open the phone device and search for headset pairing name "MOLDULL" (for some phones, enter "0000" as the pairing password). Click the connection to complete the pairing.
- ### Charging Precautions
- 1.After using for a period of time, the contact oxidizes and the earphones fails to charge or turn on the machine. Firstly, use alcohol and cloth to clean the two thimbles of the contact and charging tank, which can be solved.
 2. When you put the earphones back in the pod, they shut down and start charging.If you take it out again, they automatically turn on and pair with each other.

Storage and maintenance

- 1.Storage
Please store in a cool and dry place.
2. Maintenance:
 - a. The recommended operating temperature range is 0~35℃;Too cold, too hot, or high temperature environment will reduce the battery life, affect the product performance.
 - b.Do not use in thunderstorms.
 - c.Please charge the battery before using it ,after not using for a long time.
 - d.Please use a dry soft cloth to clean the earphones.
 - e.If there is water or sweat at the slot, wipe it dry with a dry cloth, which will not affect normal use.
 - f. Keep away from sharp and hard objects, which may damage the product easily.

Package contents

Bluetooth earphone	*2
Charging box	*1
USB charging cable	*1
Spare earbuds	*2
User manual	*1

FCC Instructions :

This product has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This product generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If the product does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the product and receiver.
- Connect the product into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

Warning: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the product.