

125.00±0.3 mm

70.00±0.3 mm

AtOMESS

Portable Power Station

Model: Boost 2200W Capacity: 43.2V, 51Ah, 2203.2Wh
AC Input: 100-120V~, 60Hz, 1800W Max
PV Input(*2): 11-46V=12A Max, 400W Max (each)
DC Output(5525*2): 13.2V=5A Max
USB-A Output(*4): 5V=3A/9V=2.6A/12V=2A (24W Max)
USB-C Output(*2): 5V=3A/9V=3A/12V=3A/15V=3A/20V=5A (100W Max)
AC Output(*4): 120V~, 60Hz, 2200W (Pure Sine Wave)
Car port: 13.2V=10A Max LED lights: 3.2W
Wireless charge Output: 15W Max
Charging Temperature: 32~104°F (0~40°C)
Discharging Temperature: 14~104°F (-10~40°C)
FCC ID: 2BA7B-BOOST-2200



FCC

RoHS

Made in China

WARNING

Do not overcharge the internal battery. See Instruction Manual.
Do not smoke, strike a match, or cause a spark in the vicinity of the power pack.
Only charge the internal battery in a well ventilated area.

CAUTION

Risk of Electric Shock. Connect only to properly grounded outlets.
Risk of Injury To Persons. Do not use this product if the power cord or the battery cables are damaged in any way.
This device is not intended for use in a commercial repair facility.

AVERTISSEMENT

Ne pas surcharger la batterie interne. Consulter le manuel d'utilisation.
Il ne faut pas fumer, allumer une allumette ou produire des étincelles à proximité du bloc d'alimentation.
Charger la batterie uniquement dans un endroit bien aéré.

MISE EN GARDE

Risque de décharge électrique. Brancher l'unité uniquement à des prises de courant correctement mises à la masse.
Risque de blessure aux personnes. Ne pas utiliser ce produit si le cordon d'alimentation ou les câbles de batterie sont endommagés de quelque façon.
Le dispositif n'est pas destiné à être utilisé dans un atelier de réparation commercial.

40mm*10mm

Label Location:

