

Label Location On EUT



 **WARNING:**

- DO NOT short the battery terminals.
- DO NOT incinerate, crush or disassemble.
- DO NOT reverse connections (polarity) from charger to battery.
- DO NOT over charge or over discharge.
- DO NOT operate battery beyond the published voltage, current and temperature limits.



12V 100Ah

LiFePO₄ Battery

* Bluetooth

SPECIFICATIONS:

| | |
|-------------------------|--------------|
| Capacity: | 100Ah |
| Nominal Voltage: | 12.8V |
| Cut-Off Voltage: | 10V |
| Max. Discharge Current: | ≤100A |
| Working Temperature: | -4°F - 140°F |

REFER TO PRODUCT SPECIFICATIONS FOR FURTHER INFORMATION.



FCCID: 2BBL3-12V100AH

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference.
- (2) This device must accept any interference received, including interference that may cause undesired operation.

A S T R O
L I T H I U M

A

12V 100Ah

LiFePO₄ Battery | * Bluetooth