



Smart WiFi+BLE sensor wall Switch(US) User Manual



Alexa  
TUTORIAL



Google home  
TUTORIAL


Attention:

1.Products should be paired on 2.4GHz band or 5GHz band.

2.Please set your home WiFi account name and password by using numeric and letters, don't use special symbols.

1.Installation

Separate the upper and lower ports from the switch by screwdriver.  
Dimensions:3.4"1.4"1.4in



See this picture before

(Please distinguish between each corresponding pin)

• Without neutral wire version(**No neutral wire is required on this switch**), according to the following diagram wiring.


1-Neutral wire

2-Live wire

3-Switch

4-Capacitor must to be connected to L and Neutral wire.

5.5.1 (Lighting) They're between L1,L2,L3,L4 and Neutral wire.




• With neutral wire version (**Neutral wire is required on the switch**) according to the following diagram wiring.

1-Neutral wire

2-Live wire

3-Switch

5.5.6 (Lighting) They're between L1,L2,L3,L4 and Neutral wire.



3.Fix the switch onto wall.


• Put the switch lower parts into switch box in the wall

• Mount the two side screws.

• Install the upper top case (install from up above).

• Cover the upper top case into switch.

• Turn on electricity, and then LED light will be flashed quickly for pairing.



4.Indicator light status.

• The WiFi indicator light went out.

• The switch is connected succeed with mobile phone APP.

• The WiFi indicator light blinking slowly.

• The switch is not connected to the network.

• The WiFi indicator light flash continuously and quickly.

• The switch is currently on the status of matching with existing home APP.

• The WiFi indicator light flash 1 time every 3 seconds.


• The switch into AP pairing Mode.

• How to reset the switch?

4.Long press any button for 10-12seconds.

• How to download APP?


Scan the QR code below or search for doodle intelligence in the iOS APP store or Google play.



5.Setting Smart Life APP:How to Register and Login?

• Download or Scan the QR Code and install Smart Life APP.

• Once download or Scan the QR Code, the APP will ask you to:



• Enter your phone number or email which you prefer and select the country you live in.

• Obtain verification code.


• Enter verification code.

• Set Password.

• Create family.

• Enter the family name and select the room.

• Family created successfully.




6.Switch pairing.


• First the Phone needs to turn on Bluetooth.

• Connect the switch with power.


• Open App and click Add Device or upper right corner "+" The APP interface will pop up a window discover the devices to be added, you can choose to add or not add, or select "Switch (BLE)".



• Select "+" then entering the WiFi password.



• Select "+" then entering the WiFi password.



7.How to match IR remote controller? or having RF function switch?


• Connect the switch with power.

• Connect the switch with WiFi.

• Hold the switch power button for 4 seconds, the buzzer sounds "ding", then press the "remote control" button, the "remote control" will sound "ding" and for the switch to sound "ding" connecting successfully, as a whole turns pairing up each group. Attention: The switch needs to be connected with the remote controller and then with the APP connect to the network, the remote controller needs the switch connected to the network, changing code matching.

• How to remove remote controller?

Press the switch touch button 6 seconds, the buzzer rings twice "dingding", the remote completes the removal.



#### FCC Warning

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

#### Radiation Exposure Statement

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator and your body.