

封面

LIVEY™

User Guide LIVEY 710BT Plus

Benutzerhandbuch | Manuel de l'Utilisateur
| ユーザーマニュアル | руководство пользователя

Livey Technologies LLC, USA
www.livey.us
hello@livey.us

Product Overview

Packing List:

- A.LIVEY 710BT Plus Stereo Bluetooth Headset
- B.Charging Stand for 710BT Plus
- C.USB Dongle for 710BT Plus
- D.TYPE-C Charging Cable
- E.User Manual

Basic Operation

Button	Function	Operation Instruction
MFB	Power On	In off status, slide ON/OFF switch to ON
	Power Off	In on status, slide ON/OFF switch to OFF
	Redial a call	In connected status, double press "MFB" to redial a call
	Voice dialing	In connected status, long press "MFB" for 1 second
	Answer a call	When a call incoming, short press "MFB" to answer
	Hang up a call	When during a call, short press "MFB" to hang up
	Reject a call	When a call incoming, long press "MFB" for 1 second to reject
	Play/Pause	Short press "MFB" when play music
	Three-way calling function	a. Call coming during a call, short press "MFB" to answer the new call and hang up current call; b. Call coming during a call, double press "MFB" to answer a new call and keep current call; c. Call coming during a call, long press "MFB" for 1 second to keep current call and reject a new call; d. When you are in a three-party call, double press "MFB" to switch audio between the current call active, answer the new incoming call.
	Volume+	Short press "Volume+"
Volume -	Short press "Volume-"	
Mute Button	Microphone mute When during a call, short press "Mute Button" to mute on, and mute LED on; Then short press "Mute Button" to cancel mute, LED off.	
Teams Function	After connecting to dedicated dongle, you can short press "Volume+" and "Volume-" at the same time to pop up windows during a business teams call, and long press "Volume+" and "Volume-" to raise hand during a meeting.	
Deleted Pairing Records	In on status, long press "MFB" and "Volume-" for 5 seconds at the same time to delete pairing records. After deleting, the headset will restart automatically and you need pairing again.	
Enter pairing	a. After power on, headset will enter pairing automatically if there is no pairing records; b. Under reconnection status, short press "MFB" to enter pairing status; c. Actively disconnected the Bluetooth device from phone, headset also can enter pairing status.	
Combine Button		

Dongle

Function	Operation Instruction
Power On	In off status, insert USB to computer device to power on, dongle display name on PC is "LIVEY 710BT Plus"
Power Off	In on status, unplug USB to power off
Teams answer/ hang up	With business Teams, you can use "MFB" button to answer and hang up
Teams Mute/ cancel Mute	With business Teams, you can use "Mute" button to control teams call mute / cancel mute, the Mute icon of Teams client will change accordingly.
Teams pop-up windows	With business Teams, in connected status, short press "Volume+" and "Volume-" at the same time to pop up windows during a call.
Teams raise hand during a meeting	With business Teams, long press "Volume+" and "Volume-" to raise hand during a meeting, perform this operation again to cancel.

Bluetooth Pairing and Connection

Bluetooth Headset

A. In off status, slide ON/OFF switch to ON to power on, if you are not entering pairing mode then you need to short press "MFB" to enter pairing mode;

B. Search and click to connect "LIVEY 710BT Plus" on your phone/laptop Bluetooth lists, after connected successfully, there will be a prompt tone, and LED change to Blue slow flash (Blue LED flash once every 10 seconds), now you can listen to music or call from phone/laptop to headphones.

C. You can press MFB / Volume+ / Volume- / Mute to control the answer/hang up a call and play/ pause of the music, next and previous song, volume up and down, microphone mute etc.

Pair Headset with Dongle

1. Insert dongle to PC/laptop, dongle display name will show on PC/laptop as "LIVEY 710BT Plus", repeat mute/cancel mute on PC for 10-11 times to delete pairing records.

2. In ON status, long press "MFB" / "Volume- " at the same time for 5 seconds, Red and Blue LED flash once at the same time to delete pairing records on headset, headset will enter pairing mode with Red and Blue LED flash alternatively.

3. Put the headset close to the dongle, when dongle turn to solid blue LED, and headset turn to blue LED and flash once every 10 seconds, paired successfully.

Connection with Two Devices

A. The mobile phones connected to LIVEY 710BT Plus are divided into two sets: Device A and Device B.

B. Turn on the Bluetooth Pairing mode on Device A first, and then slide ON/OFF switch to power on the headset, if not enter pairing mode, you need short press "MFB" to enter pairing mode. On the Device A Bluetooth pairing mode, search for "LIVEY 710BT Plus" and then click to connect. After the connection is successful, turn off the Bluetooth on Device A and LIVEY 710BT Plus will enter into pairing state again.

C. Then use Device B to pair and connect with LIVEY 710BT Plus, according to the same method followed for Device A. After the Pairing on Device B is successful, turn on the Bluetooth of Device A and click "LIVEY 710BT Plus" to connect. (Some mobile phones may have the automatic connection function in which case the headset will connect automatically to both Device A & B).

D. Music only can be played from one phone under two connections, when you want to play music from another phone, you need to pause or close the music of the previous phone.

LED Indicator

Bluetooth Headset

Status	LED Indicator
Power on	Blue LED flashes 2 times
Power off	Red LED flashes 2 times
Pairing mode	Red & Blue LED flash alternately
Connected standby mode	Blue LED flash once every 10 seconds
Playing Music	Blue LED flash once every 10 seconds
Talking	Blue LED flash once every 10 seconds
Delete pairing record	Red & Blue LED are on for 1 second at the same time
Charging	Solid Red LED
Full charged	Solid Blue LED
Low battery	Red LED flashes

Dongle

Status	LED Indicator
Power on	Blue LED flashes
Power off	Blue LED off
Pairing mode	Blue LED flash quickly
Reconnect mode	Blue LED flash once every 1 second
Disconnect mode	Blue LED flash once every 5 seconds
Connected standby mode	Solid Blue LED

Charging Stand

Please charge the "LIVEY 710BT Plus" when you see LED flashing RED color. Charging time is about 2 hours, LED will turn into Solid Blue when its fully charged.

TTS Tone

Status	Prompt Tone
Power On	Power on
Enter Pairing mode	Pairing
Pair successfully (only prompt at the first time)	Paired
Connect successfully	Your headset is connected
Disconnect	Your headset is disconnected
Power off	Power off
Microphone mute on	mute on
Microphone mute off	mute off
Low battery	Battery low

Charging

Please charge the "LIVEY 710BT Plus" when you see LED flashing RED color. Charging time is about 2 hours, LED will turn into Solid Blue when its fully charged.

Charging Connection

Please connect to the "LIVEY 710BT Plus" charging port through the Type-C end of Type-C charging cable, USB end to the charger (can be used as car charger, travel charger, computer USB, etc.).

Product Specification

Bluetooth Headset

Bluetooth Version	V5.2
Bluetooth Chipset	QCC3040
Operation Range	10 meters
Bluetooth Protocols	HSP / HFP / A2DP / AVRCP
CODEC	aptX-Adaptive, aptX HD, aptX, AAC, SBC
Battery Type	420mAh/3.7V
Charging Time	About 2 hours
Music Time	About 50 hours (70% volume)
Talking Time	About 25 hours (70% volume)

Dongle

Stand-by Time	About 350 hours
Headset Net Weight	About 202g
Headset Overall Dimension	187.5*186.5*69mm

Charging Stand

Working Temperature	-10~55°C
Working Input Voltage range	4.5V-5.5V
Overall Dimension	86.4*110.8*91.1mm
Net Weight	About 151.2g

SIZE: 85x120MM,
材质: 80g书写纸, 手风琴页折叠